Dennis Bathory Kitsz

THE CUSTOM TRS-80®

& OTHER MYSTERIES

The complete guide to customizing TRS-80 software and hardware

Dennis Bathory Kitsz

THE CUSTOM TRS-80
& OTHER MYSTERIES

David Moore — Editor

Thomas Nelson — Artistic Direction and Backup Vocals

Steve Rick and Charles Trapp — Graphics and Figures

H. C. Pennington — Cover Design

First Edition
First Printing
February 1982
Printed in the United States of America.
Copyright © 1982 by Dennis Bathory Kitsz

ISBN 0 936200 02 2

All rights reserved. No Part of this book may be reproduced by any means without the express written permission of the publisher. Example programs are for personal use only. Every reasonable effort has been made to ensure accuracy throughout this book, but neither the author or publisher can assume responsibility for any errors or omissions. No liability is assumed for any direct, or indirect, damages resulting from the use of information contained herein.

Published by
IJG Inc
1260 West Foothill Blvd.,
Upland, CA 91786, USA

714 – 946 5805

Radio Shack and TRS-80 are registered trademarks of the Tandy Corporation. Supplements to Chapters in this book have appeared in part in The Alternate Source, 1806 Ada Street, Lansing, Michigan 48910.

IMPORTANT

Read This Notice

Any warranty that may exist on any TRS-80 computer hardware product that has been modified, altered, or has the seal broken is VOID.

Any software or computer hardware modifications are done at your own risk. Neither the PUBLISHER nor the AUTHOR assumes any responsibility or liability for loss or damages caused or alleged to be caused directly or indirectly by applying any modification or alteration to software or hardware described in this book, including but not limited to any interruption of service, loss of business, anticipatory profits or consequential damages resulting from the use or operation of such modified or altered computer hardware or software. Also, no patent liability is assumed with respect to the use of the information contained herein. While every precaution has been taken in the preparation of this book, the PUBLISHER and the AUTHOR assume no responsibility for errors or omissions.

The reader is the sole judge of his or her own skill and ability to perform the modifications and/or alterations contained in this book.

The below statement is the apparent policy of the TANDY CORP. and its subsidiary RADIO SHACK as understood by the publisher. The following statement is not endorsed by the TANDY CORP., but is presented for the reader's information and as a warning regarding the consequences of modifying or altering the TRS-80 computer hardware in any way. IJG, Inc., assumes no responsibility for the accuracy of the following statement.

The reader is warned that it is the apparent policy of the TANDY CORP. and its subsidiary RADIO SHACK to refuse repair service on any TRS-80 computer product that has been modified or altered in any way whatsoever.

However, a Radio Shack Computer Service Center, at the discretion of the individual Service Center, may repair an altered or modified TRS-80 computer upon the customer's prior agreement to pay any additional charges that may be incurred to remove or repair any and all alterations or modifications that may exist and thereby return the computer hardware to factory specifications.

Editor's Note

ABOUT THE AUTHOR

Dennis Bathory Kitsz is a composer and active defender of the contemporary arts. However, this approach to life has resulted in pecuniary disaster which could only be ameliorated by working occasionally as a librarian, book editor, printing press operator, truck driver, newspaper editor, laborer, secretary, graphics designer, electronics technician, and typist. He is currently the director of the Dashuki Music Theatre, the president of Green Mountain Micro, and a regular columnist for several microcomputing magazines. He lives in Roxbury, Vermont with his wife Claire Manfredonia, as well as Aida, Mehitabel and Smokimoto (the cats), Fritz (the dog), and Fred and Ethel (the finches).

I'd like to say a word of thanks to Dennis Kitsz for helping us through the entire range of Murphy's laws that were proven, over and over again, in the preparation of this book. . .

I'd also like to thank:
Jim Perry, for teaching me to swim the old-fashioned way;
Jim Murphy of Bishop Graphics, for his typing ability;
Thomas Scott Nelson, for wandering through at a good time;
Nancy DeDiemar, for the kind of help you don't find anymore;
H.C. Pennington, for lending a hand with the impossible parts;
Bruce Stuart, for lending a hand with Harv;
and Charles Trapp for sticking with me to the end . . . which kept refusing to arrive.

And for those of you who have waited so long for this book, we believe you'll find the wait was worthwhile. There have been many updates of information that couldn't have been included a year ago, and several extras — including an additional chapter providing 111 cures for the common crash.

David E. Moore
Febuary 1982

Contents

Chapter 5:

Chapter 6:

Chapter 7:

Chapter 8:

Chapter 9:

Chapter 10:

Chapter 11: 111 Cures for the Common Crash

Appendix I:

Appendix II:

Appendix III:

Appendix IV:

Appendix V:

Appendix VI:

Appendix VII:

Preface

A few years ago, when CB was king, a company riding high with those 10-4's hesitantly announced a very expensive new product. A few typed sheets with hand drawings were all store sales personnel had to explain this small 'home and business computer'. Neither Tandy nor we few first customers had any idea that the TRS-80 would become the first true home computer, the Model T of the microprocessor age.

There's no question that the 'Trash-80' carries the burden of some weak engineering and corner-cutting decisions made at the time of the CB decline, when this personal computer could have been Radio Shack's Waterloo instead of its new Wunderkind. But, like Rabelais's Gargantua, the new child soon outgrew its expectations – as well as its clothes.

And so everyone from the inner sanctum of the Tandy Corporation to the cluttered backrooms of a thousand hobbyists began the attempt to keep this new child content and amused. Thus was born the custom TRS-80. From the very beginning, and from seemingly nowhere, came forth educated hordes who would prod, poke, paint, primp, and prime this humble computer into becoming more than itself – a five-hundred-dollar supercomputer.

The machine couldn't always do it. Tandy took the rap, but also took the cash. Bruised and broken 80's littered the electronic landscape, yet also unrecognizably modified TRS-things took on tasks as diverse as business accounting, industrial control, and music making.

In this book, pathways to creating your own customized TRS-80 will be explored. The machine will be added to, opened and altered, its software patched, its uses expanded, and its breakdowns cured. If you expect that your personal computer can do more than a fancy game of video violence, then I hope you will join me in these explorations.

As this book was completed, Tandy announced that the TRS-80 – now called the Model I – is history. Production has ended, and that's a good thing. The pressure is now off; there is no more Trash-80 to defend, but there still is a TRS-80 to put to use.

This book has been put together to please everyone. Of course it will not. Although I can't expect to help lead each of you through the intricacies of a TRS-80, I hope that, whether your wish is to jump right in and solder every wire or to learn slowly and deliberately the theory and practice of the machine, you can gain some insight from this volume.

Chapters have been arranged with basic theory and concepts toward the front. Special sections discussing the computer's software have been included to add some dimension to the concepts, and some of my own opinions, thoughts and tirades have been boxed throughout the text.

I have seen and used nearly all the commercial products presented in this book; comments, therefore, are based on first-hand knowledge, unless otherwise noted.

I have attempted in the appendices to present lists of those suppliers, publishers, terms, etc., that every TRS-80 user might want to know and not know how to find.

As the TRS-80 joins the computer museum along with the ENIAC, UNIVAC, IBM 370, and others, it still holds a more special place than many of those – with possibly half of million of its kin in use in the United States, Canada, Great Britain, Australia, Germany, and other countries. With that in mind, this book may need an occasional update.

I would appreciate receiving updated information, corrections, suggestions and criticism. Though I cannot promise a personal answer, those suggestions will be reflected in future printings of this book.

Dennis Bathory Kitsz

Roxbury, Vermont

February 1981

Acknowledgments

Someday the interdependence and cooperation among authors and programmers in this infant field will be chronicled. I can think of a hundred books or programs or articles or newsletters, each one of which gave me an essential part of the insight needed to create this volume, and without any single one of which that creation would have been impossible. Among the programmers, authors, and friends . . .

Philip K. Hooper the Codesmith, *for teaching me the simplicity and elegance of machine code*; Ron Gillen of Lab Service, Inc., *for keeping me awash in new information*; Nick "Spike" Maggio of the Philadelphia/Castor Avenue Radio Shack, *for risking life, limb and managership on Tandy's red tape battlefield, and for teaching me ventriloquism*; Roger Fuller of Fuller Software and Bryan Mumford of Mumford Micro Systems, *for two reference books I couldn't do without*; Jim Perry, *for his entrepreneurial acumen and refreshing lack of humility*; Michael Comendul of 80 Microcomputing, *for pointing out that English is a difficult second language for most programmers*; Debra Marshall of the same publication, *for pointing out that it doesn't have to be that way*; Dave Moore and Thomas Scott Nelson of IJG, *for saving this book from disaster*; Charley Butler and Joni Kosloski of The Alternate Source, *for my author's carte blanche*; Dave Beetle of the pioneering On-Line, *for really starting it all*; Harv Pennington *for jollies*; and for many and varied favors: Bill Johnson (*Cleveland Users Group*), Vaughn Jupe, Ron Troxell (*Personal Micro Computers*), Don Stoner (*The Peripheral People*), Lee Perryman (*The Associated Press*), Wayne Green (*himself*), Eric Maloney (*Kilobaud*), Jack Decker, Mike Barton (*MSB Electronics*), Leo Waltz, Jerry Sabin, Fred Blechman, Don Stevens, Walt Auch III, Vince Schulz, Bill Archbold (*Archbold Electronics*), Al Abrahamson (*Norwalk Users Group*), Bill Barden, Don Valentine (*Tecmark Associates*), Harold J. Matts, Stan Ockers, Thomas Frederick (*ABS Suppliers*), Les Logan (*TCS Newsletter*), Brian Harron (*Ottawa Users Group*), John Bilotta, Gregg Shadel, Don C. Tatum (*Barre-Montpelier Radio Shack*), Andrew Law,*the many manufacturers represented herein, and the usual coterie of others forgotten and maligned. Special thanks to the anonymous author of the TRS-80 Technical Reference Manual for a job well done.*

This book is dedicated to my wife, Claire Manfredonia, because she'll do most anything for a good gag. One day she walked into a serious meeting at an engineering company and hit me in the face with a blueberry pie. I won't tell you about the marshmallow fluff.

d.b.k.
March 1982

Introduction

The Tools You Will Need

Your basic TRS-80, with some attachments and software, is a thousand-dollar item. So I'll not encourage you to use dime-store tools. Buy the best you can afford, keep them clean, and reserve them just for use on the '80. Don't double up tools with the family auto. You may not need them all, but here is my customizer's toolbox:

A medium-sized flat-blade screwdriver and **Phillips blade screwdriver** (a reversible combination is ideal). With these you open cases and remove cabinets.

A jeweler's set of flat and Phillips blade screwdrivers; **hex nut drivers** are optional. These drivers can be used to align tape heads, help make delicate wire bends, adjust trimmer controls and even repair watches.

One very thin screwdriver for lifting integrated circuits out of sockets. This will be its only purpose, but the first time you break the pins off a $10 jumper cable, you'll wish you'd used it!

Small scissor-type cutters (manicuring types are excellent). These will be used for snipping leads in tight spots.

Small diagonal wire cutters and/or front-cutting **'nippers'.** Your general purpose cutters. They are fast and easy to use, but not to be used for heavy wire around the house.

Needlenose pliers (two pairs, normal and 90-degree types). You'll need these for bending leads, also extracting bits and pieces you've dropped into a nest of wiring.

An X-acto type knife, with a strong blade and handle you feel comfortable with. Since this will be used to cut delicate solder traces, you should be able to handle it deftly. I use a single edged razor blade, but have leather fingers!

A scalpel, if you can get one. For very delicate trimming and scraping; **a dental pick** for pulling off solder balls or lifting parts off a board (get this item from an obliging dentist — they are often discarded when worn); **tweezers and needlepoint hooks.** The latter come in handy for tracing incorrect wire-wrapped connections.

Rat-tail, triangular, and flat files. These are only for sprucing up the cosmetics, so if you don't care how it looks, save a few bucks.

A wire-wrapping tool. The decision on this can be tough. If you can afford it, get one of the electrically operated slit-and-wrap types. Stay away from 'just wrap' tools, since they depend on the sharpness and quality of the sockets; also they are useless for wrapping capacitors or resistors. I use a simple double-ended tool sold by Radio Shack for about $5. It wears out after a thousand or so connections, but it fits my hand well, and is not clumsy like some electric units.

A soldering iron. The decision is not easy. Should you spend top dollar and get an expensive one or buy a cheap unit that can be discarded when it wears out? I use a $5

To help you prepare for each project, the following graphic symbols have been used as a key to the tools needed for each project:


Phillips screwdriver


Flat-blade screwdriver


Sockets


Thin lifting tool


Scissors type cutters


Solder


Wire cutters


Needlenose pliers


Various files


Wire wrapping tool


Soldering iron


X-acto knife or blade


Solder wick


Multimeter


Oscilloscope


Drill

soldering iron which can be junked when it gets beat, but my editor uses the best he can get (a $30 temperature-controlled one).

I file a set of $1 tips to my satisfaction, and lubricate the threads with white heat sink grease. This way I have a few different tips at my disposal; with plated bits you **never** file the tips.

A Multimeter. The voltage regulators in your TRS-80 are very good, so any problems will usually show up as gross errors. This offers you a way out of buying an expensive multimeter; for most of these projects, the $10 pocket variety will suffice. However, for lots of repair work a better meter is in order; I use a $40 type (not digital!) for my work.

An oscilloscope. For the projects, no. But for repairs, yes. Don't panic thinking of a thousand dollars for a digital scope, because an old color television scope will do perfectly well; they can be found in the bargain bins for $50 to $100. If it saves you a $100 repair bill, you've paid for it. Mine is an old RCA type WO-90Q, built for early color TV, and just fine for the bulk of TRS-80 work.

You will also need supplies in the tool box. Among these are:

Solder. Get the best you can afford. There's nothing so unpleasant as a great glob of the stuff between two traces on a board. Order the multicore rosin flux type, and stay away from most the off-the-shelf stuff. Remember, multicore rosin type only, and the finer the gauge the better. **Never use acid flux solder**, as used by plumbers and electricians.

Soldering wick. Marketed under the names *Spirig, Solder Up* and *Solder Wick*, it's a copper braid impregnated with soldering flux. When heated with the soldering iron it absorbs Solder off the board, thus freeing components. Don't do without this stuff unless you like fried circuit boards and burnt fingers.

Wirewrap wire. Also called by the trade name *Kynar*, this is 28- or 30-gauge single-strand wire used to interconnect the pins of wire wrap sockets. It comes in an assortment of colors; get them all, so you can keep data, address, power and ground lines separate.

Multiconductor cable. The more flexible wire is easier on the coordination, but also the most expensive. Best buy is *Spectra Twist*, and its kin, from surplus houses. If you need jumper cables, buy them; Making a two-ended, 40-pin jumper cable can be three hours of maddening work.

Bus wire. This is solid, uninsulated stuff. A small roll will do for a lifetime. I use it for wiring, securing bulky capacitors to circuit boards, holding bundles of things together and for making special tools.

Miscellaneous. Sockets, perforated board, mounting hardware, and such will always be needed.

Details about supplies needed for each project in this book will be presented with the project. Except for integrated circuits, most of the items are available right off the shelf at a local Radio Shack or other electronics supply house.

Schematics

Schematic drawings of electronic circuits are identical to maps. They show routes, direction, junctions, relative importance and functions of locales, two-way and one-way streets, traffic flow and congestion and so forth. At first, the symbols may seem like the mysterious hieroglyphics of a secret society, but their symbolism can soon become as familiar as a roadmap. Even strange places can be assessed from afar.

First, the symbols. A line is a wire running from some point in the circuit to another. Consider the sketches below:



The first drawing is a simple wire. The electrical path moves from one point to another, in either direction. By following the path of a wire through a circuit, the pattern of connections can be discovered. When wires are forced to cross one another, but not to connect with each other, it must be made clear. On a roadmap, non-intersecting roads are shown either by a break in one of the intersecting lines, or in showing interstate highways, merely by crossing one 'below' the other in a different color.

Sketches b, c and d are the three ways of drawing wires which do not connect to each other. The first, simply crossing them, is the most common. The second method places a semicircular bump in the crossing path, and is used by Sams Publications in this country and commonly in Europe. Occasionally the broken path crossing shown in sketch d is used.

When wires connect, a dot is used to clarify that a connection is to be made. Occasionally, you may come across earlier schematics which use the 'bump' method of showing unconnected wires. On these schematics, the lack of a bump indicates wires are connected.

The wires (or patterns of copper etched on circuit boards) connect electronic components. Some of them are:



Since this is a lesson in reading schematics and not electronic theory, I recommend that you turn to an excellent book by Forrest Mims, 'Engineer's Notebook', sold by Radio Shack, for an introduction to what each of these parts does. Briefly, the symbol for a resistor has the flavor of a long wire being compressed, meaning the electrical flow is somehow being resisted. The innards of a capacitor generally consist of metal foil separated by a non-conducting paper or plastic, and the capacitor's schematic symbol is fairly representative, with two plates facing each other but not joining.

Some capacitors are designed to fit into a circuit in only one direction; the positive (+) sign identifies that direction. These capacitors are identified on their bodies by a positive or negative sign. Another one direction (polarized) device is the diode. It consists of an arrowhead striking a barrier, implying that current may flow in the direction of the arrowhead, but not back across the plate. The body of a diode may have the diode symbol imprinted on it, or a band to indicate the 'barrier' end.

The transistor usually has three connections (such connections are called 'leads' on small parts such as these). These leads are identified as collector, base and emitter or source, gate and drain, depending on the transistor type. This will be shown on the diagram, and the transistor will be imprinted with the information, or it will be provided on the package in which the transistor is sold.

A few other symbols are:

TRANSFORMER



VARIABLE RESISTORS

VARIABLE CAPACITORS

CRYSTAL

The first is a transformer, whose job it is to take current fed into one coil and induce that current into a second coil. An iron or ferrite center (the parallel lines in the symbol) aids in efficient transfer of that current.

The next three symbols look like resistors and capacitors, which they are. The added arrows show that their values may be varied; hence, they are called variable resistors and variable capacitors. The variable resistor is best known as the volume control on a television, and the variable capacitor is found as the tuning control on a table radio.

The last symbol is a crystal, a piece of cut quartz capable of vibrating (resonating) under certain electrical conditions. Because a crystal is a very accurate, fixed, molecular device, it is capable of resonating (also called oscillating) at precise intervals. It is used for the master control of all pulses in the TRS-80.

A few directional symbols are now in order:



The first are known as grounds, and they are used to indicate a potential of zero or neutral voltage. The first of the trio is an earth ground, commonly used in radio, television and hi-fi schematics, but purists use it only to describe an actual connection to a ground spike or cold water pipe. The second is a chassis ground, indicating an electrical connection to the metal case which encloses the circuit. It is often (though incorrectly) interchanged with the earth ground.

The last of the three grounds is a 'common' or neutral ground, and the one which is used to indicate the zero voltage line in the computer. All other voltages within the computer system are described in terms of their relation to this ground.

The next quartet of symbols indicate power. The up arrow generally points to an actual voltage value (such as +5 or +12).The horizontal line indicates merely a 'high' level, that is, a connection is made to the normal positive power supply for the circuits in the system (+5 volts in the TRS-80).

Non-positive voltages have no standard symbols. Negative (or below ground) voltages can have either a horizontal arrow or a down arrow, pointing to the voltage desired at that point. The schematics tells you that a connection is made to the voltage level shown.

Another use of a horizontal arrow is to point to important connections to be made elsewhere on the schematic or on other sheets of the schematic. In the former case, the arrow is used because actually drawing the wire may clutter the schematic, making it illegible. When you see an arrow, be sure to find the other end of the connection described (indicating words such as 'clock', 'mem' or 'port FF' may be used as guides to where the connection is made).

Another useful symbol is the last of the group above, the pad. It indicates a significant connection, usually to another device or circuit board. Using this symbol makes it clear that the connection is to be made somewhere off the board on which you are working. In this book, I have not used these symbols where indicating a connection to the TRS-80; instead, the cable to the TRS-80 is shown with the connecting wires striking a wide vertical band marked 'TRS-80 Edge Connector'. Other types of off-board connections, however, are shown with the pads.

The most common families of parts found in computer circuits, however, are shown below:



These symbols represent integrated circuits, those multiple lead, buglike packages that handle the bulk of the work in the computer. Briefly, these are logical building blocks. Sometimes there are several blocks in one integrated circuit, and these various blocks may be scattered throughout the circuit diagram. This can be confusing when actually building a circuit, but since pin (lead) numbers are given, you only have to remember where you put the part.

You should know that the TRS-80 *Technical Reference Handbook* uses what are called 'functional' schematic elements, meaning identical parts are not necessarily drawn the same throughout the schematic. I have chosen not to use this method, which, although it makes circuit operation less evident, is clearer when doing actual wiring.

Complete logical and physical diagrams of every circuit used in this book are give in an appendix. Those diagrams will help give you an idea of how these logical blocks are packaged inside 8-, 14-, 16-, 18-, 20-, 24-, 28- and 40-pin cases.

Basically, that covers reading a schematic roadmap. Below is a section of circuit. See how the logic elements are connected to each other as well as to two resistors, a capacitor and a crystal. Notice also that the logic elements are all marked 'Z19', since they are separate blocks within a single component. An arrowhead indicates a wire leading off the board, and power and ground connections are shown. The numbers on the logic elements are the pin numbers for the component connections:



Be Tolerant

Every electronic component is manufactured to work within specific limits, whether they be accuracy, temperature, speed, power use or other limit. These are the components parameters or *tolerances*. The circuits in this book have been designed to use the most commonly available parts, so the matter of tolerances is rarely important. However, sometimes those tolerances are important, such as when talking about memory speed or power supply voltages.

Power supply should be within five percent of the voltage specified; a supply indicated at five volts may vary only from 4.5 volts to 5.5 volts. By using the power supply regulators shown in the schematics, these voltages should not be of concern. Unless you are familiar with power supply design, do not attempt to use other methods of regulation.

Very few of the resistors have tolerances noted on the schematics. The rule of thumb is one quarter watt at five percent, but if you can only obtain half watt units, or 10 or 20 percent resistors, don't be concerned. The quarter watt

resistors are a bit less costly and are a bit more aesthetically appealing. Consider also that if a resistor is specified as 1,000 ohms, a 20 percent deviation gives a range of 800 ohms to 1,200 ohms. Thus, the standard values of 910 ohms or 1,200 ohms should do as well.

Capacitors are notoriously sloppy in their tolerances, especially electrolytic types (those whose polarity is marked on the schematics). These normally vary from 20 percent low to more than 100 percent high – thus, when a 500 microfarad capacitor is noted, it can range from 400 to 1,000 microfarads. Also, there is some revision in the standard numbering method used for parts values: 470 microfarads is now being called 500 microfarads, for example. So when you try to obtain a capacitor value marked in the parts list, remember that a nearby higher value is fine.

Voltage parameters for polarized (electrolytic) capacitors are important. Never get an electrolytic capacitor with a value less than that specified, but do not hesitate to take one with a higher voltage parameter. That is, a capacitor specified at 47 microfarads, 16 volts, can be replaced with one specified at 50 microfarads, 35 volts. It may be physically larger, but it will work equally well.

If you walk into a store and hand the sales clerk a parts list, don't be surprised if you are asked a few more questions. You might be faced with chosing between parts which are identical as far as the parts list in this book is concerned, but which include other parameters.

Resistors can be carbon composition, carbon film, glass or wire wound. These days, carbon film is common and cheap, and that's your first choice. Carbon composition is the next choice at a lower quality, and glass is excellent but at a higher cost. Forget wire wound, because they can contribute unwanted side effects.

Ordinary capacitors are manufactured in many ways: ceramic, polystyrene, polyester, silver mica, polycarbonate and paper. For the bypass capacitors necessary for all the circuits in this book, ceramic types are your choice. Cheap. If you get silver mica, so much the better, but you'll pay a price. Watch out for polystryrenes or polyesters if you plan to solder, because they are delicate and you can damage them with too much heat. Otherwise they are excellent, but quality overkill. Polycarbonates are slick types, and you might consider using these if you build the 8-track mass storage system. Run the other way if you see paper capacitors.

Electrolytic capacitors come in two basic types – metal cans (covered with plastic), and those manufactured using tantalum (an expensive metal of great strength and purity). For most digital projects, choose the ordinary cans. Tantalums of the same value, although smaller, high quality, and very pert looking, are costly and not required here.

Digital integrated circuit part numbers are generic, which means that a 74LS00 circuit might be sold as an SN74LS00 or an NEC-74LS00. The prefix characters refer to manufacturers. On the other hand, those parts whose numbers contain 'LS' may not be substituted by parts marked 'S' or 'C' or by those with no markings. 74LS00 may not be replaced by 7400, 74S00, or 74C00, nor may they be exchanged for each other. When integrated circuits are specified, try not to substitute with other circuit 'families'.

This section will not make you a master schematic reader; only practice will do that. Pick up copies of the Engineer's Notebook mentioned above, as well as various of the project books sold by Radio Shack and others.

Building a Power Supply

All the projects presented in this book will either be modifications to the TRS-80, in which case they will draw power from the computer itself, or outboard devices which will need power. There are several ways to get this power:

1. Build a power supply from scratch for each device, including transformer, rectifiers, capacitors and regulators.
2. Build a main power supply providing substantial current at between 7.5 and 15 volts, and put a voltage regulator and a capacitor on board each project.
3. Use an assembled power supply providing a 7.5 to 9 volt output for each project, and use a voltage regulator and a capacitor on each board.
4. Use an assembled power supply providing 5 volts and feed all boards from it.

My recommendation? Probably an assembled power supply of 7.5 to 9 volts feeding each project. Power supplies are important to projects, and they should be well regulated, free of residual 60 Hz (Hertz equals 'cycles per second)' ripple, and should not tend to transmit signals between projects. Some things to consider include:



Unregulated positive power supply.



Unregulated bipolar power supply.



+5 volt regulated power supply.



+5/-5 volt regulated power supply.

1. Building a power supply is not very time-consuming, but it is probably going to be bulkier than the project being constructed. Then there's the question of where do you put it? If it's in the project, you have to be very careful to shield the AC primary and secondary leads. Also, you have to be sure it's working properly before you can begin to test your project.

2. Small, assembled power supplies are inexpensive. They are normally sold as 'battery eliminators', with their current capabilities specified. The AC leads are encapsulated in plastic with the rest of the supply. Although you need a separate house-current outlet for each of these supplies, the work you do (both building and testing) is lessened and the safety to you and your project is increased.

3. Larger power supplies are expensive to buy and complicated to build. Unless they and each project being fed contain plenty of transient suppression (in other words, lots of extra capacitors), the actions of one device may affect another. But they do tend to be more immune to house current fluctuations than small homemade or purchased power supplies. With regulators on each project, moreover, you can provide more immunity to spikes and fluctuations. They are truly 'brute force' circuits.

4. Large regulated power supplies are highly stable, but expensive. They are capable of feeding a whole range of boards, less house current outlets are needed, and the level of regulation is usually substantial enough to prevent fluctuations at the board level. However, onboard filtering is still necessary to prevent interaction among external devices.

The circuit diagrams that follow present a simple, unregulated, positive power supply; a simple, unregulated, bipolar power supply; a regulated five-volt power supply; a regulated dual-voltage (+5 and +12 volts) power supply; a regulated bipolar (+5 and -5 volts) power supply; a regulated four-voltage (+12, +5, -5 and -12 volts) supply, and last (but by no means least) the design of the power supply (+12, +5, and -5 volts) used in the TRS-80. All these supplies can use the transformer / rectifier 'power supply' sold for the TRS-80 as their source.

Power Suppies

Digital electronic circuits constructed by hand can perform as well as neatly-laid-out commercial circuits. In some ways, though, these circuits have to be designed better than commercial ones, because professionally etched boards are usually designed with careful consideration given to signal paths. Wire-wrapping or soldering, on the other hand, can look like a rat's nest and sometimes act that way.

Most important: always use bypass capacitors in your projects. These are capacitors with a value of about 100 nanofarads (0.1 microfarads), ceramic discs or dipped mylar, attached between +5 volts and ground. These are *physically* placed near their respective integrated circuits. When I finish wire wrapping a circuit, I give it a quick test to make sure the wires are connected properly and the circuit behaves normally (barring occasional crashes). Then I attach a 100-nanofarad bypass capacitor between the positive power supply and ground, directly between the wire-wrap pins carrying the power.

Secondly: add termination resistors to the data lines whenever more than one project is connected to the computer. Termination resistors act as electronic clamps, holding the lines steady as the signals sweep through. These eliminate random noise, as well as signal 'overshoot', caused by capacitance introduced by the wires themselves. If you have an expansion interface of the new breed (no buffered cable), termination resistors are already in place. They are also standard with the *LNW* and *Microtek* interfaces (though I recommend doubling the value suggested by *LNW*, to at least 470 ohms and 1,000 ohms).

The simplest addition of termination resistors involves connecting a 1,000 ohm resistor from each data line to ground. To ensure even better signal clarity (and also to maintain the 'high' level the computer normally sees on its lines), also attach a 470 ohm resistor from each data line to +5 volts. In all, then, eight resistors will be needed for each project you add.

Finally, do not skimp on the power supply. Generally you will see a 2,200-microfarad capacitor followed by a regulator, a 470-microfarad capacitor and a 100-nanofarad capacitor. This is the absolute minimum configuration for a working power supply. If you have the room, increase the value of the first capacitor to 4,700 or 10,000 microfarads, and place a 100-nanofarad capacitor between input and ground physically near the voltage regulator.



+/-12, +/-5 volt regulated power supply.



TRS-80 transformer adaptor and supply.



TRS-80 power supply.

Those Colors: What They Mean and How to Read Them

The color codes used for resistors, capacitors, and other parts are brought to you by the same folks that brought you phrases like 10W-40 and RS-232C: the standards-setting powers of the engineering industry. It becomes an international shorthand.

The colors are black, brown, red, orange, yellow, green, blue, purple, grey and white. If you can't immediately remember that, then pick up a piece of multi-conductor 'rainbow' cable. The colors are all there in the same order. The table below presents the color codes and how they can be read on the bodies of resistors, capacitors, and diodes.

```
-----------------------------------------
  FIRST AND SECOND    THIRD COLOR BAND
  COLOR BANDS
-----------------------------------------
  BLACK    0          BLACK    0
  BROWN    1          BROWN    X 10
  RED      2          RED      X 100
  ORANGE   3          ORANGE   X 1000
  YELLOW   4          YELLOW   X 10,000
  GREEN    5          GREEN    X 100,000
  BLUE     6          BLUE     X 1,000,000
  VIOLET   7          SILVER     100
  GRAY     8          GOLD       10
  WHITE    9
-----------------------------------------
   FORTH COLOR BAND IS THE TOLERANCE
  GOLD = 5%   SILVER = 10%   NONE = 20%
-----------------------------------------
```

What do these values mean? Resistance is a kind of objection to electron flow, measured in ohms (pronounced with a long O). The abbreviation is a Greek omega (Ω). Thousands of ohms are kilo-ohms, or just kilohms, and abbreviated K (k in Europe). Millions of ohms are megohms, abbreviated simple M. The ability of a resistor to withstand electrical current is measured in Watts (W). Most computer work is done with 1/4 Watt resistors.

For resistors without color bands, the values are stamped on using R (instead of omega) for ohms, K and M.

Capacitance is the inclination of a non-conducting object to store an electrical charge, measured in Farads. The abbreviation is a capital F. Since this is a very large amount of capacitance, real work is generally done in millionths of Farads, or microfarads (mF), and millionths of millionths of Farads, called picofarads (pF). Since many of the more popular capacitance ranges for computer work fall between these two figures, the abbrevia0tion for thousandths of millionths of Farads, or nanofarads (nF) is common in Europe. The ability of a capacitor to withstand voltage is measured in voltage tolerance (V).

Capacitance is usually printed on the capacitor in mF; color bands are rare. Picofarads are marked "p'; the absence of an abbreviation indicates microfarads. Note that these capacitor 'base values' are equivalent: 18=20, 27=30, 39=40, 47=50.

Abbreviations and Conventions Used in this Book

A0-A15	Computer address lines.
C	A capacitor, specified in the parts list; positive and negative sides are marked.
CLK	Clock, usually a flip-flop input.
CLR	Clear, usually to flip-flop or latch.
CR	A diode, Radio Shack schematic reference.
D	A diode, specified in the parts list.
D0-D7	Computer data lines.
F	Farad; used only as part of mF, uF, pF.
GND	Common computer ground.
K	A relay, specified in the parts list.
-K	Resistance value suffix = x 1000.
LED	A light-emitting diode, specified in the parts list.
m-	Capacitance prefix for x 0.000 001.
M	A motor, specified in the parts list.
-M	Resistance value suffix = x 1,000,000.
MHz	Megahertz (million cycles per second).
p-	Capacitance prefix = x 0.000 000 000 001
P	Piggybacked integrated circuit.
PRE	Preset, usually to flip-flop or latch.
Q	Transistor, specified in the parts list.
Q	Flip-flop or latch output.
R	A resistor, specified in the parts list.
S	A switch, specified in the parts list.
T	Transformer, specified in the parts list.
u-	Capacitance prefix for x 0.000 001.
U	Integrated circuit (LNW references only).
Vcc	Collector-supply voltage, that is, the 'five-volt supply'.
W	Watt; resistor power reference.
X	DIP shunt or jumper, R/Shack reference.
X	Crystal oscillator.
Y	Demultiplexer output signal.
Z	An integrated circuit, specified in the parts list.
*	Used in text references for 'not', in place of a horizontal bar across the top of the abbreviation.
0V	Ground, zero-level, or center-ground.
+5V	Five-volt positive regulated power supply, the 'Five volt supply'.
-5V	5-volt negative regulated power supply.
+12V	12-volt positive regulated power supply.
117V	House current, 105-120 volts AC.

BASIC commands; Z-80 mnemonics and opcodes; CPU and other schematic signals are printed in UPPER CASE letters. Hexadecimal numbering is printed in **BOLD** letters.

1

Getting Inside

A TRS-80 is the proverbial black box. It's the first mass-marketed personal computer that was intended for simple home and business use. As far as retail sales are concerned – whether it's a car, a hi fi, or instant pudding – thinking of it as a black box is just fine. "Yes, it's a complete computer with a keyboard unit, video display, and cassette storage."

To have this small computer work to even a fraction of its potential, though, you've got to have the power to control it. As with driving a fine automobile, that power comes with understanding, comes with being able to look through and into the box, comes with keeping it carefully tuned and customized so that it can respond to your wishes.

In this Chapter we'll open the electronic black box a little at a time. If this is all new to you, prepare for some exciting finds inside this box; if not, then follow along and discover just how much you've learned about microprocessors in their own age.

What You See

The main computer unit is in a small case looking something like a typewriter that has lost its carriage. There are 53 keys in a typewriter style layout, and perhaps on your unit a numeric keypad to the right. Connections on the back are marked *Power, Video,* and *Tape,* along with an on/off switch.

The unit is entirely silent. It is electronic in conception and execution.

A power supply lowers and isolates the 120-volt household supply to approximately one-seventh that value, and that feeds the keyboard unit. An ordinary cassette player is cabled in, and a partly disemboweled television set plugs in place, serving as a crude video monitor.

The designers of the TRS-80 struggled with, and won, the battle of familiarity. Televisions, cassette recorders, and typewriters are among the most ordinary of home or office appliances. But by winning this battle of familiarity, the designers also clearly set themselves up to lose the battle of reliability (more on that later).

Let's first take a look at some of the things the computer does, and then very generally try to discover how and with what the machine does them.

When you power up your computer, you expect to be able to communicate with it. Unlike a television, it does not entertain, but rather evaluates and responds with an electronic psyche. If it were not capable of using a human-like language, we would be forced to use the machine's language. But since it will be asked to accomplish human tasks, we will demand that it speak a human sort of language – BASIC (Beginners' All-purpose Symbolic Instruction Code). BASIC has grown since its humble but inspired beginnings at Dartmouth College into a formidable tool capable of rocking other standard languages off their computational pedestals. If you have been using your TRS-80's BASIC, you know its fluidity. But it does not work alone.

The BASIC that is in the TRS-80 works hand-in-hand with the electronics to produce a video display for us to read, and to examine a keyboard for us to type on. The keyboard gives

input to the computer, the video display shows output from the computer. Input and output are grouped together in computer terms, and are collectively called *I/O*. The tape recorder, which saves and loads computer programs, would also be called I/O.

Forget the claims that the TRS-80 computer can do what this-or-that state-of-the-art computer could do five years ago. Maybe so, but it really can't. Because it isn't built like a piece of office furniture. Because it doesn't act, work, or 'think' the same. No matter how you paint it or pad it, a four cylinder sportscar will never be a luxury V-8 sedan. And Burger King is not a candidate for the four-star list. But they can do *what* they can do as well or better because of the simple, direct, streamlined nature of their operation and conception. Turn away the question of value judgment, and you discover that – considering portability, cost, ease of maintenance, accessibility and vastness of the software domain – the TRS-80 is probably a dimension *better* than that recently demised state-of-the-art dinosaur.

That about covers what we can say about the minimal TRS-80 setup – a keyboard computer unit with I/O. Before popping off the cover, let's name some of the rest of the I/O devices that can be hooked up to the machine. Those might include:

An Expansion Box.
This attachment expands not only the internal capacity of the computer, but also forms an electronic saddle, permitting other devices to ride on the back of the keyboard unit.

A Printer.
Obviously, an attachment to provide a permanent record of the machinations of the TRS-80.

A Diskette Drive.
A place to store information and programs when the computer is turned off; it is very like the cassette player, except that it is speedier and can be accessed differently. More on that later.

Voice Input/Output.
An ability to speak and be spoken to on the part of the computer. This is one of the experimental options.

Telephone Communications.
Communications with other computers, similar or different, nearby or across the world.

Control Centers.
The power to change, activate or extinguish electrically-powered equipment throughout a home or office.

There are more devices which might be considered, including clocks to tell the time of day, little circuits to create sound effects and music, even other computers used as 'slaves'. In fact, where electrically controlled equipment is involved, almost anything can be attached directly or indirectly to the TRS-80.

Hesitation

When you open the computer's case, you'll see an enormous amount of electronic circuitry. Before you open it though, you should have an idea why there are so many *integrated circuits* and circuit board *traces* connecting them.

We live in an analog world. We judge size or volume or loudness not by how big or full or loud it *is*, but by how big or full or loud it seems in relation to something else, even if that 'something else' is merely what we are used to hearing in our normal world.

In other words, all our evaluations are made by analogy. "How big is it?" "As big as a basketball!" "Is she pretty?" "Pretty as a picture!" "Is it far?" "About a stone's throw from the corner." Our cliches are built on comparison or analogy. Ideally, then, we might like to build a machine that work for us in our own terms . . .

"Machine!"

"Duh, yessir, sir."

"Add fourteen and thirty-seven, machine!"

"Yup, yup. Lessee. Hmmm, fourteen is this big. And thirty-seven is this big. That makes a number *this* big. . . . . Sir?"

"Yes, machine?"

"That's as much as thirty-seven and fourteen, sir! Looks just like fifty-one, sir."

"Thank you, machine."

This computer has a rather limited voice capacity, but what it did inside itself was electronically quite sophisticated. It took in a value and transformed it into an electrical voltage of fourteen units, stored it, accepted a

second value and transformed it into a voltage of thirty-seven units. Then it added the voltages together; the resulting voltage worked out to be equivalent to a value the size of fifty-one voltage units.

The manufacturers of the real world might be able to create electronic parts with this kind of accuracy, but chances are that these parts wouldn't be cheap. A TRS-80 made with them would be worth more than the previously mentioned V-8 auto.

So in the stone age of computer activity, it was decided that the simplest level of evaluations would have to be made. A low voltage or 'off' condition would be made equivalent to zero; a high voltage or 'on' condition would be set equal to one. That was it. All calculations would have to be done with ones and zeros – the binary system.

You've probably heard of, and perhaps used, binary numbers and there will be more on this system later in the book. But the point is that you can well imagine that doing work with real, human numbers means quite a basketful of the individual ones and zeros. Which means, consequently, many separate signal lines to carry those groups of numbers.

So Open it Already!

Turn the power off to your TRS-80 keyboard unit and flip over on its front. Carefully undo the cabinet, noting the different sizes of screws used to fasten it together. Holding the entire computer firmly together, again flip it on its back. Remove the top cover. Gently lift the keyboard forward and remove the five or six plastic spacers underneath it; in later 80's, one of these will be solid and the rest flexible. Note their positions. Now set the keyboard back, lift the electronics out of the case and place it on a spacious work surface.

Time out. As you make changes to your TRS-80, add memory and the like, you will be opening the case many times. Two things might happen. First, the keyboard grommets will get lost. Their purpose is twofold: to prevent the keyboard from shorting against the main circuit card, and to cushion delicate parts against a constant onslaught of none too gentle typing. If you lose them, cut new ones out of bottle corks. They'll work just fine.

Another more difficult problem is the keyboard cable itself. This is a band of springy copper leads covered with white plastic located



Photo 1-1. The TRS-80 opened and spread out.



Photo 1-2. Closeup of keyboard cable area.

Complete TRS-80 spread out for cable replacement. Other visible changes include Level I/II switch on keyboard (bottom right of keyboard), new Level II interconnect cable (center), additional keyboard socket (top left), and external reset switch connector (bottom left).

at the bottom left of the keyboard. It electrically, and physically, attaches the keyboard to the main circuit board. Very subtle cracks can occur in the copper after about a half-dozen flexes. Symptoms can be lost letters or odd combinations of letters, a system constantly crashing or otherwise acting up, constantly repeating letters, or complete lockup of the keyboard. *Avoid flexing this cable quickly or bending it sharply.* Later we'll replace this cable with something better, but for the moment be gentle with it.

Now back to the machine. Spread the two sections connected by the keyboard cable out in front of you. The keyboard and the top of the circuit card will now be visible. The Central Processing Unit is a single integrated circuit, the Z-80; it is to the far left in the photograph on this page. The power supply is the block of 'heavy equipment' at the back; the two small potentiometers regulate the voltage to within five percent, so keep clear of these controls. The eight memory circuits are in a row near the power section, and the language memory (Level I and newer Level II BASIC) is located in the center of the circuit card. On most Level II units, this language required three integrated circuits, and so these were placed on a separate two-by-three-inch card taped to the main board and connected with a 24-conductor cable. *Don't be tempted to remove that cable, yet!*

A group of circuits to the bottom left in the photograph hold the video image. Two important parts are socketed on the board; these are marked Z3 and Z71, and they are programmable shorting jumpers. What makes them programmable is the fact that with a gouging tool you can break the connections; not very subtle, but it works. Their purposes are different – one selects the amount of memory available in the keyboard unit, and the other selects which of the standard languages (Level I or Level II BASIC) is in use.

At the top left, the video and cassette output is controlled. Two small potentiometers on that side of the board position the video image on the screen, so if you received a TRS with its image off center, twiddling these will straighten it out. The



Figure 1-1. Z-80 block diagram from Zilog.

remainder of the board is dedicated to controlling the complex electronic traffic.

One last item is the edge card connector, which can be viewed at the top right hand side of the photograph. Through this connector, the TRS-80 may speak to the outside world. Much more on that connector later in this book.

On the keyboard itself there are a few circuits. Their job is to assist the Central Processing Unit (CPU) in determining which key is pressed. These circuits are sometimes remarkably sensitive; there will be more about these later.

Put it Back

Become familiar with the layout of this board, as it will assist you in locating work or repair areas. Functions of the computer parts are generally grouped together, so modifications will usually be restricted to a compact area of the board. Once you have a good idea of where everything is, put the keyboard unit back together carefully.

To really get to understand your machine you will want to obtain, either off the shelf at Radio Shack, from a Repair Center, or 'National Parts', the following manuals:

> *TRS-80 Micro Computer Technical Reference Handbook.* Catalog No. 26-2103.
>
> *TRSDOS & Disk BASIC Reference Manual.* Catalog No. 26-2104.
>
> Printer Cable Service/Installation Manual (Order).
>
> Expansion Interface Service Manual (Order). Make sure this includes the FD1771 disk controller appendix from Western Digital.
>
> 16K RAM Expansion Service Manual and Addenda (Order).
>
> *TTL Databook* (National Semiconductor). Catalog No. 62-1370. This may not be stocked anymore; if so you can order it from National Semiconductor direct.
>
> And finally, a Z80-CPU / *Z80A-CPU Technical Manual* should be ordered from Zilog, Inc., 10340 Bubb Road, Cupertino, CA 95014. It costs $7.50.

These references will not only help you to make the modifications suggested in this book, but also to understand the operation of the computer, bend it to your wishes, and repair it if it fails. Additional references which you will find valuable are listed in Appendix II.

The Hidden Insides

It's not much of a mystery to TRS-80 users that all that hardware is controlled by software. That's one of the first things you learn. But it's also as simplistic as saying that the driver makes the car go, and just as misleading. Complete computers are called 'turnkey' systems because they imply simple, appliance-level setup and use. But a customized TRS-80 suggests something more, and with that 'something more' comes a requirement to have a better handle on hardware and software.

Let's define some terms. The TRS-80 is a personal computer, which is a popular way of saying a small, microprocessor-controlled, turnkey computer. The microprocessor, a Z-80, is a complicated, general-purpose, electronic switching center capable of accepting, changing, sending, and re-routing a complex array of electronic signals.

Both the TRS-80 as a whole, and the Z-80 in microcosm, have something called *architecture.* Architecture is the overall dimension by which these devices define their electronic space. Put simply, it is 'how they work'. As with all human work, this involves defining tasks and their order, executing those tasks, and producing a result.

In the Z-80, the architecture involves accepting electronic signal groups called *instructions*, decoding them into internal activities, and executing those activities. An arithmetic logic unit (ALU) performs simple mathematical functions, internal memory cells called *registers* hold signal information to be acted upon, and an internal *bus* controls the flow of electronic traffic. The order of entering signals is identified by means of an *address*, which

identifies a fixed numbered slot in the Z-80's electronic universe.

In the block diagram of this activity, shown opposite, note the terms '8-bit data bus' and '16-bit address bus'. The Z-80 is an integrated circuit with 40 external connections. The number 40 is arbitrary, chosen because manufacturing precision is currently limited to a physical 'package' of that size. That precision is also central to why the binary system is used, as mentioned earlier.

From the viewpoint of ten-fingered humans, it would be simpler to do our computing in familiar decimal form. As with the uninspired conversation between human and computer presented earlier, different levels of voltage could be used. But such levels of precision are difficult to produce commercially and impossible to diagnose when they fail.

That is the practical origin of the simple one/zero, on/off, true-false system of numbering used by the computer. To discover how these signals are arranged, we now turn back to the Z-80 itself and the 40 external pin connections. Information put into and called for out of the processor is called *data*, with a simple small value of zero. Any reasonable number of pins could have been dedicated to accepting data, but, based on the amount of work the processor had to do, eight of the 40 pins were assigned. This is the 8-bit (binary digit) data bus.



Figure 1-2. TRS-80 memory map.

Likewise, there is the need to determine the order in which the processor is to do its work. In order to move from command to command, it identifies the order of those commands by their position, or *address*. Sixteen of the Z-80's pins are used to specify a number from 0000 0000 0000 0000 to 1111 1111 1111 1111.

When the power is turned on, this *address bus* switches to all zeros. The computer fetches its first command along the *data bus* from that all-zero location. It executes the instruction, fetches the next, and the next, and the next.

There's certainly more to this, but very basically that's the architecture of a microprocessor. Address lines for locations and order, and data lines for information. Now we'll turn to the TRS-80 and its architecture.

The TRS-80 contains the microprocessor, which is the Central Processing Unit (CPU) of the computer. Along its address bus is found the computer's internal information and instruction storage block – its *memory.* Also along this bus will be found video memory, a block which is reserved to display information to us on the screen; a keyboard, which is given its own set of addresses; the BASIC language; some unused areas; and single memory slots in which are housed windows to the cassette recorder, disk drives, printer and so forth.

This hardware is already familiar, so let's look at the hidden insides, the software. The BASIC system is found in permanent, Read-Only Memory (ROM). It consists of several major sections:

- A keyboard scanning routine to discover and interpret activities at the keyboard.
- A video processing routine which presents and updates the monitor information.
- Input/output controls for saving and loading program material and operating a printer.
- An interpreter capable of transforming the 'English' words which make up the BASIC we know, and determining what computational actions should be taken.
- Memory-management systems which apportion the computer's available memory into blocks which will not conflict.
- Arithmetic- and text-processing subroutines which can perform calculations and operations on numbers and alphanumeric characters.

Overall, the Level II BASIC language requires more than 12,000 separate 8-bit groups, known as *bytes*, to perform its work.

At the end of this Chapter is a detailed look at how the software operates from the time the machine is switched on to the time you read MEMORY SIZE? on the screen. In summary, that software disables any signals which might interrupt its operation, turns off the cassette relay and clears data from that output, restores the video screen to 64 characters per line, and sets up a block of memory for use by BASIC programs. A disk drive is searched for, and if one is found, a group of procedures are initiated in order that the disk program may take control of the TRS-80.

If no disk drive is found, the screen is cleared with blanks, the MEMORY SIZE? prompt is displayed, and a keyboard scanning process is begun. A valid response to that question is accepted, and, if necessary the entire bank of memory is tested. Error messages are updated on the video screen as needed. Finally, the memory size and available room for text strings is created, the READY prompt is displayed, and control of the TRS-80 is given to the user.

Power-Up Routines

The initialization routine of the TRS-80 is a complicated and very interesting aspect of the computer. It must, of course, set up all the parameters that will be used by BASIC programs, but it also conducts a series of tests and makes hardware adjustments to the device.

It double checks to assure the proper operation of memory, and to be certain that the parameters needed for proper operation of programs will be present. This section will take a look at the initialization process.

Here are the first few instructions:

```
0000                     ORG      0000H
0000     F3              DI
0001     AF              XOR      A
0002     C3 74 06        JP       0674H
```

At power-up, the Z-80 chip 'homes in' on address 0000, and begins its execution there. The first action is significant: DI (Disable Interrupt) keeps the clock 'heartbeat', generated by the expansion interface, from disturbing any actions of the computer – especially important, since the necessary software for handling that interrupt request is not in ROM, but rather a part of the disk BASIC, or what is also offered as 'Level III' BASIC.

So the interrupt is masked out. XOR A is the process of 'exclusive-ORing' the accumulator. Exclusive OR is a logical operation which states: of two elements, either may be zero or one, but not both. Thus, whatever is present in the accumulator is XORed with itself. Since each bit is identical with its exclusive-OR partner, each bit will be set to zero. This effectively clears the accumulator, readying it for processes to come.

The final instruction of the group, **JP 0674**, gets out of the way of the Z-80's low memory, for it is in this area that the chip's restart codes – very frequently used subroutines – are found. Going on:

```
0674     D3 FF           OUT      (0FFH),A
0676     21 D2 06        LD       HL,06D2H
0679     11 00 40        LD       DE,4000H
067C     01 36 00        LD       BC,0036H
067F     ED B0           LDIR
0681     3D              DEC      A
0682     3D              DEC      A
0683     20 F1           JR       NZ,0676H
```

After the jump to **0674**, the routine resets the output flip-flop at port FF (255 decimal). This flip-flop controls both cassette functions and the 32/64 character video, and by outputting the value in A (0, since it was exclusive-ORed earlier), the cassette will be off, no data will be present at its input, and video will come up normally.

Following this is an interesting (and encouraging) piece of code. Using the Z-80's powerful block move command LDIR, 54 bytes stored at address **06D2** are transferred to the RAM address area starting at **4000**. These are the most important pieces of information the TRS-80 must have, so the writers of this program took great care to assure that this transfer would be certain. The LDIR instruction itself takes data stored at an address specified by register pair HL (in this case, **06D2**), and moves a block whose length is specified by register pair BC (36 hex, or 54 decimal), to the location indicated by register pair DE (4000).

The interesting part is found just below. The value in A (0) is decremented twice (to FE), and the identical transfer instruction is repeated. This goes on until it reaches zero again, a total of 128 times! We may draw the conclusion that the Z-80 chip probably reaches full power and begins operating before memory gets to the point where it can reliably accept data . . . therefore, the instruction is repeated for a period of approximately 15 milliseconds.

Now a portion of RAM is cleared to zero with the following few commands:

```
0685     06 27           LD       B,27H
0687     12              LD       (DE),A
0688     13              INC      DE
0689     10 FC           DJNZ     0687H
```

Recall that after the previous setup process, the accumulator again contains zero. Here a block of RAM specified by the DE register (essentially where we left off) is loaded with zero. Using the fast DJNZ (decrement B, branch if not zero) instruction, 39 bytes are fixed at zero.

A few instructions follow that are very significant at power-up. Address 3840 contains the keyboard row where the BREAK key sits. It is connected to data line 4; thus the instruction AND 04 checks to see if it is held down. If it is not being held down, the result of the AND instruction will not be zero . . . and a jump to address 0075 will be made. This is why expansion interface owners without disks must press the break key at power-up:

```
0688      3A 40 38           LD      A,(3840H)
068E      E6 04              AND     04
0690      C2 75 00           JP      NZ,0075H
```

How does the TRS-80 find out that a disk drive is in fact connected to the interface? The answer to that – and the reason that the computer 'hangs up' when an expansion interface is connected without a disk – is found in the next few bytes of code:

```
0693      31 7D 40           LD      SP,407DH
0686      3A EC 37           LD      A,(37ECH)
0699      3C                 INC     A
069A      FE 02              CP      02
069C      DA 75 00           JP      C,0075H
```

The stack pointer is set at 407D for use by potential future programs; it is out of the way of all the BASIC pointers set up in the first data transfer, an obvious but important action.

The accumulator is then loaded with the contents of memory location 37EC. There is no 'memory' per se at address 37EC; it is instead an instance of 'memory mapping'. That is, when this memory cell is read, a signal is sent to the expansion interface. This signal strobes information from the Floppy Disk Controller (FDC) to the TRS-80. What will it find?

If no expansion interface is connected, there is no signal to strobe. Hence, the value will be floating, not pulled to ground (zero) on any bit. The computer sees all bits apparently 'high' at this location, and interprets it as binary 1111 1111, that is, hex FF.

The next instruction increments the accumulator, in this case resulting in FF plus 1, or 00. In the following intruction this value is compared to 2. A compare (in effect a subtraction, with no 'result') will cause the carry flag to be set, since 0 minus 2 is negative. (Note: Why compare with 02? Why not just 01, as a carry would still be generated? My suspicion is that it is possible for those data lines to 'float' in the low state. In that case the CPU would 'see' 0000 0000, with the INC A instruction resulting in a value of 01 – which is still incorrect. So a compare with 02 guarantees the presence or absence of the disk controller.)

Once the carry flag has been set, the instruction **JP C,0075** would be executed, sending the program to address 0075. For the moment, however, let's assume that an expansion interface is connected to the TRS-80.

The FDC, when queried by the command **LD A,(37ECH)**, will respond with 80. Incremented by one it becomes 81, and comparing it with 02 generates no carry. The **JP C,0075H** is thus ignored, and the program simply goes on to find:

```
069F      3E 01              LD      A,1
06A1      32 E1 37           LD      (37E1H),A
06A4      21 EC 37           LD      HL,37ECH
06A7      11 EF 37           LD      DE,37EFH
06AA      36 03              LD      (HL),3
```

The accumulator is set to 1, and address 37E1 is made to accept the contents of the accumulator. Again, 37E1 is a location memory mapped in the expansion interface. This code starts the disk drives rotating (or keeps them rotating), and selects drive zero.

That done, it loads HL with the disk controller address (37EC) and sends out a 'restore' command, which tells the controller to move to track zero. Thus, the data will come from drive zero and track zero. Register DE is prepared by loading it with the disk's data address, 37EF. Now:

```
06AC      01 00 00           LD      BC,0000
06AF      CD 60 00           CALL    0060H
0060                         ORG     0060H
0060      0B                 DEC     BC
0061      78                 LD      A,B
0062      B1                 OR      C
0063      20 FB              JR      NZ,0060H
0065      C9                 RET
```

This is a short but very useful subroutine. You may in fact want to call this yourself from time to time. Found at address 0060 is a simple delay loop; load the BC register pair (as is done just before the CALL instruction), and it is decremented and tested until it reaches zero. When it finally reaches zero, a return instruction sends the Z-80 back to the main program flow.

Why a delay? Merely to give the disk drive time to come up to speed, obvious but very

important. Moving ahead with this branch of the program:

```
0682                        ORG     0682H
0682      C8 46             8IT     0,(HL)
0684      20 FC             JR      NZ,0682H
```

This is a loop which waits until the disk control chip says, "Okay, disk is up to speed and everything looks pretty good", and sends along a zero. The program loop tests this bit until it receives a zero. It is this loop which is maddening to you expansion interface owners who have no disk drive. Like all the previous memory-mapped addresses, 37EC will never have that zero. If a disk is present and all is well, the loop will have found the acknowledging zero sent by the FDC:

```
0686      AF                XOR     A
0687      32 EE 37          LO      (37EEH),A
068A      01 00 42          LO      8C,4200H
0680      3E 8C             LO      A,8CH
06BF      77                LD      (HL),A
06C0      C8 4E             8IT     1,(HL)
06C2      28 FC             JR      NZ,06C0H
06C4      1A                LO      A,(0E)
06C5      02                LO      (8C),A
06C6      0C                INC     C
06C7      20 F7             JR      NZ,06C0H
```

The accumulator is cleared again, and the BC register is set to 4200. This will be an area of RAM set aside for disk use. 37EE is loaded with 0, and 37EC is loaded with byte 8C. This selects sector 0, and sets the read condition. Thus, having previously been set to drive zero, track zero, it will now read sector zero. The accumulator will look for the incoming bytes in the memory location specified by the DE register pair (37EF). This is the memory-mapped location through which the actual data will flow.

The accumulator picks up the data from DE, stores it in the RAM memory location indicated by BC (4200); the next instruction increments register C so that location 4201 is ready. The program loops back, waits for another message from the FDC, picks up another byte, and stores it. When register C finally reaches zero, the pointer will again contain 4200, and the loop terminates. Then:

```
06C9      C3 00 42          JP      4200H
```

Here the disk system takes over completely. As you recall, starting at 4200, data from the disk has been stored. By jumping to that location, the program direction is wrested from ROM and given to the first 256 bytes of the disk system bootstrap program.

Here, then, is a quick review of the activity so far: Interrupts are disabled, cassette is turned off and data are cleared from that output, video is restored to normal, and significant pointers for BASIC program operation are set up. A disk drive is searched for and if one is found, a group of procedures is initiated in order to transfer control of the TRS-80 to these disk instructions.

A series of control signals and acknowledgments is exchanged between the floppy disk controller and the CPU, a page (256 bytes) of data is poured into a RAM buffer area, and program control is given over to this new series of commands.

If a disk drive is not found, or if the break key is held down during power-up, control is transferred to address 0075. At this point it should be noted that the 'reset' button on the TRS-80 is a non-maskable interrupt, that is, the only interrupt which the DI (Disable Interrupt) command first executed by the TRS-80 cannot mask out. When pressed, the reset button goes directly to address 0066, following a much shorter series of instructions reminiscent of the power-up routine.

Because it is likely most important RAM pointers are still intact, this sequence does not reset them:

```
0066                        ORG     0066H
0066      31 00 06          LO      SP,0600H
0069      3A EC 37          LO      A,(37ECH)
006C      3C                INC     A
0060      FE 02             CP      02
006F      02 00 00          JP      NC,0000
0072      C2 CC 06          JP      06CCH
```

This group of instructions sets up the stack pointer, checks for the presence of a disk drive, and jumps to the complete initialization routine (reboot) if it finds one. If none is present, it goes to the READY sequence beginning at address 06CC.

Now let us return to the initialization program flow we have been following, which is found at 0075:

```
0075                        ORG     0075H
0075      11 80 40          LO      0E,4080H
0078      21 F7 18          LO      HL,18F7H
007B      01 27 00          LO      8C,0027H
007E      E0 80             LDIR
```

Using the LDIR instruction described earlier, a block of information located at 18F7 is transferred to RAM beginning at 4080. These bytes describe ports in use, error storage, INKEY$ information, and so forth, as needed in the general operation of Level II BASIC (see Chapter 2).

A few specific addresses are delineated, and a large group of RAM bytes is then prepared. These jump to the familiar '?L3 ERROR' message because they are disk commands not available to Level II, yet patch points are prepared for them. The result of the following program statements is to fill addresses **4152 to 41A5** with the direction **JP 012D**.

```
008E     11 20 01        LO      0E,0120H
0091     06 1C           LO      B,1CH
0093     21 52 41        LO      HL,4152H
0D96     36 C3           LO      (HL),0C3H
0098     23              INC     HL
0099     73              LO      (HL),E
009A     23              INC     HL
009B     72              LO      (HL),0
009C     23              INC     HL
0090     10 F7           OJNZ    0096H
```

Another group of ROM 'breakout' points follows; they all become returns to the main program flow. But notice something interesting about them – three bytes are set aside, but only one is filled with the return instruction (C9). This means that a jump command could be placed there. Let's first look at the series of instructions, then examine the possible benefits of changing them:

```
0D9F     06 15           LD      B,15H
00A1     36 C9           LO      (HL),0C9H
00A3     23              INC     HL
00A4     23              INC     HL
00A5     23              INC     HL
00A6     10 F9           OJNZ    00A1H
```

If we wanted to break into the BASIC operating system, this area of RAM is one place in which we could do it. Most of these are error codes of one kind or another. We could 'rescue' a program from displaying an error message, and halting, by patching in one of our own routines. If our routine were located at **5000**, for example, the C9 instruction (followed by two unused bytes) could be replaced with a **JP 5000** command, which needs all three byte positions: **C3 00 50**. Essentially, the authors of Level II BASIC provided many areas for expansion.

Now let's move on. BASIC programs begin at address **42E9**. A pointer to that beginning is found as a zero at address **42E8**. The next instruction sets that in place:

```
00A8     21 E8 42        LO      HL,42E8H
00AB     70              LO      (HL),B
```

The stack pointer is delineated, and a call is made to **1B8F**, a subroutine to turn off or reset various devices, including the printer and cassette player. It is in part redundant, but a double-check is often worthwhile.

```
00AC     31 FB 41        LO      SP,41FBH
00AF     C0 8F 1B        CALL    1B8FH
00B2     C0 C9 01        CALL    01C9H
```

The call to **01C9** results in the screen being cleared and the cursor being placed at position 0. Finally, 'MEMORY SIZE?' appears:

```
0085     21 05 01        LO      HL,0105H
008B     C0 A7 2B        CALL    2BA7H
008B     C0 B3 1B        CALL    1BB3H
```

At address **0105** is a block of ASCII bytes which spell out MEMORY SIZE. The subroutine starting at **28A7** displays the string of data at the present location of the cursor, a byte at a time, until it finds a byte in the message whose value is **00**. This terminates the display and advances the cursor. The call to **1BB3** is identical to the BASIC INPUT command, in that it displays the question mark and cursor, and halts for keyboard input.

If the keyboard input is the BREAK key, a carry is generated, and the program skips back to MEMORY SIZE and displays it again, waiting for keyboard input. The instruction **RST 10** (ReSTart at **0010**) follows, which is the quickest way of calling a routine to locate the first character of an input. If one is found, the result of an OR instruction will not be zero. Here are the instructions that perform those functions:

```
00BE     38 F5           JR      C,0085H
00C0     07              RST     10H
00C1     87              OR      A
00C2     20 12           JR      NZ,0006H
```

What if, on the other hand, there was no entry other than the ENTER key? You have no doubt noticed a slight pause in the action when you do not specifically set the memory size. Here's a look at that code:

```
00C4     21 4C 43        LO      HL,434CH
00C7     23              INC     HL
00C8     7C              LO      A,H
00C9     B5              OR      L
00CA     28 1B           JR      Z,00E7H
0DCC     7E              LD      A,(HL)
00C0     47              LO      8,A
00CE     2F              CPL
00CF     77              LO      (HL),A
0000     8E              CP      (HL)
0001     70              LO      (HL),B
0002     28 F3           JR      Z,00C7H
0004     18 11           JR      00E7H
```

For the moment we will start at the instruction LD A,(HL). HL contains the address of a byte of RAM memory, the contents of which are placed in the accumulator. From the accumulator, they are also saved in the B register. The accumulator is complemented, which inverts all the ones to zeros and all the zeros to ones. This complemented value is then placed in the

memory location still specified by HL. The accumulator is compared with what has been placed in HL.

What, you ask? But this value was just placed in memory, why compare it? Because – and this is a very elegant piece of writing – if it does not compare:

1. The memory location is bad and only the block of memory below it should be used to be safe.

2. Or, this is the end of memory.

If this is good memory, then, the test for zero passes, the contents saved in register B are returned to memory, and the program loops back, incrementing HL to the next potential memory location.

We did skip a few instructions back there. They become important only after the first loop is complete. These commands OR the contents of H and L; when the result is zero, we are at address 0000 – full 48k memory has been found, and the test is complete.

Here's what we would find, alternatively, if we entered some value (or other characters) in response to MEMORY SIZE?:

```
00D6      CD 5A 1E            CALL     1E5AH
00D9      B7                  OR       A
00DA      C2 97 19            JP       NZ,1997H
00DD      EB                  EX       DE,HL
00DE      2B                  DEC      HL
00DF      3E BF               LD       A,BFH
00E1      46                  LD       B,(HL)
00E2      77                  LD       (HL),A
00E3      BE                  CP       (HL)
00E4      70                  LD       (HL),B
00E5      20 CE               JR       NZ,00B5H
```

The call to 1E5A checks for numeric input, and jumps to 1997 ('?SN ERROR'), if it is not numeric. If the input is properly numeric, then registers DE and HL are exchanged; this action puts DE (left off at the lowest usable memory location above pre-set RAM needed by BASIC) in HL, where it can be manipulated conveniently.

Memory size minus one is usable; memory size and above is protected. So HL is decremented before being tested, then it is tested (in a manner similar, but not identical, to that done earlier). If the memory test fails, it's back to displaying MEMORY SIZE? again.

We're not quite there yet, however, as the figure entered for memory size may be too small. BASIC needs a bit of room to work with, so DE is set to 4414, and the subtraction subroutine at RST 18 is called. If a carry is generated, we're shipped off to the '?OM ERROR' message found at 197A. Here's what it all looks like:

```
00E7      2B                  DEC      HL
00EB      11 14 44            LD       DE,4414H
00EB      DF                  RST      1BH
00EC      DA 7A 19            JP       C,197AH
```

A little more work is left to do. Recall that a value for available string space is set aside, and it is 50 bytes. Here is how it is done:

```
00EF      11 CE FF            LD       DE,0FFCEH
00F2      22 B1 40            LD       (40B1H),HL
00F5      19                  ADD      HL,DE
00F6      22 A0 40            LD       (40A0H),HL
```

Register pair DE is set up with FFCE, which, if you are not yet weary of manipulation of hex numbers, is the two's complement of 50 decimal. That is, when FFCE is added to 0000, the result is FFCE hex, or 50 decimal less than the original figure. Try it to see that it works. This bit of code saves the value for top of available memory in 40B1, adds register DE to it, and saves that result (memory size minus 50 bytes for string space) in address 40A0.

There follows:

```
00F9      CD 40 1B            CALL     1B40H
```

Here let me quote Roger Fuller, whose TRS-80 Supermap identifies this subroutine this way: Revelation 21:5 – "And behold . . . He shall make all things new."

This subroutine identifies and sets up all pointers necessary for the start of a BASIC program: Variables reset, previous program deleted, etc.

And now, the moment you've all been waiting for. Here it is:

```
00FC      21 11 01            LD       HL,0111H
00FF      CD A7 28            CALL     28A7H
0102      C3 19 1A            JP       1A19H
```

The call to 28A7, you may recall, displays a string of ASCII characters. The string displayed in this case is . . .

RADIO SHACK LEVEL II BASIC

The final instruction is a jump to 1A19, the address of the 'READY' display.

To summarize this last portion of the initialization routine: all BASIC pointers, disk error codes, and ROM return codes are set up, the screen is cleared, and the MEMORY SIZE prompt is displayed. A valid response to that question is accepted, and, if necessary, the entire bank of memory is tested. Error messages are generated as needed. Finally, the memory size and available room for strings is recorded, the READY prompt is displayed, and control of the TRS-80 is given to the user.

NOTES

2

Copacetic Comprehension

There will doubtless be a day when books like this will be unnecessary. Personal computers will probably develop into the appliance area, with programmers, hobbyists, hardware designers and language specialists present only in the distant background of the market. But between now and then we are all faced with being either frustated users or solderer-programmers, tailoring machines according to our personal demands.

To do this, certain skills are inevitably required. Among these are an understanding of non-decimal number systems, digital logic devices, machine-level languages, and a smattering of diagnostic sense. There are some fine books that cover all these topics (see Appendix II), so this chapter will only deal with them as far as needed to put this book to work. Among them are:

- Binary, decimal and hexadecimal number systems, how they arose, how and why they can be used, and where understanding them is essential.
- Common digital logic devices that appear in the TRS-80 and these projects, and how and where to use them.
- Some of the basic elements of machine language, and a few personal considerations on where it is best applied, and when BASIC is a better choice.
- A look inside the TRS-80, with an eye to diagnosing where troubles might lie and where changes might be in order.
- The basics of creating a workable power supply for the projects in this book.

Number Systems

Numbering is the single most overrated problem in computer programming. The answer (posed before the question) is this: numbers are merely *counting names*. That is, it makes no difference whether we think in tenths of a mile or eighths of an inch. Nor does it bother us that a day is made up of 24 hours, while an hour is 60 minutes. That a year is 365 days frightens us not, nor that months are a motley collection of sizes.

In parking lots, does it bother us that our vehicle may be parked in Row N as opposed to Row 14? There is no mystery when we mark off points with four scratches and a crosshatch. And does a dozen always conjure up 'twelve', or is a dozen something we have understood since youth?

Names are sizes are numbers; so it is with the number systems that we arbitrarily assign for the convenience of working with computers. When we are talking about electrical signals, it is clearest and easiest to think about ons and offs. Ons look pretty much like ones, and offs look like

zeros. It's a nice, clean concept, and one that illuminates the way we can refer to the machinery.

There's more convenience to naming a computer data condition 10110100 than to calling it an on off on on off on off off. Were data the only consideration, the binary one and zero method might have been satisfactory, without resorting to other means or stroking our memories.

Finding a location in a computer's memory is a much more difficult task. Although a memory location called . . .

1110100010011010l

. . . might be easier to think about than . . .

onononoffonoffoffoffonoffoffononoffonoffon

. . . it could use another step forward. In music, a long string of sixteenth notes like this –

Figure 2-1. Illustration of illegible musical notation.

– is broken up to make it legible, so it looks instead like this –



Figure 2-2. Illustration of legible musical notation.

Likewise, that long binary string can be broken up from 1101000100110101 into convenient groups . . .

Converting Binary to Decimal

In the grade school years, students used to learn that a number like 5,163 contained a 3 in the ones place, a 6 in the tens place, a 1 in the hundreds place, and a 5 in the thousands place. It was to remind them that 5,163 was really 3 plus 60 (6 x 10) plus 100 (1 x 10 x 10) plus 5,000 (5 x 10 x 10 x 10).

The way other number systems are written follows this same pattern for their own bases. In base eight the number 5,163 would have a 3 in the ones place, a 6 in the *eights* place, a 1 in the *sixty-fours* place, and a 5 in the *five-hundred-twelves* place. That means that 5,163 is really 3 plus 48 (6 x 8) plus 64 (1 x 8 x 8) plus 2,560 (5 x 8 x 8 x 8). But notice how that's decimal thinking! Really in base eight there could be no '8' . . . it would have to be called '10'! 1, 2, 3, 4, 5, 6, 7, 10, 11, 12, 13, 14, 15, 16, 17, 20, and so on. So 5,163 in base eight is *still* 3 plus 60 plus 100 plus 5,000!

The binary system sneaks in the same way. A number like 1101 0001 0001 0011 turns into a 1 in the ones place, a 1 in the twos place, a 0 in the fours place, a 0 in the eights place, all the way up to a 1 in the thirty-two-thousand-seven-hundred-sixty-sevens place. In binary, the one on the far left is still a 1 in the quadrillions place, don't forget. But the message is how to convert all this to decimal. And here it is:

```
32768 16384 8192 4096 2048 1024 512 256 128 64 32 16 8 4 2 1
  1     0    1    0    0    0    1   0   1   0  0  1 0 0 1 1
```

Just add the numbers: 1x1 + 1x2 + 0x4 + 0x8 + 1x16 . . . + 1 times 32,768 = 41,619. Voila. No matter how long the number is, and in whatever base:

1. Start at the left and produce a chart of the base number's powers, starting with 0 (X to the 0 power is always 1).
2. Lay the number to be converted underneath the base number chart.
3. Multiply each base number power by the digit in its place.
4. Sum the resulting numbers.

Does it work? Certainly. What is 163,341 in base 9? And in base 7? And in base 10?

```
Base 9 powers:         5      4      3      2     1    0
9 to thet power:     59049   6561   729    81     9    1
Number to convert:     1      6      3      3     4    1
Multiplicetion:     1x59049 6x6561 3x729  3x81   4x9  1x1
Subtotels:           59049 +39366 +2187  +243   +36   +1
Converted result:              100882, bese 10

Bese 7 powers:         5      4      3      2     1    0
7 to that power:     16807   2401   343    49     7    1
Number to convert:     1      6      3      3     4    1
Multiplicetion:     1x16807 6x2401 3x343  3x49   4x7  1x1
Subtotels:           16807 +14406 +1029  +147   +28   +1
Converted result:              32418, bese 10

Bese 10 powers:        5      4      3      2     1    0
10 to thet power:   100000 10000   1000   100    10    1
Number to convert:     1      6      3      3     4    1
Multiplicetion:    1x100000 6x10000 3x1000 3x100 4x10 1x1
Subtotels:          100000+60000  +3000  +300   +40   +1
Converted result:              163341, bese 10
```

1101 0001 0011 0101

. . . although the legibility is improved, the human spark, the ability to look and recognize (that *aha!*) is not there. So the next step is to set about naming the sections. Since these on-off conditions can be written down as binary numbers, why not write them down in their decimal eauivalents?

The question is rhetorical, of course, because not only can it be done, it is done. The only question is how to do it. Were a computer capable of swallowing all sixteen of those binary digits (bits) in one gulp, that question might be easily answered by calculating the conversion of 1101 0001 0011 0101 using a binary-to-decimal conversion table. The result, we find, is 53557.

But the computer, alas, cannot swallow all those bits in one bite . . . it can only swallow one byte full of bits (pardon). In other words, though a computer may need numbers sixteen bits long, only eight data lines exist to carry that data.

The component parts of the number 1101000100110101 are needed, eight bits at a time: 11010001 00110101.

There's the mathematical rub. 11010001 is 209 decimal, and 00110101 is 54 decimal. This seems hardly related to 53,557. Another solution is necessary, and it is a naming system as much as a numbering system. It names each of the sixteen possible combinations of four binary digits:

Reading the Pins

Finding your way through digital circuits is much easier than finding your way through an ordinary table radio. Industry standards have made the process simple. Consumer integrated circuits are packaged in small, rectangular, plastic or ceramic cases with anywhere from 8 to 40 external connections known as pins.

Earlier integrated circuits – and many of the audio types currently being produced – were packaged in small metal cans and looked like transistors, with many wires protruding from the bottom. The wires were arranged around a keying tab on the edge of the can, and numbered like so:



Figure 2-3. Can-type IC pin numbering.

As such circuits developed into more sophisticated and powerful devices, more pins were needed for input and output. A rectangular package was developed, but it was still numbered in a circle, starting (when looking down from the top) from the left of the notch, so:



Figure 2-4. Dip-type IC pin number (8 pins).

All modern integrated circuits can be read from the top in this same way. 14- and 16-pin types start from the top left and read around:



Figure 2-5. 14- and 16-pin Dip IC pin numbering.

You can read the pinouts of 18-, 20-, 24-, 28- and 40-pin circuits in the same manner. The highest numbered pin sits just opposite the lowest numbered pin. In the beginning this practice may seem confusing; it is. But after using the circuits – and counting their pins over and again – you will probably feel comfortable with the pin arrangement.

Just one thing: when you assemble TRS-80 add-ons, most of your work will be done from the bottom . . . which means reading backwards!

```
0000   is named   0   and is equal to decimal  0
0001   is named   1   and is equal to decimal  1
0010   is named   2   and is equal to decimal  2
0011   is named   3   and is equal to decimal  3
0100   is named   4   and is equal to decimal  4
0101   is named   5   and is equal to decimal  5
0110   is named   6   and is equal to decimal  6
0111   is named   7   and is equal to decimal  7
1000   is named   8   and is equal to decimal  8
1001   is named   9   and is equal to decimal  9
1010   is named   A   and is equal to decimal 10
1011   is named   B   and is equal to decimal 11
1100   is named   C   and is equal to decimal 12
1101   is named   D   and is equal to decimal 13
1110   is named   E   and is equal to decimal 14
1111   is named   F   and is equal to decimal 15
```

This may seem overdone; but A, B, C, D, E, and F are darn good names for binary values which exceed the number nine. If you don't have a name, make one up. For practical purposes, keep it within the symbols everyone has on the Royal typewriter.

Back to the number 1101000100110101. Crack it into those four legible pieces (1101 0001 0011 0101), and it can be named **D135**. To convert it to decimal, remember the old rule: the 5 is in the ones place, the 3 is this time in the sixteens place, the 1 is in the two-hunded-fifty-sixes place, and the D is in the four-thousand-ninety-sixes place. Thus, **D135** is 5 plus 3 x 16 plus 1 x 256 plus (see the chart) 13 x 4,096, or . . . 53,557!

So, that long binary number can actually be digested by the computer as a byte of **D1** and a byte of **35**. After a while, the number system comes easily. My personal recommendation: work in it. Convert to decimal only when you absolutely must. Think in hexadecimal and binary. They are the tools with which you can speak to the computer.

Throughout this book, numbers in hexadecimal are printed in **BOLD**.

Digital Logic Devices

The binary number system and digital logic devices were developed together as a way of solving a practical dilemma: how to mass produce computers which could work quickly and accurately, and yet be inexpensive. As noted in Chapter 1, the problems of creating consistently accurate circuits, working with many different voltages levels, are formidable. Thus, simple yes-no, on-off logic was developed.

The intimidating term *Boolean algebra* is being used for the first, and last, time in this book – right in this sentence. You'll probably hear the phrase from time to time, but no matter – it's a professional's buzzword to keep the masses out. Forget it.

Back to digital logic devices. The essence of digital logic is to evaluate binary, on-off input; sometimes to determine a pattern of similarity or difference, sometimes to sense a change and sometimes to search for a signal. An appropriate result is produced as a result of the logical operation.

One of the logic building blocks is called a gate. A gate electronically evaluates its input to determine the pattern of similarity and difference of signals, and produces a specific output. A simple gate is shown below:



Figure 2-6. Simple AND gate.

Its job is to determine if the first AND second inputs are both at the one (high) level. Only under that condition will its output produce a high (one) signal. The table below shows how this AND gate works.

AND Gate

If input #1 is	If input #2 is -	The output result is
0	0	0
1	0	0
0	1	0
1	1	1

Table 2-1. AND gate action.

The table is called a *truth table*, and its purpose is to present every possible input and output condition for a given gate. Below is an OR gate. Stated in words, if either the first OR the second input is high, the output will be high. Examine the OR gate truth table; it really is quite logical.



Figure 2-7. Simple OR gate.

OR Gate

Input 1	Input 2	Output
0	0	0
1	0	1
0	1	1
1	1	1

Table 2-2. OR gate action.

Given a huge set of interconnected gates and their known inputs, the final output of the group can be determined by using truth tables like

these. Gates may have more inputs than two (some have sixteen), and may produce the opposite results from the two described above (NOT-AND and NOT-OR gates, known as NAND and NOR gates). Truth tables reveal how the integrated circuit's design engineer specified the pattern of binary logic inside the circuit.

In this way, given a desired output and a known number of input signals, it is possible to determine what set of input values will trigger the desired output.

There are a number of other types of digital circuits. Most are created out of gates like those described above, but their features are unique enough to think about them separately. Among these other digital logic circuits are buffers, flip-flops, counters, latches, multiplexers and shift registers.

A buffer can be thought of as a two-input gate with both inputs tied together, like this:



Figure 2-8. Buffer as (a) two-input gate and (b) buffer.

Its truth table is much simpler than that for two-input gates, because there are now only two input conditions. Either both inputs are high, or both inputs are low. Gates with 'true' outputs (AND, OR) will merely follow the input condition. When the inputs are high, the output is high; if the inputs go low, the output becomes low. Separate logic devices are manufactured that perform this 'follow-the-leader' function, and they are called *buffers.* They serve to isolate sections of a circuit, or rejuvenate a signal so it can feed many dozens of inputs in a large machine.

When a buffer reverses the condition of its input, (a high input is output low, and vice versa), the device is called an *inverter.* This kind of circuit can save the day in some cases, as when trying to locate a given binary number. Assume a circuit needs the binary number 1110 to turn on a pilot light. It is possible to choose four separate gates, each of which would provide an output matching the desired number. These would be connected through more gates, and eventually the number could be discovered when the final signal was triggered properly. One way of detecting 1110 is shown below:



Figure 2-9. Bad decoding scheme for 1110.

But, although this circuit works, economy of cost and space and simple clarity dictate another solution. The last input could be inverted before it is evaluated, resulting in a pattern (1111) which could be quickly recognized by a multiple-input gate. The result is electronic simplicity and legibility; an improved decoding circuit is shown below. The ultimate result is the same.



Figure 2-10. Good decoding scheme for 1110.

A flip-flop is a 'black box' which provides two outputs. When an input value is high (one), the first output will be high, and the second will be low. When the input value switches low (zero), the outputs will reverse. In other words, two opposite outputs for the price of one. But there is another significant use of the flip-flop.

Flip-flops also have an important input called a clock trigger, which is triggered only when its input returns to a given level. Only then will the outputs of the flip-flop reverse. That is, a given flip-flop clock may receive a 'zero' pulse. Its outputs will reverse. Then the zero pulse changes to a 'one' pulse. Nothing happens, but the trap is set to spring. When the one pulse changes back to a zero, the outputs reverse again. For every two changes at the clock, there will be but one change at the output. It takes four clock changes to produce two output changes.

Why is this useful? Because it is electronic, binary division. The truth table here shows how it works.

Binary Division with a Flip-Flop
Output of First Flip-Flop Connected to Clock of Second
Flip-Flops Change State Each Time Input Returns Low

Clock Input	Flip-Flop Output	Second Clock Input	Second Flip-Flop Output
0	0	0	0
1	0	0	0
0	1	1	0
1	1	1	0
0	0	0	1
1	0	0	1
0	1	1	1
1	1	1	1
(Input)	(Input/2)		(Input/4)

Table 2-3. Binary division with a flip-flop.

Digital logic devices known as *counters* are combinations of gates and flip-flops that allow certain patterns to be counted: Binary, Binary Coded Decimal (BCD, where the highest number is decimal 10), Gray code and others.

Latches are very much like flip-flops, except that the input is 'captured' at the output by a trigger signal called an enable, a select, or a gating pulse. The input may change continuously, but the output only reflects the input when the enable is activated. Latches are very useful when hundreds of thousands of signals are flying around on one set of lines, and the computer must select only certain groups of signals. The cassette output of data is a latch; only the 500-baud (bits per second) pulses of data reach the cassette output, even though many different signals reach its input.

Multiplexers are sometimes misunderstood, but mostly because of their formidable name. A traffic light is a multiplexer – it allows several streams of traffic to meet at one intersection, but only one stream to proceed. The multiplexer is the electronic equivalent, having several inputs. Gating signals select which of the inputs may reach the output. In a computer, this allows several devices to share a circuit (like the video, which must be sent to the screen, but also sends and receives characters from the rest of the computer).

Finally, *shift registers* treat bits of data like a bucket brigade sends up water: it goes in one end, and at each electronic 'go!', the bucket is sent along one position. The dots which make up the video display are produced by circuits which shift them out to the screen one bit at a time, in synchronization with the monitor's sweeping electron beam.

Into Machine Language

If we put faith in etymologists, then 'language' – which comes from the Latin meaning whole or part of a tongue – is an inappropriate word to put after 'machine'. Better to call it code, or blurms, or bingo chips even. Whatever it is, it becomes a tool for providing the user with all the power inside the TRS-80.

With a knowledge of binary and hexadecimal numbers, this language seems more fluid, and with a similar understanding of its electronic effects, it becomes the true 'lingua franca' of the computer.

In Chapter 1, I pointed out that BASIC is really just a disguised form of machine language. It is disguised because it presents itself in English-looking words, and has a large store of safety valves, error traps and messages – to prevent it from falling down an electronic rabbit hole.

For the moment I'll turn away from the metaphors, and present a practical simulation of that statement. The simulation can be familiarly written as follows:

CLS

When you command CLS (clear screen), BASIC enters a machine language subroutine to clear the screen. It automatically returns to a BASIC command-level 'READY' condition. Now I happen to know that CLS is located at memory address **01C9** (457 decimal), and that (non-disk system) 'READY' is found at **06CC** (1740 decimal).

As an experiment, type . . .

SYSTEM (ENTER)
/1740 (ENTER)

. . . and you will be presented with the familiar 'READY', exactly as if you had pressed the Reset button. You've executed a machine-language GOTO, jumping directly to the 'READY' routine in ROM. As a second experiment, type . . .

SYSTEM (ENTER)
/1457 (ENTER)

Momentarily, the screen clears, but quickly crashes to MEMORY SIZE? Why did that happen? Notice that I said CLS was a *subroutine*. In other words, the routine must be called via some sort of GOSUB. The crash back to 'MEMORY SIZE?' occurred because there are no error messages in machine language unless you create them!

There are two ways to simulate the required GOSUB. The first is to POKE the starting

address of the clear-screen subroutine into the USR(0) command. The USR(0) command is identical to the SYSTEM command, except that it is the equivalent of GOSUB, where SYSTEM is the equivalent of GOTO.

So **01C9** (clear screen address) is the USR entry point; it must be split in two pieces (**01** and **C9**), converted to decimal (1 and 201), and POKEd into USR addresses 16,527 and 16,526. So . . .

```
POKE 16527,1
POKE 16526,201
M=USR(0)
```

There. A screen clear without crashing to 'MEMORY SIZE?'. But there is another way. The machine language command for GOTO is called 'JUMP', and its hexadecimal code is C3. The machine language command for GOSUB is named 'CALL', and its code is **CD**. So here is the solution: **CALL 01C9. JUMP 06CC.**

Various hardware has its peculiarities. In the Z-80 microprocessor, addresses are always specified in reverse order. So **CALL 01C3** is written **CD** (CALL) **C9** (least significant byte of address) **01** (most significant byte of address). And **JUMP 06CC** is written **C3 CC 06**.

The whole process to clear the screen and jump to 'READY' is coded:

```
CD C9 01 C3 CC 06
```

Quite simple. CLS equals GOSUB **01C9**, GOTO **06CC**, which equals CALL **01C9**, JUMP **06CC**, which equals **CD C9 01 C3 CC 06**. The nice part of this little process is that it can be put anywhere in memory you like. Let's put it arbitrarily at **5000** to **5005** (20480 to 20485 decimal).

```
POKE 20480,205 : POKE 20481,201 :
POKE 20482,1
POKE 20483,195 : POKE 20484,204 :
POKE 20485,6
```

Convert the six hexadecimal bytes to decimal as shown earlier, and POKE them in place. Now you have the program completely under control. It is ensconced in memory, it calls the clear-screen routine, and jumps to 'READY'. Do you believe it? Just try it, entering the program at **5000**. . .

```
SYSTEM (ENTER)
/20480 (ENTER)
```

There. A complete machine language program that functions from BASIC command level.

If you're new to this, take a break. The next step is to write an elementary screen-clearing routine, instead of calling one already in ROM.

I want to introduce a dilemma early on in the process of learning machine language. There is always discussion in computer programming about 'reinventing the wheel', and there is much truth to the suggestion that one should not do programming when the work has already been done. In the case of the screen-clearing program, the subroutine to do the work has already been created, and it is right there in Level II ROM waiting to be used.

Why, then, write another one? Why, in fact, even call the routine via machine language when the BASIC CLS command works so well? Indeed, with a BASIC as powerful as Level II, machine language should probably be reserved for doing things that cannot be done in BASIC at all. Among these things are upper/lower case drivers, programs to send characters to a serial printer, music-making and sound effects, telecommunications and so on. Furthermore, where machine language seems required, it often makes sense to call as many Level II ROM subroutines as possible.

Slick as this may be, it has two disadvantages: much of programming and customizing the TRS-80 requires an intense element of learning and understanding. Re-inventing the wheel is what everyone who learns must do, from the child who is forced through the memorization of 'times-tables', to the adult who has lost a job after 25 years and must learn new skills.

I can only present this from a highly personal point of view, as one who could not have learned machine language with any fluidity had I depended upon the software black boxes of others. I suggest that if you want a program to perform a certain action, try to write it in machine language. Try to make it do the same sort of error-trapping and other housekeeping that Level II's subroutines do. Take the Level II code apart and have a look. But don't deny yourself the opportunity to learn, rather than run a personal software assembly line. End of sermon. Back to clearing the screen.

The Z-80 microprocessor has internal holding latches called registers. Some are capable of holding eight bits, others sixteen. Some eight-bit registers may be paired up with others to create a single sixteen-bit register. These might be thought of as your only Z-80 machine code variables. In this screen-clearing routine, several registers will be used. The registers to be used in this experiment are: B, paired with C; H, paired with L; and A.

The last of these is the *accumulator*, a sophisticated register capable of doing simple arithmetic. Indirectly, the 'condition code' register (called the 'flags') will also be needed, and will be described when it is used.

First, the program in its entirety:

```
21 00 3C       START——LD    HL,3C00H
01 00 04              LD    BC,0400H
36 20          LOOP———LD    (HL),20H
23                    INC   HL
00                    DEC   BC
..                    LD    A,B
..                    OR    C
C3 XX XX              JP    NZ,LOOP
```

Listing 2-1. Simple CLS demonstration.

In the first line, the H and L register pair is prepared with the values **3C** and **00**. As a pair, they are capable, then, of *pointing* to memory position 3C00. This is the memory location of the first position at the top left of the video display. The next line prepares the B and C registers with **04** and **00**. Although they are pointing to memory location **0400**, they are going to be used as a counter in this program, **400** is 1024 decimal, the number of places on the screen.

In the next line, the parentheses around HL mean 'the memory location defined by'. That is, the command is saying 'store the value **20** in the memory contents defined by the H and L register pair' – in this case, 3C00. So LD (HL),20 stores a blank space (20 is the ASCII value for such a space) at the first place on the screen. Whatever was on the screen before is turned into a space.

Notice that this has the name 'LOOP' next to it. This 'label' is for the programmer's eyes, not for the program's use. In the next two lines, the HL pair is *incremented*. That is, **3C00** is incremented to **3C01**. Correspondingly, the BC pair is *decremented*, from **0400** to **03FF**. You may see the pattern emerging – BC is being used in a kind of machine language FOR-NEXT loop.

In BASIC, a FOR-NEXT loop is sort of self-testing. The programmer doesn't have to put in anything that checks the value of the loop variable; BASIC does it automatically. But in machine language, a test has to be made. The next two lines of the program make that test. The accumulator is prepared not with an absolute numerical value, but rather with whatever the B register reads at the moment. After one pass through, it will be **03**.

Then the accumulator is asked to make a logical judgment. Recall that earlier in this Chapter, logical OR gates were discussed. If either of two inputs were high (one), the output would be high (one). In this case, there are *eight* inputs, one for each bit in the byte. So the accumulator has been loaded with **03**, thus . . .

00000011

. . . and it is being asked for the logical OR with whatever register C is now set to. In the first loop, that is FF –

11111111

What's in the Memory Map

The memory map of the TRS-80 has been designed for convenient, immediate use. It consists of seven major sections:

1. The BASIC language in read-only-memory (ROM).
2. An unassigned blank area for future expansion.
3. Special locations for cassette and disk.
4. A keyboard matrix, appearing in four locations.
5. A video memory.
6. A reserved block of RAM for BASIC use.
7. User-programmable RAM for programs, data, and variables.

The onboard jumper, X3, selects which of the various language possibilities is active in the TRS-80 (see section on electronic organization below). Level I BASIC uses only 4,096 bytes from address 0000 to 0FFF, but Level II uses from 0000 to 2FFF. Because of hardware shortcuts, the cassette, disk and keyboard locations are incompletely decoded, appearing in 'phantom' areas beyond those strictly assigned to them. Using incompletely decoded locations in the cassette/disk area can result in unexpected results. But the phantom keyboards can be used interchangeably with the actual keyboard address.

The possible memory configurations of the TRS-80 Model I, together with reserved RAM areas, are shown below.

Figure 2-39. TRS-80 memory map in detail.

Address	Function	RAM Pointer
0000	Beginning of all ROMs	
0000	Power-Up Position	
0FFF	End of Level I ROM	
2FFF	End of Level II ROM	
3000	Beginning of unassigned area	
3700	End of unassigned area	
370E	Disc Status Address	

37DF		Disc Data Address
37E0		Interrupt Flip-Flop
37E1		Disc Drive Select
37E4		Cassette Select
37E8		Line Printer Data
37EC		Disc Controller Chip
3800	———	Beginning of Keyboard ———
38FF		End of Keyboard
3900		Phantom Keyboard
3A00		Phantom Keyboard
3B00		Phantom Keyboard
3C00	———	Beginning of Video ———
3FFF		End of Video
4000	———	Beginning Reserved RAM ———
4000		Restart #0 Patch (RST 8)
4003		Restart #1 Patch (RST 10)
4006		Restart #2 Patch (RST 18)
4009		Restart #3 Patch (RST 20)
400C		Restart #4 Patch (RST 28)
400F		Restart #5 Patch (RST 30)
4012		Restart #6 Patch (RST 38)
4015	———	Keyboard Control Block ———
4015		Keyboard Device Type (01)
4016		Driver Entry Address (2 bytes)
4018		Three Reserved Bytes
401B		Two Bytes Reading "KI"
401D	———	Video Control Block ———
401D		Video Device Type (07)
401E		Driver Entry Address (2 bytes)
4020		Location of Cursor (2 bytes)
4022		Cursor Character
4023		Two Bytes Reading "DO"
4025	———	Line Printer Control Block ———
4025		Printer Device Type (06)
4026		Driver Entry Address (2 bytes)
4028		Total Lines Per Page
4029		Current Line Being Printed
402A		Reserved Byte
402B		Two Bytes Reading "PR"
402D	———	Level II Workspace ———
402D	———	Unassigned RAM ———
4035		End Unassigned RAM
4036	———	Beginning Keystroke Storage ———
403C		End Keystroke Storage
403D		Video Size / Cassette Latch
403E		Reserved for DOS Use (2 bytes)
4040	———	Storage Area for TIME$ ———
4047		End of TIME$ Storage Area
4048	———	Reserved for DOS Use ———
407F		End of DOS Reserved Area
4080	———	Storage Area for Division ———
408D		End of Division Storage Area
408E		USR Entry Point (2 bytes)
4090		RND Storage Area (3 bytes)
4093		INP Storage Area
4094		INPut Port Number (2 bytes)
4096		OUTput Storage Area
4097		OUTput Port Number (2 bytes)
4099		INKEY$ Storage Area
409A		ERROR Code Storage
409B		Line Printer Position
409C		Output Device Indicator
409D		Video Line Length (32 or 64)
409E		Video TAB area
409F		Reserved
40A0	*1	String Space Pointer (2 bytes)
40A2		Current Line in Use (2 bytes)
40A4	*2	Start of BASIC Program (2 bytes)
40A6		TAB Position Value
40A7	*3	Input Buffer Pointer (2 bytes)
40A9		Input #-1 Indicator
40AA		Seed Number for RND (3 bytes)
40AD		Reserved
40AE		LET and DIM Scratchpad
40AF		Number Type Flag
40B0		"Flag Byte for Encoder"
40B1	*4	Top of BASIC Memory (2 bytes)
40B3		String Scratchpad Pointer
40B5		String Workspace (30 bytes)
40D3		Length of String in Use
40D4		Address of String in Use (2 bytes)
40D6		Next Available String Space (2 bytes)
40D8		State of Print Using (2 bytes)
40DA		Current DATA Line in Use (2 bytes)
40DC		DIM Scratchpad (2 bytes)
40DE		Print Using Scratchpad
40DF		SYSTEM Loading Entry Point (2 bytes)
40E1		AUTO On/Off Indicator
40E2		Current Line in Use (2 bytes)
40E4		Size of AUTO Increment (2 bytes)
40E6		Location of BASIC Command in Use (2 bytes)
40E8	*5	BASIC Stack Pointer (2 bytes)
40EA		ERROR Line Number for RESUME (2 bytes)
40EC		EDIT Line Number in Use (2 bytes)
40EE		Line Number before RESUME (2 bytes)
40F0		ON ERROR GOTO Line Number (2 bytes)
40F2		Reserved (3 bytes)
40F5		Line Number Completed (see also 40E2)
40F7		CONTINUE Line Number (2 bytes)
40F9	*6	Simple Variables Pointer
40FB	*7	Arrays Pointer
40FD	*8	Free Memory Space (FRE(A))
40FF		Pointer to DATA in Memory
4101		Variable Type Workspace (27 bytes)
411B		TRON/TROFF Indicator
411C		Arithmetic Workspace (20 bytes)
413D		Line/Print Using Buffer (33 bytes)
4152	———	Disc Patch Points (see Chapter <?> ———
41A4		End Disc Patch Points
41A5	———	DOS Linking Patch Points ———
41E7		End Linking Patch Points
<*3>	———	Keyboard/Edit Input Buffer ———
42B8		Z-80 Stack During Running Program
42E8		End Input Buffer
<*2>	———	Beginning of BASIC Program ———
		End of BASIC Program
<*6>	———	Simple Variable Storage ———
		End of Variable Storage
<*7>	———	Array Storage Area ———
		End of Array Storage
<*8>	———	Free Memory Area ———
		End of Free Memory Area
<*5>	———	BASIC Stack for NEXT, GOSUB, etc. ———
		Top of BASIC Stack (works downward)
<*1>	———	String Storage Area ———
		Top of String Storage (works downward)
<*4>	———	Top of BASIC Memory ———
4FFF		End of 4K RAM
7FFF		End of 16K RAM
BFFF		End of 32K RAM
FFFF		End of 48K RAM

– each bit in the accumulator is ORed with its corresponding bit in register C. If any pair of bits is 1, the accumulator's bit will be set to 1. When the ORing process is finished, the accumulator will contain the results, and the condition code register will reflect the meaning of those results.

Listing 2-2. Complete CLS demonstration.

```
                 00100 ; ##########################################################
                 00110 ; SIMPLE CLEAR-SCREEN DEMONSTRATION IN ASSEMBLER FORMAT
                 00120 ; ##########################################################
                 00130 ;
5000             00140          ORG     5000H           ; BEGIN ROUTINE AT 20400
5000 21003C      00150          LD      HL,3C00H        ; VIDEO SCREEN, AT 15360
5003 01FF03      00160          LD      BC,3FFH         ; 1,024 SPACES ON SCREEN
5006 3620        U0170 LOOP     LD      (HL),20H        ; SPACE (DEC 32) IN PLACE
5008 23          00180          INC     HL              ; READY NEXT SCREEN LOC'N
5009 0B          00190          DEC     BC              ; DROP SPACES LEFT BY ONE
500A 78          00200          LD      A,B             ; GET CURRENT COUNT IN B
500B B1          0021U          OR      C               ; OR WITH COUNT LEFT IN C
500C 20FB        00220          JR      NZ,LOOP         ; GO BACK IF NOT YET DONE
500E C9          00230          RET                     ; BACK TO MAIN ROUTINE
06CC             00240          END     06CCH           ; READY AFTER TAPE LOAD
00000 TOTAL ERRORS
```

On the first pass, the accumulator will end up containing 11111111, and the condition code register's 'zero' flag will read 'not zero'. The last line of the program says 'jump if the result is not zero'. It jumps back to the part of the program marked LOOP, where it will store a 20 (space) in the new value pointed to by HL, increment HL again, decrement BC again, and go through the logical OR test once more.

If you carry the process through by hand, you will discover that only when B and C are *both zero* will the zero flag confirm a zero result. At that point, the program can shake loose from its loop.

Details of storage areas and their use can be found in *Microsoft BASIC Decoded, Supermap, Inside Level II,* and the *Level II BASIC Reference Manual.*

Setting MEMORY SIZE?

Because machine language programmers have devised many unique ways of storing their programs, the purpose of responding to 'MEMORY SIZE?' has been the cause of some confusion. A look at the summary of the full memory map may help clarify the reasoning.

```
Reserved Memory      (not available)
BASIC Program Text   (fills upward)
Simple Variables     (fill upward)
Array Variables      (fill upward)
****** FREE MEMORY SPACE **********
BASIC Stack          (fills downward)
String Storage       (fills downward)
MEMORY SIZE Value    (above reserved)
```

Table 2-4. Memory map summary.

This table points out two important facts: array variables grow *upward* into the free memory space. The BASIC stack (which stores GOSUB return addresses, levels of parentheses, FOR-NEXT information, etc.) grows *downward* into the free memory space.

Simple variables can also bump the array variables upward; string storage space is set ahead of time with the CLEAR statement. So you can see that the free memory area is impinged upon from both sides while a program is running. Although BASIC might have been designed to bump everything upward in memory (leaving the top area of memory unmolested), it would have resulted in considerably longer running time. This is because many changes in memory would have to be made when new variables, strings, parentheses, GOSUBs, etc., were discovered during a program's run.

If any machine language program is to be used, it certainly must be stored out of the way of this frantic activity. MEMORY SIZE therefore is used as a sacred boundary, above it is 'terra incognita' as far as the BASIC program is concerned. For example, if MEMORY SIZE in a 16K machine is set to 20480, the computer *acts precisely as if it were a 4K machine!*

To make maximum memory available for a running BASIC program, this boundary should be set only *just* low enough so that the machine language program will fit above it. Most program authors will write these programs to fit as high as possible in memory, and so you will normally see memory sizes (for a 16K machine) above 30000.

Why in a 16K machine would there be a 'memory size' of about 30000 and not 16000 or so? It's simply that the prompt 'MEMORY SIZE?' is a bad question. The memory size value is really not a size at all, but the *address* of a memory location above which the BASIC program and its variables must not go.

Why then are there machine language programs which do not require memory size to be set? That is because clever programmers write machine language programs that . . .

- may be written for Level II BASIC, and thus can reside in one of the DOS reserved areas (see memory map).
- may automatically reset the memory size value before returning to BASIC.
- may be packed into strings where they are safely protected in a program text line (see Chapter 3).
- may be short enough to reside in part of the input buffer and change its pointer.

In all of these cases, something is sacrificed for the convenience of not setting 'MEMORY SIZE?'. In the first case, DOS-like expansion programs, such as Level III BASIC, will conflict. In the second case, programs which also require the memory size to be set may be damaged when the loading program automatically resets it. Thirdly, string-packed lines may not be edited without calamitous results. And finally, a reduced input buffer makes editing long lines impossible, as they will probably run into the BASIC program text.

So the 'MEMORY SIZE?' boundary is a useful feature of BASIC, serving to protect machine language programs from the expansionist tendencies of a running BASIC program.

Comparing The Levels

Another source of confusion to a lot of users was the switch from Level I to Level II. How did this simple change of language alter the hardware? How did double-width characters, 500-baud tape loading, and key rollover suddenly appear? Why did the convenient abbreviations (P., N., M., F., etc.) suddenly go? Why were machine language programs happy with CLOAD in Level I, but needed SYSTEM with Level II?

The 4K BASIC in Level I is a compact, limited language with a few capabilities. Level II is three times as long, and much more powerful. Their authors, and hence their approaches, are different. The single hardware change in going from Level I to Level II is the installation of one ROM set in favor of another, and a minor change to allow 12K instead of 4K ROM to be accessed.

The 32-character mode hardware was already in place. The tape load speed and key rollover are all software controlled (see supplement to this Chapter). The abbreviations disappeared because Level II handled its keywords in a different manner from Level I, and such abbreviations would have increased execution time. Likewise, tape loading formats were a matter of design philosophy rather than any formal software requirements.

Level I has the advantage of being a simple, easily learned first language for computer beginners, and many TRS-80 owners learned by using that language. Level III is not a language distinct and apart from Level II, but rather an extension of the existing one. (In this sense it is much like Extended Color BASIC on the new TRS Color Computer, which does not supplant the original 8K BASIC, but merely adds another 8K to it).

What are the differences between the three levels? A command list for the three languages, with differences highlighted, follows:

Table 2-5. Comparison of Level I, II and III commands.

Command	Level I		Level II	Level III
@			X	X
A. (ABS)	X			
ABS	X		X	X
ASC			X	X
AT	X			
ATN			X	X
C. (CONT)	X			
CDBL			X	X
CHR$			X	X
CINT			X	X
CL. (CLOAD)	X			
CLEAR			X	X
CLOAD	X	*	X	X
CLOSE				X
CLS	X		X	X
CMD				X
CONT	X		X	X
COS			X	X
CS. (CSAVE)	X			
CSAVE	X	*	X	X
CSNG			X	X
CVD				X
CVI				X
CVS				X
D. (DATA)	X			
DATA	X		X	X
DEFDBL			X	X
DEFFN				X
DEFINT			X	X
DEFSNG			X	X
DEFUSR				X
DEFSTR			X	X
DELETE			X	X
DIM			X	X
E. (END)	X			
EDIT			X	X
ELSE			X	X
END	X		X	X
ERL			X	X
ERR			X	X
ERROR			X	X
EXP			X	X
F. (FOR)	X			
FIELD				X
FIX			X	X
FOR	X		X	X
FRE			X	X
G. (GOTO)	X			
GET				X
GOS. (GOSUB)	X			
GOSUB	X		X	X
GOTO	X		X	X
I. (INT)	X			
IF	X		X	X
INKEY$			X	X
IN. (INPUT)	X			
INP			X	X
INPUT	X		X	X
INSTR				X
INT	X		X	X
KILL				X
L. (LIST)	X			
LEFT$			X	X
LET	X		X	X
LSET				X
LEN			X	X
LINE				X
LIST	X		X	X
LOAD				X
LOC				X
LOF				X
LOG			X	X
LPRINT			X	X
M. (MEM)	X			
MEM	X		X	X
MERGE				X
MID$			X	X
MKD$				X
MKI$				X
MKS$				X
N. (NEXT,NEW)	X			
NAME				X
NEW	X		X	X
NEXT	X		X	X
NOT			X	X
ON	X		X	X
OPEN				X
OUT			X	X
P.(PRINT,POINT)	X			
P.A. (PRINT AT)	X			
PEEK			X	X
POINT	X			
POKE			X	X
POS			X	X
PRINT	X		X	X
PUT				X
R. (RESET, RND,RUN)	X			
RANDOM			X	X
REA. (READ)	X			
READ	X		X	X
REM			X	X
RESET	X		X	X
REST. (RESTORE)	X			
RESTORE	X		X	X
RESUME			X	X
RET. (RETURN)	X			
RETURN	X		X	X
RIGHT$			X	X
RND	X	*	X	X
RUN	X		X	X
S. (SET,STEP)	X			
SAVE				X
SET	X		X	X
SGN			X	X
SIN			X	X
SQR			X	X
ST. (STOP)	X			
STEP	X		X	X
STOP	X		X	X
STRING$			X	X
STR$			X	X
T. (THEN,TAB)	X			
TAB	X		X	X
TAN			X	X
THEN	X		X	X
TIME$				X
TROFF			X	X
TRON			X	X
USING			X	X
VAL			X	X
VARPTR			X	X
>	X		X	X
<	X		X	X
=	X		X	X
*	X		X	X
+	X		X	X
−	X		X	X
/	X		X	X
$	X	*	X	X
()	X		X	X

* indicates that Level I and Level II operations differ for this command.

Hardware Reflects Software

You are probably familiar with the general operating characteristics of your TRS-80, including BASIC commands and how the machine responds to them. These responses are characteristics of how the software treats the hardware, and also of how aspects of the hardware act independently of the software.

The hardware inside the TRS computer can be broken into seven major sections:

1. **CPU Hardware**
   - A. Central Processing Unit (Z-80), its clock, power-up, and reset circuitry.
   - B. Decoding of CPU status signals into memory/peripheral access signals such as read, write, input, output.
   - C. Buffering of address and data signals to and from the CPU.
2. **Program RAM Control**
   - A. Refresh signals to maintain memory in dynamic RAMs.
   - B. Address decoding able to distinguish 4K and 16K RAMs.
   - C. Address multiplexing for dynamic RAM address lines.
   - D. Read/Write signals to RAMs.
3. **Video RAM Control**
   - A. Address decoding for video RAM.
   - B. Read/Write signals to video RAM.
   - C. Input to character generator, timing, blanking signals so characters do not run off the screen.
   - D. Access management between display and CPU.
   - E. Alphanumeric/graphic switching and graphics character circuitry.
4. **Keyboard**
   - A. Address decoding for keyboard.
   - B. Address/data buffering and read signals.
5. **ROM Control**
   - A. Address decoding for 4K and 12K ROMs (Level I or Level II).
   - B. Outboard decoding for three 4K Level II ROMs or two Level II ROMs.
   - C. Read signals.
6. **Output Controls**
   - A. Parallel-to-serial conversion from character generator.
   - B. Horizontal and vertical video sync circuits, video output circuit.
   - C. Cassette motor, cassette data, and 32 character video output control.
   - D. Cassette audio output circuitry.
7. **Power Supply**
   - A. Three regulated voltage outputs.
   - B. Short-circuit protection.

Each of these sections plays a major role in the operation of the TRS-80, and few could be trimmed or eliminated without completely changing the character of the computer. The rest of this Chapter will be devoted to detailing those aspects of the TRS which are significant to customizing the hardware or software of the machine. For a more comprehensive examination, including timing diagrams and discussion of each signal line, turn to the *Technical Reference Handbook.*

CPU Hardware

The master clock is produced by the oscillations of a 10.6445 MHz (million cycles per second, or Megahertz) crystal. A countdown circuit (Z56) divides this by 6, producing the running frequency of the Z-80, 1,774,083 clock cycles per second. This is generally called the TRS-80's 1.77-MHz clock.



Figure 2-40. Clock circuit area of TRS-80.

It's interesting to note that there are several other clocks on the computer's board, some already wired in place, and others which can be created by interconnections. At pins 11 and 9 of Z56, 3.548 MHz is available, twice the normal TRS-80 speed. Pin 2 of Z43 clocks at 5.322 MHz, faster than the Z-80 can run, but when connected to pin 14 of Z56, a 2.661-MHz clock is available. This is 1.5 times the normal clock speed. Both the 2.661 MHz and 3.548 MHz clock rates will be used in Chapter 4.

Upon power-up, the processor's RESET input, which sets the program counter running at 0000, is triggered by Z53 in combination with Z52. The capacitor C42 takes time to charge completely, so the RESET line is held down for a few milliseconds after the rest of the system comes up and is stable. This power-on reset is a convenience so the user doesn't have to press a special reset button just to get the system going. Other computers, such as the Ohio Scientific series, demand that inconvenient action.

The TRS-80 design creates Read (RD), Write (WR), Input (IN) and Output (OUT) signals from the Z-80's Memory Use Request (MREQ), Input/Output Use Request (IORQ), Write (WR), and Read (RD) signals.These are combined by Z23, in the correct order to do that. The four Z-80 signals *are not* wired to the edge card connector, so certain functions (such as mode 0 and mode 2 interrupts – see supplement to Chapter 5) cannot be used.



Figure 2-41. Power-up reset circuit area of TRS-80.



Figure 2-42. Read/write status, multiplexer of TRS-80.

A TEST line is provided to 'float the bus' – in other words, the Z-80 becomes invisible, allowing another device to take over operation of the computer. Some outboard devices which speed up the TRS-80 use this feature, essentially taking control of the memory and peripheral devices by bringing the TEST line to ground. Z52 goes high in response, electronically disconnecting the Z-80's address and data bus from the circuitry. (Note that using the TEST line without memory-refresh backup circuitry on the outside of the computer will result in loss of memory contents).



Figure 2-43. Test line circuit of TRS-80.

In normal operation, the Z-80 lines are active and buffered by Z38, Z39, Z22 and part of Z55 (address), Z75, Z76 and the remainder of Z55 (data). Except when the TEST line is used, the address buffers are always active. The data buffers are active under any circumstances, either in their READ or WRITE configuration:

Except for the memory refresh information, this completes the role of the Z-80 CPU circuitry in the TRS-80.

Program RAM Control

The CPU is also used in the creation of the signals needed to refresh the dynamic memories. Since the TRS-80 uses dynamic RAMs, (see Chapter 5 for details on this), the normal refresh (RFSH) output of the Z-80 is less than useful, at least in the minds of the computer's design engineers. That RFSH signal, which is output when the computer is not using the memory, is ignored in the TRS-80.

Instead, the processor's MREQ line, when buffered, serves as a memory address row signal. The master clock is used in conjunction with the Z-80's RD and WR lines to produce a memory address column signal (column-address strobe, CAS) and a multiplex signal (MUX) to switch from row to column. This serves a very useful double purpose: not only does it refresh memory when the processor is not specifically using the memory in the program, but it serves as the address-select lines when the Z-80 processor *is* using memory. Refer to the Z-80 Technical Manual for details on the timing of these signals.



Figure 2-44. Address/data buffers of TRS-80.

Needless to say, should any of these signals fail or operate inconsistently, the memory will not retain its contents for very long *nor will a program even run which uses dynamic memory, because its address may not be selected.*

The next subject is memory management. This is basically the means by which the processor gets to the memory it wants to use. The heart of this sequence is found in Z35 and Z51, a pair of multiplexers which send the low bits of the memory address to the dynamic memories; flip from low bits to high bits according to the incoming multiplex (MUX) signal; and send the high bits to the memory. The memory, upon receiving these addresses together with the previously mentioned RAS and CAS signals, knows which address is being selected, and responds accordingly.

The DIP (Dual Inline Package) shunt Z71 plays an important role here. Specifically, it routes the signals to the multiplexers in such a manner that the computer can distinguish between 4K and 16K RAMs. Stated simply, what is a memory-chip select line for 4K RAMs is a complete address line for 16K RAMs, and a partial address line for 8K RAMs (which the TRS-80 was designed to use also). Thus, the higher address lines must be prevented from appearing at the CE (chip enable) input of the 4K RAMs. If this were to happen, phantom memory would appear, and a running BASIC program (and the power-up memory test) might try to use those phantom bytes:



Figure 2-47. X71 and decoding scheme of TRS-80.

Only a WR signal is used to trigger these RAMs, as a high signal on their WR lines prepares them to read data. The CE (Chip Enable) determines if data should be placed on the data bus, where it is buffered by Z67 and Z68.

Figure 2-45. Memory select/refresh of TRS-80.



Figure 2-46. Memory multiplex, CAS, RAS & memory.

Video RAM

Video memory is used in three ways: it is written to by the processor, read from by the processor and read from by the *video display circuitry*. In fact, it is constantly being read by the video display circuitry *except* when the processor demands attention.

The circuitry is complicated, and if you are interested in details, turn to the *Technical Reference Handbook*. In brief, memory is accessed by the processor using the Read (RD) and Write (WR) lines in conjunction with the decoded video area address-select line (VID). The display circuitry uses the video memory in a more complex manner: characters are output to Z27 and Z28, and these in turn are fed to Z29 (a character generator) and Z8 (a multiplexer). The characters, whether alphanumeric or graphic, are fed to Z10 (a shift register), where they are fed, a bit at a time, to the video output circuitry (beginning at the input of Z30).

The character generation process is complicated by several factors. The dots that make up each letter must be fed to the video output circuitry only when the video monitor's electron beam is sweeping the visible part of the screen. The visible part of the screen does not include the upper, lower, left or right borders. The timing process must continue correctly even when the CPU is using the video memory.

Because each letter is made up of twelve vertical dots, and each line is made up of 64 characters with six vertical dots each, different parts of the characters must be output to the screen at different times.

Again, the *Technical Reference Handbook* covers this in detail, but a few decoded signals are important. The output of Z30, pin 10, is the final BLANK signal; no characters are output when this signal is active. Presence of characters or graphics in the border areas points to problems with this line.

The signal to shift video bits out to the video circuit is provided by Z26. Pin 8 controls alphanumeric bits, pin 6 controls graphics bits. Mangled screen characters may be traced to here, or to any of the seven chips that select characters: Z65, Z50, Z12, Z32, Z64, Z49, and Z31. This is one of the most unpleasant areas to attempt to diagnose.

The 32/64 character mode select (MODESEL) is provided by Z59, pin 9, and changes the speed of the video clock at Z43. Failures in either Z59 or Z43 will show up as a lockup in one mode or the other.

The presence of bit 7 determines if the computer is to output graphics or alphanumerics, and that signal (DLY BIT 7) is output in normal and inverted forms from Z27 pins 2 and 3. Failure in either mode can be examined here, or at the outputs of Z26, pins 6 and 8.

Keyboard

The keyboard is very different from the video; it's just a simple key matrix. When the keyboard address area is read, the KYBD line from Z36 pin 11 triggers the keyboard integrated circuits (Z3 and Z4 on most keyboards) into action, outputting information to the data bus.

The data to be output is determined by the low eight bits of the address requested. The specific address requested is inverted, and a low signal is detected whenever a key in that matrix row is pressed. The inverting buffers to the data line provide the appropriate row information. For details on how the software interprets this switching matrix, see the supplement to this Chapter.



Figure 2-48. Character generator and shift register.

An interesting aspect to this is how the depression of *any key* may be detected. If address 387F is sought, all the address lines (except SHIFT) will become active, and the presence of any depressed key (except SHIFT) will appear on the address bus. Requesting the data at address 38FF will return the presence of any key *including* SHIFT. This is useful in creating a keyboard buffer, which is built from characters detected whenever the INTerrupt line is triggered.

In other words, the interrupt line triggers, and the program moves to the interrupt service routine. This routine reads address 387F, and the presence of any depressed key can be sensed. If one is pressed, it can be accepted and evaluated. Otherwise, the interrupt routine promptly returns to the program in progress.

This is also a valuable addition to INKEY$ in some situations; see 'Peeking the Keyboard' in Chapter 3.



Figure 2-49. Keyboard matrix of TRS-80.

ROM Control

Selecting the ROMs is the biggest sticking point in the Model I. This selection is accomplished by Z3, another DIP jumper shunt, in conjunction with Z21, a 74LS156 demultiplexer. Z21 joins various address lines to produce VID, KYBD, and MEM for the video, keyboard, and dynamic RAMs and to produce variants on the ROM line.

Two-chip Level I sets were selected by a combination of methods, all of which are detailed in the *Technical Reference Handbook*. Each ROM was 2K bytes in size. Three different versions of the board were publicly released, marked 'A', 'D' and 'G'. Each had a different hard wired method of decoding ROM. An occasional 'B' or 'F' board has been reported to me, but I have never seen one. Follow *Technical Reference Manual* descriptions carefully to make sense of these Level I lines.

Some of these ROMs were EPROMs with identical pinouts, so a 'ROM A' and 'ROM B' pair of lines were needed so these memories would not conflict.

Later Level I ROMs had the selecting circuitry masked right onto the chips, which removed that conflict. Finally, a single 4K ROM was introduced to eliminate these difficulties completely.

The Level II ROMs were for a long time quite consistent as a three-chip set, 4K bytes of memory in each one. A separate, piggybacked board was used. The decoded ROM line, in conjunction with address lines 11, 12 and 13, feed a 74LS42 wired as a demultiplexer. Each ROM selects a bit differently, and the combination of signals allows the memory areas from 0000 to 0FFF, 1000 to 1FFF, and 2000 to 2FFF to be selected.

In later Model I's, the three-chip set was reduced to two masked ROMs with different select characteristics. The piggyback board disappeared, and the two ROM sockets, once used for Level I, were now used for Level II. A modification to remove the two-chip ROM set, and make room for the addition of Level I, is presented elsewhere.

Output Controls

Some of the output controls have already been pointed out, including the parallel-to-serial conversion of video characters and the 32 character video control. The latter is part of a latch which is activated by information sent to port FF. Z54, Z36 and Z52 together decode port FF, and this is brought together with the computer's IN and OUT signals. The result is a pair of lines marked INSIG and OUTSIG, which are used to activate the input/output circuitry.

A latch, Z59, holds the cassette motor on or off, and also locks the video into 32- or 64-character mode. It is also latched on and off to create the 500-baud pulse rate of data to the cassette player. This output signal is purely digital, as opposed to the input signal (discussed below).



Figure 2-50. 74LS42 Level II demultiplexer of TRS-80.



Figure 2-51. INSIG and OUTSIG area of TRS-80.



Figure 2-52. Output data latch area of TRS-80.

It would have been possible to have used Z54 to decode port FF directly, without using Z52 or Z36. Whether or not this was a design expansion consideration, you can use it as such since ports FF (255 decimal) and FE (254 decimal) are created by Z54 and the separate low-bit data line. In Chapter 4 port FE will be used for video and speed changes.

Cassette input is provided via a low-pass filter, through parts of Z4, where it is turned from low grade audio into a reasonable digital signal. When INSIG is activated, whatever data is present at the cassette input is switched onto the data bus, and the CPU can read it. Then OUTSIG may reset the flip-flop created by Z24, when the program is ready to read the next piece of data from the cassette input. Note that the input can be any audio signal. The cassette port is not limited merely to taped data, but can be used to decode communications, shortwave, and ham transmissions, or test for the rise of voltage to a triggering level.



Figure 2-53. Cassette data shaping circuit of TRS-80.

The complex video divider chain provides HDRV and VDRV (horizontal and vertical drive) signals for television monitor synchronization. These signals are fed into a group of digital phase-shifting circuits which permit the signal to be adjusted on the video screen.



Figure 2-54. Horizontal and vertical phase circuitry.

The signals are mixed together at Z5 to provide a complete syncronization signal, and this sync signal is mixed with the video signal by Z41, Q1 and Q2. The result is a composite video signal which is capable of running a standard television monitor, or an RF modulator. The RF modulator signal can then drive an ordinary television.



Figure 2-55. Video mixing circuit of TRS-80.

Power Supply

Refer to the *Technical Reference Handbook* for an excellent description of this circuitry.

Wire-Wrapping Technique

It's not without a bit of hesitation that I attacked many of the hardware projects presented in this book. Some are simple, but many, particularly those using memory circuits, need many connections. The wiring is not complicated, just tedious.

If you work carefully, all is likely to be well; but even a touch of haste will encourage confused connections. It is in these cases especially that wire-wrapping is the technique to use.

Wire-wrapping is not only easier than soldering, it is secure, simple, easier for correcting mistakes – and less costly. For wire-wrapping, you will need wire-wrap sockets, which are sold by most hobbyist supply houses including Radio Shack. Likewise, wire-wrap wire and a simple hand tool are used for the process. Here are the steps:



1. Insert stripped wire.

1. The wire, still connected to the spool, is inserted in the V-shaped stripping slot. Insert between one half and one inch of wire. Pull downward from the V, and the wire will slip out, leaving a piece of insulation in the stripper, where it can be shaken out.



2. Slip over pin. Hold wire firmly, and slide fully down.

2. Look carefully at the end of the wire-wrap tool. There is a small hole, meant to fit over the pins of a wire-wrap socket. Next to it is a half-circle, into which you must slide the stripped wire. The stripped portion will slide up a groove in the side of the tool, stopping where the insulation begins.



3. Spin wire - wrap tool. Wire rises along pin.

3. When the wire is in place, pull it sharply but gently upward, and slide the tool on the wire-wrap socket. Holding the wire firmly, spin the tool in your hand. The wire will wind up on the socket pin, freeing itself from the tool. Remove the tool. The wire-wrapping is complete for that end of the connection.



4. Finished connection has no bare wire protruding.

4. Cut the wire to a length that will comfortably reach its destination, and then some. Strip the end of it, and repeat the process above. The connection is complete. Don't forget to use different colors (white, yellow, red and blue are generally available).This will help you distinguish your connection patterns if changes become necessary.

Peripheral Addressing

The bulk of the external devices attached to the TRS-80 do their own address decoding work. Some have become standardized by conventions of their use, and others have been used somewhat haphazardly by various manufacturers.

Table 2 - 6

Addresses reserved:

3000-37CF	Exatron Stringy-Floppy Personal Microcomputer Fastload Personal Microcomputer REX-80 Peripheral People Memory Sidecar
37DE	Communications Status (Expansion)
37DF	Communications Data (Expansion)
37E0	Interrupt Flip-Flop (Expansion)
37E1	Disk Drive Select Latch (Expansion)
37E4	Cassette Drive Select (Expansion)
37E8	Line Printer I/O (Expansion) Percom Electric Crayon I/O Percom Speak-2-Me-2 Microcompatible Printer Buffer
37EC	Floppy Disc Controller (Expansion)
37F8	Electronic Systems Serial I/O

Table 2 - 7

Output Ports Reserved:

0	(Selectable)	Alpha Product Interface Devices
1	(Selectable)	Alpha Product Interface Devices
2	(Selectable)	Alpha Product Interface Devices
7	(Selectable)	Alpha Product Interface Devices
8		JPC Poor Man's Floppy System
55		Electronic Systems Serial I/O
208		Microperipheral Microconnection
209		Microperipheral Microconnection
232		Lynx Modem Radio Shack RS-232 Board
233		Lynx Modem Radio Shack RS-232 Board
234		Lynx Modem Radio Shack RS-232 Board
235		Lynx Modem Radio Shack RS-232 Board
254		Archbold High Speed Board Mumford Micro Speed Mod Board Most Internal User Modifications
255		Cassette Data I/O (Internal) 80-Grafix (Programma) Cassette Motor Switch (Internal) Video Character Size Latch (Internal) Simutek T-Beep Addition
Addressable		Mullen Computer M-80 Interface Quant Systems PPI-80 I/O Port Orion Instruments In-Circuit Emulator Optimal Technology EPROM Programmer

Table 2 - 8

Other Peripheral Device Uses

Unaddressed (using bus control signals):

Cecdat Software/Hardware Extension, The Patch
Programma Programmable Graphics, Grafix-80
Microcompatible Company, The 225% Solution
Alpha Product Stick-80 Joysticks
SEL IEEE-488 to TRS-80 Interface
Xitek STD Bus I/O Card System

Unaddressed (using cassette I/O signals):

Most available Light Pens, including
Most available Cassette Data Digitizers, including
Acu-Data, Data Dubber, E-Z Loader

Unconnected (using RFI interference pickup):

Micro-Mega CPU Monitor

Soldering Technique

For projects from scratch, soldering should be considered the final process, the actions of a self-assured, confident hobbyist. For modifications, it is a necessity. In either case, and whether you are a micro-acrobat or distinctively clumsy like me, you can solder well. The requirements are patience and good solder.

To start, make sure you are using an iron in the 25 to 40 watt range, never a soldering gun. The solder should be high quality, multicore solder. It is expensive, but will save many grief stricken hours tracing 'cold solder joints', or removing globs of dull solder from between and under integrated circuits.

1. Clean the soldering iron tip, and heat the iron. Flow fresh solder on the tip to 'tin' the tip, which will help the solder flow from the tip of the iron to the part to be soldered. If the iron has been used, clean any encrusted material from the tip, and use coarse emery paper to shine the solder. If the tip gets deformed, bent, or very corroded, file it sharp with a fine file, and re-tin the tip.



1. Tin the tip.

2. Keep an old sponge handy, slightly damp. Run the tip of the iron quickly over it as you solder to remove the excess flux. Always use a soldering iron holder (usually provided with an iron); if you don't, you'll wish you had the first time you burn a large hole in your imitation walnut, vinyl-topped desk.



4. Finished solder connection.



5. Bad solder connection – no contact with board (sideview).

3. In the olden days, the rule was 'heat the parts, not the solder'. Forget it. Make sure the iron is no hotter than 40 watts (and remember never to use a soldering gun) and that the parts you are about to solder are very clean. Place the iron against the part, making as much contact with it as possible along the angled tip of the iron. Place the end of the solder at the juncture of the iron and the part, and flow just enough solder to make a clean, shiny, flowing connection.



2. Bring solder, parts and iron into contact.

4. Remove the iron immediately and let the part cool. If a wire is being soldered, hold it still until the solder becomes cloudy and cool, or else an imcomplete connection may result.



3. Lift iron and solder simultaneously.

5. If solder bridges develop between connections that are very close together, don't try to suck up the solder with the iron; you can only overheat the parts that way, and end up with blobs of solder and flux. Instead, use solder wick or solder-up to remove the excess solder, and start again. Let the parts cool before soldering again (a half minute should be enough).



6. Bad solder connection – no contact with pin (6A sideview)(6B topview).

On the Keyboard Scan

Arrows? Control codes? Autorepeat? Whatever it is you would like, that has to do with the keyboard, you can do with the TRS-80. The designers of the machine chose not to use an ASCII (Amercan Standard Code for Information Interchange) keyboard . . . one that outputs a code for each key pressed; instead, the keyboard is a matrix of switches. Because of this decision, the TRS-80 keyboard can be extremely versatile with a minimal body of software.

First let's take a look at the keyboard matrix itself. If you have been programming in machine language, or even relatively sophisticated BASIC, this map will be familiar:

Addresses	Keys							
3801	@	A	B	C	D	E	F	G
3802	H	I	J	K	L	H	N	O
3804	P	Q	R	S	T	U	V	W
3808	X	Y	Z	.......RESERVED......				
3810	0	1	2	3	4	5	6	7
3820	8	9	:*	;+	,<	-=	.>	/?
3840	ENT	CLR	BRK	UPAR	DNAR	LFAR	RTAR	SPC
3880	SHIFT	..............RESERVED...........						
Data:	01	02	04	08	10	20	40	80

At first, the arrangement of the address lines and data information may seem unappealing. What is the use of having address and data information that doubles at each change? Why not just use 3801, 3802, 3803 and so on? The reasons will eventually become apparent – in the ease and speed of the keyboard scan (and in the low cost of the hardware), but consider this binary for a moment . . .

```
00000001    00000010    00000100    00001000
00010000    00100000    01000000    10000000
```

. . . and there you have it. The bit is bumped along for each keyboard row and column, so that the presence of a single active bit instantly identifies any of the (potential) 64 keys.

The entrance to the keyboard scan is made with a jump from address **4016** in the ROM's RAM switchboard. Normally at power up, the jump address **03E3** is put in place, and the keyboard scan is entered at that point. Registers BC, DE, HL, and A are used in the scanning process:

```
03E3    21 36 40        LD      HL,4036
03E6    01 01 38        LD      BC,3801
```

The HL register pair points to the first RAM location at which the keystrokes will be stored. BC is set to look at the first row of the keyboard, whose memory map is **3801** to **3880** as noted earlier. Register D is set to zero, and it will become a 'row counter'; the process begins at address **03EB**:

```
03EB    0A                      LD      A,(BC)
03EC    5F                      LD      E,A
```

The accumulator reads the data at BC (recall at the outset it is pointing to the first keyboard row, 3801). The information it finds is stored in the memory location pointed to by HL (4036).

Okay so far. Now comes some of the interesting stuff that distinguishes this scan as an excellent piece of writing:

```
03ED    AE                      XOR     (HL)
03EE    73                      LD      (HL),E
03EF    A3                      AND     E
03F0    20 08                   JR      NZ,03FA
```

This short segment is responsible for the 'rollover' capabilities of Level II. The contents of the accumulator (the keystroke, if found) is XORed with the previous contents of **4036**. Recalling how the XOR function works, we discover that if the key pressed was the same as the previous one at this row, the accumulator will be 'toggled' to zero. In any case, the current keystroke, whatever it is, is now saved in 4036 (so that the next time 'round, it knows if a key is still pressed).

If the key was the same, AND E will be the result of A-toggled-to-zero AND the found keystroke . . . or zero. If there was no key pressed, the result will be A XORed with HL (which is essentially irrelevant) AND E-which-is-zero . . . or zero. The test at **03F0** is for not zero. Under these conditions, it fails, so the program continues:

```
03F2    14                      INC     D
03F3    2C                      INC     L
03F4    CB 01                   RLC     C
03F6    F2 EB 03                JP      P,03EB
03F9    C9                      RET
```

The 'row counter' (D register) is incremented, and the low-order byte of HL is incremented (to storage address 4037), and the low-order byte of BC is rotated. Recalling the keyboard matrix, we can see that this command to rotate moves us from **01** to **02**, from **02** to **04** from **04** to **08**, from **08** to **10** and so on. That keeps track of the row that the scan is looking at, and as long as the result of the rotate is positive (bit 7 low), the loop will travel back to **03EB**, where the next row will undergo the same testing as each previous one.

When RLC C shifts the row pointer to 3880, then bit 7 will be high (10000000); this is 'negative' in Z-80 architecture, and the loop falls through. Why does it fall through before checking the contents of address 3880? Because the only thing in this row is the shift key; it does not offer a decipherable code by itself, but merely modifies the information found when some other key is depressed. This explains why, among

other peculiarities, INKEY$ does not acknowledge SHIFT alone.

When the loop falls through, the program encounters a RETurn from subroutine, which directs it immediately back to the rest of BASIC. The routine is remarkable, looping through just over 100 bytes when the keyboard is clear. Although not as time-efficient as obtaining input from a memory-mapped ASCII keyboard, it is quite speedy, and offers considerably better 'rollover' than many encoded keyboards.

When a key is pressed, the program jumps to 03FA, and is able to provide upper/lower case ASCII codes, special functions, and, incredibly enough, all of the 'missing' ASCII control codes (form feed, ring bell, etc.). Let us now follow it through:

```
03FA    5F          LO      E,A
03FB    7A          LO      A,0
03FC    07          RLCA
03F0    07          RLCA
03FE    07          RLCA
03FF    57          LO      0,A
```

The position of the keystroke found has been stored in register E – recall that this is the 'column' of the keystroke. The row itself is not yet accessible, but the row counter (register D) is crucial to determining it. After E is saved, the accumulator is loaded with the value in this row counter, and rotated to the left three times. For those shaky in their binary arithmetic, this is the effect: if a decimal number is 045, a left rotation makes it 450. This is multiplication by ten. If a binary number is 010 (decimal 2), a left rotation gives 100 (decimal 4) . . . in other words, multiplication by two. Therefore, three left rotates gives us 2 x 2 x 2, or multiplication by eight. That result is saved back in register D.

The purpose of this clever ploy will soon become clear:

```
0400    0E 01       LO      C,01
0402    79          LO      A,C
0403    A3          ANO     E
0404    20 05       JR      NZ,040B
```

Here the C register is set to 1, sucked up by the accumulator, and ANDed with E (remember E still contains that keystroke column byte). If the result is not zero (that is, if E equals 1), then the loop falls through and the program moves on. But have a look at what follows:

```
0406    14          INC     0
0407    CB 01       RLC     C
0409    18 F7       JR      0402
```

What is this about? Well, the D register, which contains 8 times the row value, is being incremented each time C is being rotated . . . making the lower three bits of D serve now as a column counter! Whoa, you say, back up there. Okay, here it is: the original value in D could have been 0 through 6, depending on the row in use. When shifted three times, the possible values become **00, 08, 10, 18, 20, 28** and **30**. Each of these possible values, when incremented through all seven possible columns, might contain **00** to **07**, **08** to **0F**, **10** to **17**, etc., up to **37**. This gives us a complete, distinct value to represent each key.

Now a fairly crude process of hunt-'n-peck begins. The status of the SHIFT key is checked, and set aside in register B. The demultiplexed keystroke value in register D is snapped back into the accumulator, and the comparisons take off:

```
040B    3A B0 3B    LO      A,(3BB0)
040E    47          LD      B,A
040F    7A          LO      A,0
```

The character search can be followed through several branches; we will start with the most straightforward, and progress through some of the unique (and little publicized) aspects of the TRS-80 keyboard output.

The program adds **40** to the character value (address **0410**), and checks if the result is greater than or equal to **60** (**0412**).

```
.........................................................
.                                                       .
.  CHAR + 40 is       @   A   B   C   0   E   F   G    .
.  less than 60       H   I   J   K   L   M   N   0    .
.  (40 + 00 to 1F)    P   Q   R   S   T   U   V   W    .
.                     X   Y   Z                        .
.                                                       .
.  CHAR + 40 is       0   1   2   3   4   5   6   7    .
.  60 or graatar      8   9   :*  ;+  ,<  -=  .>  /?   .
.  (40 + 20 to 37)   ENT CLR BRK UPA ONA LFA RTA SPC   .
.                                                       .
.........................................................
```

If the compare finds a value less than **60**, the routine rotates the SHIFT key value – which had been saved in the B register (**0416**). If SHIFT is released, the value in B is zero, and hence the rotate resets the carry flag (**0418**). The program moves directly to the terminal steps at **044B** (to be discussed later). At this point, the character contained in A would be in the range **00+40** to **1F+40**, the ASCII values for upper case (@, A-Z, left bracket, separator, right bracket, carat, and cursor). This is the software routine that causes the bizarre 'inverted' shift pattern on the TRS-80 . . . no shift for upper case!

If the character test at **0412** returns a value greater than or equal to **60**, then **70** is subtracted (**0429**). No carry is generated if the test value was greater than or equal to **70**, so this further separates the keyboard. See the diagram below:

```
.........................................................
.                                                       .
.  60 to 6F minus 70       0   1   2   3   4   5   6   7 .
.  carries; rasult         8   9   :*  ;+  ,<  -=  .>  /? .
.  is F0 to FF                                          .
.                                                       .
.  70 to 77 minus 70                                    .
.  doas not carry;       ENT CLR BRK UPA ONA LFA RTA SPC .
.  rasult is 00 to 07                                   .
.........................................................
```

At address 043D, the value in the accumulator (00 to 07) is rotated left, producing the even values from 00 to 0E. The SHIFT byte in B is rotated right into the carry flag; if a carry is generated, the accumulator value is incremented (0442), providing the values 0+1, 2+1, 4+1 and so on – in other words, the odd values from 01 to 0F.

What follows is a classic example of machine language table look-up. HL is set to 0050, the address of the table in ROM; BC will be used as an offset, with B set to 0 and C made equal to A. When BC is added to HL, a resultant address (0050 to 005F) is produced, and the contents of that address is loaded up by the accumulator. Here is a look:

```
0443     21 50 00           LO      HL,0050
0446     4F                 LO      C,A
0447     06 00              LO      8,0
0449     09                 A00     HL,BC
044A     7E                 LO      A,(HL)
044B     57                 LO      0,A
```

What do we find at 0050 to 005F? ASCII control codes. That result is stored in the D register (044B) before the termination sequence.

Teble 2 - 9

Address	Contents	TRS-BO Action	ASCII Oescription	Keyboerd Entry
0050	00	Cerriege Ret.	Cerriege Ret.	ENTER
0051	00	Cerriege Ret.	Cerriege Ret.	SHIFT ENTER
0052	1F	Cleer Screen	Unit Seperetor	CLEAR
0053	1F	Cleer Screen	Unit Seperetor	SHIFT CLEAR
0054	01	Breek	Stert of Heeding	BREAK
0055	01	Breek	Stert of Heeoing	SHIFT BREAK
005B	5B	Up Arrow	Left Brecket	Up Arrow
0057	1B	Eoit Escepe	Escepe	SHIFT Up Arrow
005B	0A	Line Feed	Line Feed	Oown Arrow
0059	1A (00)	*See text	Substitute	SHIFT Oown Arrow
005A	0B	Beckspece	Beckspece	Left Arrow
005B	1B	Beckspece Line	Cencel	SHIFT Left Arrow
005C	09	Horizontel Teb	Horizontel Teb	Right Arrow
0050	19	32-Cher. Mode	End of Medium	SHIFT Right Arrow
005E	20	Spece	Spece	Spece
005F	20	Spece	Spece	SHIFT Spece

```
                00100 ; ########################################################
                00110 ; SIMPLE ACTIVE KEYBOARO OISPLAY ROUTINE TO SHOW THE USE
                00120 ; ANO PHANTOMING OF KEYS AS THEY ARE PRESSED BY THE USER
                00130 ;
                00140 ;    OENNIS BATHORY KITSZ, ROXBURY, VERMONT  05669
                00150 ; ########################################################
                00160 ;
5000            00170          ORG     5000H
                00180 ;
                00190 ; ########################################################
                00200 ; CLEAR SCREEN, OISABLE INTERRUPTS, CLEAR ACCUMULATOR,
                00210 ; GET "0" CHARACTER, SCREEN POSITIONS, SCREEN OFFSET,
                00220 ; ANO BEGINNING OF KEYBOARO FOR TEST; ALL ARE SET UP ONCE
                00230 ; ########################################################
                00240 ;
5000 C0C901     00250 ENTER    CALL    01C9H              ; CLEAR SCREEN TO START
5003 F3         00260          OI                         ; KILL ALL THEM BOTHERS
5004 AF         00270          XOR     A                  ; CLEAR ALL FLAGS
5005 0E30       00280 START    LD      C,30H              ; THIS IS THE "0" CHAR.
5007 211030     00290          LD      HL,3010H           ; AOORESS NEAR SCREEN CTR
500A 112400     00300          LD      0E,0024H           ; OISTANCE BETWEEN LINES
5000 05         00310          PUSH    0E                 ; SAVE LINE AOOER VALUE
500E 11013B     00320          LO      0E,3B01H           ; OEFINE FIRST KEYBOARO
5011 060B       00330          LO      B,0BH              ; NUMBER OF LOOPS TO 00
                00340 ;
                00350 ; ########################################################
                00360 ; TEST EACH ROW OF THE KEYBOARO, COLUMN BY COLUMN
                00370 ; ########################################################
                00380 ;
5013 1A         00390 LOOP     LO      A,(0E)             ; FIRST ROW OF KEYBOARO
5014 CB47       00400          BIT     0,A                ; CHECK FIRST KEY COLUMN
```

Alright, we have upper case ASCII and TRS-80 control functions. How about the rest? Back up now to the test for SHIFT, at 0416. If such a shift is present, the value in A (40 to 5F) is increased by 20 (60 to 7F). These are the ASCII codes for lower case (@, a-z, left brace, separator, right brace, delete). The resultant code, as usual, is saved in the D register.

But what follows is curious:

```
0410     3A 40 38          LO      A,(3B40)
0420     E6 10             AN0     10
0422     28 2B             JR      Z,044C
```

The keyboard is tested again, this time at row 3840, data position 10 – the down arrow. If that key is not depressed, the program skitters right to the termination routine at 044C, with the lower case ASCII code ensconced in the D register.

Why the SHIFT/down arrow combination? If the down arrow is depressed, the value in D is retrieved and placed in the accumulator (60 to 7F), then reduced by 60, becoming . . . aha! . . . 00 to 1F. The program jumps to the end sequence, with the accumulator clutching one of the complete set of 32 ASCII control codes!

(There is an anomoly in earlier Level II ROMs: the code for the down arrow at 0059 is returned before the control code. Later ROMs placed a 00 at 0059, resulting only in the return of a control code if SHIFT/down arrow was depressed.)

So where are we now? Upper and lower case, TRS-80 and ASCII control codes. We need numbers and figures, and so we shall have them. Recall the second diagram: at 042B, the command row was separated from the numbers, which were left at F0 to FF. At 042D, 40 is added, resulting in possible values of 30 to 3F. A further separation is made via a comparison with 3C:

```
......................................................
.                                                    .
.    30 to 3B           0   1   2   3   4   5   6   7   .
.    (CP 3C reeult)     8   9   :   ;   ,<  -=  .>  /?  .
.                                                    .
......................................................
```

If the comparison is less than 3C, a carry is generated. The usual SHIFT test is made (at 0435), and if it fails, the value in A (30 to 3B) is maintained as the program moves into the end routine. These are the ASCII codes for numbers 0 to 9, colon and semicolon.

If the test value is 3C, 3D, 3E or 3F, no carry would be generated at 042F, and these values are XORed with 10. This toggles the high nibble

```
5016 71         00410         LD      (HL),C          ; FIRST DISPLAY A "0"
5017 2801       00420         JR      Z,JUMP1         ; DON'T CHANGE IF NO KEY
5019 34         00430         INC     (HL)            ; MAKE IT A "1" IF A KEY
501A 23         00440 JUMP1   INC     HL              ; NEXT SCREEN LOCATION
501B 23         00450         INC     HL              ; ...PLUS TWO
501C 23         00460         INC     HL              ; ...PLUS THREE
501D 23         00470         INC     HL              ; ...PLUS FOUR
501E CB4F       00480         BIT     1,A             ; SECOND KEYBOARD COLUMN
5020 71         00490         LD      (HL),C          ; FIRST DISPLAY A "0"
5021 2801       00500         JR      Z,JUMP2         ; DON'T CHANGE IF NO KEY
5023 34         00510         INC     (HL)            ; MAKE IT A "1" IF A KEY
5024 23         00520 JUMP2   INC     HL              ; NEXT SCREEN LOCATION
5025 23         00530         INC     HL              ; ...PLUS TWO
5026 23         00540         INC     HL              ; ...PLUS THREE
5027 23         00550         INC     HL              ; ...PLUS FOUR
5028 CB57       00560         BIT     2,A             ; THIRD KEYBOARD COLUMN
502A 71         00570         LD      (HL),C          ; FIRST DISPLAY A "0"
502B 2801       00580         JR      Z,JUMP3         ; DON'T CHANGE IF NO KEY
502D 34         00590         INC     (HL)            ; MAKE IT A "1" IF A KEY
502E 23         00600 JUMP3   INC     HL              ; NEXT SCREEN LOCATION
502F 23         00610         INC     HL              ; ...PLUS TWO
5030 23         00620         INC     HL              ; ...PLUS THREE
5031 23         00630         INC     HL              ; ...PLUS FOUR
5032 CB5F       00640         BIT     3,A             ; FOURTH KEYBOARD COLUMN
5034 71         00650         LD      (HL),C          ; FIRST DISPLAY A "0"
5035 2801       00660         JR      Z,JUMP4         ; DON'T CHANGE IF NO KEY
5037 34         00670         INC     (HL)            ; MAKE IT A "1" IF A KEY
5038 23         00680 JUMP4   INC     HL              ; NEXT SCREEN LOCATION
5039 23         00690         INC     HL              ; ...PLUS TWO
503A 23         00700         INC     HL              ; ...PLUS THREE
503B 23         00710         INC     HL              ; ...PLUS FOUR
503C CB67       00720         BIT     4,A             ; FIFTH KEYBOARD COLUMN
503E 71         00730         LD      (HL),C          ; FIRST DISPLAY A "0"
503F 2801       00740         JR      Z,JUMP5         ; DON'T CHANGE IF NO KEY
5041 34         00750         INC     (HL)            ; MAKE IT A "1" IF A KEY
5042 23         00760 JUMP5   INC     HL              ; NEXT SCREEN LOCATION
5043 23         00770         INC     HL              ; ...PLUS TWO
5044 23         00780         INC     HL              ; ...PLUS THREE
5045 23         00790         INC     HL              ; ...PLUS FOUR
5046 CB6F       00800         BIT     5,A             ; SIXTH KEYBOARD COLUMN
5048 71         00810         LD      (HL),C          ; FIRST DISPLAY A "0"
5049 2801       00820         JR      Z,JUMP6         ; DON'T CHANGE IF NO KEY
504B 34         00830         INC     (HL)            ; MAKE IT A "1" IF A KEY
504C 23         00840 JUMP6   INC     HL              ; NEXT SCREEN LOCATION
504D 23         00850         INC     HL              ; ...PLUS TWO
504E 23         00860         INC     HL              ; ...PLUS THREE
504F 23         DD870         INC     HL              ; ...PLUS FOUR
5050 CB77       00880         BIT     6,A             ; SEVENTH KEYBOARD COLUMN
5052 71         00890         LD      (HL),C          ; FIRST DISPLAY A "0"
5053 2801       00900         JR      Z,JUMP7         ; DON'T CHANGE IF NO KEY
5055 34         00910         INC     (HL)            ; MAKE IT A "1" IF A KEY
5056 23         00920 JUMP7   INC     HL              ; NEXT SCREEN LOCATION
5057 23         00930         INC     HL              ; ...PLUS TWO
5058 23         00940         INC     HL              ; ...PLUS THREE
5059 23         00950         INC     HL              ; ...PLUS FOUR
505A CB7F       U0960         BIT     7,A             ; EIGHTH KEYBOARD COLUMN
505C 71         00970         LD      (HL),C          ; FIRST DISPLAY A "0"
505D 2801       00980         JR      Z,JUMP8         ; DON'T CHANGE IF NO KEY
505F 34         00990         INC     (HL)            ; MAKE IT A "1" IF A KEY
5060 D5         01000 JUMP8   PUSH    DE              ; SAVE THIS VALUE
5061 DDE1       01010         POP     IX              ; PUT IT IN IX FOR A BIT
5063 D1         01020         POP     DE              ; GET ORIGINAL DE VALUE
5064 19         01030         ADD     HL,DE           ; NOW START NEXT LINE
5065 D5         01040         PUSH    DE              ; SAVE SAME VALUE AGAIN
5066 DDE5       01050         PUSH    IX              ; STASH IT BRIEFLY
506B D1         01060         POP     DE              ; AND BACK INTO DE INTACT
5069 CB13       01070         RL      E               ; DEFINE NEXT KEYBRD ROW
5U6B 10A6       01080         DJNZ    LOOP            ; DO IT FOR EIGHT ROWS
                01090 ;
                01100 ; ##################################################
                01110 ; CLEAR UP POINTERS AND DELAY SO SCREEN DOES NOT JITTER
                01120 ; ##################################################
                01130 ;
506D D1         01140         POP     DE              ; CLEAR THE STACK
506E 010008     01150         LD      BC,800H         ; DELAY VALUE
5071 CD6000     01160         CALL    0060H           ; DELAY SUBROUTINE IN ROM
5074 188F       01170         JR      START           ; START THE ROUTINE AGAIN
                01180 ;
                01190 ; ##################################################
5000            01200         END     ENTER           ; BEGIN IT ALL HERE
00000 TOTAL ERRORS
31044  TEXT AREA BYTES LEFT


ENTER   5000 00250    01200
JUMP1   501A 00440    00420
JUMP2   5024 00520    00500
JUMP3   502E 00600    00580
JUMP4   5038 00680    00660
JUMP5   5042 00760    00740
JUMP6   504C 00840    00820
JUMP7   5056 00920    00900
JUMP8   5060 01000    00980
LOOP    5013 00390    01080
START   5005 00280    01170
```

from 3 to 2, resulting in values from 2C to 2F (, - . /). If a shift key was noted at 0437, the same toggle procedure is followed, changing values 30 to 3B into 20 to 2B (these would become space ! " # $ ( ) * = etc.).

```
0420    C6 40        ADD     A,40
042F    FE 3C        CP      3C
0431    38 02        JR      C,0435
0433    EE 10        XOR     10
0435    CB 08        RRC     B
0437    30 12        JR      NC,044B
0439    EE 10        XOR     10
043B    18 0E        JR      044B
```

Thus, the coding is complete: control codes (00 to 1F), punctuation (20 to 2F), numbers and figures (30 to 3F), upper case (40 to 5F) and lower case (60 to 7F). Just as an aside, the terms lower and upper case are sometimes written small and large case; old-time printers would chuckle at that. The case referred to is a printers case, which, when two were stacked one above the other, contained the capital and small letters. Thought you might like to know that.

Back to the routine, starting at the termination sequence (044C); the decoded character is saved in D, and that is the only information we need to preserve, since the bulk of the work is done.

```
044C    01 AC 00     LD      BC,00AC
044F    CD 60 00     CALL    0060
0452    7A           LD      A,D
```

A delay at 0060 is called, which was intended to wait through the bounce present with normal mechanical switch contacts – but the easily dirtied switches on the TRS-80 are abnormal! This delay uses the accumulator, and when it is free, the value in D is restored to it. This value is compared to 01 (the BREAK code), and returns directly to the main routine (0455) with any code other than BREAK.

If BREAK is discovered, the program executes a call to 0028 (RST 28), returning to Level II.

The routine is quite efficient, and is capable of returning 128 different values at a rate of better than 100 per second – ten times the speed of the world's fastest typist!

3

Software Modifications

Software makes the computer. With that in mind, it's not hard to understand the popularity of the TRS-80. Its BASIC is simple to use and immediately accessible. It reports back errors and provides clear screens and graphics with easy commands. At first, it was hard to imagine how such an elegant BASIC could be improved.

Such illusions could not last long, especially when weakly designed hardware started to exhibit keybounce, when machine language software was so fast but so difficult to access, when putting a program aside meant losing all variables, and so forth.

In this Chapter, several simple but very important software modifications will be presented :

Keyboard debounce with repeating keys, audible beep tone, and an upper/lower case driver.

Two methods of intercepting the BASIC interpreter in order to create your own commands.

Packing machine language programs in simple BASIC strings, where they can be moved about and accessed easily.

Sound and sound-effects generation routines.

Creating somewhat unlistable BASIC programs.

Auto-execution of SYSTEM programs, including an auto-load BASIC module.

A simple machine language monitor accessible directly from BASIC.

BASIC is not an incomprehensible, immutable, indivisible whole, but rather a pliant, carefully sewn, patchwork quilt of useful subroutines. These routines are accessed singly or as groups, not only whenever one of this BASIC's English-language commands is entered, but even while waiting for commands to be entered or programs to be run.

Chapter 1 contained an overview of the structures that BASIC is composed of; below is a more detailed look at the building blocks out of which Level II is created.

1. A power-up sequence: including preparation of blocks of reserved memory, clearing of internal hardware systems, and total memory examination.

2. Numeric conversion routines: single precision to integer and vice versa, numeric to string and vice versa, assignment of levels of precision.

3. Simple arithmetic operations: addition, subtraction, multiplication, division, comparison, and raising to a power (exponentiation); integer, single, and double-precision calculations.

4. Mathematical functions: activities based on the sine function, as well as logrithms, square roots, absolute value and truncation, and random number generation.

5. String operations: concatenation and truncation of strings, direct keyboard scan conversions (INKEY$), alphabetic comparisons.

6. Variables: assignment of numeric, string, and array variable names, variable assignments (LET), updating of values, searching for variable names. Partly integrated with NEW routines.

7. Keyboard input: polling of the keyboard matrix, conversion to characters, searching for carriage return, building a keyboard buffer.

8. Cassette input/output: motor relay control, assembly of parallel data into serial form, timing of output pulses, timing of input, reassembly of data from serial to parallel form.

Listing 3-1. Custom BASIC interpreter patch routine.

```
               00100 ; ####################################################
               00110 ; OEBOUNCE, AUTO-REPEAT, ANO BEEP KEYBOARO PATCH ROUTINE.
               00120 ; THIS ROUTINE AS WRITTEN PATCHES INTO 4016.  TO USE
               00130 ; OTHER ORIVERS SUCH AS LOWERCASE, GRAPHICS, ETC., THE
               DD140 ; RETURN ADDRESS (NORMALLY 03E3) MUST BE REPLACEO BY THE
               001S0 ; AOORESS OF THE OTHER ORIVER.  ALSO, TO USE THIS ROUTINE
               00160 ; WITH THE CUSTOM INTERPRETER /ON ANO /OUT COHHANOS BY
               00170 ; PATCHING THIS ORIVER IN PLACE WITH /ON ANO THE NORHAL
               00180 ; (OR UPPER/LOWER, ETC.) ORIVER IN PLACE WITH /OUT.
               00190 ; ####################################################
               00200 ;
4016           00210          ORG     4016H          ; KEYBOARO SCAN PATCH
4016 0030      00220          OEFW    ENTREE         ; START OF OEBOUNCE ROUT.
3000           00230          ORG     3000H          ; NOTE THAT THIS UTILITY
               00240                                 ; IS CURRENTLY SET UP FOR
               00250                                 : USE WITH A HEHORY AOO'N
               00260                                 ; AT 3000H.  IT CAN BE
               00270                                 ; RE-ORGEO AT ANY LOC'N.
06CC           00280 BASIC2   EQU     06CCH          ; BASIC "REAOY" OISPLAY
4036           00280 KEYHLO   EQU     4036H          ; NORHAL KEYSTROKE STORE
3801           00300 KEYBRO   EQU     3B01H          ; FIRST KEYBOARO AOORESS
401A           00310 HOLOER   EQU     401AH          ; RESERVEO BYTE FOR OELAY
4099           00320 INKEYS   EQU     4099H          ; INKEY$ STORAGE BYTE
0060           00330 OELAYS   EQU     0060H          ; ROH OELAY SUBROUTINE
               00340 ;
               00350 ; ####################################################
               00360 ; ROUTINE BEGINS HERE, PATCHING ITSELF INTO PLACE AT 4016
               00370 ; ####################################################
               00380 ;
3000 ES        00390 ENTREE   PUSH    HL             ; SAVE HL IF TRANSPARENT
3001 210830    00400          LO      HL,START       ; GET START OF ROUTINE
3004 221640    00410          LO      (4016H),HL     ; PUT INTO KEYBOARO PATCH
3007 E1        00420          POP     HL             ; RESTORE HL VALUE
3008 C3CC06    00430          JP      BASIC2         ; ANO GO BACK TO "REAOY"
               00440 ;
               004S0 ; ####################################################
               00460 ; THIS AREA MAKES THE PRELIMINARY CHECK OF KEYBOARO ROWS
               00470 ; ####################################################
               00480 ;
300B 213640    00490 START    LO      HL,KEYHLO      ; SET UP STORAGE AREA
300E 01013B    00500          LO      BC,KEYBRO      ; SET UP FIRST KBO ROW
3011 1600      00S10          LO      0,0            ; SET UP COUNTER OF ROWS
3013 0A        00S20 CHKKEY   LO      A,(BC)         ; FINO IF A KEY PRESSEO
3014 SF        00530          LO      E,A            ; SAVE VALUE IN E REG.
3015 A3        00S40          ANO     E              ; TEST IF KEY WAS PRESSEO
3016 2018      00550          JR      NZ,CKPREV      ; IF YES, SEE IF SAME ONE
3018 77        00560          LO      (HL),A         ; SAVE VALUE IN STORAGE
3019 14        00570 INCO     INC     0              ; INCREHENT ROW COUNTER
301A 2C        00S80          INC     L              ; INCREMENT STORAGE AREA
3018 C801      00S90          RLC     C              ; SHIFT TO NEXT KBO ROW
3010 79        00600          LO      A,C            ; GET VALUE OF KBO ROW
301E 06B0      00610          SUB     80H            ; CHECK IF SHIFT KEY ROW
3020 20F1      00620          JR      NZ,CHKKEY      ; IF NOT THEN CONTINUE
               00630 ;
               00640 ; ####################################################
```

Listing Continued . .

9. Video input/output and display management: screen clear, scrolling, tabbing, character display including line feed, carriage return, backspace, set/reset, POS, POINT, cursor control, characters per line.

10. Printer control: lines per page, top of form, output of characters, waiting for handshake.

11. A command interpreter for organizing the entry points and order of chosen subroutines.

12. Error reporting routines.

13. Program line management routines. Partly integrated with NEW routines.

14. Editing functions: Insert, delete, kill, exit, etc. Integrated in part with program line managment routines.

15. Run-time management: Integrated with most of the above functions, but including subroutine handling, loop handling, etc.

A more complete rundown on the TRS-80 Level II ROM memory map can be found in *Inside Level II, Supermap, Microsoft BASIC Decoded,* and *TRS-80 Disassembled Handbook* (see Appendix II for details).

Sophisticated Debouncing

The first few hundred thousand TRS-80's were afflicted with serious keybounce problems – the appearance of double letters when only a single letter was typed. Full-scale preventive maintenance is presented in the following chapter; but there are software solutions as well. If debounce were the only criterion, though, maintenance would be the ideal solution.

But the software designers made no provision for repeating keys, nor did the hardware designers include access to lower case characters. Furthermore, the silent keyboard remains a frustration to touch-typists and others who do not refer constantly to the screen for feedback.

Thus, some sort of audible reinforcement (as with the Apple's entry-error beep) would be a thoughtful addition to the keying process.

Listing 3-1 is a complete debounce, audible beep, key repeat, and upper/lower case driver routine. The program is written as three independent subroutines, each of which may be disabled or removed before assembly.

Continued Listing

```
               00650 ; CHECKING IS OONE - NOW SEE IF PREVIOUS KEYS HELO OOWN
               00660 ; #######################################################
               00670 ;
3022 0607      00680          LO      B,7               ; ELSE GET NUMBER OF ROWS
3024 20        00690 OECL     OEC     L                 ; HOVE BACK THRU STORAGE
3025 B6        00700          AOO     A,(HL)            ; ANO MAKE TOTAL OF KEYS
3026 10FC      00710          OJNZ    OECL              ; ANO OO IT FOR ALL ROWS
302B A7        00720          ANO     A                 ; TEST IF ANY KEYS STOREO
3029 3E00      00730          LO      A,0               ; A=0, FLAGS REMAIN SAHE
302B C0        00740          RET     NZ                ; BACK IF KEY IN STORAGE
302C 321A40    00750          LU      (HOLOER).A        ; SAVE NEW VALUE IN CTR.
302F C9        00760          RET                       ; ANO BACK TO HAIN ROUT.
               00770 :
               00780 ; #######################################################
               00790 ; NEXT TEST IS FOR STATUS OF INKEY$, IF IT IS IN USE
               00800 ; #######################################################
               00810 ;
3030 A6        00820 CKPREV   ANO     (HL)              ; SEE IF VALUE IS SAHE
3031 2B1F      00830          JR      Z,STORE           ; STORE VALUE IF ZERO
3033 3A9940    00840          LO      A,(INKEYS)        ; FINO VALUE AT INKEY$
3036 A7        00850          ANO     A                 ; SEE IF SOMETHING THERE
3037 20E0      00860          JR      NZ,INCO           ; IF SO THEN GO AWAY
3039 3A1A40    00870          LO      A,(HOLOER)        ; GET OELAY COUNTER VALUE
303C 3C        00880          INC     A                 ; INCREMENT THE COUNTER
3030 321A40    00890          LO      (HOLOER),A        ; ANO SAVE VALUE BACK
3040 FEFF      00900          CP      OFFH              ; IS COUNTER AT ENO YET?
3042 2B09      00910          JR      Z.OECA            ; IF SO, THEN REPEAT
               00920 ;
               00930 ; #######################################################
               00940 ; REPEATING-KEY TIHE-WASTE VALUE (FF) MAY BE VARIEO
               00950 ; #######################################################
               00960 ;
3044 C5        00970          PUSH    BC                ; SAVE BC FOR LATER
3045 06FF      00980          LO      B,OFFH            ; GET OELAY VALUE
3047 00        00990 TMWSTE   NOP                       ; WASTE SOME TIME
304B 10F0      01000          OJNZ    THWSTE            ; ANO OO IT FF TIMES
304A C1        01010          POP     BC                ; RESTORE BC VALUE
304B 1BCC      01020          JR      INCO              ; ANO GO BACK TO SCANNING
3040 30        01030 OECA     OEC     A                 ; MAKE A BECOME FE
304E 321A40    01040          LO      (HOLOER).A        ; ANO SAVE IT IN OELAY
3051 7B        01050          LO      A.E               ; GET KEYSTROKE FOUNO
3052 73        01060 STORE    LO      (HL),E            ; ANO PUT IT IN STORAGE
               01070 ;
               01080 ; #######################################################
               01090 ; OEBOUNCE BELOW MAY BE ELIMINATEO BECAUSE BEEP USES TIME
               01100 ; #######################################################
               01110 ;
3053 C5        01120          PUSH    BC                ; SAVE VALUE IN BC
3054 010002    01130          LO      BC,200H           ; GET OEBOUNCE OELAY
3057 C06000    01140          CALL    OELAYS            ; ANO CALL ROM OELAY
305A C1        01150          POP     BC                ; ANO GET VALUE TO BC
305B 0A        01160          LO      A,(BC)            ; GET VALUE AT KEYBOARO
305C A3        01170          ANO     E                 ; ANO TEST IF IT'S THERE
3050 CB        01180          RET     Z                 ; IF NOT IT WAS BOUNCE
               01190 ;
               01200 ; #######################################################
               01210 ; BEEP ROUTINE PROOUCES VERY SOFT (NOT ANNOYING) SOUNO
               01220 ; #######################################################
               01230 ;
305E C5        01240          PUSH    BC                ; ELSE SAVE THE VALUE
305F E5        01250          PUSH    HL                ; ANO SAVE THE LOCATION
3060 F5        01260          PUSH    AF                ; ANO SAVE THE KEYSTROKE
3061 0640      01270          LO      B,40H             ; ANO KEY BEEP OURATION
3063 3A3040    01280          LO      A,(4030H)         ; ANO GET SCREEN STATUS
3066 E6F0      01290          ANO     OFOH              ; ANO MASK OUT ALL BITS
306B 67        01300          LO      H,A               ; SAVE WAVE "0" MASK IN H
3069 F602      01310          OR      2                 ; CREATE A WAVE "1" MASK
306B 6F        01320          LO      L,A               ; SAVE WAVE "1" MASK IN L
306C 70        01330 LOOP     LO      A,L               ; GET THE WAVE "1" HASK
3060 03FF      01340          OUT     (OFFH),A          ; ANO CREATE WAVEFORH 1
306F 7C        01350          LO      A,H               ; GET THE WAVE "0" MASK
3070 03FF      01360          OUT     (OFFH),A          ; ANO CREATE WAVEFORM 0
3072 C5        01370          PUSH    BC                ; SAVE THE OURATION VALUE
3073 0640      01380          LO      B,40H             ; GET THE PITCH VALUE
3075 10FE      01390          OJNZ    $+0               ; ANO WAIT THRU WAVEFORM
3077 C1        01400          POP     BC                ; RESTORE THE OURATION
307B 10F2      01410          OJNZ    LOOP              ; ANO OO FOR FULL BEEP
307A F1        01420          POP     AF                ; RESTORE KEYSTROKE VALUE
307B E1        01430          POP     HL                ; RESTORE STORAGE VALUE
307C C1        01440          POP     BC                ; RESTORE COUNTER VALUE
3070 C3FB03    01450          JP      03FBH             ; ANO RETURN TO KEYSCAN
               01460 ;
               01470 ; #######################################################
06CC           01480          ENO     BASIC2

    BASIC2 06CC 00280   00430 01480
    CHKKEY 3013 00520   00620
    CKPREV 3030 00820   00550
    OECA   3040 01030   00910
    OECL   3024 00690   00710
    OELAYS 0060 00330   01140
    ENTREE 3000 00390   00220
    HOLOER 401A 00310   00750 00870 00890 01040
    INCO   3019 00570   00060 01020
    INKEYS 4099 00320   00840
    KEYBRO 3801 00300   00500
    KEYHLO 4036 00290   00490
    LOOP   306C 01330   01410
    START  3008 00490   00400
    STORE  3052 01060   00830
    TMWSTE 3047 00990   01000
```

This routine patches into the keyboard control block driver address at **4016**, leading the program to its own entry point instead of 03E3 (see the Supplement to Chapter 2 for details on the operation of the TRS keyboard scan).

At START, the keyboard scan begins with HL pointing to the first position in a keystroke storage buffer (4036). BC points to the first keyboard row (3801). The program proceeds similarly to the normal Level II scan, except that a location (401A) has been set aside to 'count down' the time a key remains pressed. If any key or combination of keys remain pressed for the duration of the loop, the character (normally rejected by Level II's rollover capabilities) is accepted again. This is the start of the repeating process. The INKEY$ storage area is checked (so that programs using INKEY$ are not delayed by an unusable character acceptance), and a short debounce-delay loop is entered.

If a legitimate key is found, a different debounce-delay loop is entered, and a rapidly-fluctuating one-zero pattern is sent to the cassette port (**FF**). This sounds as a beep if an amplifier and speaker are connected. The routine can be exited before the beep, so only the debounce-repeat options are present; it can also be exited after the beep, returning to the main routine with the keystroke.

The final portion of the program is an upper/lower case driver program. This driver is irrelevant unless you have a lower case modification in place, and should be disabled (or not assembled) if you have not made the modification. It merely strips the conversion to upper case normally made by the Level II software, and returns to the running program with the actual key depressed instead of an upper case converted version.

Upper/Lower Case Driver

When the TRS-80 keyboard is used, all characters are automatically converted to upper case before being displayed. The keyboard itself, however, returns a full upper/lower case value (albeit inverted – shift for lower case) to the display routine. The display routine then sends this information to the screen. The screen always displays upper case because the hardware to provide lower case was not a part of the TRS-80 as sold. The addition of a single integrated circuit (see Chapter 4) provides this access.

The lower-case driver patches into the display routine just as the character to be displayed is returned in the accumulator. Control is taken

from the convert-to-upper-case display function in ROM. Ideally, this ROM routine could just be entered after its convert-to-upper case code; unfortunately, this would result in the famous inverted display . . . normal upper case, shifted lower case.

To avoid this, the character is tested and converted to its proper case before being returned to the ongoing display driver routine in ROM. Notice something interesting: when programs are listed with this driver, the letters appear in lower case. That is because when the programs are entered, they are in fact being entered with the keyboard *unshifted.* Because this can be a bit disconcerting (and also quite illegible, since we all are used to upper case lists), an upper case on/off software patch is provided.

```
                  00100 ; ########################################################
                  00110 ; 5IMPLE LOWER-CA5E ORIVER ROUTINE FOR BA5IC AND OOS
                  00120 ; ########################################################
                  00130 ;
7F00              00140         ORG     07F00H          ; NEAR TOP OF BA5IC
                  00150 ;
                  00160 ; ########################################################
                  00170 ; GET CONTROL BLOCK FOR 5CREEN ANO CHANGE CHARACTER5
                  00180 ; ########################################################
                  00190 ;
7F00 006E03       00200 LCORIV  LO      L,(IX+3)        ; IX POINT5 TO OEVICE
7F03 006604       00210         LO      H,(IX+4)        ;   CONTROL BLOCK (VIOEO)
7F06 0A9A04       00220         JP      C,049AH         ; BACK TO 5CREEN ORIVER
7F09 007E05       00230         LO      A,(IX+5)        ; GET CURSOR CHARACTER
7F0C B7           00240         OR      A               ; CHECK IF CUR5OR I5 ON
7F00 2801         00250         JR      Z,GETCHR        ; GET ONE IF CUR5OR OFF
7F0F 77           00260         LO      (HL),A          ; PUT CUR5OR INTO PO5N.
7F10 79           00270 GETCHR  LO      A,C             ; GET CHARACTER TO 5HOW
7F11 FE20         00280         CP      20H             ; 5EE IF A CONTROL COOE
7F13 0A0605       00290         JP      C,0506H         ; BACK TO ORIVER IF C.C.
7F16 FE80         00300         CP      80H             ; SEE IF GRAPHIC CHAR.
7F18 02A604       00310         JP      NC,04A6H        ; BACK TO ORIVER IF SO
7F1B FE5B         00320         CP      05BH            ; CHECK UPPER/LOWER CASE
7F10 300B         00330         JR      NC.CHECK1       ; IF >5B, CHECK FURTHER
7F1F FE40         00340         CP      40H             ; CHECK UPPER CA5E
7F21 380E         00350         JR      C,GOAWAY        ; IF<40, CHECK NO FURTHER
7F23 C620         00360         AOO     A,20H           ; IF 40-5B, MAKE UPPER
7F25 180A         00370         JR      GOAWAY          ; OONE - BACK TO ORIVER
7F27 FE7B         00380 CHECK1  CP      7BH             ; 5EE IF ALPHABETIC
7F29 3006         00390         JR      NC,GOAWAY       ; NO FURTHER IF NOT ALPHA
7F2B FE60         00400         CP      60H             ; 5EE IF ALPHABETIC
7F20 3802         00410         JR      C,GOAWAY        ; NO FURTHER IF NOT ALPHA
7F2F 0620         00420         5UB     20H             ; PLAY 5WITCH TO LOWER
7F31 C37004       00430 GOAWAY  JP      0470H           ; OUT TU ORIVER NOW
                  00440 ;
                  00450 ; ########################################################
                  00460 ; PUT VIOEO PATCH INTO PLACE UPON LOAO
                  00470 ; ########################################################
                  00480 ;
401E              00490         ORG     401EH           ; THI5 IS VIOEO PATCH
401E 007F         00500         OEFW    LCORIV          ; PUT LCORIV ROUTINE IN
                  00510 ;
                  00520 ; ########################################################
06CC              00530         ENO     06CCH           ; BACK TO BA5IC READY
00000 TOTAL ERROR5
```

Listing 3-13. Upper/lower case driver.

Using The Editor/Assembler

The Editor/Assembler is one of the most powerful tools available to the TRS-80 customizer. It is a fast, high-level compiler which produces a block of Z-80 machine code. Its job is to provide an easily accessible substitute for the tedious creation of bytes of Z-80 coded information.

The Z-80 microprocessor is capable of responding to many hundreds of combinations of ones and zeros. Each pattern causes the Z-80 to follow a unique pattern of electronic activity, and many thousands of those activities in concert create a sophisticated language like BASIC.

Using these patterns can be very tricky and time-consuming. Long ago, computer designers learned that it was easier to remember an action like 'load the accumulator with the contents of byte counter register' as 'Load A with B', abbreviated LD A,B. This is much handier than trying to recall 01111000. These abbreviations are called mnemonics, which are what you will find in all the program listings in this book.

You will also find that, instead of specific locations in memory (such as 3C00), there may be a 'label' (such as VIDEO). Once VIDEO has been defined as 3C00 to the Editor/Assembler, it will always interpret the label as the number that was assigned to that label.

Line numbers are provided to keep things in order and to insert or edit pieces of code, and there is space on every line for comments.

Load the Editor/Assembler tape under the SYSTEM command. Its name is EDTASM. When the loading is complete, enter a slash (/), and you will be presented with the prompt:

```
TRS-80 EOITOR/ASSEMBLER 1.1
*_
```

This is EDTASM's equivalent of the BASIC prompt:

```
RAOIO SHACK LEVEL II BASIC
REAOY
>_
```

You are being asked for input. Unlike BASIC, EDTASM has only a few commands. They are (in the order you are likely to use them):

I
This command inserts numbered program lines almost exactly like the BASIC command AUTO. When I is entered alone, numbering starts with line 100 in increments of 10 line numbers. On the other hand, I15,15 will start with line 15 in increments of 15.

P
The equivalent of a list. A single P lists the next sixteen lines of the program. P10:100 lists 10 to 100. P# is the first line, P. is the current line, and P* is the last line.

N
Here is the renumber command. All lines are

automatically renumbered in increments of 10 starting with line 100. Again, specific lines and increments may be specified: N300,50 will renumber all lines in increments of 50, with the first line being 300.

L
Loads a source tape, but not an object tape. Up to a six-character name may be specified.

W
Writes a source tape (the program listing). Up to a six-character name may be specified.

D
Deletes the specified line or lines. D# deletes the first line, D. deletes the current line, and D* deletes the last line. Groups of lines are specified with a colon, as D40:170 or D#:90.

E
The edit function. The pound (#), period (.), and asterisk (*) represent the first, current, and last lines. A line number (as E400) may be specified.The editing functions are identical to BASIC's editing functions – except that characters to be deleted are *not* deliniated by exclamation points.

R
Replaces the indicated line. The line number is presented, and new information may be entered.

F
This command finds a text string. It is not followed by a space. To search for the phrase 'ENTRY', type FENTRY (ENTER). The entire line containing the phrase will be printed. To find the next identical phrase, merely type F (ENTER).

H
This sends the source listing, unassembled, to the printer. The complete source listing, including line numbers, is printed. As usual, (#), (.) and (*) may be used to indicate first, current, and last line, and groups of lines may be printed (as H55:3000).

T
The poor person's text editor. The source code is sent to the printer without line numbers. Thus, text may be entered a line at a time, and the numberless result printed. The same functions provided with H are available.

B
The exit to BASIC. As sold, EDTASM returns only to MEMORY SIZE?, and all programs and information, including EDTASM itself, are lost. Patches are available to re-route this exit.

A
This command directs EDTASM to compile your source code into object code, make a list of all the labels (symbols) used, and check for errors. The A command may be followed by a six-letter name, as well as the 'switches' /NL (no listing), /NS (no symbol table), /NO (no object code), or /WE (wait upon error). The switches may be used in any combination, and are useful in shaking the errors out of an assembly program.

Lines are always entered into EDTASM under the I (insert) or R (replace) commands. A line number is presented, so:

```
00010*_
```

Several columns are then available, consisting respectively of an optional label, the mnemonic instruction, the 'operand' (if any), and any comments (always following a semicolon). A complete group of lines would look like this:

```
00010   VIOEO   EQU    3COOH        ;SCREEN TOP
00020           ORG    5000H        ;START PROGRM
00030   ENTRY   LO     A,B          ;GET B INTO A
00040           LO     HL,VIOEO     ;HL AT SCREEN
```

This excerpt gives this information: the label VIDEO is an 'equate' (is defined as) location 3C00. The program starts (has its origin – ORG) at 5000. The label ENTRY is assigned to the start of the program, and that program's first action is to load the accumulator with register B. Next, the HL register is pointed to VIDEO (3C00), the start of the screen memory.

When told to assemble this (using the A command), the results will look like the following:

```
3C00           00010  VIOEO   EQU  3COOH       ;SCREEN TOP
5000           00020          ORG  5000H       ;START PROGRM
5000 78        00030  ENTRY   LO   A,B         ;GET 8 INTO A
5001 21003C    00040          LO   HL,VIOEO    ;HL AT SCREEN
```

The EDTASM program evaluated all the information in the source code and created the columns at the left. The first column specifies the current address, and the second column specifies the machine language code, if any, for that particular line. Note the correct assignment of 3C00 to VIDEO in line 00040. 78 is the machine code for LD A,B and 21 is the machine code for LD HL,NNNN. In this case, NNNN is VIDEO is 3C00.

For detailed instructions, refer to the EDTASM instruction manual. One thing to note: you can conserve source code memory space by using the right arrow (tab) instead of spacing between program lines, labels, commands, operands, and comments. Each tab is a single character, but spaces are counted separately.

```
               00100 ; #######################################################
               00110 ; CUSTOM BASIC INTERPRETER PATCH FOR USE WITH ALL OF THE
               00120 ; ROUTINES PRESENTED IN CUSTOM TRS-80 WHICH ARE TRANS-
               00130 ; PARENT TO BASIC.  THESE ROUTINES ARE CALLED BY THIS
               00140 ; ROUTINE, WHICH HAS ALREADY PLACED A RETURN VALUE ON THE
               00150 ; STACK.  ALL TRANSPARENT ROUTINES MUST EXECUTE A RETURN
               00160 ; INSTRUCTION AS THEIR FINAL INSTRUCTION TO WORK WITH
               00170 ; THIS CUSTOM INTERPRETER ROUTINE.  THE COMMANDS AVAIL-
               00180 ; ABLE WITH THIS INTERPETER ARE:
               00190 ;        /LOAD    /SAVE    /NEW     /OPEN
               00200 ;        /ON      /OFF     /GET     /PUT
               00210 ;        /STEP    /MEM
               00220 ; AND OTHER USER-DEFINED "/" COMMANDS AND ROUTINES.
               00230 ; THIS ROUTINE HAS PUSHED THE RETURN ADDRESS (107B) ON
               00240 ; THE STACK.  THE ROUTINE JUMPED TO IS A PSEUDO-CALL
               00250 ; IN THAT IT EXECUTES A "RET", THUS RETURNING TO 1078.
               00260 ; #######################################################
               00270 ;
1078           00280 BYTE    EQU     107BH   ;ROM READ KEYS & TOKENIZE
               00290 ;
               00300 ; #######################################################
               00310 ; CHECK THAT THE BASIC STACK IS IN INTERPRETATION MODE
               00320 ; #######################################################
               00330 ;
0000 E3        00340 BEGIN   EX      (SP),HL          ; GET SP INTO HL FOR TEST
0001 70        00350         LD      A,L              ; GET L INTO A FOR TEST
0002 FE5B      00360         CP      5BH              ; IS LSB OF STACK 5B?
0004 2003      00370         JR      NZ,NOTRDY        ; NOT INTERPRETING IF NZ
0006 7C        00380         LD      A,H              ; GET H INTO A FOR TEST
0007 FE10      00390         CP      10H              ; IS MSB OF STACK 10?
0009 E3        00400 NOTRDY  EX      (SP),HL          ; RESTORE STACK TO SP
000A C27810    00410         JP      NZ,BYTE          ; IF NOT 10H THEN TO ROM
   ..          00420 ;
               00430 ; #######################################################
               00440 ; MUST HAVE BEEN AT 105B FOR INTERPRETATION; THEREFORE,
               00450 ; CHECK TO SEE IF SPECIAL SLASH (/) COMMAND THAT IS NEXT
               00460 ; #######################################################
               00470 ;
0000 C07810    00480         CALL    BYTE             ; READ CHAR. & TOKENIZE
0010 F5  ..    00490         PUSH    AF               ; SAVE VALUE READ
0011 FE00      00500         CP      000H             ; IS IT "/" COMMAND?
0013 2805      00510         JR      Z,OKSLSH         ; IF SO, THEN CONTINUE
0015 F1        00520         POP     AF               ; ELSE RESTORE AF VALUE
0016 28        00530         DEC     HL               ; PUT POINTER BACK ONE
0017 C37810    00540         JP      107BH            ; AND BACK TO NORMAL ROM
               00550 ;
               00560 ; #######################################################
               00670 ; SLASH (/) HAS BEEN FOUND, THEREFORE MUST BE COMMAND
               00680 ; #######################################################
               00690 ;
001A F1        00600 OKSLSH  POP     AF               ; RESTORE VALUE TO AF
001B C07810    00810         CALL    BYTE             ; NEXT COMMAND IN LINE
001E 2003      00620         JR      NZ,SAVE          ; GO IF ONE IS IN PLACE
0020 C39718    00630 SYNERR  JP      1997H            ; ?SN ERROR IF LINE END
               00640 ;
               00660 ; #######################################################
               00660 ; SINCE SLASH & NEXT CHARACTER HAS BEEN FOUND, NOW NEXT
               00670 ; CHARACTER IN LINE MUST BE TESTED FOR VALIDITY AS USER-
               00680 ; DEFINED COMMAND.  SEE ABOVE FOR THOSE AVAILABLE HERE.
               00890 ; #######################################################
               00700 ;
0023 117810    00710 SAVE    LD      DE,1078H         ; GET RETURN ADDRESS
0026 06        00720         PUSH    DE               ; PLACE IT ON STACK
0027 FEA0      00730         CP      0A0H             ; ---- SAVE ----
0029 CA0000    00740         JP      Z,SAVER          ; GO TO SAVE ROUTINE
002C FEBB      00750         CP      0BBH             ; ---- NEW ----
002E CA0000    00760         JP      Z,RENEW          ; GO TO RENEW ROUTINE
0031 FEA2      00770         CP      0A2H             ; ---- OPEN ----
0033 CA0000    00780         JP      Z.OPENER         ; GO TO OPEN ROUTINE
0036 FECC      00790         CP      0CCH             ; ---- STEP ----
0038 CA0000    00800         JP      Z,STPSET         ; GO TO STEPPING ROUTINE
0038 FEC8      00810         CP      0C8H             ; ---- MEM ----
0030 CA0000    00820         JP      Z.MEMSET         ; GO TO MEMORY SET ROUT.
0040 FEEA      00830         CP      0EAH             ; ---- LOC ----
0042 CA0000    00840         JP      Z,RELOC          ; GO TO RELOCATION ROUT.
0045 FEA1      00850         CP      0A1H             ; ---- ON ----
0047 CA0000    00860         JP      Z,KEYON          ; GO TO DEBOUNCE ON ROUT.
004A FEA0      00870         CP      0A0H             ; ---- OUT ----
004C CA0000    00880         JP      Z,KEYOFF         ; KILL DEBOUNCE ROUTINE
004F FEA4      00890         CP      0A4H             ; ---- GET ----
0051 CA0000    00900         JP      Z,COPYIN         ; GO TO READ TAPE ROUTINE
0054 FEA5      00910         CP      0A5H             ; ---- PUT ----
0056 CA0000    00920         JP      Z,DUBBER         ; GO TO WRITE TAPE ROUT.
0059 C32000    00930         JP      SYNERR           ; ?SN ERROR IF UNDEFINED
               00940 ;
               00950 ; #######################################################
               00960 ; THIS ROUTINE WILL NOT ASSEMBLE AS IT STANDS.  IT MUST
               00970 ; BE APPENDED TO THE OTHER ROUTINES WHICH WILL BE USED
               00980 ; IN CONJUNCTION WITH BASIC.  ALL THE TERMS LISTED ABOVE
               00990 ; MUST BE DEFINED, OR ELSE THEY MUST BE DELETED FROM THE
               01000 ; ASSEMBLY LISTING.
               01010 ; #######################################################
               01020 ;
0000           01030         END
00010 TOTAL ERRORS
```

Patching the BASIC Interpreter

Each time a BASIC command is entered or a program line is being run, a section of ROM evaluates each of these commands in order, jumping to internal subroutines that will produce the desired result. This section of ROM is called the interpreter, an area which translates the commands into program action.

At address 4003, the machine language instruction C3 78 1D can be found, which means 'jump to address 1D78'. 1D78 is the main entry point to the BASIC interpreter. But the routine can be intercepted *before* going to 1D78, by patching a different jump into addresses 4004 and 4005.

This intercept is very important, because every BASIC - transparent software modification in this book will be patched into this location, leading to the master custom interpreter program below (Listing 3-2). When a command line is entered, the program in Listing 3-2 intercepts the routine at 4003, and first examines the status of the stack pointer; if it points to 1D5B, then the intercept program knows BASIC is in the interpretation mode.

Its next step is to CALL 1D78. By calling 1D78 instead of jumping to it, a 'tokenized' version of the next command in line is returned to the master custom interpreter. Tokenizing is an important, specialized process which allows the BASIC listings to use very little memory and allows the interpreter to evaluate commands at high speed.

When the token is returned to the custom interpreter, it can then be evaluated to see if it is a specially designated indicator command.

If the slash command indicator is found by the custom interpreter, it moves on to a lookup table to search for one of the specialized commands. All these commands will be tokens as well, so only a single byte comparison need be made.

There is another method of patching into the BASIC interpreter. If you are a Level II user, merely enter the command OPEN. Very promptly the computer will respond with '?L3 ERROR'. What is an '?L3 ERROR'? It refers to a 'Level III Error', the extended BASIC that is available as a part of the TRS-80 disk system.

Now enter the statement OPNE. This time a '?SN ERROR' is produced. How does the machine know that OPEN is a disk command and that OPNE is just garbage?

```
                 00100 ;
                 00110 ; #####################################################
                 00120 ; FULL-FEATURED KEY/SCREEN DRIVER - DENNIS BATHORY KITSZ
                 00130 ; THIS ROUTINE IS A LEVEL II KEYBOARD REPLACEMENT ROUTINE
                 00140 ; CAPABLE OF PROVIDING:  AUTOREPEAT AFTER SELECTED DELAY
                 00150 ; (FOUND IN B REGISTER IN DELAY SECTION); BEEP WITH ANY
                 00160 ; CHOICE OF PITCH; RESULTANT DEBOUNCE; CORRECTED SHIFT-
                 00170 ; DOWN ARROW CONTROL CODE FOR EARLIER LEVEL II ROMS; A
                 00180 ; SHIFT-0 SELECTABLE UPPER/LOWER CASE DRIVER AND DISPLAY.
                 00190 ; NOTE THAT THIS ROUTINE IS SET UP FOR USE AT 3039 HEX
                 00200 ; (12345 DECIMAL) FOR ENTRY IN THE MEMORY SIDECAR WHICH
                 00210 ; IS ADDRESSED FROM 3000 TO 3700 HEX.  IT MAY BE SET TO
                 00220 ; ANY ORIGIN OF THE USER'S CHOICE, SUCH AS USUAL HIGH MEM
                 00230 ; #####################################################
                 00240 ;
4099             00250 INKEYS  EQU     4099H   ;INKEY$ BYTE STORAGE AREA
403D             00260 PORTFF  EQU     403DH   ;CASSETTE OUTPUT PORT
401A             00270 KPLACE  EQU     401AH   ;1-BYTE KEYSTROKE STORE
4019             00280 SHIFTR  EQU     4019H   ;STORAGE FOR LC DRIVER
                 00290 ;
                 00300 ; #####################################################
                 00310 ; PATCH KEYBOARD ROUTINE INTO 4016 AND DISPLAY INTO 401E
                 00320 ; #####################################################
                 00330 ;
4016             00340         ORG     4016H           ; START OF KEYBOARD SCAN
4016 393D        00350         DEFW    KBPFIX          ; PATCH KEYBOARD ROUTINE
401E             00360         ORG     401EH           ; START OF DISPLAY SWEEP
401E 2A31        00370         DEFW    LOWER           ; PATCH UPPR/LOWR ROUTINE
                 00380 ;
3039             00390         ORG     3039H           ; START AT MEMORY SIDECAR
                 00400 ;
                 00410 ; #####################################################
                 00420 ; SET STORAGE #1, ROW #1, COUNTER #0 PARAMETERS FOR SCAN
                 00430 ; #####################################################
                 00440 ;
3039 213640      00450 KBPFIX  LD      HL,4036H        ; STORAGE FOR KEYSTROKE
303C 010138      00460         LD      BC,3801H        ; FIRST ROW OF KEYS
303F 1600        00470         LD      D,0             ; COUNTER FOR COLUMS
                 00480 ;
                 00490 ; #####################################################
                 00500 ; CHECK EACH ROW OF KEYS IN SEARCH OF ONE THAT IS PRESSED
                 00510 ; #####################################################
                 00520 ;
3041 0A          00530 KEYPRS  LD      A,(BC)          ; RETRIEVE ROW CONTENTS
3042 5F          00540         LD      E,A             ; SAVE IT TEMPORARILY
3043 A3          00550         AND     E               ; SET FLAGS FOR TEST
3044 2018        00560         JR      NZ,STROKE       ; NOT ZERO IF KEY PRESSED
3046 77          00570         LD      (HL),A          ; SAVE CURRENT VALUE
                 00580 ;
                 00590 ; #####################################################
                 00600 ; INCREMENT AND ROTATE PATTERN CHECKS EACH ROW IN TURN
                 00610 ; #####################################################
                 00620 ;
3047 14          00630 RECHEK  INC     D               ; INCREMENT ROW COUNTER
3048 2C          00640         INC     L               ; INCREMENT STORAGE AREA
3049 CB01        00650         RLC     C               ; GET NEXT KEYBRD COLUMN
304B 79          00660         LD      A,C             ; GET VALUE INTO ACCUM.
                 00670 ;
                 00680 ; #####################################################
                 00690 ; CHECK IF LAST VALID ROW (I.E., NOT INCLUDING SHIFT KEY)
                 00700 ; #####################################################
                 00710 ;
304C D680        00720         SUB     80H             ; LAST ROW IS 3880 HEX
304E 20F1        00730         JR      NZ,KEYPRS       ; NEXT CHECK IF NOT DONE
                 00740 ;
                 00750 ; #####################################################
                 00760 ; AUTOREPEAT STATUS TEST ... CHECK IF KEYBOARD IS CLEAR
                 00770 ; #####################################################
                 00780 ;
3050 0607        00790         LD      B,7             ; COUNTER OF KBRD ROWS
3052 2D          00800 CLRMEM  DEC     L               ; START COUNTING BACK
3053 86          00810         ADD     A,(HL)          ; AND ADD IT UP IN ACCUM
3054 10FC        00820         DJNZ    CLRMEM          ; AND DO IT FOR 7 ROWS
3056 A7          00830         AND     A               ; TEST FOR ANY KEY DOWN
3057 3E00        00840         LD      A,0             ; A=0, FLAGS ARE INTACT
3059 C0          00850         RET     NZ              ; BACK IF KEYS IN USE
                 00860 ;
                 00870 ; #####################################################
                 00880 ; RESET AUTOREPEAT DELAY TO ZERO IF THE KEYBOARD IS CLEAR
                 00890 ; #####################################################
                 00900 ;
305A 321A40      00910         LD      (KPLACE),A      ; ELSE DELAY GETS RESET
305D C8          00920         RET                     ; AND GO BACK ANYWAY
                 00930 ;
                 00940 ; #####################################################
                 00950 ; IF KEYSTROKE IS FOUND, CHECK STATUS OF AUTOREPEAT LOOP
                 00960 ; #####################################################
                 00970 ;
305E A6          00980 STROKE  AND     (HL)            ; CHECK KEYSTROKE STORAGE
305F 281E        00990         JR      Z,FOUND         ; NEW KEY IF NOT SAME
3061 3A9940      01000         LD      A,(INKEYS)      ; CHECK STATUS OF INKEY$
3064 A7          01010         AND     A               ; TEST IF SOMETHING THERE
3065 20E0        01020         JR      NZ,RECHEK       ; IF THERE IS, LOOP BACK
3067 3A1A40      01030         LD      A,(KPLACE)      ; NOW CHECK SPECIAL STORE
306A 3C          01040         INC     A               ; LET STORE = STORE + 1
```

Listing Continued . . .

It is in this distinction that the other patch can be made into the BASIC interpreter. All the DOS (disk operating system) commands *already exist* in Level II BASIC! A patch point (sometimes called a 'vector', other times a 'hook') is provided for each of these commands in RAM. When the disk system is added to the TRS-80, each of these patch points is filled with a jump to a DOS parameter.

Table 3-(?) presents a list of the DOS commands and their patch points in RAM. If you are not (and do not plan to be) a disk user, and if your programs will not be sold to potential disk users, then these patch points are for you. Each one can be used for your own set of commands, and every one will be accepted by a running BASIC program.

List of DOS Patch Points

DOS COMMAND	REPLACEMENT PATCH POINTS (HEX)	REPLACEMENT PATCH POINTS (DECIMAL)
CVI	4153 - 4154	16723 - 16724
FN	4156 - 4157	16726 - 16727
CVS	4159 - 415A	16729 - 16730
DEF	415C - 415D	16732 - 16733
CVD	415F - 4160	16735 - 16736
EOF	4162 - 4163	16738 - 16739
LOC	4165 - 4166	16741 - 16742
LOF	4168 - 4169	16744 - 16745
MKI$	416B - 416C	16747 - 16748
MKS$	416E - 416F	16750 - 16751
MKD$	4171 - 4172	16753 - 16754
CMD	4174 - 4175	16756 - 16757
TIME$	4177 - 4178	16759 - 16760
OPEN	417A - 417B	16762 - 16763
FIELD	417D - 417E	16765 - 16766
GET	4180 - 4181	16768 - 16769
PUT	4183 - 4184	16771 - 16772
CLOSE	4186 - 4187	16774 - 16775
LOAD	4189 - 418A	16777 - 16778
MERGE	418C - 418D	16780 - 16781
NAME	418F - 4190	16783 - 16784
KILL	4192 - 4193	16786 - 16787
&	4195 - 4196	16789 - 16790
LSET	4198 - 4199	16792 - 16793
RSET	419B - 419C	16795 - 16796
INSTR	419E - 419F	16798 - 16799
SAVE	41A1 - 41A2	16801 - 16802
LINE	41A4 - 41A5	16804 - 16805

Creating BASIC Tokens

Here's a program to start this discussion:

```
10 CLS : REM XXXXXXXXXXXXX
20 Y = 15360
30 FOR X = 17129 TO 17300
40 POKE Y, PEEK (X)
50 Y = Y + 1 : NEXT X
60 PRINT "END OF PROGRAM"
70 PRINT "LIST OF PROGRAM"
80 LIST : REM ZZZZZZZZZZZZ
```

On the screen you now have two versions of the identical information – the BASIC program. The lines of X's and Z's are there to help you locate the program amidst some of what looks like garbage. You will also see that there are some familiar elements missing: the line numbers (which have been converted to hexadecimal), and all the BASIC commands

Continued Listing

```
3068 321A40   01050        LD    (KPLACE),A    ; AND PUT IT BACK THERE
306E FEFF     01060        CP    0FFH          ; CHECK IF IT IS AT END
3070 2808     01070        JR    Z,DECA        ; IF SO, THEN HOLD THERE
3072 C5       01080        PUSH  BC            ; SAVE ROW COUNTER REG.
3073 06FF     01090        LD    B,0FFH        ; GET DELAY VALUE INTO B
3075 10FE     01100 TMWSTE DJNZ  THWSTE        ; AND DELAY JUST A BIT
3077 C1       01110        POP   BC            ; AND RESTORE ROW COUNTER
3078 18C0     01120        JR    RECHEK        ; AND BACK TO CHECK NEXT
307A 3D       01130 DECA   DEC   A             ; LET A = A - 1 (STORAGE)
307B 321A40   01140        LD    (KPLACE),A    ; AND PUT IT IN STORAGE
              01150 ;
              01160 ; ####################################################
              01170 ; GET KEYBOARD BYTE BACK, STORE AND PREPARE TO MANIPULATE
              01180 ; ####################################################
              01190 ; FIRST CONVERT D FROM COUNTER TO PSEUDO ASCII EQUIVALENT
              01200 ; ####################################################
              01210 ;
307E 7B       01220        LD    A,E           ; GET KEYBOARD BYTE BACK
307F 73       01230 FOUND  LD    (HL),E        ; STORE IT IN STROKE AREA
3080 7A       01240        LD    A,D           ; GET ROW COUNTER FROM D
3081 07       01250        RLCA                ; AND BEGIN A PROCESS...
3082 07       01260        RLCA                ; ...OF CONVERTING IT...
3083 07       01270        RLCA                ; ...TO AN OFFSET VALUE.
3084 57       01280        LD    D,A           ; AND PUT IT BACK IN D
              01290 ;
              01300 ; ####################################################
              01310 ; NOW PREPARE ROW COUNTER C TO COMPLETE ASCII CONVERSION
              01320 ; ####################################################
              01330 ;
3085 0E01     01340        LD    C,1           ; GET NUMBER ONE READY
3087 79       01350 BACKUP LD    A,C           ; ACCUM. HAS C FOR MATH
3088 A3       01360        AND   E             ; TEST IF C = KEYSTROKE
3089 2005     01370        JR    NZ,AROUND     ; IF NOT, THEN GO AROUND
308B 14       01380        INC   D             ; ELSE D = ROW + COLUMN
308C CB01     01390        RLC   C             ; C SET TO NEXT COLUMN
308E 18F7     01400        JR    BACKUP        ; GO BACK AND TEST AGAIN
              01410 ;
              01420 ; ####################################################
              01430 ; SHIFT ROW IS TESTED TO DETERMINE UPPER/LOWER STATUS
              01440 ; ####################################################
              01450 ;
3090 3A803B   01460 AROUND LD    A,(3880H)     ; GET SHIFT ROW FOR TEST
3093 47       01470        LD    B,A           ; AND SAVE IT IN B
3094 7A       01480        LD    A,D           ; GET ROW COUNTER BACK
3095 C640     01490        ADD   A,40H         ; AND CONVERT TO ASCII
3097 FE60     01500        CP    60H           ; IS IT UP/LW/GRAFIX/ETC
3099 3016     01510        JR    NC,Z0429H     ; GO OUT IF GRAPHICS MODE
309B 57       01520        LD    D,A           ; SAVE PARTLY CONVERTED
              01530 ;
              01540 ; ####################################################
              01550 ; SHIFT/DOWN ARROW CHECKED FOR CONVERSION TO CONTROL CODE
              01560 ; ####################################################
              01570 ;
309C 3A403B   01580        LD    A,(3840H)     ; GET VALUE FOUND 7TH ROW
309F E610     01590        AND   10H           ; CHECK IF DOWN ARROW
30A1 2009     01600        JR    NZ,CNTROL     ; IF SO, PRODUCE CONTROL
30A3 7A       01610        LD    A,D           ; ELSE GET VALUE BACK
30A4 CB08     01620        RRC   B             ; B BUMPS INTO CARRY FLAG
30A6 3830     01630        JR    C,GOAWAY      ; IF CARRY, THEN SHIFT
              01640 ;
              01650 ; ####################################################
              01660 ; LOWER CASE CONVERSION, MASK STRIPPING, FINAL TOUCHES
              01670 ; ####################################################
              01680 ;
30A8 C620     01690        ADD   A,20H         ; IF NOT THEN LOWER CASE
30AA 1839     01700        JR    GOAWAY        ; AND GET OUT OF ROUTINE
30AC 7A       01710 CNTROL LD    A,D           ; IF CONTROL CODE, GET IT
30AD D640     01720        SUB   40H           ; GET RID OF ASCII MASK
30AF 1834     01730        JR    GOAWAY        ; AND GET OUT OF ROUTINE
30B1 D670     01740 Z0429H SUB   70H           ; THE BALANCE OF THE
30B3 3010     01750        JR    NC,Z0430H     ;    ROUTINE BELOW UP TO
30B5 C640     01760        ADD   A,40H         ;    THE BEEP SECTION IS
30B7 FE3C     01770        CP    3CH           ;    VIRTUALLY IDENTICAL
30B9 3802     01780        JR    C,Z0435H      ;    TO THE KEYBOARD
30BB EE10     01790        XOR   10H           ;    DETERMINATION SUB-
30BD CB08     01800 Z0435H RRC   B             ;    ROUTINE FOUND IN
30BF 3024     01810        JR    NC,GOAWAY     ;    ROM.  A COMPLETE
30C1 EE10     01820        XOR   10H           ;    DESCRIPTION OF THIS
30C3 1820     01830        JR    GOAWAY        ;    SECTION OF THE KEY-
30C5 07       01840 Z0430H RLCA                ;    BOARD SCAN IS FOUND
30C6 CB08     01850        RRC   B             ;    IN THE CHAPTER
30C8 3001     01860        JR    NC,Z0443H     ;    SUPPLEMENT ON THE
30CA 3C       01870        INC   A             ;    ROM KEYBOARD SCAN.
30CB 210530   01880 Z0443H LD    HL,TABLET     ; THIS TABLE IS CHANGED
30CE 4F       01890        LD    C,A           ;    FROM THE ONE FOUND
30CF 0600     01900        LD    B,0           ;    IN EARLIER ROMS, BUT
30D1 09       01910        ADD   HL,BC         ;    THE ROUTINE USED TO
30D2 7E       01920        LD    A,(HL)        ;    ACCESS IT IS THE
30D3 1810     01930        JR    GOAWAY        ;    SAME.
              01940 ;
              01950 ; ####################################################
              01960 ; TABLE BELOW DETERMINES TRS-80 (NOT ASCII) CONTROL CODES
              01970 ; SEE SUPPLEMENT ON KEYBOARD SCAN FOR DETAILS ON CODES
              01980 ; ####################################################
              01990 ;
```

Listing Continued . . .

(CLS, FOR, TO, POKE, PEEK, NEXT, PRINT, and LIST). What has happened to them?

For two purposes – economy of memory and speed of execution – legitimate BASIC commands are converted to single-byte keys called 'tokens'. When you enter a BASIC command line, a subroutine evaluates each character group in that line, searching through all the keywords in ROM until it finds a match. When it finds a match, it replaces the original group of characters (PRINT, for example, which is five characters) with a single byte (178 in this case). Four bytes are saved, and the lengthy process of looking up the word PRINT is eliminated at run time.

Evaluating for tokens is indeed a time-consuming process. If you type 255 characters of garbage and press (ENTER), the computer will spend nearly two seconds attempting to tokenize that line before reporting a ?SN ERROR. A line which uses the command CHR$() very often also takes time to tokenize. You can imagine the speed difference if this process were left to be done at RUN time.

The presence of tokens in a complicated program can make the difference between a running program and an ?OM ERROR. As an experiment, return to MEMORY SIZE? and respond with 17250. This gives you about 50 bytes of program space (at least 83 are needed to run any program). Enter these lines:

```
10 PRINT"THIS IS A TEST TO FIND OUT"
20 PRINT"HOW MUCH MEMORY SPACE IS IN HERE"
```

In attempting to run this program, you will get an ?OM ERROR. Now remove the word 'IN' and one space from the second line. The program will run fine. Finally, insert PRINT: on line 10. In spite of the fact that it *looks like* you have inserted 6 new characters (P-R-I-N-T-:), you have really only inserted two – the PRINT token (178) and a colon.

There is a lesson in this. If your program is running quite close to the end of your system's available memory, try cutting down the lines of text within the program. Many more BASIC commands will then open up for use.

Another interesting trick opens up. You may have a BASIC program which you would like to convert for use on a printer. This can take up quite a bit of time. As a quick fix, you might just leaf through your program, replacing all PRINTs with LPRINTs. This won't work every time (I'll explain later), but it's a useful

Continued Listing

```
30DS 000D      02000 TABLET  DEFW    0000H           ; CARR. RET. / CARR. RET.
30D7 1F1F      02010         OEFW    1F1FH           ; CLEAR SCRN / CLEAR SCRN
3009 0101      02020         DEFW    0101H           ; BREAK KEY / BREAK KEY
300B SB1B      02030         OEFW    1BSBH           ; EOIT ESCAPE / UP ARROW
30D0 0A00      02040         DEFW    000AH           ; NOP (CHANGE) / LINEFEED
30DF 0B1B      020S0         DEFW    1B0BH           ; BACKSP. LINE / BACKSP.
30E1 0919      02060         OEFW    1B0BH           ; 32-CHAR MOOE / HOR. TAB
30E3 2020      02070         OEFW    2020H           ; SPACE / SPACE
               020B0 ;
               02090 ; ####################################################
               02100 ; FINAL VALUE IS SAVED IN O; STATUS OF SHIFT-O TESTEO
               02110 ; ####################################################
               02120 ;
30ES 57        02130 GOAWAY  LO      O,A             ; SAVE VALUE IN O REG.
30E6 3A103B    02140 BEEEEP  LD      A,(3B10H)       ; GET O KEYBOARO ROW
30E9 FE01      02150         CP      1               ; SEE IF IT IS ZERO (0)
30EB 2016      02160         JR      NZ,BLEEEP       ; GO OUT IF NOT ZERO
30ED 3AB03B    02170         LO      A,(3BB0H)       ; IF O, CHECK SHIFT ROW
30F0 FE01      021B0         CP      1               ; CHECK IF SHIFT KEY
30F2 200F      02190         JR      NZ,BLEEEP       ; IF NOT GO OUT TO BEEP
30F4 3A1940    02200         LD      A.(SHIFTR)      ; ELSE GET SHIFTLOCK
30F7 EE01      02210         XOR     1               ; ANO SWITCH 1-0 OR 0-1
30F9 321940    02220         LD      (SHIFTR),A      ; ANO PUT IN SHIFTLOCK
30FC 010005    02230         LD      BC,S00H         ; GET LONGER DELAY
30FF C06000    02240         CALL    0060H           ; CALL ROM OELAY SUBR.
3102 C9        022S0         RET                     ; ANO GO BACK, NO BEEP
               02260 ;
               02270 ; ####################################################
               02280 ; DEBOUNCE IS ADOEO; ALTERNATE: BEEP MAY BE LENGTHENED
               02290 ; ####################################################
               02300 ;
3103 01B001    02310 BLEEEP  LO      BC,1B0H         ; DEBOUNCE VALUE AND
3106 C06000    02320         CALL    0060H           ;    DELAY CALL TO ROM
3109 7A        02330         LD      A,O             ; GET STOREO VALUE BACK
310A C5        02340         PUSH    BC              ; SAVE BC REGISTER
310B F5        023S0         PUSH    AF              ; SAVE ACCUM ANO FLAGS
310C 0640      02360         LO      B,40H           ; GET NOTE LENGTH VALUE
310E 3A3040    02370         LO      A,(PORTFF)      ; GET STATUS OF SCREEN
3111 E6FD      02380         ANO     0F0H            ; MASK SCREEN CHANGE OUT
3113 67        02390         LO      H,A             ; STORE MSB IN H REG.
3114 F602      02400         OR      2               ; SET BIT 1 TO BE ON
3116 6F        02410         LD      L,A             ; STORE ALT. MSB IN L REG
3117 7D        02420 BEEPER  LO      A,L             : GET ALT. MSB TO OUTPUT
311B D3FF      02430         OUT     (OFFH),A        : AND OUTPUT RISING WAVE
311A 7C        02440         LD      A,H             ; NOW GET NORMAL MSB
311B D3FF      02450         OUT     (OFFH),A        ; ANO OUTPUT FALLING WAVE
3110 CS        02460         PUSH    BC              ; SAVE NOTE LENGTH REG.
311E 0640      02470         LO      B,40H           ; GET FREQUENCY DELAY
3120 10FE      02480 FREQCY  OJNZ    FREQCY          ; ANO WAIT A LITTLE WHILE
3122 C1        02490         POP     BC              ; NOW RESTORE LENGTH VAL.
3123 10F2      02S00         DJNZ    BEEPER          ; ANO GO BACK THAT LENGTH
312S F1        02S10         POP     AF              ; RESTORE ORIGINAL CHAR.
3126 C1        02S20         POP     BC              ; ANO RESTORE ORIGINAL BC
3127 C35204    02530         JP      0452H           ; BACK TO ROM IN PROGRESS
   /           02S40 ;
               02SS0 ; ####################################################
               02560 ; THIS IS LOWER CASE DETERMINATION FROM STOREO INFO
               02S70 ; ####################################################
               025B0 ;
312A FS        02S90 LDWER   PUSH    AF              ; SAVE NEEOEO REGISTER
312B 3A1940    02600         LD      A,(SHIFTR)      ; GET STATUS OF SHIFTLOCK
312E FE01      02610         CP      1               ; CHECK IF STATUS = 1
3130 2804      02620         JR      Z,LOWER1        ; IF SO THEN GO TO L.C.
3132 F1        02630         POP     AF              ; ELSE GET ORIGINAL VALUE
3133 C35B04    02640         JP      045BH           ; LEAVE TO NORMAL OISPLAY
3136 F1        02650 LOWER1  POP     AF              ; ELSE GET ORIGINAL VALUE
3137 0D6E03    02660         LD      L,(IX+3)        ; GET CURSOR LSB INTO L
313A 006604    02670         LD      H,(IX+4)        ; GET CURSOR MSB INTO H
313D DABA04    026B0         JP      C.049AH         ; BACK TO ROM IF CARRY
3140 007E05    02690         LD      A,(IX+S)        ; GET CURSOR CHARACTER
3143 B7        02700         OR      A               ; TEST IF CURSOR IS ON
3144 2801      02710         JR      Z,GETCHR        ; IF NOT THEN GO DO IT
3146 77        02720         LD      (HL),A          ; ELSE PUT IT BACK
3147 79        02730 GETCHR  LD      A,C             ; GET VALUE TO OISPLAY
314B FE20      02740         CP      20H             ; IS IT A SPACE OR CNTRL?
314A DA060S    02750         JP      C,0S06H         ; OUT IF SPACE OR CONTROL
3140 FE80      02760         CP      B0H             ; IS IT GRAPHICS OR TAB?
314F 02A604    02770         JP      NC,04A6H        ; OUT IF GRAPHICS OR TAB
31S2 C37D04    027B0         JP      047DH           ; DO UNCONVERTED DISPLAY
               02790 ;
               02B00 ; ####################################################
06CC           02810         ENO     06CCH           ; BACK TO BASIC READY
00000 TOTAL ERRORS
2429S  TEXT AREA BYTES LEFT

  AROUNO 3090 01460   01370
  BACKUP 30B7 013S0   01400
  BEEEEP 30E6 02140
  BEEPER 3117 02420   02S00
  BLEEEP 3103 02310   02160 02190
  CLRMEN 30S2 00B00   00B20
  CNTROL 30AC 01710   01600
  OECA   307A 01130   01070
  FOUNO  307F 01230   00990
  FREQCY 3120 02480   02480
  GETCHR 3147 02730   02710
```

Listing Continued . . .

crude first pass; enter this line from command level (no line number):

```
FOR X=17130 TO 32767 : IF PEEK(X)=17B THEN POKE X,17S : NEXT
```

ELSE NEXT

This line will search through all of memory (in a 16K machine), looking for the PRINT token (via PEEK), and replacing it wherever it finds it with the LPRINT token (via POKE).

There are occasional risks with this kind of POKEing. Occasionally, a line number or part of the BASIC line organization addresses may have the same value as the PRINT token and get changed with this process. You might end up with a line like 37549 in the middle of a nicely ordered sequence of 1000, 1010, 1020, etc. Another possible flaw is that the value stored as a pointer to the next BASIC line may also correspond to the PRINT token, and get changed. You may get into a LIST-loop or 'lose' some lines (at least to the eye – they are still in there).

If a line number is wrong, merely delete the incorrect line number and retype a new line with the correct number. If some lines seem lost or the LIST command keeps looping, then temporarily reverse the process . . .

```
FOR X=17130 TO 32767 : IF PEEK(X)=17S THEN POKE X,17B : NEXT
```

. . . and add a few REM statements in a line before the error occurred. Adding statements will alter the position of program lines in memory, and you will probably be able to perform the original conversion again safely.

As you can see, the tokenizing process has a lot of distinct advantages. As a postscript, consider the program that opened this section. The tokens were displayed as graphics characters. Why is this so?

Since there are only 256 possible combinations of bits in a byte, many times they have to serve multiple masters. In a machine language program, these bytes can be instructions. In a BASIC program, they are tokenized commands. On screen – which means in video memory – they appear as graphics. The 26 letters of our alphabet can be combined and recombined to form words, sentences, paragraphs, etc., and many words can sound alike or be spelled alike and still have different meanings. Context changes how words are understood.

Douglas Hofstadter played on this most dramatically when he wrote, "This sentence no verb".

Continued Listing

```
GOAWAY 30E5 02130   01630 01700 01730 01810 01830 01830
INKEYS 4099 00250   01000
K8PFIX 3039 00450   00350
KEYPR5 3041 00530   00730
KPLACE 401A 00270   00910 01030 01050 01140
LOWER  312A 02590   00370
LOWER1 3136 02650   02620
PORTFF 4030 00260   02370
RECHEK 3047 00630   01020 01120
5HIFTR 4019 00280   02200 02220 02600
5TROKE 305E 00980   00560
TA8LET 3005 02000   01880
TMWSTE 3075 01100   01100
Z0428H 3081 01740   01510
Z0435H 3080 01800   01780
Z0430H 30C5 01840   01750
Z0443H 30C8 01880   01860
```

```
               00100 ; ############################################################
               00110 ; AOOING OE8OUNCE/8EEP/AUTOREPEAT TO EDITOR/ASSEM8LER 1.1
               00120 ; ############################################################
               00130 ; NEW EOTASM SCAN PATCH WILL USE ROM ROUTINE IN ITS PLACE
               00140 ; ############################################################
               00150 ;
4016           00160         ORG     4016H            ; KEYBOARO PATCH POINT
4016 68        00170         OEF8    068H             ; LS8 OF NEW START
4017 50        00180         OEF8    050H             ; MS8 OF NEW START
5068           00190         ORG     5068H            ; NEW PARTIAL K8O ORIVER
5068 211640    00200         LD      HL,4016H         ; FORMER K8O PATCH POINT
5068 36E3      00210         LD      (HL),0E3H        ; LS8 OF AOORESS IN ROM
5060 23        00220         INC     HL               ; GET NEXT POSITION REAOY
506E 3603      00230         LO      (HL),03H         ; MS8 OF AOORE5S IN ROM
5070 C38A46    00240         JP      468AH            ; JUMP TO EOTASM PROGRAM
               00250 ;
               00260 ; ############################################################
               00270 ; NEW KEY8OARO 5CAN IS PLACEO AT FORMER SOURCE COOE START
               00280 ; ############################################################
               00290 ;
5000           00300         ORG     5000H            ; NEW 8LOCK OF COOE
5000 212140    00310         LO      HL,4021H         ; GET REPEAT 5TORAGE BYTE
5003 01013B    00320         LO      BC,3801H         ; GET FIRST ROW OF KEYBRO
5006 1600      00330         LO      0,0              ; ROW COUNTER REGISTER
5008 0A        00340 LOOPX   LO      A,(BC)           ; FINO KEY PRESSEO IN ROW
5009 5F        00350         LO      E,A              ; SAVE VALUE IN E REG.
500A A3        00360         ANO     E                ; TE5T FOR PRES5EO KEY
5008 2019      00370         JR      NZ,FOUNO         ; JUMP OUT IF KEY PRESSEO
5000 77        00380         LO      (HL),A           ; SAVE CURRENT KEY IN HL
500E 14        00390 REOOIT  INC     0                ; INCREMENT ROW COUNTER
500F 2C        00400         INC     L                ; INCREMENT KEY 5TORAGE
5010 C801      00410         RLC     C                ; GET NEXT ROW INTO 8C
5012 79        00420         LD      A,C              ; GET VALUE OF C FOR TEST
5013 0680      00430         SU8     80H              ; 80H I5 SHIFT KEY ROW
5015 20F1      00440         JR      NZ,LOOPX         ; LOOP 8ACK IF NOT SHIFT
5017 0607      00450         LO      8,7              ; NUMBER OF 8UMP5 TO 00
5019 20        00460 LOOPY   OEC     L                ; OECREMENT 8YTE 5TORAGE
501A 86        00470         A00     A,(HL)           ; A00 TOTAL VALUE STORED
5018 10FC      00480         OJNZ    LOOPY            ; LOOP 8ACK FOR 7 TIMES
5010 FE00      00490         CP      0                ; WERE NO KEYS PRESSEO?
501F 3E00      00500         LO      A,0              ; CLEAR ACC., NOT FLAG5
5021 C0        00510         RET     NZ               ; 8ACK TO MAIN ROUTINE
5022 321A40    00520         LO      (401AH),A        ; SAVE VALUE IF ZERO
5025 C9        00530         RET                      ; 8ACK TO MAIN ROUTINE
5026 A6        00540 FOUNO   ANO     (HL)             ; TEST IF SAME CHARACTER
5027 2610      00550         JR      Z,SAME           ; IF SAME, JUMP OUT ...
5029 3A1A40    00560         LO      A,(401AH)        ; GET COUNTER 8YTE INTO A
502C 3C        00570         INC     A                ; INCREMENT IT EACH TIME
5020 321A40    00580         LO      (401AH),A        ; SAVE IT AGAIN FOR NEXT
5030 FEFF      00590         CP      0FFH             ; IS IT PAST FULL OELAY?
5032 200A      00600         JR      NZ,REOOIT        ; IF NOT GO BACK FOR MORE
5034 30        00610         OEC     A                ; OEC A TO 0FE FOR REPEAT
5035 321A40    00620         LO      (401AH),A        ; SAVE THAT VALUE IN CNTR
5038 78        00630         LO      A,E              ; GET ORIGINAL CHARACTER
5039 73        00640 SAME    LO      (HL),E           ; SAVE THAT VALUE IN HL
503A C5        00650         PUSH    8C               ; SAVE ROW COUNTER
5038 010002    00660         LO      8C,0200H         ; GET OELAY VALUE REAOY
503E C06000    00670         CALL    0060H            ; CALL ROM OELAY 5U8ROUT.
5041 C1        00680         POP     8C               ; RESTORE ROW COUNTER
5042 0A        00690         LD      A,(8C)           ; GET VALUE AT ROW CNTR.
5043 A3        00700         ANO     E                ; TEST IF STILL PRESSEO
5044 C8        00710         RET     Z                ; IF NOT THEN IT'S 8OUNCE
6045 C6        00720         PU5H    8C               ; SAVE ROW COUNTER AGAIN
5046 E5        U0730         PU6H    HL               ; 5AVE STORAGE AREA
5047 F5        00740         PU5H    AF               ; SAVE CURRENT KEY5TROKE
5048 0640      00750         LO      8,40H            ; GET OURATION VALUE
504A 3A3040    00760         LO      A,(4030H)        ; GET 5TATUS OF 5CREEN
5040 E6F0      00770         ANO     0F0H             ; CLEAR THE OATA OUTPUT
504F 67        00780         LO      H,A              ; H 8ECOME5 OUTPUT MASK
5050 F602      00798         OR      02               ; REAOY ACC. FOR 8IT-SET
```

Listing Continued . . .

Packing BASIC With Machine Code

One of the most attractive aspects of interpreted code like Level II BASIC is the hide-n-seek game you can play with it. One of the most fruitful games is called 'string packing', a technique that allows machine language programs to be hidden inside ordinary program lines.

It is convenient and efficient, but once it's part of a program, it looks very obscure. There are three ways of creating machine-coded programs through BASIC strings, but all depend on the code being relocatable (see Supplement to Chapter 4 regarding relocatable code). The three ways are:

1. Packing the machine code into a string on a program line, one character at a time. This is done when the program is created.
2. Packing the machine code into a string on a program line, one character at a time, reading data on other program lines. This is done each time the program is run. The read/data lines containing the packing information are then automatically deleted.
3. Building a string in the string variable area from in-line CHR$() commands. The strings are built each time the program is run.

First, some background on strings and how to find them. In the TRS-80, all variables can be located with a Level II command known as VARPTR (VARiable PoinTeR). The variable pointer can find out a lot about variables – their type, location, and length. In the case of string variables, VARPTR returns a memory location in which the length of the string is stored.

Assume A$ is a string variable in a program line. The statement X=VARPTR(A$) assigns the address of the first part of the A$ story to X. Here's what X can reveal:

```
PEEK (X)   ...the length of A$
PEEK (X+1) ...the least significant byte of where A$ is found
PEEK (X+2) ...the most significant byte of where A$ is found
```

These values are returned in decimal form, because Level II doesn't provide a hexadecimal numbering option. To find where A$ is actually located, then, use this formula:

```
AD = PEEK (X+1) + 266 * PEEK (X+2)
```

Do you see what is happening here? And what can be done with it? If you know, for example, that A$="XXXXXXXXXX", then you can actually *change* A$ by POKEing values into the

Continued Listing

```
5052 6F         00800          LO      L,A            ; L 8ECOMES OUTPUT MASK
5053 70         00810 SOUNO    LO      A,L            ; GET BIT-SET MASK
5054 03FF       00820          OUT     (OFFH),A       ; OUTPUT IT (WAVEFORM HI)
5056 7C         00830          LD      A,H            ; GET BIT-RESET MASK
5D57 03FF       00840          OUT     (OFFH),A       ; OUTPUT IT (WAVEFDRM LO)
5059 C5         D0850          PUSH    BC             ; SAVE OURATION VALUE
505A 0640       D0860          LO      B,40H          ; GET PITCH VALUE
5D5C 1DFE       00870          OJNZ    $              ; OELAY FOR AUOI8LE TONE
505E C1         00880          POP     BC             ; RESTORE BEEP OURATION
505F 10F2       00890          DJNZ    SOUND          ; LOOP FOR FULL OURATION
5061 F1         00900          POP     AF             ; RESTORE KEYSTROKE VALUE
5D62 E1         00910          POP     HL             ; RESTORE STORAGE VALUE
5063 C1         D0920          PDP     BC             ; RESTORE ROW COUNTER
5064 C30744     00930          JP      4407H          ; JUMP INTO EDTASM...!
                00940 ;
                00950 ; #####################################################
                00960 ; FOLLOWING PATCH NEW SOURCE CODE START & KEYBOARO SCAN
                00970 ; #####################################################
                00980 ;
468A            00990          ORG     468AH          ; PLACE TO PATCH ENO
468A 21005E     01000          LO      HL,5E00H       ; NEW ENO DF EDTASM
4710            01010          ORG     4710H          ; PLACE TO PATCH END
4710 11005E     01020          LD      OE,5E00H       ; NEW ENO OF EDTASM
4A07            01030          DRG     4A07H          ; PLACE TO PATCH END
4A07 11005E     01040          LD      OE,5E00H       ; NEW ENO DF EOTASM
4AD8            01050          ORG     4A08H          ; PLACE TO PATCH END
4A08 21005E     01060          LO      HL,5E00H       ; NEW ENO DF EOTASM
4850            01070          ORG     4850H          ; PLACE TD PATCH END
4850 21005E     01080          LD      HL,5E00H       ; NEW ENO OF EOTASM
4039            01090          ORG     4D39H          ; PLACE TD PLACE ENO
4039 21005E     01100          LD      HL,5E00H       ; NEW ENO OF EDTASM
4D80            01110          ORG     4080H          ; PLACE TO PATCH ENO
4D80 21005E     01120          LO      HL,5E00H       ; NEW ENO OF EOTASM
5227            01130          ORG     5227H          ; PLACE TO PATCH ENO
5227 21005E     01140          LD      HL,5E00H       ; NEW ENO OF EOTASM
43EF            01150          ORG     43EFH          ; PLACE TO PATCH KBD SCAN
43EF C30050     01160          JP      5000H          ; NEW KEYBOARD SCAN
                01170 ;
                01180 ; #####################################################
5000            01190          ENO     5000H
00000 TOTAL ERRORS
3D935  TEXT AREA 8YTES LEFT


FOUND   5026 00540   00370
LOOPX   5008 00340   00440
LOOPY   5019 00460   0048D
REDOIT  5D0E D0390   0060D
SAME    5039 00640   D0550
SOUNO   5053 00810   00890
```

address you have calculated.

Run the following demonstration program:

```
10 CLS
20 A$ = "XXXXXXXXXX"
30 X = VARPTR(A$)
40 Q = PEEK (X)
50 AO = PEEK (X+1) + 256 * PEEK (X+2)
60 PRINTA$
70 L = 65
80 FDR N = 1 TO Q
90 POKE AD,L
100 L = L + 1
110 AO = AO + 1
120 PRINT A$
130 NEXT N
140 LIST 20
```

A$ is created in line 20, and its information storage area is found by X in line 30. Its length is discovered in line 30 and assigned to variable Q; its location is determined in line 50 (assigned to variable AD), and it is printed in its original form in line 60. Line 70 assigns the value 65 (an ASCII 'A') to variable L, and a Q-character loop is created in line 80. The first character in A$ is POKEd with L, i.e., changed to letter 'A'. L is incremented (to letter 'B'), AD is incremented (to the next character in A$), and the new A$ is printed. When all characters in A$ have been changed, it is listed. You can see that the list itself is changed because A$ is defined and stored right there in line 20!

As a further experiment, change the value of L in line 70 to 129 and watch what happens (see Box on Tokenizing for details).

Here is the point: you can create a dummy string like A$ which will become the residence of a machine language program. By finding A$ and POKEing your program into it, it can be CLOADed and CSAVEd at will.

Now we turn to the three string-packing methods themselves. For the sample program, the following 20-byte routine will be used:

```
21 01 3C          LO      HL,3C01H
E5                PUSH    HL
01                POP     OE
2B                OEC     HL
01 FF 03          LO      BC,03FFH
36 20             LD      (HL),20H
ED B0             LOIR
21 11 01          LO       HL,D111H
CD A7 2B          CALL     2BA7H
C9                RET
```

This routine clears the screen, prepares the message 'RADIO SHACK LEVEL II BASIC', and displays it.

The first and second string-packing methods are essentially identical, except that in the first method, A$ is created and the program saved for later use. The second method creates A$ at every program run. Here is a simple BASIC program using the routine above packed into A$:

```
               00100 ; #####################################################'
               00110 ; ELEMENTARY (ANO SLOW) FOUR-VOICE MUSIC SUBROUTINE.
               00120 ; THIS ROUTINE IS CURRENTLY SET UP FOR FOUR INOEPENOENT
               00130 ; VOICES.  BECAUSE OF TIMING CONSTRAINTS, VOICES ARE VERY
               00140 ; LOW IN PITCM.  BY USING THE FOUR SUBROUTINES ALTERNATE-
               00150 ; LY FOR SOUNO EFFECTS. A HIGHER SPEEO CAN BE OBTAINEO.
               00160 ; A TEST-ANO-JUMP LOOP CAN BE INSERTEO FOR THIS PURPOSE.
               00170 ; ALSO, AS LONG AS LABELS ARE CHANGEO, VOICES CAN BE
               00180 ; OROPPEO FROM THE SEOUENCE, RESULTING A 50%, 100% ANO
               00190 ; 150% SPEEO INCREASE, RESPECTIVELY.  SOUARE WAVE OUTPUT.
               00200 ; NOTICE ALSO THAT, WHEN VOICES ARE OROPPEO, OTHER REG-
               00210 ; ISTERS MAY BE SUBSTITUTEO FOR IX, FOR A SPEEO INCREASE.
               00220 ; FURTHERMORE, CHANGING THE SPEEO OF THE PROCESSOR WILL
               00230 ; PROVIOE AN IOENTICAL INCREASE IN THE OUTPUT PITCH.
               00240 ; #####################################################
               00250 ;
4F60           00260         ORG     4F60H             ;   :NEAR TOP OF MEMORY
4F60 00210050  00270         LO      IX,5000H          ;   :START PITCH & RHYTHM
4F64 01FF4F    00280         LO      BC,4FFFH          ;   :MEMORY-MAPPEO SOUNO
               00290 ;
               00300 ; #####################################################
               00310 ; OUTER (INTER-NOTE) LOOP BEGINS HERE: T-STATES 212 - 244
               00320 ; #####################################################
               00330 ;
4F67 09        00340 LOOP1   EXX                       ;04:READY OURATION REGS.
4F68 004600    00350         LO      8,(IX+0)          ;19:MS8 OF NOTE OURATION
4F6B 004E01    00360         LO      C,(IX+1)          ;19:LS8 OF NOTE OURATION
4F6E 09        00370         EXX                       ;04:STASM REGISTER AWAY
4F6F 006602    00380         LO      H,(IX+2)          ;19:FIRST PITCH INTO H
4F72 006E03    00390         LO      L,(IX+3)          ;19:SECONO PITCM INTO L
4F75 00S604    00400         LO      0,(IX+4)          ;19:THIRO PITCH INTO 0
4F78 005E05    00410         LO      E.(IX+S)          ;19:FOURTH PITCH INTO E
               00420 ;
               00430 ; #####################################################
               00440 ; EACM VALUE ACQUIREO FROM IX IS TESTEO TO SEE IF IT IS 0
               00450 ; ANO THE VOICE IS TURNEO OFF IF IT IS (OEFINING A REST).
               00460 ; #####################################################
               00470 ;
4F7B 0A        00480         LO      A,(BC)            ;07:READY TO TWEAK MEM
4F7C E60F      00490         ANO     0FH               ;04:TURN ALL VOICES ON
4F7E 24        00500         INC     H                 ;04:8UMP VALUE: REST TEST
4F7F 2S        00510         OEC     H                 ;04:8UMP VALUE: REST TEST
4FB0 C2854F    00520         JP      NZ,REST1          ;10:ONLY 00 OEFINES REST
4F83 C8E7      00530         SET     4,A               ;08:SILENCE VOICE IF REST
4FB5 2C        00S40 REST1   INC     L                 ;04:8UMP VALUE: REST TEST
4F86 20        00550         OEC     L                 ;04:BUMP VALUE: REST TEST
4F87 C28C4F    00560         JP      NZ,REST2          ;10:ONLY 00 OEFINES REST
4F8A C8EF      00S70         SET     S,A               ;08:SILENCE VOICE IF REST
4F8C 14        00580 REST2   INC     0                 ;04:8UMP VALUE: REST TEST
4F80 15        00590         OEC     0                 ;04:8UMP VALUE: REST TEST
4F8E C2934F    00600         JP      NZ,REST3          ;10:ONLY 00 OEFINES REST
4F91 C8F7      00610         SET     6,A               ;08:SILENCE VOICE IF REST
4F93 1C        00620 REST3   INC     E                 ;04:BUMP VALUE; REST TEST
4F94 10        00630         OEC     E                 ;04:8UMP VALUE; REST TEST
4F95 C29A4F    00640         JP      NZ,REST4          ;10:ONLY 00 OEFINES REST
4F9B CBFF      00650         SET     7,A               ;08:SILENCE VOICE IF REST
4F9A 02        00660 REST4   LO      (BC),A            ;07:SET VOICES ON OR OFF
               00670 ;
               00680 ; #####################################################
               00690 : OECREMENT H,L,O,E (WAVEFORM OURATION FOR EACH VOICE)...
               00700 ; NEEOEO EACH TIME THE WAVEFORM IS TOGGLEO OURING LOOPS..
               00710 : ...INNER LOOP 8EGINS HERE.  T-STATES STRICTLY EOUAL 246
               00720 : MEANING MAXIMUM FREOUENCY IS APPROXIMATELY 1770000/246
               00730 ; OR 7195.1 HZ. USEFUL FREQUENCIES ARE CONSIOERA8LY LESS.
               00740 ; #####################################################
               00750 :            8EGIN PITCH ANO RHYTHM COUNTOOWN LOOPS
               00760 ; #####################################################
               00770 :        COUNT OOWN THE PITCH LOOP FOR VOICE NUM8ER ONE
               00780 ; #####################################################
               00790 ;
4F98 0A        00800 LOOP2   LO      A,(BC)            :07:WHAT WAVE IS LURKING
4F9C 25        00810         OEC     H                 :04:COUNTOOWN FREOUENCY 1
4F90 C2AB4F    00820         JP      NZ,EXIT1          ;10:SAME WAVE IF NOT 0
4FA0 EE01      00830         XOR     1                 ;07:TOGGLE WAVEFORM 8IT 1
4FA2 006602    00840         LO      M,(IX+2)          ;19:RESTORE PITCH VALUE
4FA5 C3AE4F    00850         JP      EXIT1A            ;10:JUMP PAST TIMEWASTERS
4FA8 FOE5      00860 EXIT1   PUSH    IY                ;15:WASTE 15 T-STATES
4FAA FOE1      00870         POP     IY                ;14:WASTE 14 T-STATES
4FAC E6FF      00880         ANO     0FFH              ;07:WASTE 7 MORE T-STATES
               00890 ;
               00900 : #####################################################
               00910 ;        COUNT OOWN THE PITCH LOOP FOR VOICE NUMBER TWO
               00920 ; #####################################################
               00930 ;
4FAE 20        00940 EXIT1A  OEC     L                 ;04:COUNTOOWN FREQUENCY 2
4FAF C28A4F    00950         JP      NZ,EXIT2          ;10:SAME WAVE IF NOT 0
4F82 EE02      00960         XOR     2                 ;07:TOGGLE WAVEFORM 8IT 2
4FB4 006E03    00970         LO      L,(IX+3)          ;19:RESTORE PITCH VALUE
4FB7 C3C04F    00980         JP      EXIT2A            ;10:JUMP PAST TIMEWASTERS
4FBA FOES      00990 EXIT2   PUSH    IY                ;1S:WASTE 1S BANANAS
4F8C FOE1      01000         POP     IY                ;14:ORUM FINGERS ON 14
4F8E E6FF      01010         ANO     0FFM              ;07:USELESS ARITHMETIC
               01020 :
               01030 : #####################################################
               01040 :      COUNT OOWN THE PITCH LOOP FOR VOICE NUM8ER THREE
               01050 ; #####################################################
               01060 ;
4FC0 1S        01070 EXIT2A  OEC     0                 ;04:COUNTOOWN FREOUENCY 3
4FC1 C2CC4F    01080         JP      NZ,EXIT3          ;10:SAHE WAVE IF NOT 0
4FC4 EE04      01090         XOR     4                 ;07:TOGGLE WAVEFORM BIT 3
4FC6 005604    01100         LO      0,(IX+4)          ;19:RESTORE PITCH VALUE
4FC9 C3024F    01110         JP      EXIT3A            ;10:JUMP PAST TIMEWASTERS
4FCC FOE5      01120 EXIT3   PUSH    IY                ;15:SCRATCH LEFT HANO
4FCE FOE1      01130         POP     IY                ;14:SCRATCM RIGHT HANO
```

Listing Continued . .

```
5 POKE 16553,255 : REM OPTIONAL LINE
10 PRINT"THE PROGRAM IS RUNNING"
20 A$ = "12345678901234567890"
30 X = VARPTR (A$) : Q = PEEK (X)
40 A0 = PEEK (X+1) + 256 * PEEK (X+2)
50 FOR N = 1 TO Q : REA0 A
60 POKE A0,A : A0 = A0 + 1 : NEXT
70 H8 = PEEK (X+1) : POKE 16526,HB
80 LB = PEEK (X+2) : POKE 16527,LB
90 INPUT"ENTER TO RUN M/L";Z
100 M$ = USR (0)
110 OATA 33,1,60,229,209,43,1,255,3,54
120 OATA 32,237,176,33,17.1,205,167,40,201
```

Line 5 is optional if you have an early ROM set, where data reads could RESTORE after every READ. Line 20 contains the string to be packed, and, as before, lines 30 and 40 identify the string's length and location. The data is read and POKEd into place sequentially by lines 50 and 60.

Finally, lines 70 and 80 identify the beginning of the string and place it in the USR(X) entry points at 16526 and 16527. The program pauses for user input in line 90, and then jumps to the packed routine.

After the program has been run, list it. Note that A$ is now packed with new information replacing the string '12345678901234567890'. The first string-packing method saves space by deleting lines 40 through 60, 110 and 120, which have done their work. The program is then CSAVEd, and can be loaded and run at any time. The second string-packing method leaves all lines intact so that any future users may modify them as necessary.

There are a few disadvantages to this method of string packing. First of all, two machine language instructions or pieces of data may not be used directly: 00 and 22. 00 tells a BASIC program it has found the end of a program line; two 00's in a row indicate the end of the program. 22 is the quotation mark symbol, and will inform the program that the string has ended; a ?SN ERROR will then be produced in the rest of the line.

A second difficulty is that the line containing A$ may not be edited. This is because when a line is edited, it is placed from the LIST into a buffer that acts exactly like the keyboard buffer; the bytes within the quotes are then converted into the individual letters. For example, code (178) is a machine command which also is the BASIC token for PRINT; when listed, it comes up on the screen as PRINT. Editing the line puts P-R-I-N-T in the edit buffer; but since it is *within the quotation marks,* it is not tokenized. The result? The string now contains five ASCII characters where it once contained a machine language instruction!

Continued Listing

```
4F00 E6FF     01140         ANO     OFFH            ;07:CHECK KITCHEN CLOCK
              01150 ;
              01160 ; ##########################################################
              01170 :     COUNT OOWN THE PITCH LOOP FOR VOICE NUHBER FOUR
              011B0 ; ##########################################################
              01190 ;
4F02 10       01200 EXIT3A  OEC     E               ;04:COUNTOOWN FREQUENCY 4
4F03 C20E4F   01210         JP      NZ,EXIT4        :10:SAHE WAVE IF NOT 0
4F06 EE0B     01220         XOR     B               ;07:TOGGLE WAVEFORH BIT 4
4F0B 00SE0S   01230         LO      E,(IX+5)        ;19:RESTORE PITCH VALUE
4F0B C3E44F   01240         JP      EXIT4A          :10:JUHP PAST TIHEWASTERS
4F0E F0ES     012S0 EXIT4   PUSH    IY              ;1S:WATER NASTURTIUHS
4FE0 F0E1     01260         POP     IY .            ;14:PICK 14 ZUCCHINI
4FE2 E6FF     01270         ANO     OFFH            :07:HIX APPLES ANO ORANGE
              012B0 ;
              01290 ; ##########################################################
              01300 ; CHECK FOR ENO OF NOTE OURATION: GET MORE NOTES IF OONE
              01310 : ##########################################################
              01320 ;
4FE4 02       01330 EXIT4A  LO      (BC),A          ;07:OUTPUT NEW WAVEFORHS
4FE5 09       01340         EXX                     ;04:GET STASHEO OURATION
4FE6 0B       013S0         OEC     BC              :06:COUNT OOWN OURATION
4FE7 7B       01360         LO      A,B             ;04:SET UP B FOR TEST
4FEB B1       01370         OR      C               ;04:CHECK AGAINST C
4FE9 09       013B0         EXX                     :04:STASH OURATION AGAIN
4FEA C29B4F   01390         JP      NZ,LOOP2        ;10:GO BACK TIL NOTE ENO
              01400 ;
              01410 ; ##########################################################
              01420 : HOVE ALL POINTERS PAST CURRENT BATCH OF NOTES/OURATIONS
              01430 ; ...THIS IS THE REHAINOER OF OUTER LOOP, T-STATES = B0,
              01440 ; TOTAL T-STATES OF OUTER LOOP = B0 + 244 = 324, WHICH IS
              014S0 ; ABOUT 2 OF THE MAXIMUM CYCLE FREQUENCIES (.0002 USEC).
              01460 ; ##########################################################
              01470 ;
4FE0 110600   014B0         LO      OE,6            ;10:MEMORY POS'NS TO HOVE
4FF0 0019     01490         AOO     IX,OE           ;1S:MOVE 6 PLACES FORWARO
              01500 ;
              01S10 ; ##########################################################
              01S20 : CHECK FOR ENO OF PROGRAH COOE (00) OR OEPRESSEO BREAK
              01530 ; ##########################################################
              01S40 :
4FF2 007E00   01550         LO      A,(IX+0)        :19:NEXT NOTE OURATION
4FFS B7       01S60         OR      A               ;04:SET ENO-OF-HUSIC FLAG
4FF6 CB       01570         RET     Z               ;0S:BACK TO BASIC IF OONE
4FF7 3A403B   01SB0         LO      A,(3B40H)       ;13:TEST BREAK KYBO ROW
4FFA B7       01S90         OR      A               ;04:SET FLAG FOR KEY TEST
4FFB CA674F   01600         JP      Z.LOOP1         ;10:CONTINUE PIECE IF OK
4FFE C9       01610         RET                     ;  :TO BASIC IF BREAK
              01620 ;
              01630 ; ##########################################################
              01640 ;
06CC          016S0         ENO     06CCH           ;  :READY AFTER SLASH
00000 TOTAL ERRORS
```

The last method of string packing is capable of overcoming both these flaws. Examine the listing below:

```
10 PRINT"THE PROGRAM IS RUNNING"
20 A$ = CHR$(33) + CHR$(1) + CHR$(60) +
        CHR$(229) + CHR$(209) + CHR$(43) +
        CHR$(1) + CHR$(255) + CHR$(3) +
        CHR$(S4) + CHR$(32) + CHR$(237) +
        CHR$(176) + CHR$(33) + CHR$(17) +
        CHR$(1) + CHR$(205) + CHR$(167) +
        CHR$(40) + CHR$(201)
30 X = VARPTR (A$)
40 POKE 16526, PEEK (X+1)
50 POKE 16527, PEEK (X+2)
60 INPUT "ENTER TO RUN M/L";Z
70 M$ = USR(0)
```

This time, A$ has been defined in the BASIC variable area using CHR$(). In other words, because A$ is no longer defined within the program line, *any value may be used in the machine language program.* Hybrid strings can also be used, as:

```
A$ = "1234567890" + CHR$(0) + "12345" + CHR$(34)
```

This method uses both the POKEing via READ-DATA statments, plus concatenation with 00 and 22 where necessary. Once again, A$ is stored in the variable area, and none of the 00's or 22's affect the BASIC program. As a final amusement, RUN listing 3-(?) above, then PRINT A$. The A$ in listing 3-(?) and the A$ in this listing both contain identical machine code. RUN listing 3-(?) again. LIST line 20. Now PRINT A$. The answer is up to you.

String-packing will likely become a very important addition to your library of BASIC tools. Here, then, is a summary of the string-packing technique:

1. Write the BASIC program.
2. Create a dummy string of any unused variable name (for example, A$="LOONIETUNES"
3. Make the string the exact length of your machine language program.
4. Write a program line that sets another variable to point to the string's variable information.
   For example, X = VARPTR(A$).
5. Find the starting address of the string by converting the decimal bytes into a single decimal value.
   AD = PEEK(X+1) + 256 * PEEK (X+2).
6. Create a set of READ and DATA lines in your BASIC program which will POKE the machine language program into place in the dummy string. (For example:

```
Line #  FOR N = AO TO AD+3 : REAO L : POKE N,L : NEXT
Line #  DATA 33, 16, 16, 204 .....                 )
```

7. Set the USR(0) entry point at 16526 and 16527 to the beginning of the string variable storage address (for example, PEEK (X+1) and PEEK (X+2), respectively.
8. If you wish, delete the READ, DATA and POKE loop lines used for that routine. CSAVE the program.

Sound-Effects Generation

The essence of sound generation has already been sneaked in: the audible beep in the keyboard routine at the beginning of this Chapter. Sound has been something of a mystery, but there could hardly been a simpler machine language program. Try this experimental program with the tape recorder running in record mode (the motor plug removed), and a cassette in place:

```
10 FORX=1TO2000:OUT255,0:OUT255,255:NEXT
```

In order that this program can operate at top speed, make sure you do not use spaces, and keep the program on one line. You'll hear the tape relay clatter and see the screen jitter. Now play back the short segment of tape you recorded. There is a buzzing on that tape, similar in pitch to the buzzing of the cassette relay. What does all this mean?

It is quite simple. There is an electronic switch inside the TRS-80 which controls several activities: whether the screen is in 64 or 32 character mode, whether the cassette relay is on or off, and whether the cassette data output is 'on' or 'off'.

I've put on and off in quotation marks for a reason: which video mode is used and whether the cassette motor is on or off are examples of states or conditions. But in audio terms, the latter output represents very swift sound wave *transitions*, not on or off *conditions*. In other words, the transition from on to off or from off to on can be heard as only a slight click; but many of them in quick succession sound like a buzz; in even faster succession, they become actual pitches.

```
               00100 ; ##########################################################
               00110 ; SINGLE-VOICE MUSIC SUBROUTINE FOR USE WITH CASSETTE
               00120 ; OUTPUT PORT CAN BE EMBEOOEO OIRECTLY IN A BASIC STRING
               00130 ; ##########################################################
               00140 ;
0000 C07F0A    00150        CALL    0A7FH            : ACCEPT BASIC VARIABLE
0003 E5        00160        PUSH    HL               ; STASH BASIC VARIABLE
0004 C1        00170        POP     BC               ; TRANSFER VAR. TO BC
0005 C5        00180 LOOP   PUSH    BC               ; SAVE OUTER LOOP VAR.
0006 41        00180        LO      B,C              ; GET MSB FOR TONE
0007 10FE      00200        OJNZ    $-0              ; ANO OELAY THAT TIME
000B 3A3040    00210        LO      A,(4030H)        ; GET SCREEN STATUS
000C F602      00220        OR      2                ; ANO SET BIT ONE
000E 03FF      00230        OUT     (OFFH),A         ; OUTPUT PART OF WAVE
0010 41        00240        LO      B,C              ; GET VARIABLE AGAIN
0011 10FE      00250        OJNZ    $-0              : OELAY WHILE WAVE HIGH
0013 E6F0      00260        ANO     OFOH             ; ANO SET OTHER BIT HIGH
0015 03FF      00270        OUT     (OFFH),A         ; TO OO OTHER WAVE HALF
0017 C1        00280        POP     BC               ; RESTORE OUTSIOE VALUE
001B 10EB      00280        OJNZ    LOOP             ; ANO LOOP BACK FOR FREQ.
001A C9        00300        RET                      ; GO BACK TO BASIC
               00310 ;
               00320 ; ##########################################################
0000           00330        ENO
00000 TOTAL ERRORS
   LOOP    0005 00180   0U290
```

The single-line BASIC program, short though it may be, cannot move fast enough to produce pleasant tones or dramatic sound effects. For that you must turn to machine language for its speed. Listing 3-(?) presents a complete sound subroutine with ten sample sounds built in.

Listing 3-(?) presents a different sound subroutine which accepts values passed from BASIC.

Again, each program has an advantage. The first allows you to tailor specific sounds and their durations and repetitions with care; the second lets you develop many different sounds easily, directly from BASIC, without altering the machine subroutine already in place.

What's in a List?

Often it's reassuring to be able to give your program to others without having to worry about gratuitous examination of your code, and finding your own, carefully developed techniques in someone else's product. The easiest thing to do, then, is UN-LIST the program.

Actually, the program still LISTS, but can't be seen; and the program still LLISTs, but uses a whole sheet of paper for each line. In either case, it's a discouragement if you've got some code you like. And protecting just a few lines might give the impression that's all there is to your program – a psychological ploy.

The trick is to add two bytes to the end of the program: the command to 'Home Cursor', and the command to 'Form-Feed'. Here are a few normal program lines:

```
0 REM&&
1 CLS:PRINT:PRINT:PRINT"CHANGING...":X=17129:REM&&
2 X=PEEK(X)+256*PEEK(X+1):PRINTX"... ";:REM&&
3 IFX=0THEN10ELSEPOKEX-2,28:POKEX-3,12:GOTO2:REM&&
10 PRINT:PRINT"THIS IS A TEST ";:REM&&
20 PRINT"OF A TECHNIQUE TO KILL";:REM&&
30 PRINT"THE FEATURE THAT LISTS";:REM&&
40 PRINT"OR LLISTS THE PROGRAM.":REM&&
50 PRINT"THE PROGRAM HAS NOW BEEN CHANGEO":REM&&
60 PRINT"A COMPLETE LIST FOLLOWS....":REM&&
70 LIST:REM&&
80 REM&&
```

This process uses four bytes per line (colon, REM, two ampersands), and diminishes the usable characters per line by six, but if you have the memory and think you need a little protection, this is a way to go. Delete lines 1, 2 and 3, and save the program. When LIST is commanded, nothing will list on the screen but two REM lines (0 and 80). The program will require nine sheets of paper to LLIST.

Autoexecute BASIC Programs

One of the pleasures of disk operating systems is the ability to load and run programs automatically. This can be done with tape systems as well, simply because all the Level II BASIC operations are organized as subroutines. Any one may be called at any time. To autoexecute a program, then:

1. The SYSTEM command must be entered and the load begun in this mode.
2. The SYSTEM tape must load over its own return point so that it can begin execution automatically.
3. The SYSTEM program loaded must CALL the CLOAD routine, first preparing the stack to return to itself instead of command level.
4. Upon return, the SYSTEM program must prepare the stack once again for return to normal Level II operation, and jump to the RUN routine.

The process is straightforward with one exception: the CLOAD routine is terminal. That is, it forces a return to command level upon completion by clearing out the return address on the stack. It means that a program which might have been written in little more than a dozen bytes must instead play some memory hopscotch first.

Before turning to this loading routine itself, here is a look at the heart of the autorun sequence itself – a mere thirteen bytes! Enter any short BASIC program first, then the routine below:

```
5000    21 E8 41     LD     HL,41E8
5003    36 8E        LD     (HL),8E
5005    23           INC    HL
5006    36 00        LD     (HL),00
5008    2B           DEC    HL
5009    2B           DEC    HL
500A    C3 5A 1D     JP     1D5A
```

From BASIC, you can put this program in place with the following lines from command level:

```
X=20480 : POKEX,33 : POKEX+1,232 : POKEX+2,65 :
POKEX+3,54 : POKEX+4,241 : POKEX+5,35 : POKEX+6,54 :

POKEX+7,0 : POKEX+8,43 : POKEX+9,43 : POKEX+10,185 :
POKEX+11,90 : POKEX+12,29                 <ENTER>.
```

This simple routine sets the HL register to point to the usual beginning of the keyboard input buffer, puts an 8E (the RUN command value) into that place, bumps the register one place forward, and puts a zero there. The HL register is bumped back to just before the beginning of the keyboard buffer, and the execution routine at 1D5A is entered.

```
                00100 ; ######################################################
                00110 ; BASIC AUTOEXECUTION ROUTINE PATCH FOR LEVEL II BASIC
                00120 ; ######################################################
1D78            00140 BYTE    EQU     1D78H            ; INTERPRETER CALL ADDR.
                00150 ;
                00160 ; ######################################################
                00170 ;
7F00            00180         ORG     7F00H            ; RELOCATE IF DESIRED
7F00 2A0440     00190 START   LD      HL,(4004H)       ; GET INTERPRETER PATCH
7F03 22587F     00200         LD      (RETURN),HL      ; CHAINING PROCESS HERE
7F06 210F7F     00210         LD      HL,ENTRY         ; ENTRY OF AUTOEXECUTOR
7F09 220440     00220         LD      (4004H),HL       ; PATCH INTO INTERPRETER
7F0C C3CC06     00230         JP      06CCH            ; RETURN TO BASIC READY
                00240 ;
                00250 ; ######################################################
                00260 ; CHECK FOR STATUS OF INTERPRETER (MUST BE AT 1D5BH)
                00270 ; ######################################################
                00280 ;
7F0F E3         00290 ENTRY   EX      (SP),HL          ; GET RETURN ADDRESS
7F10 7D         00300         LD      A,L              ; GET LSB INTO A REG.
7F11 FE5B       00310         CP      5BH              ; CHECK LSB OF 1D5BH
7F13 2003       00320         JR      NZ,NOTRDY        ; GO OUT IF NOT AT 1D5B
7F15 7C         00330         LD      A,H              ; GET MSB INTO A REG.
7F16 FE1D       00340         CP      1DH              ; CHECK MSB OF 1D5BH
7F18 E3         00350 NOTRDY  EX      (SP),HL          ; RETURN STACK POSITION
7F19 C2577F     00360         JP      NZ,AWAY          ; BEGONE IF NOT 1D5BH
                00370 ;
                00380 ; ######################################################
                00390 ; COMPARE PRESENT LINE POSITION WITH CLOAD (TOKEN B9)
                00400 ; ######################################################
                00410 ;
7F1C CD781D     00420         CALL    BYTE             ; GET NEXT BUFFER CHAR.
7F1F F5         00430         PUSH    AF               ; SAVE PRESENT ACCUM.
7F20 FEB9       00440         CP      0B9H             ; SEE IF CLOAD TOKEN
7F22 2804       00450         JR      Z,CLOAD          ; SPECIAL ROUTINE IF B9
7F24 F1         00460         POP     AF               ; RESTORE PRESENT ACCUM.
7F25 2B         00470         DEC     HL               ; RESTORE HL POINTER
7F26 182F       00480         JR      AWAY             ; OUT TO NORMAL MODE
                00490 ;
                00500 ; ######################################################
                00510 ; IF CLOAD TOKEN IS FOUND, EXECUTE CLOAD PROCESS, BUT
                00520 ; FIRST INTERCEPT KEYBOARD SCAN (CRUDE WAY OF DOING IT)
                00530 ; TO GRAB PROGRAM ON ITS WAY BACK TO A READY CONDITION
                00540 ; ######################################################
                00550 ;
7F28 F1         00560 CLOAD   POP     AF               ; CLEAR STACK OF AF REG.
7F29 2A1640     00570         LD      HL,(4016H)       ; GET CURRENT KEYBRD SCAN
7F2C 22557F     00580         LD      (STORE),HL       ; SAVE IT FOR A WHILE
7F2F 21427F     00590         LD      HL,BYPASS        ; GET VALUE OF ROUTINE
7F32 221640     00600         LD      (4016H),HL       ; PATCH INTO KEYBRD PLACE
7F35 21E941     00610         LD      HL,41E9H         ; POINT TO BUFFER LOC'N
7F38 3600       00620         LD      (HL),00          ; PLACE END OF LINE CMD.
7F3A 2B         00630         DEC     HL               ; BUMP HL BACK TO START
7F3B 3EB9       00640         LD      A,0B9H           ; GET CLOAD VALUE
7F3D D680       00650         SUB     80H              ; STRIP OFFSET VALUE
7F3F C3651D     00660         JP      1D65H            ; BACK TO EXECUTION ROUT.
                00670 ;
                00680 ; ######################################################
                00690 ; CLOAD ABOVE WILL EXECUTE, RESET THE STACK, AND ATTEMPT
                00700 ; TO RETURN TO A READY CONDITION.  AT THIS POINT, THE
                00710 ; KEYBOARD DRIVER INTERCEPT WILL REDIRECT THE PROCESSOR
                00720 ; TO THE BYPASS ROUTINE BELOW, WHICH WILL AGAIN SET UP
                00730 ; THE BUFFER, REPATCH THE KEYBOARD DRIVER, AND RUN.
                00740 ; ######################################################
                00750 ;
7F42 2A557F     00760 BYPASS  LD      HL,(STORE)       ; GET BACK KEYBRD SCAN
7F45 221640     00770         LD      (4016H),HL       ; PUT BACK INTO PLACE
7F48 21E841     00780         LD      HL,41E8H         ; GET BUFFER LOCATION
7F4B 368E       00790         LD      (HL),8EH         ; GET RUN COMMAND TOKEN
7F4D 23         00800         INC     HL               ; BUMP UP BUFFER POS'N
7F4E 3600       00810         LD      (HL),00          ; CLOSE OFF THE BUFFER
7F50 2B         00820         DEC     HL               ; BUMP BACK IN BUFFER...
7F51 2B         00830         DEC     HL               ; ...TO THE RUN COMMAND
7F52 C35A1D     00840         JP      1D5AH            ; AND THEN EXECUTE IT
                00850 ;
                00860 ; ######################################################
                00870 ; THE FOLLOWING FOUR BYTES ARE TEMPORARY KEYBOARD STORAGE
                00880 ; ######################################################
                00890 ;
7F55 0000       00900 STORE   DEFW    0000             ; TEMPORARY TWO-BYTE AREA
7F57 C3         00910 AWAY    DEFB    0C3H             ; JUMP COMMAND IN PLACE
7F58 781D       00920 RETURN  DEFW    1D78H            ; ORIGINAL VALUE CHANGES
                00930 ;
7F00            00940         END     START            ; PATCH ROUTINE AT START
00000 TOTAL ERRORS
31717  TEXT AREA BYTES LEFT
   AWAY    7F57 00910   00360 00480
   BYPASS  7F42 00760   00590
   BYTE    1D78 00140   00420
   CLOAD   7F28 00560   00450
   ENTRY   7F0F 00290   00210
   NOTRDY  7F18 00350   00320
   RETURN  7F58 00920   00200
   START   7F00 00190   00940
   STORE   7F55 00900   00580 00760
```

```
                 00100 ; ###########################################################
                 00110 : MINIATURE MACHINE-LANGUAGE MONITOR OISPLAYING HEX/ASCII
                 00120 ; ###########################################################
06CC             00130 READY   EOU     06CCH              ; RETURN TO READY INTACT
1D78             00140 8YTE    EOU     1078H              ; ROM REAO KEY & TOKENIZE
1997             00150 SYNERR  EOU     1997H              ; ENTRY POINT TO SN ERROR
                 00160 ; ###########################################################
                 00170 : GET REST OF DATA ANO CONVERT
0000 CD781D      00180 OPENER  CALL    8YTE               ; NEXT CHARACTER IN LINE
0003 FE22        00190         CP      22H                ; IS IT A QUOTE MARK?
0005 C29719      00200         JP      NZ,SYNERR          ; OUT TO ERROR IF NOT
0008 E5          00210         PUSH    HL                 ; SAVE LINE POINTER
0009 F0E1        00220         POP     IY                 ; STASH POINTER IN IY
0008 C0F800      00230         CALL    XX99               ; CONVERT CHARS TO HEX
000E C0C901      00240         CALL    01C9H              ; CLEAR SCREEN (ROM CALL)
0011 184C        00250         JR      NEXT99             ; JUMP PAST SU8ROUTINES
                 00260 : ###########################################################
                 00270 ; GET 16 SCREEN POSITIONS REAOY (10H)
0013 7A          00280 CONTNT  LD      A,D                ; GET AOORESS LOW 8YTE
0014 21403C      00290         LO      HL,3C40H           ; GET SECONO SCREEN LINE
0017 E6F0        00300         ANO     0F0H               ; MASK OUT LOW BITS
0019 C0E200      00310         CALL    RRRRS              : ROTATE/OISPLAY ROUTINE
001C 7A          00320         LO      A,D                ; GET AOORESS LOW 8YTE
0010 E60F        00330         AND     0FH                ; MASK OUT HIGH 8ITS
001F C00800      00340         CALL    HEXASC             ; CONVERT WORKS TO ASCII
0022 77          00350         LO      (HLJ,A             ; OISPLAY THE CHARACTER
0023 23          00360         INC     HL                 ; NEXT SCREEN POSITION
0024 78          00370         LD      A,E                ; GET HIGH 8YTE
0025 E6F0        00380         ANO     0F0H               ; MASK OUT LOW 8ITS
0027 CDE200      00390         CALL    RRRRS              ; ROTATE/OISPLAY ROUTINE
002A 78          00400         LD      A.E                ; GET HIGH 8YTE AGAIN
0028 E60F        00410         AND     0FH                ; HASK OUT LOW 8ITS
0020 CD0800      00420         CALL    HEXASC             : CONVERT HEX TO ASCII
0030 77          00430         LD      (HL),A             ; OISPLAY THE CHARACTER
0031 21803C      00440         LO      HL,3C80H           ; GET NEXT SCREEN ROW
0034 0610        00450         LD      8,10H              : GET 16 VALUE INTO 8
                 00460 ; ###########################################################
                 00470 : OISPLAY CONTENTS OF ADDRESS CHOSEN
0036 1A          00480 CONT02  LO      A,(DE)             ; GET VALUE AT AOORESS
0037 E6F0        00490         AND     0F0H               ; MASK OUT HIGH 8ITS
0039 CDE200      00500         CALL    RRRRS              ; CONVERT/OISPLAY ROUTINE
003C 1A          00510         LD      A,(DE)             ; GET VALUE AT ADDRESS
003D E60F        00520         AND     0FH                ; MASK OUT LOW 8ITS
003F CD0800      00530         CALL    HEXASC             ; CONVERT CHAR TO ASCII
0042 77          00540         LO      (HLJ,A             ; DISPLAY THE CHARACTER
0043 23          00550         INC     HL                 ; GET NEXT SCREEN POSN.
0044 23          00560         INC     HL                 ; GO ONE PLACE MORE
0045 13          00570         INC     DE                 ; GET NEXT AODRESS LOCN.
0046 10EE        00580         OJNZ    CONT02             ; FULL 16 BYTES OISPLAYEO
                 00590 : ###########################################################
                 00600 ; DISPLAY ASCII VALUES TOO
0048 0610        00610         LD      8,10H              ; GET 16 TIMES IN 8 REG.
004A 48          00620         LO      C,8                ; SAVE IT IN C FOR USE
0048 18          00630         DEC     0E                 ; GET NEXT LOWEST ADDRESS
004C 10FD        00640         DJNZ    $-1                ; DECREMENT 8ACK TO START
004E 41          00650         LD      8,C                ; GET 16 TIMES IN 8 AGAIN
004F 21C03C      00660         LD      HL,3CC0H           : GET NEXT LINE OF SCREEN
0052 1A          00670 888A    LO      A,(0E)             ; GET CONTENTS OF ADDRESS
0053 77          00680         LD      (HL),A             : OISPLAY EXACTLY AS IS
0054 23          00690         INC     HL                 ; GET NEXT SCREEN LOCN.
0055 23          00700         INC     HL                 ; GET NEXT AFTER THAT
0056 23          00710         INC     HL                 ; VISUALLY MATCHES HEX
0057 13          00720         INC     0E                 ; GET NEXT AOORESS TO SEE
0058 10F8        00730         OJNZ    888A               ; DO IT FOR 16 ADDRESSES
005A 41          00740         LD      8,C                ; GET 16 INTO 8 AGAIN
0058 18          00750         DEC     0E                 ; GO 8ACK TO PREVIOUS
005C 10F0        00760         OJNZ    $-1                ; AND 8ACK TO 8EGINNING
005E C9          00770         RET                        ; DONE WITH DISPLAY ROUT.
                 00780 : ###########################################################
                 00790 ; SCAN KEY8OARD FOR EDIT SEQUENCE
005F C01300      00800 NEXT99  CALL    CONTNT             ; FIND WHICH KEYS PRESSEO
                 00810 : ###########################################################
                 00820 : SCAN KEY8OARD FOR 8REAK, ARROWS
0062 3A4038      00830 EDITOR  LD      A,(3840H)          ; GET 8REAK, ARROWS ROW
0065 FE04        00840         CP      4                  : IS IT 8REAK KEY?
0067 2006        00850         JR      NZ,ARROW           ; IF NOT TEST FOR ARROW
0069 F0E5        00860         PUSH    IY                 ; ELSE RETRIEVE LINE PTR.
0068 E1          00B70         POP     HL                 ; SWITCH BACK INTO HL
006C C3CC06      00880         JP      READY              ; 8ACK TO 8ASIC REAOY
006F FE10        00890 ARROW   CP      10H                ; 8EGIN ARROW COMPARES
0071 2007        00900         JR      NZ,AAAA            ; GO IF NOT OOWN ARROW
0073 0610        00910         LO      8,10H              ; GET B REAOY WITH 16
0075 18          00920         OEC     0E                 ; GO 8ACK IN MEMORY
0076 10FD        00930         OJNZ    $-1                ; DO IT FOR 16 TIMES
0078 1848        00940         JR      STNDRD             ; OONE NOW; GO OUT
007A FE08        00950 AAAA    CP      8                  ; CHECK IF UP ARROW
007C 2007        00960         JR      NZ,AAA8            ; GO OUT IF NOT UP ARROW
007E 0610        00970         LD      8,10H              ; GET 16 PLACES READY
0080 13          00980         INC     0E                 : GET NEXT MEMORY LOCN.
0081 10F0        00990         DJNZ    $-1                ; 00 IT 16 TIMES IN ALL
0083 1840        01000         JR      STNDRD             ; DONE NOW: GO OUT
0085 FE20        01010 AAA8    CP      20H                ; CHECK IF LEFT ARROW
0087 2003        01020         JR      NZ,AAAC            ; GO OUT IF NOT LEFT
0089 18          01030         OEC     OE                 ; GET PREVIOUS MEM. LOCN.
008A 1839        01040         JR      STNORO             ; OONE NOW; GO OUT
008C FE40        01050 AAAC    CP      40H                ; CHECK IF RIGHT ARROW
008E 2003        01060         JR      NZ,AAA0            ; GO OUT IF NOT RIGHT
0090 13          01070         INC     OE                 ; GET NEXT MEMORY LOCN.
0091 1832        01080         JR      STNORO             ; OONE NOW; GO OUT
                 01090 : ###########################################################
                 01100 ; GET FIFTH LINE OF SCREEN AND OISPLAY CHOSEN EOITING
```

Listing Continued . . .

The routine at 1D5A bumps the HL register forward, evaluates the byte (finding 8E = RUN), then looks for a possible line number to execute. Finding a zero means the command ends there, and so a simple RUN routine is entered. Here's how to try it out once you have it in place:

```
SYSTEM          <ENTER>
/20480          <ENTER>
```

The BASIC program you had entered earlier should now run just as any other BASIC program might. So the idea is to make this autorun routine the heart of the area that the CLOAD might make its way back to.

Listing 3-(?) presents a machine language program which must precede any program to be autoexecuted. It follows the rules above by taking over control of the computer, placing a patch into the keyboard scan in order to intercept the terminal CLOAD routine's return to BASIC, and directing the computer to the usual CLOAD routine. When CLOAD gets back into BASIC, it will present a 'READY' and begin to scan the keyboard. It will, however, never get there.

Instead, the intercept now patched in place will redirect the computer to a short routine also present in the keyboard input buffer area. This routine restores the original plundered keyboard return address, and executes the automatic RUN routine. The autoload remnants in the keyboard buffer are no longer needed, and will be wiped out at the next keyboard input of any kind.

To use this program, assemble it and save it at the beginning of each in a batch of tapes. Use these tapes to CSAVE any programs you wish to autoexecute. Whenever you wish to run one of these programs, type . . .

```
>SYSTEM         <ENTER>
*? AUTO         <ENTER>
```

. . . and the program will load, acting as if a normal CLOAD were in action, but immediately beginning execution of the BASIC routine.

Machine Language Monitor

It can be very frustrating when you need to make some quick alterations to memory, or when you need to install a short machine language program. The options are few: load a decimal-to-hex conversion program and enter the code; convert the values to hex by hand and POKE them in place; write the code into a short

Continued Listing

```
0093 210030    01110 AAA0    LO      HL,3000H         ; FIFTH LINE ON SCREEN
0096 365F      01120         LO      (HL),5FH         : GET CURSOR CHARACTER
0098 23        01130         INC     HL               ; NEXT SCREEN LOCATION
0099 365F      01140         LO      (HL).5FH         ; GET CURSOR CHARACTER
0098 28        01150         OEC     HL               ; 8ACK TO FIRST LOCN.
009C 0602      01160         LO      8,2              ; GET 2 TRIE5 INTO 8
009E 05        01170 AAAE    PU5H    OE               ; SAVE MEMORY LOCATION
009F E5        01180         PUSH    HL               ; SAVE SCREEN LOCATION
00A0 C04900    01190         CALL    0049H            ; 8ASIC'5 KEY8OARO 5CAN
00A3 E1        01200         POP     HL               ; RE5TORE SCREEN LOCN.
00A4 01        01210         POP     OE               ; RESTORE MEMORY LOCN.
00A5 FE47      01220         CP      47H              ; CHECK IF ALPHA HEX
00A7 3089      01230         JR      NC,EOITOR        ; GO OUT IF NOT ALPHA HEX
00A9 FE30      01240         CP      30H              ; CHECK IF NUMERIC HEX
00A8 3885      01250         JR      C,EOITOR         ; OUT IF NOT NUMERIC HEX
00A0 FE3A      01260         CP      3AH              ; CHECK IF OV NUMERIC
00AF 3804      01270         JR      C,AAAF           ; CHECK NEXT IF IN RANGE
0081 FE40      01280         CP      40H              ; CHECK IF OV ALPHAHEX
0083 38A0      01290         JR      C,EOITOR         ; OUT IF OV ALPHA HEX
0085 77        01300 AAAF    LO      (HL),A           ; PLACE CHAR ON 5CREEN
0086 23        01310         INC     HL               ; GET NEXT SCREEN LOCN.
0087 10E5      01320         OJNZ    AAAE             ; GO GET ANOTHER CHAR.
               01330 ; ########################################################
               01340 ; CONVERT CHO5EN OATA TO HEX
0089 28        01350         OEC     HL
008A COC000    01360         CALL    ASCHEX
008U 4F        01370         LO      C,A
008E 28        01380         OEC     HL
008F COEC00    01390         CALL    LLLL5
00C2 81        01400         A00     A,C
               01410 ;
               01420 ; PUT NEW 8YTE IN PLACE
00C3 12        01430         LO      (OE),A
00C4 13        01440         INC     OE
               01450 ;
               01460 ; OI5PLAY REVI5EO LINE OF OATA
00C5 C01300    01470 5TNORO  CALL    CONTNT
00C8 COF400    01480         CALL    OELAY
00C8 1895      01490         JR      EOITOR
               01500 ;
               01510 ; ASCII TO HEXAOECIMAL CONVER5ION
00C0 7E        01520 A5CHEX  LO      A,(HL)
00CE FE40      01530         CP      40H
0000 3003      01540         JR      NC,NEXT98
0002 0630      01550         5U8     30H
0004 C9        01560         RET
0005 0637      01570 NEXT98  5U8     37H
0007 C9        01580         RET
               01590 ;
               01600 ; HEXAOECIMAL TO ASCII CONVERSION
0008 FE0A      01610 HEXA5C  CP      0AH
000A 3003      01620         JR      NC,NEXT96
000C C630      01630         A00     A,30H
000E C9        01640         RET
000F C637      01650 NEXT96  A00     A,37H
00E1 C9        01660         RET
               01670 ;
               01680 ; RIGHT ROTATE5 FOR CONVERSION5
00E2 0F        01690 RRRR5   RRCA
00E3 0F        01700         RRCA
00E4 0F        01710         RRCA
00E5 0F        01720         RRCA
00E6 C00800    01730         CALL    HEXA5C
00E9 77        01740         LO      (HL),A
00EA 23        01750         INC     HL
00E8 C9        01760         RET
               01770 ;
               01780 ; LEFT ROTATES FOR CONVERSION
00EC COC000    01790 LLLL5   CALL    A5CHEX
00EF 07        01800         RLCA
00F0 07        01810         RLCA
00F1 07        01820         RLCA
00F2 07        01830         RLCA
00F3 C9        01840         RET
               01850 ;
               01860 ; OELAY FOR 5CREEN OISPLAY5
00F4 010020    01870 OELAY   LO      8C,2000H
00F7 C06000    01880         CALL    0060H
00FA C9        01890         RET
               01900 ;
               01910 ; GET/CONVERT A5CII FROM 8UFFER
               01920 ; TO HEXAOECIMAL AOORESS
00F8 0604      01930 XX99    LO      8,4
00F0 C07810    01940 5555    CALL    8YTE
0100 F5        01950         PU5H    AF
0101 10FA      01960         OJNZ    5555
0103 F1        01970         POP     AF
0104 77        01980         LO      (HL),A
0105 COC000    01990         CALL    A5CHEX
0108 5F        02000         LO      E,A
0109 F1        02010         POP     AF
010A 77        02020         LO      (HL),A
0108 COEC00    02030         CALL    LLLLS
010E 83        02040         A00     A,E
010F 5F        02050         LO      E,A
0110 F1        02060         POP     AF
0111 77        02070         LO      (HL),A
0112 COC000    02080         CALL    ASCHEX
0115 57        02090         LO      0,A
0116 F1        02100         POP     AF
0117 77        02110         LO      (HL),A
```

Listing Continued . . .

BASIC program that does the work. None of these are satisfactory. Ideally, a machine language monitor is the tool to use.

But there are disadvantages to the monitors currently available. Many are too long, and are part of other, lengthier programs. Others overlap resident BASIC programs. And none make available ASCII representations as well as BASIC graphics characters. The short monitor presented in this section provides the latter, can be executed from BASIC (using the patch table presented earlier), and sits wherever in memory you would like.

It consists of a few major sections: The first clears the display, presents the requested address, displays the hex contents of that address and the sixteen following, displays the ASCII or graphics values of that address and the sixteen following, and presents a cursor for hex code entry. The second section searches the keyboard for a valid hex character, displays the character, waits for another, displays that, and advances the address and display.

The second section also searches the keyboard for the arrows, and advances the display (a) one place forward on a right arrow; (b) one place back on a left arrow; (c) sixteen places forward on an up arrow; and (d) sixteen places back on a down arrow. Last of all it searches for the (BREAK) key, which returns it to BASIC.

This monitor, as with all the BASIC-transparent programs presented in this book, must be executed by using the special command patch table (see Listing (?)-(?)). The command used in this table is /OPEN"NNNN", where NNNN is the address to be opened for examination (in hex).

Undoing NEW

This is a much easier task than the Level II manual would have you believe. When the NEW command is entered, the program remains in place, *completely unchanged!* The only alteration is that the end-of-BASIC-program pointer in memory has been changed to the beginning of the program. Hence, the computer believes that the program has a total length of zero.

But the old end-of-program information is still intact elsewhere, and can be found very easily. In fact, to restore a program you have actually

Continued Listing

```
0118 COECOO      02120          CALL     LLLLS
0118 B2          02130          AOO      A,0
011C 57          02140          LO       0,A
0110 C9          02150          RET
08CC             02160          ENO      READY
00000 TOTAL ERRORS
    AAAA    007A 00950   00900
    AAA8    0085 01010   00960
    AAAC    008C 01050   01020
    AAA0    0093 01110   01060
    AAAE    009E 01170   01320
    AAAF    0085 01300   01270
    ARROW   006F 00890   U0850
    ASCHEX  00C0 01520   01360 01790 01990 02080
    B88A    0052 00670   00730
    BYTE    1078 00140   00180 01940
    CONT02  0036 00480   U0580
    CONTNT  0013 00280   00800 01470
    UELAY   00F4 01870   01480
    EOITOR  0062 00830   01230 01250 01290 01490
    HEXASC  0008 01610   00340 00420 00530 01730
    LLLLS   00EC 01790   01390 02030 02120
    NEXT96  000F 01650   01620
    NEXT98  0005 01570   U1540
    NEXT99  005F 0U800   00250
    OPENER  0000 00180
    READY  .06CC 00130   00880 02160
    RRRHS   00E2 01690   00310 00390 00500
    SSSS    00F0 01940   01960
    STNORO  00C5 01470   00940 01000 01040 01080
    SYNERR  1997 00150   00200
    XX99    00F8 01930   00230
```

```
               00100 ; ##########################################################
               00110 ; ONLY A SHORT ROUTINE IS NECESSARY TO OETERHINE WHERE
               00120 ; A 8ASIC PROGRAH WAS 8EFORE ITS POINTERS WERE RESET. THE
               00130 ; BEGINNING OF PROGRAM POINTER HUST BE RESET, THE LINE
               00140 ; NUMBERS RUN THOUGH, THE ENO OF PROGRAH POINTER RESET,
               00150 ; THE STACK POINTER RESET, THE SCREEN CLEAREO, ANO THE
               00160 ; CLEAR (RESET VARIABLES ANO PROGRAH CONOITIONS) EXECUTEO
               00170 ; ##########################################################
               00180 ; NOTE THAT THIS ROUTINE IS ALSO CALLEO FROH BASIC USING
               00190 ; THE FORHAT /NEW.  THE CUSTOH INTERPRETER IS EHPLOYEO.
               00200 ; ##########################################################
               00210 ;
0000 E058A440  00220 RENEW   LO      OE,(40A4H)        ; GET START OF PRGRM PTR
0004 3EFF      00230         LO      A,0FFH            ; GET FF RESETTING COOE
0006 12        00240         LO      (OE),A            ; PLACE AT PROGRAM START
0007 C0FC1A    00250         CALL    1AFCH             ; GO THRU ALL LINES TILL
               00260                                   ; ENO OF PRGRH 00 FOUNO
000A 23        00270         INC     HL                ; HL MOVEO JUST PAST PRGM
000B 22F940    00280         LO      (40F9H),HL        ; SIMPLE VARIA8LE POINTER
000E E07BEB40  00290         LO      SP,(40EBH)        ; RESET STACK TO NORHAL
0012 C0C901    00300         CALL    01C9H             ; CLEAR THE SCREEN NOW
0015 C0611B    00310         CALL    1B61H             ; CLEAR ALL THE POINTERS
0018 C3CC06    00320         JP      06CCH             ; BACK TO BASIC "REAOY"
               00330 :
               00340 : ##########################################################
0000           00350         ENO
00000 TOTAL ERRORS
   RENEW  0000 00220
```

```
               00100 ; ##########################################################
               00110 ; RAH CHECKING PROGRAH - FIRST VERSION WITHOUT OISPLAY -
               00120 ; EXHAUSTIVELY CHECKS EACH TRIO OF RAH LOCATIONS WITHOUT
               00130 ; OISPLAYING CURRENT AOORESS; BAO AOORESSES ONLY SHOWN.
               00140 ; ##########################################################
               00150 ; NOTE THAT THIS PROGRAM IS * SELF-RELOCATING * ANO MUST
               00160 ; 8E ASSEH8LEO AT THE ORIGIN AOORESS SPECIFIEO 8ELOW.
               00170 ; ##########################################################
               00180 :
5000           00190         ORG     5000H             : 00 NOT CHANGE ORIGIN!
               00200 :
               00210 ; ##########################################################
               00220 ; SUBROUTINE TO CLEAR THE SCREEN WITH NORMAL SPACES
               00230 ; ##########################################################
               00240 ;
5000 21003C    00250         LO      HL,3C00H          ; BEGINNING OF VIOEO
5003 11013C    00260         LO      OE,3C01H          ; OESTINATION OF SPACE
5006 01FF03    00270         LO      8C,03FFH          ; SPACES ON SCREEN
5009 3620      00280         LO      (HL),20H          : OISPLAY BLANK SPACE
5008 E0B0      00290         LOIR                      : CLEAR THE SCREEN
               00300 ;
               00310 ; ##########################################################
               00320 ; SET UP HIOOLE OF PROGRAM POINTER, OISPLAY STAR TO SHOW
               00330 ; PROGRAH IS WORKING. SET UP THE STACK POINTER IN RELA-
               00340 ; TIONSHIP TO THE IX REGISTER, ANO SPECIFY START OF TEST
               00350 ; ##########################################################
```

Listing Continued . . .

wiped out, you need to invoke a few ROM routines and restore the beginning-of-program pointer.

Although variables are cleared in this process, the program is totally restored. If you wish to make this a part of a transparent operating system using the interpreter patch presented earlier in this chapter, Listing 3-(?) presents a complete routine. Enter /NEW, and the lost program reappears.

One warning is in order: if before restoring the program you cause a ?SN ERROR, the computer will jumble up the first part of the program, mess around with some other memory pointers, and the program will *really* be lost.

Resetting MEMORY SIZE?

The size of BASIC memory available can also be changed from BASIC itself, because it too is simply stored in a two-byte pointer in the RAM patch area. New values may be POKEd into place, so long as they meet two conditions:

1. The new value must be within the range of actual memory available.
2. It must not dip below the top of an existing BASIC program already in memory.
3. If no program is in memory, it must not dip below address 4414.

Here's how to do it. Convert the desired new memory size to split decimal with this formula:

```
X = NNNNN                      <ENTER>
Y = FIX (X/256)                <ENTER>
Z = X - Y * 256                <ENTER>
PRINT Z,Y                      <ENTER>
```

The value of Z is the least significant byte of the new memory size, Y is the most significant byte. Now:

```
POKE 16561,Z : POKE 16562,Y : CLEAR50
```

The new memory size has been set, and 50 bytes are cleared for string space, as usual. If you haven't followed the rules about legitimate memory sizes, expect a fast system crash.

Continued Listing

```
                 00360 ;
5000 0021B050 00370          LO      IX,5080H            ; MIOOLE OF TEST PROGRAM
5011 3AFE3F   00380          LO      A,(3FFEH)           ; 8OTTOM RIGHT OF 5CREEN
5014 EE0A     00390          XOR     0AH                 ; ALTERNATE SPACE & STAR
5016 32FE3F   00400          LO      (3FFEH),A           ; OI5PLAY IT ON 5CREEN
5019 00F9     00410          LO      5P,IX               ; 5TART STACK POINTER
501B 067F     00420          LO      B,7FH               ; NUMBER OF MOVE5 FOR SP
5010 33       00430          INC     5P                  ; SP = 5P + 1
501E 10F0     00440          OJNZ    $-1                 ; 00 IT 127 TIMES
5020 210060   00450          LO      HL,6000H            ; BEGINNING OF TEST AREA
              00460 ;
              00470 ; ##################################################
              00480 ; TEST BEGIN5 WITH THE VALUE OF ZERO, ANO PROCEEOS TO
              00490 ; VALUE FF.  EACH VALUE I5 WRITTEN IN TURN TO EACH OF A
              00500 ; TRIO OF HEMORY LOCATIONS IN ORDER TO OETERMINE THEIR
              00510 ; EFFECT ON EACH OTHER AS VALIO ELECTRONIC STORAGE CELL5.
              00520 ; ##################################################
              00530 ;
5023 AF       00540          XOR     A                   ; CLEAR ACCUHULATOR
5024 77       00550          LO      (HL),A              ; PLACE VALUE IN MEMORY
5025 4F       00560          LO      C,A                 ; PLACE VALUE IN C
5026 F5       00570          PU5H    AF                  ; SAVE VALUE IN ACCUM.
5027 79       00580          LO      A,C                 ; GET VALUE FROM C
502B 77       00590          LO      (HL),A              ; PLACE VALUE IN MEMORY
5029 23       00600          INC     HL                  ; INCREMENT TO NEXT MEM
502A 7C       00610          LO      A,H                 ; GET MSB OF AOORESS
502B FEB0     00620          CP      80H                 ; I5 MEM AT 8000 YET?
              00630                                      ; NOTE THAT THE VALUE
              00640          CP      00H                 ; ABOVE IS FOR 16K; USE
              00650                                      ; CO FOR 32K, 00 FOR 48K
5020 2B30     00660          JR      Z,$+32H             ; IF 50, THEN RELOCATE
502F E5       00670          PU5H    HL                  ; 5AVE MEMORY VALUE
5030 00E5     00680          PU5H    IX                  ; 5AVE HIOOLE OF PROGRAM
5032 E1       00690          POP     HL                  ; GET POSITION INTO HL
5033 BC       00700          CP      H                   ; CHECK AGAINST 80 VALUE
5034 2B29     00710          JR      Z,$+2BH             ; RELOCATE IF OONE
5036 E1       00720          POP     HL                  ; RE5TORE ORIGINAL VALUE
5037 F1       00730          POP     AF                  ; RESTORE ORIGINAL TEST
503B 77       00740          LO      (HL),A              ; PUT VALUE INTO MEMORY
5039 2B       00750          OEC     HL                  ; BACK TO ORIGINAL LOC'N
503A 2B       00760          OEC     HL                  ; BACK TO ONE BEFORE IT
503B 77       00770          LO      (HL),A              ; PUT VALUE INTO MEMORY
503C 47       00780          LO      B,A                 ; 5AVE VALUE IN B REG.
5030 7E       00790          LO      A,(HL)              ; GET VALUE AT LOC'N HL
503E BB       00800          CP      B                   ; CHECK AGAINST B VALUE
503F 2B05     00810          JR      Z,$+7               ; GO ON IF IT CHECKS OKAY
5041 161B     00820          LO      0,1BH               ; GET VALUE OF REL. SUB.
5043 05       00830          PUSH    OE                  ; SAVE VALUE ON STACK
5044 1B1B     00840          JR      $+10H               ; JUMP TO 5UBROUTINE
5046 23       00850          INC     HL                  ; GET ORIGINAL TEST POS'N
5047 23       00860          INC     HL                  ; GO ONE BEYONO IT
504B 7E       00870          LO      A,(HL)              ; GET VALUE AT THAT PO5'N
5049 BB       00880          CP      B                   ; CHECK AGAINST B REG.
504A 2B05     00890          JR      Z,$+7               ; GO ON IF MEMORY OKAY
504C 1610     00900          LO      0,10H               ; GET JUMP FOR REL. SUB.
504E 05       00910          PU5H    OE                  ; SAVE VALUE ON STACK
504F 1B10     00920          JR      $+12H               ; JUMP TO 5UBROUTINE
5051 2B       00930          OEC     HL                  ; BACK TO ORIGINAL PO5'N
5052 34       00940          INC     (HL)                ; INCREMENT VALUE IN MEM
5053 0C       00950          INC     C                   ; INCREHENT TEST VALUE
5054 7E       00960          LO      A,(HL)              ; GET VALUE IN HEMORY
5055 47       00970          LO      B,A                 ; SAVE VALUE IN B REG.
5056 FE00     00980          CP      00                  ; CHECK IF 256 BYTES OONE
505B 20CC     00990          JR      NZ,$-32H            ; LOOP BACK ANO CONTINUE
505A 23       01000          INC     HL                  ; GET NEXT MEHORY VALUE
505B 0E00     01010          LO      C,0                 ; RESET TE5T VALUE TO 0
5050 1BC7     01020          JR      $-37H               ; LOOP BACK FOR NEXT TEST
505F 1B64     01030          JR      $+66H               ; REL.5UB. 5TEPPING STONE
              01040 ;
              01050 ; ##################################################
              01060 ; 5UBROUTINE BELOW I5 ENTEREO WHEN A BAO MEMORY LOCATION
              01070 ; HA5 BEEN OETERMINEO.  IT CONVERTS HEX VALUES TO ASCII
              01080 ; ANO OI5PLAYS THEH ON THE 5CREEN.  NOTE THE RELATIVE
              01090 ; SUBROUTINE ENTRY ANO EXIT METHOO U5ING THE 0 REGI5TER.
              01100 ; ##################################################
              01110 ;
5061 7C       01120          LO      A,H                 ; GET VALUE FROM H REG.
5062 E6F0     01130          ANO     0F0H                ; MASK OFF LOW BITS
5064 0F       01140          RRCA                        ; ROTATE RIGHT FOR CONV.
5065 0F       01150          RRCA                        ; .... SOME MORE ....
5066 0F       01160          RRCA                        ; .... ANO SOME MORE ....
5067 0F       01170          RRCA                        ; .... UNTIL IT'S OONE.
506B 1622     01180          LO      0,22H               ; GET VALUE FOR REL. SUB.
506A 1B22     01190          JR      $+24H               ; ANO JUMP TO SUBROUTINE
506C 7C       01200          LO      A,H                 ; GET VALUE FROM H REG.
5060 E60F     01210          ANO     0FH                 ; MASK OUT HIGH BITS
506F 161B     01220          LO      0,1BH               ; GET VALUE FOR REL. SUB.
5071 1B1B     01230          JR      $+10H               ; ANO JUMP TO SUBROUTINE
5073 70       01240          LO      A,L                 ; GET VALUE FROM L. REG.
5074 E6F0     01250          ANO     0F0H                ; MA5K OUT LOW BIT5
5076 0F       01260          RRCA                        ; ROTATE FOR CONVERSION
5077 0F       01270          RRCA                        ; .... 5OME MORE ....
507B 0F       01280          RRCA                        ; .... SOME MORE ....
5079 0F       01290          RRCA                        ; .... ANO IT'S OONE.
507A 1610     01300          LO      0,10H               ; GET VALUE FOR REL. SUB.
507C 1810     01310          JR      $+12H               ; ANO JUMP TO SUBROUTINE
507E 70       01320          LO      A,L                 ; GET VALUE FROM L REG.
507F E60F     01330          ANO     0FH                 ; MASK OUT H1GH 8ITS
5081 1609     01340          LO      0,9                 ; GET VALUE FOR REL. SU8.
5083 1B09     01350          JR      $+0BH               ; ANO JUMP TO SUBROUTINE
5085 01       01360          POP     OE                  ; RESTORE VALUE TO OE
5086 3E03     01370          LO      A,003H              ; GET RETURN PO5'N VALUE
```

Listing Continued . . .

Peek that Keyboard

One of the handiest functions for fast-running, convenient BASIC programs is the INKEY$ command. This allows the latest keystroke to be transferred to a program variable, where it can then be evaluated.

For action games, BASIC word processors and other speed-conscious programs, INKEY$ can be too long because it requires considerable evaluation and juggling of memory space. There is a faster way, and it involves examining the keyboard's memory contents directly. Below is the keyboard matrix:



You can see that various memory locations refer to various rows of keys. Depending on the key pressed, different values will be discovered by PEEKing. For example, A=PEEK(14400) returns a value of 1 if ENTER is pressed, and a value of 2 if CLEAR is pressed, 4 if BREAK is pressed, 8 for down arrow, 16 for up arrow, 32 for left arrow, 64 for right arrow, and 128 for a space. If only a few keys are being sought – perhaps the arrow in an action game – a very tight loop can be constructed that is many times faster than INKEY$:

```
10 A = PEEK(14400) : IF A=0 THEN 10
20 IF A=8 THEN 100 : IF A=18 THEN 200
30 IF A=32 THEN 300 : IF A=64 THEN 400
40 GOTO 10
```

ELSE

For top-speed operation, this should all appear on one line; try it in comparison with testing for CHR$(8) or CHR$(9), etc., etc., to determine the arrows.

Continued Listing

```
5D8B 92       D13BD          5UB     D                  ; 5UBTRACT RETURN DIFF.
5DB9 DD77DD   D139D          LD      (IX+DDH),A         ; AND HAKE JR OPERANO
5DBC 1BFF     D1400          JR      $+1                ; IRRELEVANT OPERANO
5DBE 05       D1410          PUSH    DE                 ; SAVE VALUE DN STACK
5DBF F5       D142D          PU5H    AF                 ; SAVE VALUE DN 5TACK
5D9D 11DD3C   D143D          LD      DE,3CDDH           ; GET TDP LEFT DF 5CREEN
5D93 1A       0144D          LD      A,(DE)             ; GET VALUE DN SCREEN
5D94 FE2D     D145D          CP      2DH                ; I5 IT A 5PACE NDW?
5D96 2BD3     D146D          JR      Z,$+5              ; IF 5D, GD AHEAD 5DHE
5D9B 13       D147D          INC     DE                 ; INCREMENT SCREEN PDS'N
5D99 1BFB     D14BD          JR      $-6                ; AND GD AHEAD PA5T TE5T
5D9B 7B       D149D          LD      A,E                ; GET VALUE DF SCREEN
5D9C FED4     D15DD          CP      D4                 ; I5 IT 4 PD5'N5 DVER?
5D9E 2DDA     D151D          JR      NZ,$+DCH           ; IF NDT, GD ON AHEAO
5DAD 3E2D     D152D          LD      A,2DH              ; IF 5D GET A 5PACE READY
5DA2 18       D153D          DEC     DE                 ; GD BACK 5DME....
5DA3 12       D154D          LD      (DE),A             ; AND FILL WITH A 5PACE
5DA4 1B       D155D          DEC     DE                 ; AND BACK 5DME MDRE....
5DA5 12       D156D          LD      (DE),A             ; AND IN5ERT ANDTHER DNE
5DA6 1B       D157D          DEC     DE                 ; AND BACK A BIT MDRE....
5DA7 12       D15BD          LO      (DE),A             ; AND 5TASH ANDTHER 5PACE
50AB 1B       D1590          OEC     OE                 ; ANO BACK ONE MORE TIME
50A9 12       01600          LO      (OE),A             ; ANO STUFF A SPACE THERE
50AA F1       D1610          POP     AF                 ; RESTORE VALUE TO AF
5DAB FEDA     0162D          CP      DAH                ; I5 VALUE LE55 THAN 1D?
5DAD 3DD4     D1630          JR      NC,$+6             ; IF LESSER, THEN JUMP
5DAF C63D     D164D          ADD     A,3DH              ; CDNVERT HEX TD A5CII
5DB1 1BD2     D165D          JR      $+4                ; AND GD DN PA5T THE RE5T
5DB3 C637     D166D          ADD     A,37H              ; CDNVERT HEX TD A5CII
5DB5 12       D167D          LD      (DE),A             ; AND 5TA5H ON THE 5CREEN
              D16BD ;
              D169D ; ##########################################################
              D17DD ; SHDRT RDUTINE BELDW USED A5 DELAY AFTER LDC'N DISPLAY.
              D171D ; ##########################################################
              D172D ;
5DB6 C5       D173D          PUSH    BC                 : 5AVE VALUE IN BC REG
5DB7 D6FF     D174D          LD      B,DFFH             ; GET DELAY VALUE
5DB9 1DFE     D175D          DJNZ    $-D                ; AND DELAY JU5T A LITTLE
5DB8 C1       D176D          PDP     BC                 ; RESTDRE 8C VALUE
5DBC D1       D177D          PDP     DE                 ; RE5TDRE DE VALUE
50BD 3EC9     D17BD          LD      A,DC9H             ; GET VALUE TO RETURN
5DBF 92       D1790          5UB     D                  : 5UBTRACT JUMP DFF6ET
5DCD DD7744   D18DD          LD      (IX+44H),A         ; PLACE A5 JR DPERAND
5DC3 1BFF     D1B1D          JR      $+1                ; IRRELEVANT DPERAND
              D1B2D ;
              D1B3D ; ##########################################################
              D1B4D ; PRDGRAM RELDCATIDN RDUTINE.  HL AND DE REGISTER5 ARE
              D1B5D ; LDADED FRDM THE IX REGI5TER, AND MDDIFIED BY EXCLU5IVE-
              D1B6D ; DRING WITH A KNDWN VALUE IN A.  THU5, A NEW PRDGRAM
              D1B7D ; 8EGINNING CAN 8E DETERMINED, INTERNAL TE5T PDSITIDNS
              01B80 ; CAN BE MOOIFIEO, ANO THE IX ANO SP POINTERS RESET.
              D1B9D ; ##########################################################
              D19DD ;
5DC5 DDE5     D1910          PU5H    IX                 ; SAVE PRDGRAH PD5ITIDN
5DC7 DDE5     D192D          PU5H    IX                 ; 5AVE PRDGRAM PD5ITIDN
5DC9 E1       D193D          PDP     HL                 ; TRAN5FER TD HL REG.
5DCA D1       D194D          PDP     DE                 ; TRANSFER TD DE REG.
5DCB 7A       D195D          LD      A,D                ; GET VALUE FRDH D REG.
5DCC EE2D     D196D          XDR     2DH                ; TRAN5FER TD HIGH MEM.
5DCE 57       D197D          LD      D,A                ; PUT BACK IN D REG.
5DCF D5       D19BD          PU5H    DE                 ; AND 5TA5H DN 5TACK
5DDD D68D     D199D          LD      8,BDH              ; DEC. TD PRDGRAM 5TART
5DD2 28       D2DDD          DEC     HL                 ; AND BEGIN DECREMENTING
50D3 1B       D201D          OEC     OE                 ; FOR BOTH THE REGISTERS
5004 1DFC     D2D20          OJNZ    $-2                ; UNTIL IT'S ALL OONE
5D06 D1FF00   02D3D          LD      8C,ODFFH           ; AND GET REAOY TRANSFER
50D9 EDBD     D204D          LDIR                       ; AND THEN DO IT!
5DDB D0E1     D2D5D          POP     IX                 ; RESTORE NEW VALUE
5DD0 3E2D     D2060          LD      A,2DH              ; VALUE TO MOO. AOORESSES
50DF DDAEA2   D2D7D          XDR     (IX+DA2H)          ; MDDIFY IX+A2 ADDRESS
5DE2 DD77A2   D2D8D          LD      (IX+DA2H),A        ; ANO STORE IT IN PLACE
5DE5 3EFD     D2D9D          LD      A,~~0E0H~~ to      ; VALUE TO HOD. AOORESSES
              021DD                                     ; CHANGE OPERANO A8OVE TD
              D211D          LD      A,70H              ; 8O FDR 32K HEM TEST ANO
              D2120                                     ; TO 70 FOR 48K MEM TEST
5DE7 DDAEAC   D213D          XDR     (IX+DACH)          ; HODIFY IX+AC AOORESS
5DEA DD77AC   0214D          LD      (IX+0ACH),A        ; AND STORE IT IN PLACE
50ED 0DE5     D215D          PUSH    IX                 ; STORE THE PRDGRAH PTR.
50EF E1       D216D          POP     HL                 ; AND TRANSFER IT TO HL
50F0 2E11     02170          LO      L,11H              ; SET LSB OF HL REGISTER
5DF2 E9       D218D          JP      (HL)               ; JUMP TD PRDGRAH STARTI
              D2190 ;
              D22D0 ; ##########################################################
5D0D          D221D          ENO     5DDDH
ODDDO TDTAL ERRORS
```

There is yet another use for this PEEK function. As noted in Chapter 2, location 387F reveals if any key is pressed at all. This can be used in a BASIC text editor, for example, and is much faster than INKEY$ to check for keypressing:

```
10 A = PEEK(14463) : IF A=0 THEN 10
```

This is one of the fastest keystroke-detectors in BASIC, and from there a group of PEEKs could be done, checking the most-used rows of characters first. It's both a matter of taste and programming skill whether INKEY$ or PEEK is used for keyboard input, but in some situations (such as testing for carriage returns and other control codes), PEEK is the winner.

KEYBOARD PEEK PDSITIONS

DATA:	1	2	4	8	16	32	64	128
ADDRESS:								
14337	@	A	8	C	D	E	F	G
14338	H	I	J	K	L	M	N	D
14340	P	Q	R	S	T	U	V	W
14344	X	Y	Z					
14352	D	1 !	2 "	3 #	4 $	5 %	6 &	7 '
14368	8 (	9)	: *	; +	, <	- =	. >	/ ?
14400	ENT	CLR	8KR	UPAR	DNAR	LFTAR	RTAR	SPACE
14464	SHIFT							

Figure 3-(?) is a chart of all the characters and their respective PEEK positions and data returned. Remember, when more than one key is depressed at a time, the *row* of the data at that address is returned. For example, if PEEK (14400) returns 129, then both ENTER and SPACE are being held down. This is significant because INKEY$ returns only the last character pressed, and there is no real way of getting to multiple characters. Try this:

```
10 A = PEEK (14400)
20 IF A = 129 THEN 100
30 PRINT "PRESS ENTER AND CLEAR"
40 GOTO 10
100 PRINT"DONE!"
```

Simple as this may appear, it offers an 'out' for programs that need special, unusual input for some functions. It can be used as the sort of double-interlock protection switch found on industrial machinery to keep both hands out of blades and moving parts.

Furthermore, when the keyboard is PEEKed, the values returned can be changed and mutated at will – for example, a BASIC letter-writer could have two easily written routines to make the keyboard the standard 'QWERTY' type or changing it to the faster Dvorak type. Of course, even with PEEK statements, BASIC is not likely to keep up with that sort of speed typing!

Make-'Em-Sweat Memory Test

Many memory tests are available for testing the dynamic memory in the TRS-80 and expansion interface, including the simple test done by the computer itself on power-up (see Supplement to Chapter 1). Most have a significant disadvantage: they are *software* tests rather than *electrical* tests. Certainly, since memory involves operating software, a software test seems to be a logical solution.

On the other hand, memories are electronic devices, run by electricity and influenced in their failings by electrical and physical forces. Barring removing each memory and running sophisticated electrical tests on it, then, there is only one serious memory test option: test each bit in combination with each and every other bit in the device. Unfortunately, that is impractical, since there are 393,216 bits in a 48K system, and testing every one would result in over 150,000,000,000 separate tests – a task that would take nearly a solid month running at the TRS-80's 1.77 MHz clock rate!

The remaining option, then, is to make reasonable electrical tests that exercise the neighboring bits in a memory chip, and read and write to them about as fast as the TRS-80 is likely to do it in real time. The process I have chosen is twentyfold:

1. Write a value to memory.
2. Read the stored value and check its accuracy.
3. Change the surrounding bits from zeros to ones.
4. Change the surrounding bits from ones to zeros.
5. Read the stored value and check its accuracy.
6. Change the surrounding bits from zeros to ones.
7. Change the surrounding bits from ones to zeros.
8. Write the value to memory again.
9. Read the stored value and check its accuracy.
10. Change the surrounding bits from zeros to ones.
11. Read the stored value and check its accuracy.
12. Change the surrounding bits from ones to zeros.
13. Read the stored value and check its accuracy.
14. Change the surrounding bits from zeros to ones.
15. Write the value to memory again.
16. Read the stored value and check its accuracy.
17. Change the surrounding bits from ones to zeros.
18. Write the value to memory again.
19. Read the stored value and check its accuracy.
20. Increment the value to be written and repeat.

This process is repeated 256 times, writing values from **00** to **FF**, and producing the electrical switches noted above. The program then moves itself to another area of memory, and checks the area in which it was just residing.

The entire memory test is still very time-consuming, since the address under test is displayed while the process is continuing.

In the program presented in Listing 3-(?), the test displays the memory location under test; any failed memory location is displayed on the screen, along with the bits which have failed. The test is presented in a 16K version with changes for 32K and 48K systems.

Cassette I/O

One of the most maligned aspects of the TRS-80 is its cassette loading procedure. Interestingly, it is a lengthy and skillfully designed piece of coding, a victim of a combination of poor hardware (an inexpensive cassette recorder), the inclination personal computer owners have to purchase the least expensive tapes they can find, and the lack of foresight on the part of the engineers designing the routines. But there's no question that with a good tape recorder and reasonable tape, it works well. Here's how.

The routine to read and accept serial information is fairly convoluted, collapsed to about a dozen major subroutine CALLs. We will start with the SYSTEM command; since BASIC programs have other bytes to juggle (looking for out-of-memory errors, etc.), we won't tackle its major routines.

The SYSTEM module

The SYSTEM command is evaluated by the BASIC interpreter, and its control routine is entered at 02B2. If you don't want to know how this command gets to work, then skip right to the tape loading routine two paragraphs below. An initial CALL is executed to DOS link 41E2, which in Level II merely executes a RETurn. The stack is set up at 4288, and another CALL executed to 20FE, which checks the DOS link at 41C1, picks up the 'device type' – video, tape, or printer – (video at this time), displays a carriage return, checks and saves port FF status (32 or 64 character mode and cassette state), clears the accumulator, and returns. This is preparatory housekeeping.

The accumulator is set up with a star, it is displayed (with more housekeeping), and the INPUT routine is CALLed from location 1BB3. This is the same routine used for INPUT statements, and it displays a question mark, evaluates the input line, discards everything after certain punctuation, and returns the evaluated line to the CALLing program. If a BREAK is discovered, the program returns to READY. Spaces, line feeds, tabs, etc., are cleaned out, and a syntax error is declared if no alphanumeric characters are found. If a slash (/) is found, the SYSTEM program jumps past its loading routines, picks up the start address from 40DF (more about that later), cleans out blanks again, and evaluates the string after the slash as an interger (a CALL to 1E5A). The whole business starts over if a non-numeric string is found. If, at last, the program does discover that a number was input, the SYSTEM module is executed from the starting address stored at 40DF.

Build-a-Byte

The first major loading call is to 0293, which searches for a synchronization byte. Since this will eventually call the 'build-a-byte' routine, let's move there first. It begins at 0241; BC and AF registers are saved. Then:

```
0243    0B FF           IN      A,(FF)
0245    17              RLA
0246    30 FB           JR      NC,0243
0248    06 41           LD      B,41
024A    10 FE           DJNZ    024A
```

Port FF is checked repeatedly by inputting the value to the accumulator and rotating that value into the carry flag. If no carry is found – i.e., no 'one' bit has yet triggered port FF – the program loops back to 0243. Once a bit is found, the B register is loading with 41, and a 'waste time' loop is executed at 024A (a total of just under 500 microseconds). A CALL is then executed to 021E. Let's have a look at that:

```
021E    21 00 FF        LO      HL,FF00
0221    3A 30 40        LO      A,(4030)
0224    A4              ANO     H
0225    B5              OR      L
0226    03 FF           OUT     (FF),A
0228    32 30 40        LD      (4030),A
022B    C9              RET
```

This curious subroutine seems to stumble through checking port FF for its video state, then resetting the OUTSIG flip-flop (see the *Technical Reference Handbook* for details on this circuitry). Isn't a byte ANDed with FF and ORed with 00 merely itself? True enough, but since this is also called as a subroutine entering at 0221, with a different value for HL, the complex AND/OR strategy makes sense.

So at this point we have picked up a bit from tape, delayed, and reset the flip-flop, readying it for the next bit to trigger it. Another delay loop follows (over 850 microseconds), and a byte is input to A from port FF:

```
0253    0B FF           IN      A,(FF)
0255    47              LO      B,A
0256    F1              POP     AF
0257    CB 10           RL      B
0259    17              RLA
025A    F5              PUSH    AF
```

The input byte is saved in the B register, and the previously saved value of A is restored from the stack. Here is a wonderful piece of serial-to-parallel conversion – a sort of software shift register. Bit 7 of port **FF** was input to A and saved in B, and is then rotated left into the carry flag. Then the accumulator is rotated left, bringing the state of the carry flag into bit 0 of A. The accumulator is then saved once more on the stack. Another CALL to **021E** resets the port **FF** flip-flop, both registers are restored, and the subroutine returns to the calling program.

You'll notice that at this point we have only one bit saved in the accumulator. An eight-iteration loop would be necessary to create a whole byte . . . and it will be done. But for the moment let's see how this routine is used in the initial syncing program, which we were about to enter at 0293.

The routine's first action is to **CALL 01FE**. This is a detailed routine to determine the drive number and other parts of the syntax, the state of port **FF** (again), select the drive and get it moving. Examining the code will show that it also uses the routine entered at **0221**, but with a value of **FF04** in HL; this routine won't be covered here, but it is worth looking at.

The find-sync-byte routine thus turns on the tape, saves the HL register, clears the accumulator, and calls the 'build-a-byte' routine at **0241**. Since this is the synchronization process, no loop value is specified:

```
0297    AF              XOR     A
029B    C0 41  02       CALL    0241
029B    FE A5           CP      A5
0290    20 FB           JR      NZ,029B
```

It continually seeks bits, endlessly rotating the accumulator until it assembles a serial stream which matches **A5** (i.e., binary 10100101 – nice and symmetrical). This routine is so accurate, in fact, that whenever tape motor start-up is not a consideration, the leader consisting of zero bytes would be unnecessary. The leading '1' of **A5** serves as a kind of serial 'start bit' – and the routine at **0241** handles it from there.

Any kind of match to sync byte **A5** might be found, tough, since the serial stream coming in from the tape does not distinguish start and end of byte. For example, the byte pattern **DD 28** also contains an A5 embedded in it. As a serial stream, **DD 28** is

1101110100101000
. . . . .**10100101**. . . .

- with the **A5** appearing at the junction of **DD** and **28**. So once the matching **A5** is found, a return is executed to the main SYSTEM loading module. That module then CALLs a subroutine at **0235**, which is a gussied-up bit reader. BC and HL are saved, then:

```
0237    06  0B          LD      B,0B
0239    C0  41  02      CALL    0241
023C    10 FB           DJNZ    0239
```

There's the byte read . . . read a bit with eight iterations. HL and BC registers are restored, and the subroutine returns to the main program.

Loading the Code

The SYSTEM module now compares the byte it created with the value **55**, the code assigned to machine language programs. It loops until it finds that code, then proceeds:

```
02D8    06  06          LO      B,6
020A    7E              LO      A,(HL)
02DB    B7              OR      A
020C    28  09          JR      Z,02E6
02DE    C0  35  02      CALL    0235
02E1    BE              CP      (HL)
02E2    20  E0          JR      NZ,02C1
```

Above, the B register is loaded with the number of characters to be found in the SYSTEM program's name. The accumulator is set up with the first character of the name as entered on the *? command line. The accumulator is tested for zero, and skips out of the loop when the end of the entered name is found. Each character following the name is read into the accumulator (**CALL 0235**) and compared with each letter of the entered name. If at any point the entered name does not match the name on tape, the program goes back to searching for **55** (machine program indicator) and the name search begins again.

There is a minor flaw in this process. Let's look at the succeeding lines of code:

```
02E4    23              INC     HL
02E5    10 F3           DJNZ    020A
```

This coding increments the HL register to the next character and loops back, looking for a total of six letters in the name. But what if the machine program code (55) is found, and one or more characters of the name match, but the rest do not match? There is no provision in this routine to decrement the HL register pair . . . which means that, if only part of a correct name has been found,the program will begin its search anew until it finds a program that matches only the last part of the entered name! This is the

reason the SYSTEM routine is not always able to search until it finds the correct program, the way the BASIC load does.

Let's assume the best – that a machine program was found with the name as entered from the keyboard. A CALL is then made to 022C, where the star or space at 3C3F is toggled (XORed) with 0A. Star XOR 0A is a space, and space XOR 0A is a star; easily done.

The SYSTEM Module Continues —

```
D2EA     CD 35 D2        CALL     D235
D2ED     FE 78           CP       78
D2EF     28 88           JR       Z,D2A9
D2F1     FE 3C           CP       3C
D2F3     2D F5           JR       NZ,D2EA
```

– searching for either 78 (end of program code) or 3C (beginning of data block code). If 78 is found, the program skips back to 02A9, where a CALL is executed to 0314. This subroutine merely reads the last two bytes on tape into the HL register, preparing the start address. This is saved at 40DF, the cassette recorder is turned off (CALL 01F8), and the SYSTEM module is re-entered from the start at 02B2. This module is a continuous loop, allowing a group of machine-language programs to be entered sequentially. Only the presence of the slash-start address combination will break out of the loop.

If a 3C is found, the beginning of a block of machine code is assumed. (If neither is found, the program loops until it finds one or the other). Here's a snippet of code:

```
D2F5     CD 35 D2        CALL     D235
D2F8     47              LD       8,A
D2F9     CD 14 D3        CALL     D314
02FC     85              A0D      A,L
D2FD     4F              LD       C,A
```

A byte is read and saved in B. At 0314, two bytes are read and saved, respectively, in the HL register pair. These three bytes are, first, the number of bytes to read, and second, the two-byte starting address of the block. The 0314 subroutine leaves the value transferred to H in the accumulator; to it is added the value in L, and this number, sans carry value, is saved in the C register. The C register will be used to calculate the checksum for the block being read.

Curious Checksum

Each succeeding byte is read from tape and placed at the address now specified by HL. That byte is also added to the C register to update the simple checksum. HL is incremented to the next contiguous address, and the loop is iterated until B (the number of bytes to read in the block) reaches zero.

When the block is fully read, another byte is read from tape. This is the checksum byte, and should match the last updated value in the C register. If it does match, the program loops back, toggles the star, and begins anew the search for end-of-program (78) or block header (3C).

A correct checksum byte, curiously enough, is not a necessary element of the SYSTEM module. If the checksum is incorrect, the program will display a 'C' at video location 3C3E, and loop back regardless to continue reading the program from tape. I first noticed this action when a gentleman from New Hampshire called; he had been using a tape duplication routine to make a corrected copy of a machine language program. He had loaded the tape, returned to BASIC, then POKEd in a few byte changes. He then continued with the duplication. When he loaded the tape later on, he got a 'C' error message on the screen . . . but the program continued to load and did execute properly. The checksum was wrong because of the byte changes he had made, but the program, checksum notwithstanding, was read and loaded completely.

Let's take a look at that final portion of code:

```
D2FE     CD 35 D2        CALL     D235
D3D1     77              LD       (HL),A
D3D2     23              INC      HL
D3D3     81              ADD      A,C
D3D4     4F              LD       C,A
D3D5     1D F7           DJNZ     D2FE
D3D7     CD 35 D2        CALL     D235
D3DA     89              CP       C
D3D8     28 DA           JR       Z,D2E7
03DD     3E 43           LD       A,43
D3DF     32 3E 3C        LD       (3C3E),A
0312     18 06           JR       02EA
```

Overall, these routines give the appearance of being reasonable and reliable, and they should be. What, then, gives rise to the tape problems? Mostly the timing loop in the 0235/0241 subroutine. The values placed in the B register at 0248 and 024F are too short for low-grade audio processing. Simply stated, the audio waveform coming in from tape 'rises' too slowly for the fast bit-check loop at 0251 to catch. A 'one' might come through, but it comes through too laggardly for port FF to have flipped into place.

```
                00100 ; ####################################################
                00110 ; VOICE INPUT/OUTPUT ROUTINE USING THE CASSETTE PORT ANO
                00120 ; AMPLIFICATION.  CAN BE USEO WITH CTR TAPE RECOROERS ANO
                00130 ; BUILT-IN MICROPHONES OR PREFERABLY EXTERNAL CRYSTAL
                00140 ; MICS.  SMALL SPEAKER OUTPUT INCREASES INTELLIGIBILITY.
                00150 ; ####################################################
                00160 ;
4300            00170          ORG     4300H            ; LOW POINT IN MEMORY
                001B0 ;        ORG     6500H            ; USE WITH OISK BASIC
D6CC            D0190 MONITR   EQU     06CCH            ; BASIC EXIT (OR OTHER)
4300 F3         00200 START    OI                       ; NO BOTHERSOME STUFF
4301 C0C901     0021D          CALL    01C9H            ; CLEAR THE SCREEN
4304 3A3040     00220          LD      A,(4030H)        ; START BY RESETTING PORT
4307 03FF       00230          OUT     (OFFH),A         ; TO CLEAR INCOMING BITS
                00240 ;
                00250 ; ####################################################
                00260 ; KEYBOARO ROUTINE FOR ENTER (INPUT), CLEAR (OUTPUT), OR
                00270 ; UP-ARROW (BASIC).  UP-ARROW GOES TO EXIT IF NOT BASIC.
                00280 ; ####################################################
                00290 ;
4309 3A403B     00300 KEYTST   LD      A,(3B40H)        ; GET ENTER/CLEAR ROW
430C FE01       00310          CP      1                ; CHECK IF ENTER PRESSEO
430E 2B0B       00320          JR      Z,INPUT          ; GO TO INPUT ROUTINE
4310 FE02       00330          CP      2                ; CHECK IF CLEAR PRESSEO
4312 2850       00340          JR      Z,OUTPUT         ; GO TO OUTPUT ROUTINE
4314 FE0B       00350          CP      B                ; CHECK FOR UP-ARROW
4316 CACC06     00360          JP      Z,MONITR         ; OUT TO BASIC OR MONITOR
4319 1BEE       00370          JR      KEYTST           ; BACK FOR A VALIO KEY
                003B0 ;
                00390 ; ####################################################
                00400 ; INPUT FROM PORT FF (255 OECIMAL) ANO STORAGE IN MEMORY
                00410 ; ####################################################
                00420 ;
431B 21A343     00430 INPUT    LO      HL,MSG01         ; GET THE "INPUT" MESSAGE
431E C0A728     00440          CALL    2BA7H            ; ANO OISPLAY ON SCREEN
4321 3A3D40     0D450          LD      A,(403DH)        ; GET VALUE FDR PDRT MASK
4324 4F         00460          LD      C,A              ; SAVE MASK IN C REGISTER
4325 210044     00470          LD      HL,4400H         ; BEGIN VOICE STORAGE
                004B0 ;        LO      HL,6700H         ; BEGIN STORAGE (OISK)
4328 160B       00490 LOOP1A   LD      0,B              ; NUMBER OF BITS IN BYTE
432A 0BFF       00500 LOOP2    IN      A,(OFFH)         ; GET VALUE AT THE PORT
432C CB17       00510          RL      A                ; STASH IT IN CARRY BIT
432E CB13       00520          RL      E                ; BUMP IT INTO E REGISTER
4330 79         00530          LD      A,C              ; GET VALUE OF PORT MASK
4331 3A4D3B     00540          LD      A,(3B40H)        ; CHECK ENTER/CLEAR ROW
4334 FEB0       00550          CP      B0H              ; CHECK IF SPACE PRESSEO
4336 C25343     00560          JP      NZ,ESCAPE        ; OUT IF KEYBDARO CLEAR
                00570 ;
                005B0 ; #### NOTE:  OELAY VALUE USEO IN THE B REGISTER IS ####
                00590 ; #### CHOSEN FOR OPTIMUM INTELLIGIBILITY.WITH THE  ####
                00600 ; #### CTR TAPE RECOROER ANO HAROWARE MOOIFICATION. ####
                00610 ; #### A LONGER VALUE CAN BE USEO IF HIGH-FIOELITY  ####
                00620 ; #### INPUT IS PROVIOEO.  FOR EACH INCREASE IN THE ####
                00630 ; #### B-REGISTER OELAY VALUE, ALSO INCREASE THE B- ####
                00640 ; #### REGISTER BY THE SAME AMOUNT FOR PLAYBACK.    ####
                00650 ; #### LIKEWISE, A OECREASE IN THE OELAY VALUE MAY  ####
                00660 ; #### INCREASE FIOELITY AT A SACRIFICE OF MEMORY.  ####
                00670 ;
4339 0604       006B0          LD      B,4              ; GET SHORT OELAY VALUE
433B 10FE       00690 OELAY1   OJNZ    OELAY1           ; ANO OELAY A WHILE
4330 03FF       00700          OUT     (OFFH),A         ; MUST RESET PORT INPUT
433F 15         00710          OEC     0                ; OECREMENT TOTAL BITS
434D C22A43     00720          JP      NZ,LOOP2         ; CONTINUE IF MORE TO DO
4343 73         00730          LO      (HL),E           ; SAVE FULL BYTE IN MEM.
4344 23         00740          INC     HL               ; GO ON TC NEXT BYTE
4345 7C         00750          LO      A,H              ; GET VALUE OF M.S. BYTE
4346 FE00       00760          CP      00H              ; USE FOR 4BK MACHINE
                00770 ;        CP      0C0H             ; USE FOR 32K MACHINE
                007B0 ;        CP      0B0H             ; USE FOR 16K MACHINE
4348 C22B43     00790          JP      NZ,LOOP1A        ; IF NOT OONE THEN MORE
434B 21C743     00B00          LD      HL,MSG02         ; GET "INPUT COMPLETE"
434E C0A728     00B10          CALL    2BA7H            ; ANO OISPLAY THE MESSAGE
4351 1BB6       00B20          JR      KEYTST           ; OONE - BACK TO KEY TEST
                00B30 ;
                00B40 ; ####################################################
                00B50 ; PAUSE CHECK OURING ENTRY; SPACEBAR = GO, OTHERWISE STOP
                00B60 ; ####################################################
                00B70 ;
4353 E5         00BB0 ESCAPE   PUSH    HL               ; SAVE CURRENT POINTER
4354 CDAF0F     00B90          CALL    0FAFH            ; OISPLAY CURRENT MEM.
4357 213944     00900          LO      HL,MSG05         ; GET "WORO START" MESS.
435A C0A728     00910          CALL    2BA7H            ; ANO OISPLAY THE MESSAGE
4350 E1         00920          POP     HL               ; RESTORE MEMORY PTR.
435E 3A403B     00930 RECHEK   LO      A,(3B40H)        ; ENTER/CLEAR KEYBRO ROW
4361 FEB0       00940          CP      B0H              ; CHECK IF SPACE AGAIN
4363 28C3       00950          JR      Z,LOOP1A         ; BACK TO MAIN LOOP
4365 FE04       00960          CP      4                ; CHECK IF BREAK KEY
4367 20F5       00970          JR      NZ,RECHEK        ; KEEP LOOKING ENT OR BRK
4369 21C743     009B0          LD      HL,MSG02         ; GET "INPUT COMPLETE"
436C C0A72B     0D990          CALL    2BA7H            ; AND DISPLAY THE MESSAGE
436F 1B98       01000          JR      KEYTST           ; ANO BACK TO KEY MENU
                01010 ;
```

Listing Continued . . .

Special Loaders

This was initially one of the mysteries of TRS-80 operations. *Microchess* was produced with a loader, then others quickly followed, mysteriously taking control of the machine and locking it up completely.

Let's now take a look at some of these special loaders, which will be designated Loaders A, B, C, and D in order to help them continue to do the job they were supposed to – protect software.

Loader A sets up a stack at **5000**, clears the accumulator, and calls ROM to turn on the tape recorder and find the sync byte. It places a star on the bottom of the screen, sets up the HL register to receive the program, and prepares register C to perform simple checksum. A byte is read, it is saved in memory, and the checksum is created as in the SYSTEM mode. Then:

```
4D25    7C              LD      A,H
4026    1F              RRA
4027    23              INC     HL
4028    3E 2A           LO      A,2A
402A    DA 2F 40        JP      C,402F
4020    3E 20           LD      A,20
402F    32 F0 3F        LO      (3FF0),A
4032    3E 4C           LO      A,4C
4034    BC              CP      H
4035    C2 1F 40        JP      NZ,401F
403B    3E FF           LD      A,FF
4D3A    B0              CP      L
403B    C2 1F 40        JP      NZ,401F
4D3E    B9              CP      C
403F    C2 00 00        JP      NZ,0000
4042    C0 FB 01        CALL    01FB
4045    C3 B0 47        JP      47B0
```

The strange appearance of RRA has nothing to do with rotating incoming bits. Rather, since the accumulator contains the H register value, each page (256 bytes) of information will change the high page value by one. Consequently, the high page will alternate between odd and even values, and the least significant bit, rotated into the carry flag, will trigger the display-star or display-space routines at **4D2F**.

Finally, this somewhat awkward loader does a pair of compares to see if it has yet reached **4CFF**, the end of the program load. If not, it loops back and continues; if so, it examines the checksum in C. Amazingly enough, it goes back to MEMORY SIZE? if there is a checksum error! There's no tampering with this program. A successful load is followed by a jump to the program's beginning at **4780**.

Loader B is virtually identical to Loader A, except that the beginning of the program is found at **41FD** instead of **4780**.

Loader C is of a more interesting variety. It is written entirely without calls to ROM, because it

Continued Listing

```
                01020 ; ###########################################################
                01030 ; OUTPUT FROM MEMORY OF RECOROEO VOICE TO CASSETTE PORT
                01040 ; ###########################################################
                01050 ;
4371 21E743     01060 OUTPUT  LO      HL,MSG03            ; GET "BEGIN OUTPUT"
4374 C0A728     01070         CALL    28A7H               ; ANO OISPLAY THE MESSAGE
4377 3A3040     01080         LD      A,(4030H)           ; PORT FF OUTPUT MASK
437A 4F         01090         LD      C,A                 ; SAVE OUTPUT MASK IN C
437B 210044     01100         LD      HL,4400H            ; START VOICE STORAGE (*)
437E 1608       01110 LOOP3A  LO      0,8                 ; NUMBER OF BITS IN BYTE
4380 7E         01120         LD      A,(HL)              ; GET VALUE FROM MEMORY
4381 5F         01130         LD      E,A                 ; SAVE IT IN E REGISTER
4382 AF         01140         XOR     A                   ; CLEAR ACCUMULATOR TO 0
4383 C813       01150 LOOP4   RL      E                   ; SENO BIT TO CARRY FLAG
4385 C817       01160         RL      A                   ; ANO ROTATE 'ROUNO TO A
4387 B1         01170         OR      C                   ; USE THE PORT FF MASK
4388 03FF       01180         OUT     (OFFH),A            : ANO SENO OUT THE VALUE
                01190 ;
                01200 ; #### NOTE:  PLAYBACK VALUE BELOW MUST BE CHANGEO  ####
                01210 ; #### TO MATCH SAMPLING OELAY IN THE INPUT SECTION ####
                01220 ; #### OF THIS I/O PROGRAM.  THIS VALUE IS ROUGHLY  ####
                01230 ; #### TWO TIMES THAT IN THE 8-REGISTER OURING THE  ####
                01240 ; #### INPUT SAMPLING.  VARIOUS OUMMY OPCOOES MAY   ####
                01250 ; #### BE INSERTEO WHERE NECESSARY TO KEEP VOICE    ####
                01260 ; #### AT THE PROPER PITCH ANO QUALITY.  USING THIS ####
                01270 ; #### PROGRAM, THERE IS A QUARTER-TONE OIFFERENCE. ####
                01280 ;
438A 0606       01290         LO      8,6                 ; GET SHORT OELAY VALUE
438C 10FE       01300 OELAY   OJNZ    OELAY               ; ANO OELAY SHORT WHILE
438E AF         01310         XOR     A                   ; CLEAR ACCUM. BACK TO 0
438F 15         01320         OEC     0                   ; BITS = 8ITS MINUS ONE
4390 C28343     01330         JP      NZ,LOOP4            ; ANO 8ACK FOR SOME MORE
4393 23         01340         INC     HL                  : GET NEXT 8YTE FROM MEM.
4394 7C         01350         LO      A,H                 ; GET VALUE OF M.S. 8YTE
4395 FE00       01360         CP      00H                 ; FOR 48K MACHINE
                01370 ;       CP      0C0H                ; FOR 32K MACHINE
                01380 ;       CP      080H                ; FOR 16K MACHINE
4397 C27E43     01390         JP      NZ,LOOP3A           ; ANO GO BACK FOR MORE
439A 210E44     01400         LO      HL,MSG04            ; GET "OUTPUT COMPLETE"
4390 C0A728     01410         CALL    28A7H               ; ANO OISPLAY THE MESSAGE
43A0 C30943     01420         JP      KEYTST              ; ANO BACK WHEN OONE
                01430 ;
43A3 48         01440 MSG01   OEFM    'HOLO SPACE BAR ANO BEGIN SPEAKING.'
43C5 00         01450         OEF8    00H
43C6 00         01460         OEF8    00H
43C7 49         01470 MSG02   OEFM    'INPUT COMPLETE OR MEMORY FULL.'
43E5 00         01480         OEFB    00H
43E6 00         01490         OEFB    00H
43E7 42         01500 MSG03   OEFM    '8EGINNING PLAYBACK; 8REAK IS IGNOREO.'
440C 00         01510         OEF8    00H
4400 00         01520         OEF8    00H
440E 50         01530 MSG04   OEFM    'PLAYBACK COMPLETE; PRESS CLEAR TO REPEAT.'
4437 00         01540         OEF8    00H
4438 00         01550         OEF8    00H
4439 20         01560 MSG05   OEFM    ' = WORO SEPARATION POINT.'
4452 00         01570         OEFB    00H
4453 00         01580         OEFB    00H
                01590 ;
                01600 ; ###########################################################
4300            01610         ENO     START
00000 TOTAL ERRORS
29121  TEXT AREA BYTES LEFT


OELAY  438C 01300  01300
OELAY1 433B 00690  00690
ESCAPE 4353 00880  00560
INPUT  4318 00430  00320
KEYTST 4309 00300  00370 00820 01000 01420
LOOP1A 432B 00490  00790 00950
LOOP2  432A 00500  00720
LOOP3A 437E 01110  01390
LOOP4  4383 01150  01330
MONITR 06CC 00190  00360
MSG01  43A3 01440  00430
MSG02  43C7 01470  00800 00980
MSG03  43E7 01500  01060
MSG04  440E 01530  01400
MSG05  4439 01560  00900
OUTPUT 4371 01060  00340
RECHEK 435E 00930  00970
START  4300 00200  01610
```

is capable of loading into a Level I or Level II TRS-80. Less fortunately, the ROM timing errors are not corrected, so the chances of loading this program on a marginal machine are not at all improved. The stack is prepared, and a block of memory is cleared from **5800** to the end of potential RAM at **FFFF**. My only guess as to the reason for this is that the authors wish to wipe out any programs such as monitors or disassemblers, as the clearing byte (**A5**) does not strike me as otherwise meaningful.

The tape is then turned on, and a pattern of three asymmetrical and two symmetrical sync bytes is found (**B1, 83, 79, 5A, 00**). Again, the choice strikes me as arbitrary, and may be the authors' way of identifying their own code. If these bytes are found, the program continues; if not, the entire five-byte pattern is sought again.

As in the other loaders, register C is set to zero for use as a checksum byte. The program load point is set high in memory (**747F**), and a byte is read. Here is a part of the code:

```
4330     C0 BF 43        CALL    43BF
4340     77              LO      (HL),A
4341     32 3F 3C        LO      (3C3F),A
4344     81              AOO     A,C
4345     4F              LO      C,A
4346     2B              OEC     HL
4347     70              LD      A,L
4348     3C              INC     A
4349     C2 53 43        JP      NZ,4353
434C     C0 8F 43        CALL    43BF
434F     B9              CP      C
4350     C2 66 43        JP      NZ,4366
```

The secret to this portion of code rests in address **4346**. Unlike most other loaders, this one loads (and displays) the last byte of code first, moving backwards through memory. (**438F** is the location of the byte-read subroutine). When the page is crossed (**4346-4348**), the checksum is evaluated; if the checksum is incorrect the program jumps to **4366**, where an error message is displayed and the machine locks up.

The user's display is worth noting:

```
4353     7C              LO      A,H
4354     32 3E 3C        LO      (3C3E),A
```

This loader actually displays the ASCII equivalent of the page of memory being loaded with data . . . and it looks like an alphanumeric countdown as the program is fit into place.

Finally, Loader C does a comparison for the end of the first major load block, changes the value of H, and loads the next block. It then overwrites critical portions of the load routine, effectively obscuring the loading and entry point of the program. Interrupts are disabled, and the

process moves out of the loader into the main program. Interestingly, the authors forgot to turn the tape recorder off.

Finally, Loader D is of an entirely different sort. First, some code:

```
BEFE    3E 04          LD      A,4
BF00    03 FF          OUT     (FF),A
BF02    0B FF          IN       A,(FF)
BF04    17             RLA
BF05    30 FB          JR      NC,BF02
BF07    06 XX          LO      B,XX
BF09    10 FE          OJNZ    BF09
BF0B    06 09          LO      B,9
BF00    3E 04          LO      A,4
BF0F    03 FF          OUT     (FF),A
BF11    0B FF          IN       A,(FF)
BF13    17             RLA
BF14    00             NOP
BF15    3B 0C          JR      C,BF23
BF17    23             INC     HL
BF18    2B             OEC     HL
BF19    10 F6          DJNZ    BF11
```

This remarkable loader is written for high-speed operation, setting up the output ports BEFE and BF0D), clocking itself with start bits (BF0D), and then reading a nine-bit serial stream. Careful timing and self-clocking are essential in high-speed data I/O, and this routine is capable of reading and writing on ordinary audio cassettes, with excellent reliability, at better than 2000 baud. The only point to the instructions at **BF17** and **BF18**, for example, is the delay introduced by executing them; yet that timing is very important. The actual timing value at **BF07** has been dropped for a measure of protection of this author's fine software.

Conclusions

In sum, the tape read/write routines of the TRS-80 are efficient and, especially now with special loaders and a corrected ROM, quite reliable. Different levels of user prompts, particularly those used by the reverse-loading module described above, are probably more satisfactory than flashing stars. A checksum process for BASIC similar to the SYSTEM module would have been valuable. Finally, by careful attention to clocking details, a reliable, higher speed loader could have been included in the TRS-80.

For those especially interested in high-speed loaders, I recommend examining the *Exatron Stringy-Floppy* operating system, which shows what can be done with equipment designed for digital operation. It is capable of reliable loading and saving at rates exceeding 11,000 baud.



Fig. 2. Full schematic for the Model I cassette modification for speech input. It should be switched out when cassette programs are being loaded (see Fig. 4).



Fig. 3a.



Fig. 3b.

NOTES

4

Simple Modifications

Why hardware modifications? Simply because they help a limited computer broaden its ability to serve our needs. Looking at glowing blue-white letters on a dark screen is comfortable for only a limited time . . . waiting through many minutes for the computer to make a game play is frustrating . . . attempting to imagine which characters are upper case and which are lower case is nearly impossible . . . emphasizing individual words and characters is only possible with arrows and stars . . . and so forth.

In this chapter, eleven simple modifications to the standard TRS-80 will be presented:

- Installing 16K memory to the keyboard unit, and to the expansion interface.
- A change to enable recovering Resets when there is an expansion interface attached.
- Moving the Reset button to a more accessible position.
- Adding both an extra keyboard and an extra video output for extending the computer's portability.
- Adding an RF modulator to further increase the TRS-80's portability.
- Installing a modification to increase the computer's computational speed.
- Installing a modification to reverse the video display for black letters on a white background, more in keeping with real text.
- Adding the feature of dual-language operation: Level I and Level II in the same computer.
- Accessing the lower case capabilities built into the TRS-80 by adding a single circuit.
- Reversing individual characters on the screen for emphasis.
- Adding a hexadecimal keypad for faster entry of machine code information.

Almost all of these modifications will require you to open the cabinet of your TRS-80. Should you do it? Or should you not? First of all, consider that your computer has but a three month warranty; after that, you will have to pay repair charges should something go wrong. Radio Shack has, in response to public protests, changed its former policy and will now repair machines with the most popular modifications installed, at no extra charge. They will not remove those modifications if you say so, but may refuse repair if (a) you have mangled the board, or (b) if you cannot document your modifications.

Yes, there is a chance that you can damage your TRS-80 when you make modifications. This will not be the fault of the modifications themselves, though. My own TRS-80 has been modified many times, and the only damage has been to the notoriously flakey cable that connects the keyboard to the main circuit card, and the failure of one RAM chip. The latter would have happened anyway.

How many TRS-80's have been damaged during modification? That's a hard question to answer, but I will describe briefly the failed 80's I have seen:

1. A damaged integrated circuit in the data section was caused when heavy wire was used to make the modification.
Lesson — use the parts specified.
2. Two RAM chips were blown when the user dropped a soldering iron into the unit when he was modifying it.
Lesson — always turn the power off when making the physical changes.
3. A blown power supply regulator. The user had left the unit under an open window.
Lesson — close the windows in case of rain!
4. High levels of garbage causing keyboard lockout and blown programs. The computers were being used next to heavy electrical equipment.
Lesson — treat the computer as if it were a very sensitive piece of electronic equipment. It is.
5. Constant keyboard lockout or odd characters. The TRS-80 cable had been flexed too many times, causing breaks. These breaks had destabilized the keyboard circuits, causing two ICs to blow.
Lesson — handle the keyboard cable, that most delicate of hardware, with utmost care.
6. Constant lost memory and programs. The RAM chips were not being 'refreshed' because the refresh multiplex line was not working. The user had plugged in a peripheral device upside down, with the power on to both.
Lesson — make all interconnections with the power off.

In sum, all the above damage was caused by carelessness, haste, or attempting to use inappropriate materials to do the job. The solutions? Resolve not to do all the work in one evening. Turn back to the introduction to make sure you have the right tools. Work slowly and take breaks often. Buy parts from reliable suppliers. Read and understand the instructions *and the theory* before you start.

And finally, if you have any serious doubts about the accuracy of the printed information, contact the author. That's me. And if you have any problems that won't go away, write. If you write, you *must* enclose a self-addressed, stamped envelope, a complete description of any problem, and all tests you have made. Also, I cannot cover much beyond the scope of this book, which includes the myriad competing disk operating systems and support software.

Expanding the Memory

The simplest modification, once you have braved opening the cabinet, is expanding the unit's memory from the 4K supplied to a full 16K RAM. At this writing, 16K of reliable RAM memory can be purchased for less than $20.

Keep It Clean!

If you examine the contacts on the keyboard unit's edge-card connector, as well as on the five connectors (expansion in, expansion out, printer, RS-232, disk) of the Expansion Interface, you will see a major cause of the TRS-80's instability: solder-plated connectors. In the interest of economy, Radio Shack did not use gold to ensure a good cable contact. This turned out to be a serious error in judgment.

There are two options in dealing with these solder-plated connectors. The first is to keep them clean. Remove the cables regularly and vigorously rub the contact surfaces with a dollar bill or talc buffing wheel. Bring the solder to a bright shine, and spray it with contact cleaner. Reinstall the cables and memory crashes should lessen.

The other option is expensive and time-consuming, but much more reliable. The contacts can be freed of solder plating with solder wick, cleaned with flux remover, brushed to a high shine, and a soft silver compound can be flowed onto the edge contacts. Fuller Software (see Appendix I) sells a contact plating kit; price varies with the price of silver, but at this writing it is more than $20. The process is very tedious because silver melts at a much higher temperature than lead, but the results are noise-free connections and greater reliability.





There are several types of so-called '16K memories', so when you set out to upgrade your TRS-80 memory, make sure you order the correct type. 16K is actually a shorthand term for 16,384 bytes of memory. In the TRS-80, the 16K memories are integrated circuits containing 16,384 single-bit memory cells each. To create an entire byte, then, eight integrated circuits are needed. Furthermore, the TRS-80 memory needs very little power, and must take only a small amount of space in its cabinet. The only small, low-power memories made are 'dynamic' memories. The 16K-by-one-bit, dynamic memory is industry type 4116, also called type 416.

There is one other consideration in purchasing memory expansion chips, and that is a popularly misunderstood quality called *access time*. Access time can be thought of as the time it takes the computer to inform the memory chip that it needs information (or will give it information) until the memory chip is electronically ready to respond. This figure is usually given in *nanoseconds* (see Table 4-1).

Second	1
Millisecond (mS)	0.001
Microsecond (uS)	0.000001
Nanosecond (nS)	0.000000001

Table 4-1. Relative time units.

This time is very small but quite critical to the operation of the computer. If the memory is not ready, programs and data will be recorded or reported incorrectly, and the computer will have no chance of working properly. The minimum access time for memory in an unmodified TRS-80 is 450nS; with the speed-up modifications presented in this book, that figure drops to 300 nS or less.

Most of the current crop of memory chips easily meet the 450 nS requirement, and many of those sold as 450 nS chips can be run reliably at 300 nS. A problem arises with the expansion interface, as older units had a bit of trouble with 'hotter' (faster) memory. So as a general rule, refer to Table 4-2 when looking for memory to upgrade your TRS-80 or its expansion interface.

Equipment	Access Time
TRS-80 keyboard unit, unmodified	450 nS max, 350 nS optimum
TRS-80 keyboard unit with speed-up	300 nS max, 250 nS optimum
Expansion Interface made before 1/80	300 nS min, 450 nS max
Expansion Interface made after 1/80	450 nS max, 350 nS optimum
Expansion Interface made before 1/80 with speed-up	300 nS min optimum
Expansion Interface made after 1/80 with speed-up	300 nS max, 250 nS optimum

Table 4-2. Memory access time for various TRS-80s.

Opening and Closing the Case.

1. Locate a spacious workplace, and set a soft towel on it. You will need a Phillips screwdriver and a small box in which to set the screws and spacers.
2. Remove the power and disconnect all cables to the keyboard unit. Set it face down on the towel.



Photo 4-1. Photos showing opening computer.

Unit is placed face down and screws are removed. On newer units one screw is beneath a warranty notice.

3. There are six screws of three different sizes which hold the case together. In later TRS-80's, one of these is covered by a label warning you not to go inside. This label just won't peel off for later use. You'll have to punch through it to remove the last screw.
4. Hold the case together and place it face up on the towel. Gently lift off the top cover. Some TRS-80's have a 'flying lead' LED (light-emitting diode) power indicator, meaning you will have to pull it gently out of the hole in the top cover. Other power indicators are fastened to the keyboard, and the cover lifts off directly.



Computer is placed face up and the top removed by lifting back and up.

5. This step is the most delicate. Lift the keyboard slightly upward, and then swing it toward you. A cable attaches from the keyboard to the main circuit card at the bottom left side. This cable is made up of flat copper bands which have a tendency to break when flexed.



Keyboard is rocked gently forward to show white plastic spacers, which are then removed.

6. While holding the keyboard up at about a 90-degree angle, look at the main circuit card. There are five soft plastic white spacers which cushion the keyboard. On later models, a sixth, central spacer is hard plastic. Note their positions, remove them, and set them in the parts box.

7. Swing the keyboard downward gently, and lift the entire computer out of the base of the cabinet. Set the computer down and put the base aside.



With the keyboard supported upright against a firm backing, the CPU board is lifted from the case bottom.

8. Most modifications will be done to the integrated circuit side of the circuit board, so turn the entire unit face down again. Unless the modification calls for work on the solder side of the board, do not flex the keyboard cable again.

9. If the modification calls for work on the bottom of the board, get a heavy box or other support. Set the keyboard face up, and swing the keyboard out and up a bit wider than 90 degrees, leaning it against the support. Never open the unit fully like a book, as this badly deforms the interconnect cable.



The complete unit is ready for work with the keyboard supported at a 90-degree angle.

10. To close the case, fold the unit back together, and set it into the base. The unit may have to be jostled gently to get it to fit over the plastic support posts. Make sure any added wires do not get caught and cut by the support posts.

11. Lift the keyboard slightly and restore the white spacers to their former positions. Fit the keyboard back into place.

12. If any long wires or cables have been added, make sure they all clear the cabinet edges. Restore the LED to its place on the keyboard top if it is a flying-lead type, or straighten the LED on the circuit card so it fits into the cover hole.

13. Fit the cover into place lightly, making sure there are no newly installed parts being crushed or bent in the process. Be sure no leads creep out the joints on either side.

14. Holding the unit together firmly, flip it on its face. While holding it with one hand, drop the screws into the holes, longest one towards

the top. Fasten one screw on either side; this will hold the computer together while you tighten the remainder.

15. Remember that the case is soft plastic, so just tighten enough to pull the two sides together. Otherwise, the plastic may be stripped and the screws will fall out. If that happens, drop in some clear acrylic cement (not white glue), and insert the screw. Remove it just before the glue hardens, and replace it about an hour later.

16. Flip the computer on its back, restore cables, and turn on the power. If the slightest problem seems apparent, open up and try again!



Photo 4-2. Memory chip area in TRS-80.

Power Supply and Memory: 2N5594 transistor handles 5-volt supply; adjustments are seen at top of photo. 16K RAM chips are plugged into sockets Z13 to Z20, unusually close to the power transistor's heat sink. Replacement memory chip in socket Z13 attests to the degrading capacities of excess heat.

Tips on Handling Integrated Circuits

In the early days of microcomputers, there was a lot of user hesitation about installing memory chips because of warnings about static electricity damaging the memory devices. At that time the fear was reasonable; but today (with just a little caution) there need be no problem.



Figure 4-1. Grounding a soldering iron.

1. Never place any integrated circuit on highly charged plastic material, especially styrofoam.

2. Handle memory chips, CPUs (such as the Z-80), LSI devices (large-scale integrated circuits, usually those with 28 or 40 pins), or any marked MOS, CMOS, or NMOS (metal-oxide semiconductors), with care. Hold them by their ends, never by the connection pins.

3. Purchase a static-free workbench, which is a conductive cloth sheet with a wrist strap and safe grounding cable. These can be obtained from Wescorp for about $18.

4. Ground your soldering iron to an earth ground *but only through a series-connected one-megohm resistor — never directly!* The grounding is not absolutely essential, but helps if you live in a very dry, static-producing environment.

5. Work with any integrated circuits with the power off. Make sure the integrated circuit's ground and power pins are all connected (soldered or in sockets) before turning on the juice! A difference of a mere half a volt between certain pins can kill an IC.

6. Use high-quality sockets for integrated circuits wherever you can. This will not only keep excessive heat away from them, but will also save the day if one is damaged. Unsoldering a 40-pin integrated circuit is not pleasant.

7. Above all, work slowly and carefully. By far the greatest villain is haste. Oh yes — do keep furry animals out of the area!



Level I ROMs: Rockwell single-chip ROM and Motorola 2-chip set are pushed into aluminum-foil-covered vegetable tray.

Before installing your new memory chips, take a styrofoam meat or vegetable tray, trim off the curved ends, and cover the center with aluminum foil. This will be your static-free storage for the 4K memory chips you will be removing. To install the 16K memory in your keyboard unit, turn off the power, open the case and find the 4K memory chips.

Slide a thin-bladed screwdriver under the end of one of these chips, and rock it slighly upwards. Slide the blade under the other side, and rock. Move back and forth gently until the chip is free, but don't spring it out of the socket. Lift it by the ends and press it into the foil-covered tray. As you are doing this, notice that each of the chips has a notch or dot at one end. Keep this position in mind; the 16K chips will be installed in the same direction.



Figure 4-2. 16K RAM expansion shunt versions.

Once all the 4K chips have been removed, lift the 16K chips one at a time and press them in the empty sockets. If the pins are spread too wide, set the chip sideways on the foil-covered tray and press gently. Try again to insert the chips. Be sure none of the pins are bent underneath, or slide outside the socket.

Now turn your attention to a pair of on-board sockets marked Z3 and Z72. 16K chips will need more attention from the address lines, so these decoding shunts will have to be changed. If you didn't receive these shunts with your order of 16K chips, have no fear — just slide wires into the sockets. Or, obtain an 8-position DIP switch and push it into the socket. Turn the switches *on* where the shunt is to be connected, *off* where the bars are broken. Figure 4-1 shows the old and new positions of the shorting bars or wires of these shunts.

When you have placed the new, corrected shunts, switches or wires into sockets Z3 or Z72, and all the 16K chips are installed, the keyboard upgrade is complete. Reinstall the computer in its case, turn on the power, and press (ENTER) in response to MEMORY SIZE? Then PRINT MEM, and you should see a value of 15572 (15570 on newer machines). If you don't get that value, turn the machine off and troubleshoot:

1. MEMORY SIZE? reads much less than 15570. Turn off the computer and try again.

If you have no expansion box, type SYSTEM (ENTER) /0 (ENTER), and keep trying. If the value never changes, you may have either a bad memory chip or incorrect shunt wiring. Go back to MEMORY SIZE?, only this time enter 15560. If you get the READY message, this might point to a failed memory chip or an incorrect DIP shunt (especially if PRINT MEM? reads the same as that for 4K). To test memory, run the RAM test printed in Chapter 3. If instead you get the flash of an ?OM ERROR and a return to MEMORY SIZE?, then suspect that you've wired the shunt or shorting wires incorrectly.

2. You get a partial RADIO SHACK LEVEL II BASIC (or R/S LEVEL 2 BASIC) message, with or without READY, and with or without incorrect characters, but it only lasts for a short time before crashing back to MEMORY SIZE?

Suspect that a memory chip is very balky, is inserted only partly or with pins bent, or that you've lifted the Level II interconnect cable (if your unit has one). You may also have damaged some other circuitry, but this is very unlikely.

3. The screen never gets past a pile of garbage.

You may have lifted the Level II interconnect cable (if your unit has one), one or more memory chips may be completely dead, inserted backwards or only partly, or you may have forgotten to reinstall (or have reversed) either of the two shunts at Z3 and Z72.

4. Unexpected characters are displayed after MEMORY SIZE?, sometimes acting as if they were 'entering' themselves.

You have broken one or more wires of the keyboard interconnect cable. You can look for cracks, or just replace the whole cable.

5. The machine responds correctly, but only for a short while; it often crashes; occasionally PRINT MEM will give a smaller number than 15570, but not always.

This is probably balky memory or memory that is the wrong speed (usually older, slower memories that some discount houses may sell). For starters try reinserting the memory in case of a bad contact; run the RAM test; or just buy new memory.

6. The computer displays a screen full of 999, etc.

You have lifted the Level II interconnect cable out of its socket. Replace it very carefully.

Adding to the Expansion Interface is a much easier task. Your keyboard unit must have 16K in it already in order that the memory map be complete from **4000** (decimal 16384) to the start of expansion box memory at **8000** (decimal 32768). And, sadly, you cannot use your 4K chips in the expansion box without a hardware modification.







First, remove the cover over the power supplies and remove them; this will prevent them from tumbling all about when you open the bottom cover. Now flip the expansion box over and remove and set aside the six screws that fasten the cover. Also disconnect the power cable inside the expansion interface case.

Inside, you will find two rows of empty sockets for memory expansion. The first 16K of expansion memory goes in the sockets marked Z9 to Z16, and the second 16K into sockets Z1 to Z8. The memory must be inserted in this order, unless you want a permanently protected, 16K, high-memory block (which might be useful). Use the same procedure for installing these memory chips as for the keyboard unit, facing them in the direction of the notch on the sockets. Once again, check carefully for bent pins or pins out of the sockets, reinstall the cover, and power up the interface and keyboard.

Press ENTER in response to MEMORY SIZE?, and your 32K machine should read 31956, and the 48K machine will read 48340 (two bytes less each in later models). Early expansion boxes, because of design flaws in memory timing, are significantly more sensitive to memory speed. If expansion memory is occasionally balky or shows frequent glitches when peripheral devices are attached, make the hardware changes to Z69 recomended in the 200% speed modification (later in this Chapter). Seeming memory failures can most often be attributed to these timing problems, although earlier interfaces (particularly those with the bulbous buffered cable) had hardware difficulties which made them extremely sensitive to noise and vibration.

Most of these earlier units had their circuit board layout and plating done in such a way that a sharp tap on the box, board, or cable would cause a 'microphonic' reaction. That is, the vibration would be transmitted along power supply and signal lines, interfering with the actual data. The result would be frequent memory crashes. Likewise, a noisy environment (nearby washers, mixers, fluorescent lights, transformers, and even printers) can cause electronic interference which would disrupt memory.

Rescuing the RESET

Among the conveniences of the TRS-80 keyboard computer is the Reset button. A program, especially one with machine language components, may cause the computer to 'hang'. The Reset button conveniently recovers control of the machine and returns it to you.

Once the Expansion Interface is connected, though, things begin to change. The Reset button becomes a Reboot button, causing any operating programs in memory to be lost and the complete system to restart from initialization of the disk operating system (see Supplement to Chapter 1, on the power-up sequence).

As an aside, let me note that the Z-80 HALT instruction does not have the effect of a true HALT. Instead, the CPU's Halt Acknowledge output line is tied in with the Reset button. The result is a READY in Level II and a disastrous reboot with an expansion box connected. This is another good reason for reasserting the Level II reset function with this modification.

The solution to this problem is to disable the disk controller whenever disk access is not expected. Open the expansion box, and locate Z32, near the power switch. If you have a newer expansion interface, this circuit will be marked Z39. This is a 16-pin circuit, type 74LS155. Identify the circuit trace that runs from pin 4 underneath the IC and out the opposite side. Use an ohmmeter if necessary to make sure you have the right trace. This signal activates the disk controller chip's output to the CPU; when it is cut, the keyboard unit cannot 'see' the disk controller.

Take a sharp blade and cut this trace. Solder a 10K ohm resistor from the *far side* of this trace to pin 16 of Z32 (or Z39). This is the +5 volt lead, and will hold the pin high.

Next run a pair of fine wires from either side of the cut trace to each connection of a small toggle switch. When the switch is on, the cut trace is bridged, and the disk controller buffer can be activated normally; when the switch is off, the Reset button sends the software to a routine that checks for a disk controller. Since it does not 'see' the controller, it acts as if it were simply in Level II BASIC and returns to READY.

Be sure to mount the switch as close as possible to the trace cut, preferably right on the front of the expansion box, as shown in Photo 4-1. This will prevent noise from creeping in to an already somewhat noisy box.



Photo 4-3. Expansion box reset modification.

Visible in this photo are a 12-inch replacement expansion cable, and the disk-defeat switch to recover the reset function.

The LNW expansion interface change would normally be identical to that for the Radio Shack box, except for the integrated circuit numbers. One additional change is necessary.

The trace from U19 pin 4 leading to U8 and U15 is cut, and a 10K resistor wired from the trace end closest to U8 and U15 to +5 volts (found at U19) pin 16).

However, the pullup/pulldown resistors in the LNW expansion box can still give an 'on' reading to the CPU. To avoid this, change the pulldown resistors from 220 ohms to 470 ohms (or, if they already are 470 ohms, from 470 ohms to 680 ohms). This will result in the 'high' reading needed to avoid picking up the disk controller signal.

Up-Front RESET

If you are a frequent user of the Reset button in Level II — and once again a user of it with your expansion box — then you will want to get the button out of the area of the sensitive interconnect cable, and well within reach. It will be a welcome relief from clawing at the silver port cover, or totally wiping out your program by jostling the cable.



Figure 4-3. Expansion box reset modification.



Figure 4-4. Up-front reset addition.

A momentary-on pushbutton (such as Radio Shack part number 275-1547) can be added to the cover of the keyboard unit. Photo 4-2 shows the position of the Reset button on the left side of the computer. Run two wires from the pushbutton to a small cable connector (a submini plug), and run two wires from the Reset button (see Figure 4-2) to the other end of the cable connector (a submini jack). The project can be completed in ten minutes, carpentry and all, and reset will be less frustrating.



Photo 4-4. Up-front reset addition.

Reset switch added to the top cover. A connector is added so the cover can be removed easily.



Piggybacking sequence: pins are removed from short solder-tail socket, and it is used as a grommet for a wire-wrap socket. After this is soldered to the baseboard, a third socket is plugged in place.

Note : Don't risk being a victim of the Apple syndrome! Apple's Reset button is placed much too close for comfort to the user's work area, and many a program has disappeared into the electronic stratosphere when inadvertently pressed while typing. So keep that Reset button just out of reach!

Working by the Woodstove

There comes a time when sitting up straight by the computer is no longer fun. Or when the neighborhood kids howl because they can't all reach the keyboard at once during an action game. Or when those kiddie hands are just too sticky for your sacred micro. Or, in my case, when the computer's room is just too cold to share with my typing fingers. That's when you need a keyboard and monitor in the room by the woodstove. Or an extra keyboard for the young'ns. Or a keyboard for the lap in an easy chair and a monitor on the mantle.

The additional keyboard is mostly a matter of carpentry, because there's nothing special about the TRS-80 keyboard. It's merely a matrix of switches, eight by eight. Each position in the matrix is identified by the computer's software and turned into a character.

Start by obtaining two high-quality wire-wrap integrated circuit sockets, and one good solder-tail type. These are 16-pin sockets. You will also need fine wire, a 16-wire jumper cable with plug attached, and a keyboard.

The keyboard can be any style you like, from a complete alphanumeric keyboard ($40 to $120), to a $10 numeric keypad if you work mostly with numbers. Whichever you choose, it must consist of individual keys, each with a single-pole, single-throw (SPST) contact pair. Many small calculators have a prearranged matrix which is incompatible with the TRS-80. If you choose a matrix keyboard, check that it will work with the TRS keyboard pattern shown in Table 4-3.

@	A	B	C	D	E	F	G
H	I	J	K	L	M	N	O
P	Q	R	S	T	U	V	W
X	Y	Z	....Unassigned....				
0	1	2	3	4	5	6	7
8	9	:	;	,	-	.	/
ENT	CLR	BRK	UPR	DNR	LFR	RTR	SPC
SHIFT	........Unassigned........						

Table 4-3. Keyboard matrix.



Since depressed keys are identified in software by the row and column, you only need to know which column-row combinations produce the letter you want. That way, you can reassign your keyboard's characters for any purpose that suits you – including the Dvorak keyboard. Thus, you need make no software modifications to your favorite machine language programs to use them with different keyboard combinations.

Furthermore, the attachment of a 64-key musical keyboard can open the door to direct compiling of music as you play it.

The physical layout of the TRS-80 keyboard unit is fairly compact, leaving only a space on the far left or far right for the added keyboard connection. I have chosen the left side for that addition. Inside the computer, this location is directly above a blank part of the keyboard's circuit card.

Use a strong flat screwdriver to snap out the black portion of the keyboard cover. Six tabs hold it in place at the top and bottom. Mark precisely where the free area can be found on the baseboard.

You will be using the three IC sockets to make a standoff-style keyboard connector. Pull all the pins from the solder-tail socket, and use this socket as a guide to drill 16 holes in the baseboard. Use a very fine hobby drill — #68 is good. When you have the holes completed, slide one of the wire-wrap sockets into the disemboweled solder-tail socket, and feed the wire-wrap pins through the circuit board. Fasten with fast-drying epoxy; do not use white glue, as this will react badly with metal.



The extra keyboard socket is soldered in place, with the gutted solder-tail socket used as a grommet.



Plastic carriers from flat-pack integrated circuits make excellent 'bridges' to hold wires in place. A drop of glue holds them there.

When the glue is set, remove the entire keyboard cover, turn the baseboard over, and identify pin 1 of the newly installed socket. This pin will attach to column one of the keyboard matrix (see Table 4-4). On most versions of the TRS-80, you can use the keyboard's resistors to identify the columns; I recommend this, because there were at least three separate runs of keyboards, each with a different layout.

Column 1	R8	@ H P X 0 8 ENTER SHIFT
Column 2	R5	A I Q Y 1 9 CLEAR
Column 3	R3	B J R Z 2 : BREAK
Column 4	R2	C K S 3 ; UPARROW
Column 5	R7	D L T 4 , DOWNARROW
Column 6	R1	E M U 5 - LEFTARROW
Column 7	R4	F N V 6 . RIGHTARROW
Column 8	R6	G O W 7 / SPACE

Table 4-4. Keyboard column assignments.

Match column one, then, with socket pin 1; column two with socket pin 2; column three with pin 3; etc. Solder a separate wire to each of the resistors, and wire-wrap or solder the other end to their respective socket pins. Make sure you solder to the end of the resistors which are connected to the keyswitches, not the other ends, which are all connected together.

The keyboard matrix rows are found at the input pins of the on-board ICs, but because of the many versions of the TRS-80 keyboard which have been issued, this sequence is inconsistent. The technical manual identifies the rows as shown in Table 4-5, but it's better to check for yourself. Look for the traces that connect



The extra keyboard socket is soldered in place, with the gutted solder-tail socket used as a grommet.



Socket rises perfectly to the height of the outer shell. Note reset button extension at left.



Completed extension cable plugs discreetly into the socket. Any type of keyboard, from a small numeric pad to a full 64-key musical keyboard, can be used.

together @, A, B, C, D, E, F and G. These are all in row one. Solder a wire to some point in this row, and run it to pin 16 of the new keyboard socket.

Row 1	Z1 Pin 8	@ A B C D E F G
Row 2	Z1 Pin 2	H I J K L M N O
Row 3	Z1 Pin 10	P Q R S T U V W
Row 4	Z2 Pin 2	X Y Z
Row 5	Z1 Pin 6	0 1 2 3 4 5 6 7
Row 6	Z1 Pin 4	8 9 : ; , - . /
Row 7	Z1 Pin 12	ENTER CLEAR BREAK UPARROW DOWNARROW LEFTARROW RIGHTARROW SPACE
Row 8	Z2 Pin 4	SHIFT

Table 4-5. Keyboard row assignments.

Locate row two by using Table 4-5, and solder a wire from somewhere in this row to pin 15. Likewise, identify rows three through eight, and solder them to pins 14, 13, 12, 11, 10 and 9, in order. When viewed from the top, the pin arrangement is as shown in Figure 4-4.

Figure 4-4.



Once the wiring is complete, clip the pins on the added socket very short, turn the board over, and put everything back in the case. Power up and check the operation of the computer.

Now clip a small length of bare wire about an inch long, and bend it in the shape of a 'U'. At the newly installed socket, jumper each row across to each column, one at a time. You should produce all the non-shifted keyboard characters on the screen, including the previously inaccessible four arrows and the cursor character.

Clip an additional jumper, and cross row eight with column one. This simulates the pressing of the SHIFT key. Repeat the column-row jumpering, and note that all the shifted characters now appear. Any unusual behavior, such as repeated letters or groups of unrelated letters produced from a single jumpering, indicates a wire may be shorted, attached to the wrong column or row, or left out completely.

Finally, as with all modifications, make the cosmetics pretty. Snap the black plastic cover off again, and in it cut a rectangular hole the size

of the 16-pin socket, using a hot, sharp X-acto knife or razor blade. Work slowly, filing or smoothing, and rub the finished hole with a marble. This will result in a professional-looking addition.

The second wire-wrap socket now piggybacks into the first one, and the black cover snaps back on. The socket should fit perfectly, rising about 1/16 inch above the surface of the cover. The 16-wire cable plugs into it a comfortable distance from the typing area, well above and to the left of the up-arrow key.

For each keyboard you wish to add, work out the row-column matrix using the table. A jumper cable may be an integral part of each keyboard, or an IC socket'lug arrangment similar to the main unit can be included with each added keyboard. You can even chain keyboard to keyboard by including two sockets on each one – just be sure all the sockets and plugs are identically wired!

Working by the Woodstove – II

Once you've got a new keyboard in your lap, you'll probably want a nearby screen to glance at. There are two ways to do this: by using a video monitor or by using an ordinary television. There are advantages and disadvantages to both methods.

A video monitor is the ideal tool because the image is crisp and clear, and your TRS-80 provides a 'composite video' (video with both image and synchronization signals) output. But a video monitor also costs somewhat more than a new black and white television, and means an added expense in any case.

A television on the other hand has limited 'bandwidth'; that is, it was made for fluctuating images, and not for the precise on-off quality of white letters on a dark background. If you've ever noticed that it's sometimes hard to read telephone numbers, addresses, or credits for television programs, you've got an idea of how hard it can be for some sets to reproduce crisp computer lettering.

Furthermore, most televisions accept only radio frequency (RF) input, meaning your TRS-80 output has to be converted to RF before your television can make sense of it. The last complication is that such a close and strong RF signal can overload your television's automatic gain control (AGC) resulting in an unstable, twisting, rolling, or badly contrasted picture.

But chances are you already have a television, and chances are even better that the television is

Making it Look Manufactured

One of the worst curses of a customized anything is how it tends to look – homemade. Now I have absolutely nothing against something looking homemade, but whenever I do that, somehow it also *acts* homemade – that is, just a bit too eccentric to be reliable as a computer!

Instead, attend to the cosmetic aspects of the TRS-80. Since the plastic case is very pliable and 'works' easily, these touches are easy. The silver coloring is a flake paint, and tends to wear off, particularly below the shift keys where the typing hands rest. The black plastic cover is very soft and can be scratched; its pebbled surface makes such scratches stand out.

If the silver flake paint wears off, it can be resprayed with the kind of paint used on model cars. Work the spray can valve for a while until it is spraying evenly, and then spray the silver cover from a slight distance. If the color match is not perfect, the bottom can be sprayed as well. Use two or three extremely light coats for a good effect.

The black plastic cover can even have deep, obvious scratches repaired by rubbing it with a glass marble. The scratch will smooth over, making it different from the area around it. Next, pick at the smooth area very lightly with a needle, making pebble-size marks similar to the rest of the case. Rub with the marble again until the scratched area looks exactly like the surrounding area. It really works.

When cutting holes for switches, buttons, sockets, jacks, keypads, etc., always cut the holes slightly smaller and use rattail (for round holes) or triangular (for rectangular holes) file to expand it to the correct size. This way, no unsightly cut marks will extend away from the area of the modification. Bevel cut rectangular surfaces with a flat file, smooth them with a letter opener or librarian's 'bone', and touch up the corners. The result will be almost precisely like the manufacturer's molded cutouts.



Figure 4-5. Extra video jack.



Photo 4-7. RF modulator hookup.

Additional jacks added in order to feed both the video monitor and an RF modulator installed in the expansion box.



Figure 4-6. RF modulator hookup.

Photo 4-6. Extra video jack.

just where you were thinking of using your computer.

Before going on with these modifications, there is one important note. Working with any unknown television or monitor can crash your system if it is electrically noisy. If you plan to send a video signal directly to a monitor, or especially to a television modified for video input, make sure the set isn't 'hot' – no AC line voltage should be floating on the case. This can damage your computer . . . or you! If you are considering a monitor or direct video input, and you are not familiar with your video sets, then take the television or monitor to a service person who can check them out. With appliance devices such as ordinary televisions, this is doubly important. This note does *not* apply if you will use RF input to a television.

Whichever method of added video you decide upon, though, there is a solution. The first and easiest is to add an extra video output jack to your computer. There's plenty of video signal to be had, and it can be shared among several sets. Figure 4-5 shows how to wire that extra jack, and Photo 4-6 shows how mine is installed. The













connector shown in the photo is a miniature Amphenol connector used for microphone cable, although any kind of microphone, video, CB, phono, or other shielded coaxial cable and connector can be used.

A second approach is to send the computer's video signal to an RF generator, and feed that to your television. An RF modulator is available in kit form from Radio Shack (part number 277-122, with TRS-80 installation instructions) and also from other suppliers. A few plugs and jacks are needed to complete the job.

Assemble the kit or purchase a surplus modulator, and hook it to an ordinary television. Either run the new video output to the modulator's input (use the directions with your modulator), or install a separate DIN plug-and-jack pair as in Photo 4-7.).

Actually modifying an ordinary television for video input is tricky, and I won't cover the topic here. If you are interested in doing this — and picture quality will be very much improved — refer to Don Lancaster's *TV Typewriter Cookbook.*

The results of your video modifications will be dependent on how clean your soldering is, the layout of your wiring, etc. If you add the RF modulator, you may notice something similar to herringbone on your TRS-80 monitor if the contrast is turned all the way up. Move the modulator away, or put it in a shielded (all metal) box, and the herringbone will disappear.



Photo 4-8. An Extra system near the woodstove.

The kitchen installation. An old RCA television and a surplus keyboard make working with the TRS-80 more convenient. Computer remains in one place, but extra monitor and keyboard can be moved closed to the woodstove on cold days. The woodstove offers no electronic interference.

If you use a long cable directly from the video output, there will be a huskiness to the characters on your TRS-80 monitor. This is actually a kind of 'smearing' introduced by the capacitance of a long cable. This is not bothersome to me; in fact, it actually seems to improve the clarity and boldness of the screen characters.

Finally, if your RF-input television addition results in an unpleasant display on the TV, try to adjust the automatic gain control (AGC) on the back of the set. Tune it in carefully as well. There will probably be less clarity in the 64-character mode than you are used to with your monitor, unless you have a very good set.

Hexadecimal Keypad

Entering machine language programs using T-Bug or another monitor is tedious enough without having to search all over the QWERTY keyboard for hexadecimal numbers. Instead, a keyboard can be added right onto the TRS-80. If you have a numeric keypad included with your Level II unit, you might want to remove it to add this one.

The addition of a hexadecimal keypad is mostly carpentry, since the connections are made in parallel to the main board, exactly like those connected to the socket addition described earlier. An unencoded hexadecimal keypad to do the job is available from Jameco Electronics (see Appendix 1.), and one of its keys can be set aside for an *Electric Pencil* or other control key, adding significant programming power to your custom TRS-80.

For this modification, you will need two 10-inch strips of 1/2-inch by 1/2-inch plastic rod (plexiglas or lucite are best, but wood strips will work as well), five-minute epoxy, wire, and the notorious hot razor blade and marble for the cosmetics.

Undo the cabinet as usual, and take the entire electronics out of the case. Later TRS-80's have an on-board, two-chip Level II ROM set, but if your Level II ROMs are the type on a separate board fastened to the end of an interconnect cable, then they will have to be moved. They are fastened to the bottom right of the circuit card with double-face tape; slit the center of the tape with a razor blade. Do not pull the ROM board off by force, as the pressure might crack either circuit board.

The interconnect cable to the ROMs is long enough so they can be remounted inside one of the case 'feet', or above the hexadecimal keypad. Pick up a small piece of double-face tape to refasten them, or roll masking tape into cylinders (remember hanging pictures in fourth grade?).

The Jameco Electronics keypad base is identical to the TRS-80's in height and depth, so the two plastic strips can be used to create a 'trailer hitch' arrangement with the smaller keyboard. Support both boards firmly so that they are parallel and the hex pad meets the TRS-80 printed circuit base. Cement the plastic strips in place with the quick-setting epoxy, and make sure the vertical alignment of both keyboards is identical. If you have a later style

Photo 4-10. Black plastic cover used as template.



Photo 4-10. Black plastic cover used as template.

The black plastic keyboard cover can be snapped out and cut to fit. A paper template is used first to verify the position of the hex keypad.



Keyboard is attached with runners to the main keyboard, and glued in place with epoxy.

Cleaning the Keyboard

If your TRS has the old-style keyboard that was badly afflicted with keybounce, there are many ways to take care of it other than perennially loading a KBFIX routine.

The first rule is to *make sure you have the old style keyboard!* The newer keyboards have a sculptured curve to their arrangement when viewed from the side. These new boards have a contact arrangement which can be destroyed by trying to remove the keycaps. But these keyboards don't have a keybounce problem anyway.

Bend a paper clip into an ingenious keycap lifting tool, like this:



Figure 4-7. Keycap lifting tool.

Slip this clip underneath a keycap, and lift up. The plastic cap will come off, revealing a hole in which two metal plates are protruding upward.

The best way is to test the keys. Press each key quickly, gently, slowly, or sharply, until you decide whether it is a 'bouncy' key. If it still bounces after the cleaning, then take a hatpin (are there still hatpins?) or heavy sewing machine needle, and push the tines in line. This is a very delicate job; use caution and a magnifying lens. If the plates are not parallel to each other, or if they are vertically misaligned, use the pin to shift their positions.

The villians are dirt and bent tines on the plates. Brush out the dust, dirt, or hair (or much better, blow it out, using photographers' compressed air, such as 'Dust-Off'). You will be amazed at the cloud of grit that rises from the keyboard. Next, examine the tines of each key very carefully. They should be perfectly in line, so that when a key is pressed, all come into contact with their opposite (un-tined) plate.

Check all the keys for bounce again, and work until it is completely cured. Some folks recommend a spray of contact cleaner at this point; I recommend against it. The cleaner tends to stay wet for a while, and dust and grit can get back into it very quickly, collecting into a dusty mudpile. Instead, give all the keys a last brushing or spraying with compressed air, and fit the keycaps back on.

Keybounce should be gone for quite a while. Monthly cleaning will keep the keyboard in shape.

keyboard (with the curved keyboard array), you will have to adjust the carpentry slightly. You may also experience a bit of keybounce on the new keyboard unless you keep the keys clean.

When the glue has set, use the black plastic cover as a template for drawing your current key positions and, with the aid of a straightedge, draw extension lines horizontally across that drawing. These are the upper and lower limits of the new keypad opening. Align the template with the complete alpha/hex keyboard assembly, and mark the vertical positioning of the hex keys, allowing about 1/32 inch additional on both sides for key-travel room. This will bring you within 1/4 inch of the power LED.



Back of keyboard is wired by soldering directly to the key pins. Wires are then run to resistors and integrated circuits found on the main keyboard.

Using the template with the black plastic cover, carefully cut an opening in the cover with the hot razor blade. This is the most time-consuming task, and should be accurate enough for the keys to travel easily (fit it atop the keyboard before re-installing the modified computer), and should look factory-finished.

It's about time to interconnect the wires from the hex pad to the main keyboard, but before that, you'll probably want to rearrange the keycaps on the hex pad. Using the lifting tool, pull off the keycaps and put them in a convenient order for hex entry; I used the accounting arrangement, bottom to top. This is the pattern used for the wiring arrangement shown in Diagrams 4-1 and 4-2.

Rest the keyboard on its face, and separate it gently from the main circuit card. Set the keyboards in an accessible position, and solder fine wires (wire-wrap type is easiest to use) to the hex pad connections shown in Diagram 4-1. Route the individual wires from the hex keys to the points on the circuit card shown in Table 4-5. As before, check to make sure this IC arrangement matches your board.

Next, solder wires to the hex pad contacts as shown in Figure 4-1, and route these wires from the hex keys to the circuit card's resistors noted in Table 4-4. Double check these too against your version of the keyboard. Once both sets of wires have been run, gather them in neat hanks and fasten them along their routes with wire ties (plastic bag ties will also work well).



Completed keyboard seats easily in the case bottom. A piece of insulating plastic should be inserted under the added keyboard to prevent pushing the keyboard pins into the main circuit board and causing a short.

Table 4-3

@	A	B	C	D	E	F	G
H	I	J	K	L	M	N	O
P	Q	R	S	T	U	V	W
X	Y	Z	....Unassigned....				
0	1	2	3	4	5	6	7
8	9	:	;	,	-	.	/
ENT	CLR	BRK	UPR	DNR	LFR	RTR	SPC
SHIFT	........Unassigned........						

Table 4-4

Column 1	R8	@ H P X 0 8 ENTER SHIFT
Column 2	R5	A I Q Y 1 9 CLEAR
Column 3	R3	B J R Z 2 : BREAK
Column 4	R2	C K S 3 ; UPARROW
Column 5	R7	D L T 4 , DOWNARROW
Column 6	R1	E M U 5 - LEFTARROW
Column 7	R4	F N V 6 . RIGHTARROW
Column 8	R6	G O W 7 / SPACE



DIAGRAM 4-1

Table 4-5

Row 1	Z1 Pin 8	@ A B C D E F G
Row 2	Z1 Pin 2	H I J K L M N O
Row 3	Z1 Pin 10	P Q R S T U V W
Row 4	Z2 Pin 2	X Y Z
Row 5	Z1 Pin 6	0 1 2 3 4 5 6 7
Row 6	Z1 Pin 4	8 9 : ; , - . /
Row 7	Z1 Pin 12	ENTER CLEAR BREAK UPARROW DOWNARROW LEFTARROW RIGHTARROW SPACE
Row 8	Z2 Pin 4	SHIFT



DIAGRAM 4-2



Level II ROM board can be fit immediately above the hex pad. Insulating double-face tape can be used to hold them in place.

Reassemble the keyboard in its case, remembering to orient the Level II ROM board safely in its new position. Reinsert all cables, and restore power. The keys on the main keyboard should respond normally; check them all. Now check the keys on the hex pad. All but the bottom right one should have an effect. To test its operation, enter this program:

```
10 CLS
20 PRINT PEEK (14464);
30 GOTO 20
```

The value you read should be zero unless either the shift key on the main board or the bottom right hand key on the hex pad is depressed. The shift key will return a value of 1; the new key will display a value of 16. Pressed together, they will read 17.

All keys should now be working properly. As with the socket addition described above, problems will occur in the form of incorrect letters, groups of letters on a single keypress, or dead keys. If any of these symptoms appear, recheck for shorted or unconnected wiring, or a difference in your model TRS-80 keyboard. Refer to Tables 4-3 through 4-5 if you suspect the latter.

The final modification with black plastic cover fit back in place looks manufactured (almost).

Reversing the Video

The video display of most computers including the TRS-80 suffers from a tremendous flaw – contrary to what we have known since we first learned to read, the letters are presented to us in glowing blue-white on a black background. Serious use of a computer as a day-to-day appliance, as a true adjunct to our daily lives, is limited by its formidably unappealing, tiresome, and illegible display.

The reverse video modification is surprisingly easy, so the question arises: why is it not a standard feature of small computers? The answer is found partly in a tradition of computer monitors which have always been lighted characters on a dark background. The remainder of the answer is found in the video display itself, which is more often than not incapable of presenting a legible character in the black-on-white mode.

This problem arises with the TRS-80 as well; the video monitor has weaknesses which are emphasized by reversing the characters. But overall, and with a small change to the monitor itself, the display can be made quite legible and easy on the eyes.

For this modification, you will need three integrated circuits: 74LS02, 74LS74, 74LS368.

A 1.5K-ohm resistor will also be used, and wire-wrap wire for the interconnections. There are two ways of making this modification: on a separate board, or piggybacked atop chips already present inside the TRS-80. Since the latter approach would involve at least 15 separate wires, both this change and the high-speed modification presented below will use the piggyback system.



THIS IS AN EXAMPLE OF
NORMAL VIDEO IN THE
32-CHARACTER MODE,
WITH SOME GRAPHICS
CHARACTERS:

Normal screen has unnatural bright characters against a dark background, which is wearying on the eyes.

Open the computer's case, and remove the electronics so the integrated circuit side of the main card is up. Locate the following circuits (the numbers are silkscreened on the board): Z22, Z26, Z27, Z30, Z52, Z53, Z54, and Z59.

The output of Z54 (pin 8) is a decoded signal representing ports 254 and 255. Combined directly with the output of Z52 (pin 6), port 255 is selected for use by the cassette and video circuits. By inverting the output of Z52 and combining it with the output of Z54 and the computer's OUT signal (Z22, pin 3), port 254 can be selected. Figure 4-8 is the schematic for this complete decoding process.

The decoder uses the 74LS02. Prepare the integrated circuit by bending all the leads except pins 7 and 14 so that they are parallel with the IC's body. Locate Z53 on the TRS-80. Seat the 74LS02 directly atop Z53, with both notches or dots facing in the same direction. Solder power pins 7 and 14 of the piggybacked IC to corresponding pins 7 and 14 of the one below. I will refer to this piggybacked IC as ZPORT.

Figure 4-8. Reverse video schematic.



Find Z52. Run a wire from pin 6 of Z52 to both pins 2 and 3 of ZPORT, and solder it. Next locate Z54. Solder a wire from its pin 8 to pin 11 of ZPORT. Finally run a wire between pins 1 and 12 of ZPORT.

As mentioned, Z22 contains the needed OUT signal. Run a wire from pin 3 of this circuit to pin 5 of ZPORT. Solder together pins 8, 9 and 13 of ZPORT, and run a wire between pins 6 and 10 of ZPORT. Pin 4 remains unused, and it contains the complete decoded signal of port 254 as shown in Figure (?). The BASIC command OUT 254,N will activate this signal.

The next IC to be prepared is the 74LS74. Again, bend all leads parallel to the body except 7 and 14, seat this upon Z26, and solder the power pins (7 and 14) in place. This piggybacked circuit I will call ZFLOP, as it will determine which state (normal or reverse video) is flip-flopped into place when OUT 254,N is commanded.

Run a wire from the decoded signal at pin 4 of ZPORT to pin 11 of ZFLOP. Z59 has a convenient data line (bit 1) at its pin 5; run a wire from there to pin 12 of ZFLOP. Now run short wires connecting together pins 10, 13, and 14 of ZFLOP. With these connections made, OUT 254,0 will flip the circuit, and OUT 254,2 will flop it. (Is the suspense building?)



THIS IS AN EXAMPLE OF
REVERSE VIDEO IN THE
32-CHARACTER MODE,
WITH SOME GRAPHICS
CHARACTERS:

Photo 4-11. Reverse video screen example.

Illuminated background with dark characters is clear and, together with a green screen of some type, much more gentle to look at over long periods.

The final IC is now prepared. Bend the leads of the 74LS368 parallel to its body, except for pins 8 and 16. Seat this on Z27 and solder power pins 8 and 16 to it. For convenience, this piggybacked circuit will be called ZMODE.

Find Z30 and Z41. Pin 1 of Z30 is connected via a circuit board trace on the *underside* of the board to pins 6 and 7 of Z41. Z30 provides the characters to be output to Z41, which is part of a circuit that mixes in the synchronization information to produce 'composite video'. Cut this trace near Z30.

Why cut this trace? The TRS-80 produces characters on the screen by turning on 'dots' as the electron beam sweeps across the tube. Each dot is part of a continuous stream of pulses which might be called 'dots' and 'undots' – ones and zeros. To reverse the video, then, all you need to do is to turn the 'dots' into 'undots', and turn the 'undots' into 'dots'. We insert an electronic fork in the road at the output of Z30. When directed toward one side of the fork, the characters are made up of dots; when directed down the other fork, the characters become undots, and the background becomes dots.

Run a wire between pin 1 of Z30 and pins 2 and 14 of ZMODE. These are two inputs of an inverting buffer, the 'fork in the road'. If we invert the signal once, the video reverses . . . invert it twice, and the signal returns to normal. Connect pins 3 and 4 of ZMODE together to perform the double inversion. Pin 5 is the normal video output, and pin 13 becomes the reversed output. Connect both these outputs (pins 5 and 13) together.

Find the opposite side of the broken trace from Z30, and follow it to a hole that is plated through the board; it is at the end of a row outlined by Z29 and Z30. Be careful to select the correct hole. Run a wire from this hole to pins 5 and 13 of ZMODE. This connection feeds both normal and reverse video back into Z41 and through to the video output jack.

I have chosen ZMODE because it is a three-state circuit. That is, its outputs can be made electronically invisible. Otherwise, both normal *and* reverse video would be output at the same time. To choose between them, ZFLOP is used to *enable* one or the other of those outputs. Run a wire from pin 8 of ZFLOP to pin 15 of ZMODE. Run a wire from pin 9 of ZFLOP to pin 1 of ZMODE.

By commanding OUT 254,2 or OUT 254,0, data line 1 selects which output of ZFLOP will be enabled, and which video mode will be visible on the screen

Check your wiring and restore the computer to its case. Power up, and command OUT 254,2. The screen will reverse. The effect, alas, will not be as dramatic as you might expect because the video monitor is not a great piece of work.

Power down the system, unplug the monitor, and open it up. You might find that a hex-nut driver is necessary to open the monitor intead of a Phillips type; later monitors used 1/4-inch hex nuts.

When it is open, find the plug-in circuit card closest to the monitor wall (some have only one), and locate the resistor marked R14. The present value should be 3.3K ohms (orange, orange, red, silver or gold). We want to give the video signal a bit more 'oomph', so piggyback the 1.5K ohm resistor atop R14 and solder it in place. Restore the cabinet. The reverse video modification is complete.


Photo 4-9. Two photos (a) & (b) of two keyboards.

Clumsy? Me Too. Do This First.

During the course of these modifications, there will be connections made to integrated circuits which are carrying piggies atop their back. In case your soldering iron is a bit obese, you might want to solder wires to these circuits in advance.

All these pins will have wires running to them:

Z22, pin 3
+Z25, pins 11, 12 and 13
+Z27, pins 4 and 5
Z30, pins 1 and 13
Z41, pin 6
Z52, pin 6
Z54, pin 8
Z59, pin 5
Z60, pins 4 and 5
Z63, pin 12

Only those marked with a plus sign (+) actually carry piggies, but since everything is close together, you might want to make all the connections in advance anyway; so there they are.

Lower Case with Upper

Many modifications have been proposed to obtain lower case characters already present in the TRS-80 character generator. Some are incompatible with each other, although they do provide access to a group of special control characters also burned into the character generator.

The modification provided here is simple, compatible with both the Radio Shack and Electric Pencil modifications, and should give no grief throughout its life. For this modification you will need a single integrated circuit, and 2102 AN-4L memory chip. These chips are available from several suppliers; in a pinch, the 21L02 sold by Radio Shack will do the job.

The 2102 will be piggybacked – except for pins 11 and 12 – atop Z45, also a video memory chip (it will not necessarily be marked a 2102, since Radio Shack ordered house numbered parts for a while, but it is a 2102). Bend pins 11 and 12 of the piggyback 2102 parallel with its body, and fit the integrated circuit on Z45, making sure it is positioned in the correct direction. Solder extremely carefully, pin for pin, down one side (pins 1 to 8), and up the other (pins 9 to 10, 13 to 16).

Now locate Z25. It is an integrated circuit containing four OR-gates, one of which is not used. With solder-wick, suck up the extraneous solder that is present on pins 11, 12, and 13, and with a sharp X-acto knife or razor blade, cut pins 12 and 13 free from each other and from the ground lead going to pin 7.

Now locate the trace on the circuit board running from Z60 pin 4 to Z30 pin 13. Use an ohmmeter if necessary to make sure you have the correct trace. Cut it through. Double check that you have not cut the trace that runs from Z60 pin 4 to Z27 pin 13.



Figure 4-9. Upper/lowercase schematic.

Finally, run four wires: from Z60 pin 4 to piggy-Z45 (call it ZMEM from now on); from Z60 pin 5 to Z25 pin 13; from Z30 pin 13 to Z25 pin 12; and from Z25 pin 11 to ZMEM pin 11.

The lowercase modification is complete. A memory chip to represent the missing bit 6 has been added, and the necessary triggering information (bit 7 and bit 5) has been gated through Z25. Why is it necessary to gate bits 7 and 5 to trigger ZMEM? Because the information sent by Radio Shack's print routine does not include bit 6; in an unmodified machine the bit is generated by the presence of bit 7 and bit 5! Check the *Technical Reference Handbook* for details. In this case, the false bit 6 is generated where necessary by Z30, and ORed with a true bit 6. In other words, either case will result in bit 6 being embedded in the new bit 6 video RAM, ZMEM.

> **Note**: *Several TRS-80's in which I have installed this modification contained a Z25 with the spare gate dead. Perhaps it was a Radio Shack economy move. If so, piggyback a 74LS32 on Z25, soldering pins 7 and 14 to Z25, and continue with the remaining lowercase mod instructions.*

The lowercase modification can be tested as follows; a complete lowercase driver is presented in Chapter 3:

```
10 CLS
20 FOR X = 15360 TO 15360+255
30 POKE X,Y
40 Y=Y+1
50 NEXT
60 GOTO 60
```

One by One

Reversing individual characters is similar to the process of reversing the entire video screen, except that the reversal is carried out only for a short period of time. That period is determined, of course, by the letters being displayed. (At this point, I should note that all four internal hardware modifications in this chapter are partly interrelated. Both reverse video and high-speed modifications use the same output port decoding; both reverse video and reverse characters use the same flip-flop; both reverse characters and upper/lower case use the same video memory decoding hardware).

Before installing the individual-character reverse video, the upper/lower case modification must be installed. This will provide the essential bits 6 and 7 (see that section for an

explanation of the 'phantom' bit 6). For the individual character reverse, three additional integrated circuits will be needed: one 74LS86 Exclusive-OR gate, one 74LS10 triple-input NAND gate, and one 74C04 hex inverter. The last is very important, because it is used for aligning the reversal pattern with the letter to be reversed. You will also need a small variable resistor (trimmer potentiometer, or 'trimpot'), approximately 50,000 to 100,000 ohms; two capacitors, one 330 picofarads (pF) and one 0.033 microfarads (mF).

As before, bend all pins of the 74LS86 except pins 7 and 14 parallel with the body of the integrated circuit. Affix the 74LS86 atop Z24, and solder power pins 7 and 14 to it. This gate will multiplex the combined bit 6/7 signal with the output of ZFLOP (from the previous complete reverse video modification). Call this gate ZMUXX.

Remove the wires attached to the outputs (pins 8 and 9) of ZFLOP, and run them, respectively, to pins 2 and 5 of ZMUXX. Now run a pair of wires from pins 6 and 3 of ZMUXX to pins 15 and 1 of ZMODE (which were just disconnected from ZFLOP). In other words, ZMUXX has been inserted between ZFLOP and ZMODE.

Next position the 74LS10 correctly atop Z25 and solder the power pins in place. Call this circuit ZBITS, because it will evaluate which bits of given letters should cause the reversal to take place.

The steps below summarize all the activities to complete this modification; some have been done already, (such as the lowercase modifications) but are included for clarity:

1. Break trace from Z30, pin 13 to Z60, pin 4.
2. Break trace from Z63, pin 12 to Z42, pin 13.
3. Break trace from Z42, pin 12 to Z27, pin 4.
4. Cut loose Z25 pins 11, 12, 13, from pin 7.

Carpentry Considerations

When you first open your TRS case, you'll probably be unfamiliar with what comes out. The photo below is presented to remind you that six screws and five white spacers make up that group:



Photo 4-12. *Screws and spacers in keyboard unit*

When you have been soldering in and around the circuit board, chances are that a lot of ugly, crusty brown flux residue will build up. In order to see what you are doing and make sure connections are sound, you should clean this mess. There are flux removal compounds available, and these should be applied with cotton swabs.

My own choice is a gentle but very fast acting substance which can sometimes be found in surplus – Thermo-Fax brand belt cleaner. This treats the boards and their coating without harsh chemical action, but removes the flux within seconds.

Another area of difficulty in doing these modifications is cutting traces. Place the circuit board on a very secure and stable table, cushioned just a little with a towel. Lean firmly but gently on the board, and move an X-acto knife or single-edged razor blade back and forth until the trace gives way. This may take as many as 20 or 30 scrapings.

When the trace looks cut, make sure. Cut deep into the fiberglass base so you can see a cut space, and then wipe the area clean with flux or tuner cleaner so the break is obvious.

If you must resolder a trace, scrape the green masking from both sides of the cut, wipe it clean, and flow solder on both sides, but *don't* bridge the trace with solder. Instead, take a piece of bus wire or stripped wire-wrap wire, form it into an 'L' shape, and solder the base of the L across the trace. Then cut off the excess. Bridging with solder alone is dangerous because it can look fine, but really be attached only by a glob of flux, or be attached so weakly that flexing the board will crack the solder off.

5. Piggyback on Z45 a 2102, soldering pins 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 13, 14, 15 and 16.
6. Piggyback on Z24 a 74LS86.
7. Piggyback on Z25 a 74LS10.
8. Piggyback on Z6 a 74C04.
9. Run a wire from Z60, pin 5 to Z25, pin 13.
10. Run a wire from Z30, pin 13 to Z25, pin 12.
11. Run a wire from Z25, pin 11 to Z45piggy, pin 11.
12. Run a wire from Z45piggy, pin 12 to Z60, pin 4.
13. Run a wire from Z45piggy, pin 12 to Z25piggy, pin 1.
14. Run a wire from Z63, pin 12 to Z25piggy, pin 13.
15. Run a wire from Z25piggy, pin 2 to Z27, pin 5.
16. Run a wire from Z25, pin 12, to Z6piggy, pin 1.
17. Connect together Z6piggy, pins 2 and 3.
18. Attach one terminal of the 100,000-ohm trimpot to Z6piggy, pin 4.
19. Attach the other terminal of the 100,000-ohm trimpot to Z6piggy, pin 5.
20. Attach one end of the 330-pf capacitor to Z6piggy, pin 5.
21. Connect together Z6piggy, pins 6 and 13.
22. Attach the other end of the 330-pf capacitor to Z6piggy, pin 12.
23. Attach one end of the 0.033-mf capacitor to Z6piggy, pin 12.
24. Attach the other end of the 0.033-mf capacitor to Z6piggy, pin 11.
25. Connect together Z6piggy, pins 9 and 10.
26. Run a wire from Z6piggy, pin 8 to Z24piggy, pin 1.
27. Connect together Z24piggy pins 1 and 4.
28. Run a wire from Z63, pin 12 to Z25piggy, pin 3.
29. Run a wire from Z42, pin 12 to Z25piggy, pin 4.
30. Connect together Z25piggy, pins 5 and 14.
31. Run a wire from Z25piggy, pin 6 to Z27, pin 4.
32. Disconnect the wires running from ZFLOP pins 8 and 9 to ZMODE.
33. Run the wire from ZFLOP, pin 8, to Z24piggy, pin 2.
34. Run the wire from ZFLOP, pin 9, to Z24piggy, pin 5.
35. Run a wire from Z24piggy, pin 3 to ZMODE, pin 1.
36. Run a wire from Z24piggy, pin 6 to ZMODE, pin 15.

The modification is complete. Using the individual reverse video is not the easiest process, but works nonetheless. Printing CHR$(0) through CHR$(31) results in control codes being acted upon; CHR$(32) through CHR$(127) now produce the full range of ASCII letters; CHR$(128) through CHR$(191) produce graphics characters; and CHR$(192) through CHR$(255) produce the 63 possible TAB positions.

To use the individual character reverse, then, you cannot PRINT the CHR$ value. Instead, you must POKE the value onto the screen. Granted, this is a pain, but when a program is completed, the prompting can be extraordinarily effective. Besides, it's not that hard. Try this:

```
10 CLS : Y=15360
20 FOR X = 0 TO 255
30 POKE Y,X
40 Y=Y+1
50 NEXT X
60 GOTO 60
```

Listing 4-1. Individual character test program.

Chances are that a group of reversed characters appeared, but the reversal band didn't match up with the actual characters. That's the reason for the 74C04 and the 100,000-ohm potentiometer. Run the following test program:

```
10 CLS
20 FOR X = 16040 TO 16060
30 POKE X,255
40 NEXT
50 GOTO 50
```

Listing 4-2. Individual character alignment program.

Now adjust the potentiometer until the crosshatches are centered precisely within the white band (or rather, so the white band is in the correct background position).



Complete font of reversed characters. Because only 64 characters remained in the available set, upper and lower case were chosen as opposed to numbers and symbols.

That is a simple example of the individual character-reverse process, using BASIC. By using ordinary displa routines in machine language programs, the individual character reverse is an entirely trivial matter, but really putting it to work in BASIC requires a bit of fancier footwork.

Using it through BASIC can be done without POKEing large numbers of characters in prearranged locations. Instead, the position of the cursor on the screen can be determined, and the characters POKEd in place from there. The subroutine below is useful:

```
10000  X = PEEK(16416) + 256*PEEK(16417) : RETURN
```

This subroutine determines the position of the cursor and assigns it to X. Then characters may be POKEd as follows:

```
40 GOSUB 10000
50 A$ = "THESE ARE REVERSE LETTERS"
60 FOR N = 1 TO 25
70 Q = ASC (MIO$ (A$,N,1))
80 POKE X,Q
90 NEXT
100 GOSUB 20000
```

Listing 4-3. Individual reverse demo program.

The GOSUB 20000 executes the following one-line subroutine:

```
20000 ZH = FIX (X/256) : ZL = X-ZH*256 :
      POKE 16416,ZL : POKE 16417,ZH : RETURN
```

This short routine restores the cursor position after the POKEs have taken place. There are two very important things to note:

1. If the POKE is to take place on the last line of the screen, make absolutely certain that the value of X does not exceed 16383, because this will POKE nasty values into BASIC vectors beginning at 16384. A test for X greater than 16383 can be made so:

```
10005 IF X>16383 THEN X=96383 : GOSUB 20000
        : PRINT : RETURN
```

This will have the effect of restoring the cursor, printing a carriage return, and finishing the text to be printed.

2. The POKE feature does not include a carriage return, so this method of printing a reversed message has the effect of a PRINT; (PRINT semicolon) statement. Immediately follow the return-from-subroutine with a PRINT statement if the rest of the message is to be printed on the next line.

A few peculiarities may arise with this modification; among them:

1. The 'fill' character of Electric Pencil may change. This is because any program defining graphics characters as 192 to 255 instead of 128 to 191 is not using them according to the original Radio Shack specifications.
2. Single reversed letters scattered throughout text may not work. This is due to the extremely fast requirements of the circuit, and the fact that certain integrated circuits may not be up to it. Two characters together, however, will print properly.
3. The timing is so crucial that temperature may offset the image slightly. Use polystyrene or polycarbonate capacitors, never ceramic disc capacitors, for this modification.
4. With a screen full of reversed letters, some increase of the brightness control may be needed.
5. The full character set is not available because more hardware would be necessary to obtain the logic information necessary to select out, for example, letters and numbers or letters and symbols.

Although it sounds like I am doing a lot of warning about the limitations of this sort of modification, you should realize that the TRS-80



WELCOME

THIS IS A TEST OF THE REVERSE LETTER ...

HERE ARE SOME MORE LETTERS

THE LETTERS CAN ALSO BE MIXED ON THE SAME LINE FOR EMPHASIS

Photo 4-13. Individual reverse screen example.

Reverse lettering provides an emphasis; flashing from one to the other is extremely effective for prompts.

was never meant to do this sort of thing, and the fact that it does work is remarkable. Once it is in place, you will wonder how you could have created reasonable self-prompting programs without it. See Photo 4-13 for proof of the impressive results.

A complete circuit containing the reverse video, upper/lower case, and individual reverse video modifications appears in Figure 4-10 , below:

Stepping on the Accelerator

When you first unpacked your TRS-80 and tried a few calculations and displays, you were likely amazed at the speed with which the TRS-80 was able to respond. But certainly as you used the machine, you realized that it could spend quite a while performing complex tasks. It was then that you joined the ranks of the dozens of thousands of micro users searching for a faster running computer.

When the TRS-80 was designed, the options for higher speed were put in place. Normal and 200 percent speed options were right there on the circuit board, and 150 percent speed required the routing of but a single circuit trace; yet the final design opted for the lowest speed (1.77 MHz).

This modification releases the permanent connection of the 100 percent (1.77 MHz) clock and allows the computer to switch back and forth between this clock rate and a rate one-and-one-half times faster – 2.66 MHz – or two times faster – 3.55 MHz. There are a few pitfalls, but the actual modification is a simple one. For it, you will need the decoded port 254 explained in the reverse video section of this chapter (74LS02), the other half of the flip-flop (74LS74), and one 74LS367.



Figure 4-10. Complete video modifications schematic.

Before you perform this modification, there are a few things you should know. For a reason which I have yet to determine, some Level II machines with the *two-chip* ROM set will not accept a speed-up successfully, though most will. Second, later units have been manufactured (or earlier units may have been retrofitted) with a small board known as 'XRX III', a synchronous, 500-baud wave shaper. Cassette load at the 750- and 1000-baud rates will not work unless the modification is deactivated (for details on the cassette system, see the Supplements to Chapters 3 and 6).

The third item concerns the expansion interfaces manufactured since January 1980. Unfortunately, these interfaces must also be modified to accept a higher-speed CPU. But this modification (see Chapter 5) is quite simple and very reliable. Finally there is the question of memory speed. If your TRS-80 is *very* early and the 16K RAMs were shipped with the unit, there is a small chance that one or more of these RAMs will not be capable of running at 3.54 MHz – and an even smaller chance of not operating at 2.66 MHz.

That said, I'll turn to the modification itself. Locate Z56 on the circuit board. Cut the foil trace that leads from this pin to the hole that is plated through the circuit board. Mark that hole for future reference. By cutting this trace, you separate the 1.77 MHz output of Z56 from the clock input of the Z80 processor.

If you have not created the port 254 decoding used in the reverse video modification, you will need to piggyback a 74LS02 on Z53. Bend all the leads except 7 and 14 parallel with the body of the IC, and seat it atop Z53 with the notch or dot pointing in the same direction as the rest of the integrated circuits on the board. Solder pins 7 and 14 to Z53; this piggybacked circuit will be called ZPORT.

Locate Z52; run and solder a wire from pin 6 to pins 2 and 3 of ZPORT. Find Z54. Run and solder a wire from pin 8 of Z54 to pin 11 of ZPORT. Pins 1 and 12 of ZPORT are connected together. This completes the decoding of port 254 (hex FE). To add the necessary OUT signal, run a wire from Z22 pin 3 to ZPORT pin 5. Solder together pins 8, 9, and 13 of ZPORT; solder together pins 6 and 10 of ZPORT. The BASIC command OUT 254,X will activate the signal found at ZPORT pin 4.

Also a part of the reverse video modification was the piggybacking of a 74LS74 atop Z26. Bend all leads parallel to the body of the IC except power pins 7 and 14. With the integrated circuit oriented in the same direction as Z26, mount it there, soldering pins 7 and 14 to the IC below. This IC is called ZFLOP.

Run a wire from the decoded signal at pin 4 of ZPORT to pin 3 of ZFLOP. Z59 has a data line (bit 0) at its pin 4; run a wire from that pin to pin 2 of ZFLOP. Now run wires connecting together pins 1, 4 and 14 of ZFLOP. With these connections made, OUT 254,0 will flip the circuit, and out 254,1 will flop it. Note that OUT 254,0 and OUT 254,2 were the flip-flop commands for the reverse video.

Now the 74LS367 is put in place. As with the other ICs, bend all leads except the power pins (pins 8 and 16 on this circuit) parallel with the body. Place the 74LS367 on Z44, and solder pins 8 and 16 to it. Call this ZFAST.

Locate pin 8 of Z56, whose trace is already cut. Run and solder a wire from this pin to pin 2 of ZFAST. Run a wire from pin 3 of ZFAST to the plated-through hole, which was previously marked for reference. Take care that this is the correct hole before soldering; it is the other end of the trace cut from Z56.

The normal clock will now be reunited with the CPU. Run a wire from pin 5 of ZFLOP to pin 1 of ZFAST and solder. When OUT 254,1 is executed, the normal speed will flip in place. The other speed output buffer is wired now. Tie pins 13 and 3 of ZFAST together. Last, run a wire from pin 6 of ZFLOP to the second gated section of ZFAST, pin 15.

The higher speed will now be selected. The options are two, and you may try either 150 percent normal speed or a hot 200 percent normal speed.

150 percent normal speed: Locate Z43, pin 2, which is the 5.32 MHz clock normally used in the video divider chain. Run a wire from this pin 2 to Z56 pin 14. That pin is the input of an unused divide-by-two segment of Z56. The output (2.66 MHz) of this divider is present at Z56 pin 12. Run a wire from there to pin 14 of ZFAST.

200 percent normal speed: Locate Z56, pin 11. This is the 3.54 MHz clock not used in the TRS-80. Run a wire from this pin 14 of ZFAST. For this super-fast mod, the memory select circuits must also be dealt with. Locate Z69, and cut the trace running from pin 5 to pin 12. Connect pin 12 to pin 13. This speeds the memory-select process (from MREQ and RD) just a tad, but enough to cope with the 200 percent modification.



Figure 4-11. High-speed circuit diagram.

The high speed modifications are now complete. Reassemble the TRS-80 and run a test by trying OUT 254,0 and OUT 254,1, which will flip and flop the speeds. The following short BASIC program will give a good demonstration of the speed differences:

```
10 FOR B = 0 TO 1
20 CLS
30 OUT 254,B
40 FOR X = 1 TO 50
50 PRINT X;
60 NEXT : NEXT
70 GOTO 10
```

Listing 4-4. High-speed demo/test program.

In addition to the modifications themselves, it is often useful to know which speed is active. There are ways of telling after working with the higher speeds: the very slight herringbone in the video monitor (turn contrast high to see it) changes pattern, programs work faster, etc. However, a bipolar LED is ideal for this.

To pin 1 of ZFAST, attach one end of a bipolar LED. Attach the other pin to a 470-ohm resistor, and run this resistor to pin 15 of ZFAST. The light will show green for one speed and red for the other; by reversing the center pin of the LED, the color pattern selected can be reversed. I use red for the normal speed, and green for the higher speed.



Figure 4-12. LED hig-speed indicator circuit diagram.

Level I and Level II Together

Little defense of Level I BASIC has been made, but from my point of view, it's a delightful, compact little BASIC. My own familiarity with it is relatively recent, because I ordered my TRS-80 with Level II installed. Aside from the maddening lack of key rollover, Level I seems an ideal teaching language, especially for youngsters. Together with the excellent Level I manual created by David Lien, it is a fine introduction to the language, and to computers themselves.

Enough for the defense. The problem with Level I is that it is not Level II, and the bulk of we TRS users have Level II BASIC installed. Level I can nonetheless be co-resident, and there are three ways to do it: install the Level I ROM with a switch (this is the method presented here); use a disk system with the Level I-in-Level II program (offered by Apparat and others); or relocate and rewrite Level I a bit and burn it into an EPROM placed in high memory.

Level I ROMs are getting harder to obtain because of the Model I's discontinuance, but cooperative repair centers or franchise Radio Shacks ('Associate Stores', Tandy calls them) can often provide the ROM for a few dollars. Although I am not one to encourage software copying, I do feel that as a TRS-80 purchaser, you paid for your Level I ROM if you bought the unit with one. If it was not returned when Level II was installed, then Radio Shack owes you one. Try to get it.

The other way is to order the ROM as a replacement part; Radio Shack's latest replacement number is MX4126, and they charge $71.25 (!) for it. Finally, you can borrow one from someone who has it and copy it into a 2732 EPROM, but that's still about a $40 investment.

Let's assume you're able to obtain a Level I ROM. The ones you want are marked National, and are identified with parts numbers M2316E/MMS258ET R/N and S/N, or Motorola, marked 7807 and 7804 or 7831-BASIC1-ROM A and 7832-BASIC1-ROM B. Ideal is the single-chip ROM from Motorola or Rockwell, marked 7809 and 7845, respectively (phew!). Photo 4-(?) shows the two-chip (7831/32) set and the Rockwell (7845), mounted on an aluminum-foil-covered vegetable tray.

You do *not* want the chips marked Intel; these are 2716 EPROMs, and the wiring is complex. About the only thing they are good for is scraping off the label and erasing under ultraviolet light. Then you have two spanking new $12 EPROMs.

Check next to see if you have the two- or three-chip Level II ROM set. If you have the three-chip set, there will be a connector cable running to a separate board taped to the main circuit card. If not, both ROM sockets will be filled, and installing Level I will be more difficult. Last of all, make sure your circuit board is a 'D' board, 'G' board or later. 'A' boards won't do. (The number is part of the lettering silkscreened on the board, such as 1700069D or 1700069G).

First will be instructions for installing the ROM in the TRS-80's with outboard Level II ROMs. Mount a double-pole, double-throw switch conveniently, but discreetly enough that you won't be knocking it into Level I in the middle of a four-hour data sort.



Level II ROMs: 3-chip set on individual board at the end of a cable which is plugged into the main CPU card.

Open up the TRS-80, and note where the Level II ROM cable is plugged. Four (or six) other wires run from this Level II board to the rest of the circuit card. Find these locations:

1. The green wire on the Level II board, connected near the underside of dip shunt X3.
2. ROM socket Z33 or Z34 (whichever is empty), pins 18 and 20.

Cut the traces leading from pins 18 and 20 of the unused ROM socket. Add a short length of wire between pin 20 and the far end of the trace that used to lead from pin 18. Solder a long white wire to pin 18. Remove the far end of the Level II board's green wire from its connection point near shunt X3, and solder a red wire there. Solder a blue wire to the 5-volt supply found at Z57, pin 14. Using Figure 4-13, run the white, green, red and blue wires to the double-pole, double-throw switch.

Add two 1000-ohm resistors to the circuit to hold the ROM chips inactive when they are not in use. Without them, inadverent selection might take place, and the running program (in either language) might crash.

If you've got the single-chip Level I ROM, you're all set to go. If not, the fun begins here. Locate the notch on each Level I ROM chip, and line up the two chips with each other, *precisely pin for pin.* Now piggyback one atop the other and solder all 24 pins so that the result is a single, hulking, integrated circuit. Solder carefully, keeping the bottom IC anchored in conductive foil. The foil will act as a static remover and heat sink, both essential in this mod.

Blobs of solder can be removed with some sort of solder-wick or a solder-removing vacuum tool. This entire chip is then inserted in the empty socket, and the unit is ready for testing. Level II gives you the expected MEMORY SIZE?, while Level I only reports 'READY'.

If you have the two-chip *Level II* ROM set, there's a bit more work to do. One ROM must be removed and piggybacked on the other, except for pin 20. Bend pin 20 out straight on ROM A (Z33), and piggyback it on ROM B (Z34). Run a wire from ROM A pin 20 to Z74 pin 9. Bend pin 20 out straight on ROM B (Z34), and run a wire from this pin to Z74 pin 12. Now insert your *Level I* ROMs in the socket for Z33.



Figure 4-13. Level I and II switch wiring (3-chip set).



Figure 4-14. Level I and II switch wiring (2-chip set).

Since these languages use memory and pointers in such a different manner (Level I is not by Microsoft, as I understand it), they cannot be switched from one to the other directly. You must power up to the language you want.

This can present a problem. If you have installed various speed and video modifications, you may get the mode you don't want. Level I, lacking OUT statements, can't recover from this. To avoid it, solder a wire to Z53, pin 12, and attach it to one end of a pushbutton; to the other end of the button, solder a wire to ground (Z53 pin 7 is fine for that). This is the system reset (SYSRES) signal, a true restart to 0000.

To use it, power up to Level II, get in the video/speed mode you wish using OUT statements, switch to Level I (the screen will likely display a mess of @9@9@9's), and press the SYSRES button. A READY should appear. Now dig back in the Level I manual to determine if the amount of memory reads correctly.



Two-chip Level I ROM set can be added by piggybacking them and soldering them together. Together with the snaking Level II cable, they form a surrealistic electronic landscape.

On Relocatable Code

A great noise is often made by programmers and users of the TRS-80. The clamor is for an elusive programming quality which allows code to be placed anywhere in memory and to function from that place. The cry is for relocatable code, but it is often called for without understanding either the process or the sacrifices it requires. In this section I will take a look at the various levels of relocatability, and the ways it can be applied in low-level languages.

The most 'relocatable' code TRS-80 users see is BASIC itself. No matter what configuration changes the system undergoes, whether they be the use of low-memory utilities, DOS, etc., a normal BASIC program will load and run. A BASIC program's portability depends on the premise that it is *interpreted*, containing statements that are equally meaningful irrespective of the program's position in memory. Occasionally that position gains importance, as when numerical variables, strings or arrays are referenced within program lines, but normally those positions do not become significant until the program is in operation.

Unless the BASIC program is truly a hybrid (having other, lower-level languages artificially embedded in the code), it is eminently portable. All references are resolved by its interpreter, and relocatability of BASIC is assumed in the very nature of it and similar high-level, interpreted languages. In fact, that is the nature of a real 'language' as we know it as opposed to the mysteries of 'code'.

The distinction between language and code is not an accepted one, and the differences will be characterized only for descriptive clarity within the context of this article. By 'language', I intend BASIC, FORTRAN, Pascal, and others, as well as assembly language. By 'code', I suggest machine code as written in binary or hexadecimal for direct insertion in memory. The assembly language/machine code interface is curious and I will address it in terms of the conflict between understanding and using a language as opposed to a code.

At the High Level

The highest levels of languages are the so-called 'descriptive' languages, like IBM's report-generator, RPG II. A programmer need only describe a group of tasks and the order in which they should be performed, and they will be magically executed. Full-dress accounting reports, billings, and record-keeping can be done with a language like RPG II. Relocatability is at best the task of a dour 'systems engineer'.

Likewise, BASIC normally requires no thought to its arrangement beyond the proper sequence of line numbers. Statements are arranged in the programmer's chosen order, and the interpreter selects each one for execution in that order. Line numbers are the programmer's relocatable reference. Languages containing no line numbers often use an implicit 'top-down' order; that is, once a task is completed, it is never returned to. Still, the program is created with an arbitrary arrangement selected by the programmer and evaluated by an interpreter before its execution.

Languages which use compilers rather than interpreters work in much the same manner. Whereas an interpreter selects and executes each command and operand during the program's run, a compiler produces a block of machine-coded information from high-level commands and operands. The process is completed before executing the program, so valuable space and running time can be saved. In either case, arbitrary, high-level language can be moved about, deleted, inserted, or otherwise altered with little regard for the program's ultimate position within the bowels of the computer.

In fact, the question of relocatability is implicit in the term 'high-level language', and is an essential of its high-level quality.

The reason the question arises at all is because, when writing machine-coded utilities, many programmers feel that emulating the portability of a high-level language is crucial. It becomes even more desirable when programming is done for a user rather than another programmer, a user whose contact with the machine may go little further than that of a traditional computer 'operator'.

Accomplishing relocation can be an easier task on the Model I than on other computers simply because of the extensive ROM-based operating system. Before examining some ROM uses (and its advantages and pitfalls), let's have a look at the qualities and constraints of relocatable machine code.

As a user interested in accomplishing a task, I might need to select from a group of utilities including sort routines, multiple-precision transcendental functions, mundane key-debounce and upper/lower case drivers, and so forth. Ideally, the order in which I select and load these routines should be irrelevant to their

operation, in much the same way that utilities can be 'ordered up' on a mainframe.

Microcomputer software authors have not generally respected this need; in some measure that is forgivable because the approach and intent of different utilities from a variety of vendors demonstrates that relocatability is only one of many potential conflicts to be resolved.

Hunting Through Memory

Nearly any well-written program is tailored to meet certain requirements which may not easily co-exist. Among them are:

Speed of execution. This applies in two ways. The first is the speed at which the *need* for the utility is evaluated - an example might be a routine scanning a keyboard for a unique combination of characters. This should be accomplished expeditiously, since no real program 'work' is being done. The second speed consideration is that, once called for, the main routine should complete its work handily.

Conservation of memory. In a system of unlimited size, speed can be optimized by replication of routines rather than use of subroutines. In appliance-level microcomputers like the TRS, however, support utilities cannot be allowed to consume memory space needed by the operation of the target program.

Resolution of Conflicts.
All operating systems make use of areas of critical reserved RAM, which are employed to tie together the major pieces of hardware and blocks of software. These patch points (I prefer this term to 'vector', which also means a disease-carrying insect) may be needed by many other utilities as well as the operating system, and must be redirected carefully.

ROMability. The traditional approach states that programs must be created so that they can be committed to ROM at any time. That is, they should neither modify themselves nor contain variable data within their bounds. This approach can certainly be argued against (I shall).

Three of these four elements – speed, size, and memory sharing – are normally considered in utility programming, and become critical in relocatable programs.

In addition, factors to be considered exclusively for program relocation are:

The placement of the program in memory. This can be a single- or multiple-step process. For example, during loading from disk or tape, a program may temporarily reside in a single block of memory, only to separate itself into smaller blocks which are shepherded to other memory fields. *Electric Pencil* is one such program.

Absolute jumps within a program. The program counter is instructed to take on a new value, a value specified as an address. Thesejumps are, when taken, faster than the relative branches, because the program counter need not calculate an offset to its current address.

(indent absorber)**Subroutine calls within a program.** Effective use of memory space makes subroutines very attractive, but they require that the program counter be assigned a specific new value for their duration.

A relocation block. If the program is provided to a user in object-code (SYSTEM) format, some portion of the program must be dedicated to relocating itself in another area of memory.

Assembly Programming

When programming for programmers, the most convenient way to effect relocatable code is to use assembly language, and supply that to the user. By labeling all jumps and calls, such a program becomes 'relocatable', somewhat in the sense that a program conceived in a high-level language is relocatable. In fact, in its assembly phase, machine coding is a high-level language.

```
        8000     ORG   8000
21003C  8000     LO    HL,3C00H
11003C  8003     LD    0E,3C01H
01FF03  8006     LO    8C,3FFH
3620    8009     LO    (HL),20H
ED80    8008     LOIR
21E942  8000     LO    HL,42E9H
7E      8010     LO    A,(HL)
A7      8011     ANO   A
C29719  8012     JP    NZ,1997H
C30043  8015     JP    4300H
        4300     ORG   4300H
C08843  4300     CALL  4388H
23      4303     INC   HL
```

Listing 4-5. Machine coding in assembly language.

Above is a section of assembly programming. It makes several assumptions, some valid and some not. Let's consider that this program has cleared the screen (which it would in the TRS-80

configuration) after having performed some operations on a BASIC program. It checks location 42E9, the start of BASIC, for a zero. If it does not find a zero, it assumes a syntax error. Otherwise, it moves to location 4300, where it immediately calls a subroutine at 4388.

This is perfectly valid code, but here's a look at another way of creating it in this high level language:

```
04XA FIGURE 2           SETUP   EQU     8000H
                        VIOEO   EQU     3C00H
                        SCREEN  EQU     03FFH
                        BASIC   EQU     42E9H
                        PROGRM  EQU     4300H
                        SYNERR  EQU     1997H
                        TESTER  EQU     4388H
                8000            ORG     $
        21003C  8000    SETUP   LO      HL,VIOEO
        11013C  8003            LO      OE,VIOEO+1
        01FF03  8006            LO      8C,SCREEN
        3620    8009            LO      (HL),20H
        E080    8008            LOIR
        21E942  8000            LO      HL,BASIC
        7E      8010            LO      A,(HL)
        A7      8011            ANO     A
        C29719  8012            JP      NZ,SYNERR
        C30043  8015            JP      PROGRM
                4300            ORG     $
        C08843  4300            CALL    TESTER
        23      4303    PROGRM  INC     HL
```

Listing 4-6. Machine coding in assembly language.

This assembly program, using its high-level, interpretive capabilities, can be easily relocated by a programmer changing a few equates. But it is not relocatable because it does not meet the criteria outlined above – i.e., it contains a specific origin (or rather, two), absolute jumps, calls to subroutine, and has no visible relocation block. Fortunately the start of BASIC has been defined in the table of equates, for it too can be a variable element where low-memory alterations have been made.

As a programmer's utility, this method is acceptable. As a public program, it is questionable. The solutions, however, are neither easy nor obvious.

Relocation Blocks, Time, and Space

The first option is to provide a relocation block. The amount of coding the programmer must perform is increased, but memory use is not affected because this relocation block can be deleted upon relocation. A relocation block is provided with Radio Shack's KBFIX, for example, and with other utilities. The sample above might have a relocation block which asks for a new base address in protected memory, protects that memory, adjusts its internal addresses, and automatically checks for the beginning of BASIC program storage and other patch points it may require.

For very short utilities, the relocation block may be longer than the utility itself, because it demands a user prompt and input, minimum error checking, calculation of base address, and adjustment of patch points. Even using ROM routines (such as 28A7 to display a message, 1BB3 to accept user input, 1E4A for numeric conversions), this process is lengthy.

One of the most painful aspects of this relocation is the adjustment of internal addresses; absolute jumps, calls, and table locations are among the addresses requiring such changes. Then what of the questions of speed and conservation of memory? Programs that move themselves during the course of operation must carry the excess baggage of a lengthy self-relocation block or use a plethora of relative instructions which can cost time during program execution.

Let's address these speed and space questions. Table I lists a number of the relative instructions in the Z-80 set, along with the bytes, machine cycles and time required for their execution. In contrast, Table II presents similar absolute Z-80 instructions, their execution speeds, and the percentage of time and space they require as opposed to the relative instructions.

TABLE I

Z-80 INSTRUCTION	BYTES	T-STATES	TIME AT 1.77 MHz
LO r, (IX+d)	3	19	10.7 uS
LO (IX+d), r	3	19	10.7 uS
LO (IX+d), n	4	19	10.7 uS
AOO A, (IX+d)	3	19	10.7 uS
INC (IX+d)	3	23	13.0 uS
RLC (IX+d)	4	23	13.0 uS
BIT b,(IX+d)	4	20	11.3 uS
SET b,(IX+d)	4	23	13.0 uS
JR e*	2	12	6.8 uS
OJNZ e	2	13	7.3 uS

When this instruction is conditional, and the condition is not met, it uses 7 **T**-states (3.9 uS).

Note:
'r' = registers A, B, C, D, E, H or L.
'd' = displacement byte 00 to FF
'n' = single-byte integer 00 to FF
'b' = bit position 0 to 7
'e' = offset byte 00 to FF

TABLE II

Z-80 INSTRUCTION	BYTES	T-STATES	TIME AT 1.77 MHz	% TIME & SPACE VS. REL. INSTR.	
LD r, (HL)	1	7	3.9 uS	37%	33%
LO (HL), r	1	7	3.9 uS	37%	33%
LO (HL), n	2	10	5.6 uS	53%	50%
AUO A, (HL)	1	7	3.9 uS	37%	33%
INC (HL)	1	11	6.2 uS	48%	33%
RLC (HL)	2	15	8.5 uS	65%	50%
BIT b,(HL)	2	12	6.8 uS	60%	50%
SET b,(HL)	2	15	8.5 uS	65%	50%
JP nn*	3	10	5.6 uS	83%	150%
JP NZ,nn	3	10	5.6 uS	77%	150%

When this instruction is conditional, and the condition is not met, it still uses 10 T-states, 3 more than the relative branch instruction. In programs where such a condition is generally not met, the JR e instruction will save both time and memory.

Note:
'nn' = two-byte interger 0000 to FFFF

Relative instructions in many cases command considerably more time than absolute ones. How does this reflect on program speed? The design engineers for the 6809 chip reported in *BYTE* a survey of 6800 instruction class usage based on static analysis (i.e., with the program not running) of 25,000 lines of source code. Because of the considerable differences in chip architecture between the Z-80 and the 6800, especially in regard to the Z-80's multitude of registers, this information (see Table III) is not directly applicable. Yet it is instructive, particularly in the percentage of subroutine calls and branches, instructions similar in the two microprocessors.

TABLE III

Use of 6800 Instruction Types

Loads (movement from register to register, and from memory to a register)	23.4%
Stores (movement from a register to memory)	15.3%
Calls and returns (absolute addressing)	13.0%
Conditional branches (relative)	11.0%
Unconditional branches (relative) and jumps (absolute)	6.5%
Others	30.8%

(Adapted from BYTE, 4:1, January 1979, p. 26)

A remarkable 30 percent of program space is dedicated to motion of the program counter. This might suggest that a program using absolute instructions would be 15 percent faster overall than one using relative branches and calls. Since relative calls and returns are complex, however (see below), the time savings might be even greater. Absolute jumps use more space than relative ones, so space savings, though significant, would not be as impressive.

What are the practical implications of this speed differential? A 1,000-byte subroutine (long by microprocessor standards) with no internal loops might execute in four milliseconds, as opposed to five milliseconds for such a routine written exclusively with relative functions. On the average, it might be 200 bytes longer. This means 200 iterations per second as opposed to 250. For a complex mathematical function which iterates through a routine many times, it could mean the difference between a four-hour and a five-hour run. For a patch to a keyboard scan, it could mean adding only a few seconds to an hour's program time. And for routines involved in occasional string handling, printing, low-speed input/output, error reporting, or a host of other applications, the loss of time is insignificant.

The application itself is the answer to the viability of relative coding. In time-sensitive applications (music-generation routines, for example), and where every byte of code is crucial, relative instructions can interfere with a program's effectiveness. In the bulk of TRS-80 applications, which are seldom so time-conscious, relocatable coding through use of relative instructions can be very successful.

Creating Relocatable Code

The Relative Branch. The first coding choice is the two-byte instruction for changing the program counter. No matter where the program counter is currently pointing, it can be shifted by specifying a relative branch. When the high bit of the specified offset is zero, the program counter is moved ahead (for example, 18 37 adds 37 to the program counter). When the high bit of the offset is one, the program counter is moved back, in effect subtracting 80 before adding the offset:

```
   5236         5236        :     5236          5236
   + 00         + 80        :     + 7F          + FF
   ----         ----        :     ----          ----
   5236         5186        :     5285          5235
 (5236+0)  (5236-100+80)    :  (5236+7F)   (5236-100+FF)
```

Especially gratifying is the notion that the page of the address (the high byte) is incremented or decremented automatically by this instruction:

```
PC = 52C5                    (page 52)
Execute 18 37
PC = 52C7+37 = 52FE          (page 52)
Execute 18 37
PC = 52FE+37 = 5335          (page 53)
Execute 18 A7
PC = 5335+CA = 52FF          (page 52)
```

The branching can be done unconditionally, or on the basis of the zero or carry flags (JR, JR Z, JR NZ, JR C, JR NC). This does not provide the options available when using the absolute jump (which can act on the status of the parity and sign flags), and thus presents additional coding demands.

A special relative branch instruction, DJNZ e, automatically decrements the B register, and performs a branch to the indicated offset whenever B is not decremented to zero. Although this instruction can have many uses, its two-byte brevity makes it most attractive when executing loops.

The problem of branches outside the range of the **+7F/-80** byte offset can be solved by inserting 'stepping stones' in the main program flow. At the end of any logical program section, two unconditional branches may be inserted: the first branch serves to skip past the second branch to prevent disturbing the program flow in that area. The second serves as a stepping stone for some branch which is too far (more than 127 bytes) from its eventual destination. The program can be ordered judiciously so as to avoid overusing such memory-gobbling stepping stones.

Indexed Addressing. One of the best features of the 6500 and 6800-series CPUs is their ability to address and manipulate memory without continually reloading a register or using an absolute address in an instruction's operand. In fact, using these processors would be incredibly cumbersome without this mode since they contain merely two storage registers (X and Y) as opposed to the Z-80's sixteen (B, C, D, E, H, L, B', C', D', E', H', L', R, I, IX, IY).

The value of the indexing features was recognized by the Z-80's designers, who added them to the 8080's primitive instruction set. As with relative branch instructions, a single-byte offset may be added to the value specified by registers IX or IY in order to produce the address of the desired memory location:

```
             IX = 6AA1      IX = 6AA1      IX = 6AA1
                  + D1           + 7F           + A1
                  ----           ----           ----
resulting
address:          6AA2           6B2D           6A42
```

The address of the index registers themselves does not change; the resultant value is stored in temporary internal Z-80 registers while an instruction is being executed. For example, when **IX = 6AA1** and the instruction –

```
INC     (IX + A1)
```

– is specified, the CPU temporarily creates the resulting address **6A42** and increments its contents. The value **6A42** itself is then discarded.

When a desired value is outside the range of an indexed register, the instruction ADD IX,pp comes to the rescue. The designation 'pp' is for any of registers BC, DE, IX or SP, which can be assigned specific values representing a full 16-bit offset, rather than the 8-bit offset of the indexing itself. For example:

```
        IX = 57EB
        DE = 41CC
Execute ADD IX,DE
        IX = 99B7
        DE = 41CC
```

Since it is an offset rather than a specific address, and since it remains unchanged after the execution of ADD IX,pp, it becomes a perfect candidate for use in relocatable code.

Instructions using the index registers can be particularly valuable when lookup tables must be accessed again and again. With these commands, any registers used as pointers may remain unaltered; they need not be redefined each time the lookup routine is used. An excellent application of the index registers for five-character string comparisons is found in William Barden's *Z-80 Microcomputer Handbook*.

Relative Subroutines. No, there aren't any secret relative call-and-return instructions that Zilog never told us about. Rather, there is a way to create the effect of a relocatable call by using an index register in combination with relative branches.

This method was detailed in my article, 'Relative Subroutines for the Z-80', *BYTE*, 4:12, December 1979. It is a bit cumbersome at first, and makes it impossible to produce 'ROMable' code. In summary, here is how it works (see also Table IV):

1. An index register is set to some point in the program. This becomes a reference point.
2. The call is prepared by determining the offset from the *end* of the subroutine *back* to the main program flow.
3. During program execution, the offset is assigned, (using the indexed instruction LD (IX+d), n) as the *operand* of a relative branch placed at the *end* of the subroutine.
4. A relative branch is executed to the beginning of the subroutine.
5. When the subroutine reaches the end of its execution, it moves back to the program in progress.

TABLE IV

Relative Subroutine Flow

```
7000    0021B070     LO    IX,7080   :IN PROGRAM AREA
7004    ............< MAIN PROGRAM HERE >............
7006    ............< PROGRAM CONTINUES >............
 .
 .
7040    00360BBF     LO    (IX+B),BF ;RETURN OFFSET
7044    1820         JR    $+22      ;JUMP TO SUBR.
7046    ............< RESUME PROGRAM HERE  >........
7047    ............<  PROGRAM  CONTINUES  >........
 .
 .
7066    ............< SUBROUTINE IS HERE   >........
7067    ............< SUBROUTINE CONTINUES >........
 .
 .
7087    1880         JR   $-41       ; "RETURN" INSTR.
        < NOTE THAT "BO" IN OPERANO ABOVE WAS PUT
          IN PLACE BY CALLING PROGRAM AT 7040. >
```

This method requires careful program preparation in that the beginning and end of each subroutine must be within the range of the calling program, and the offset to IX or IY must be within the range of the end of the subroutine. If the offset is outside the range of these registers, a 16-bit offset can be created as described above under indexed addressing.

There is another option to create relative subroutines using the Z-80, but it is not time-effective. This involves a ROM call to **000B**. *Jerry Lindsly* of West Chester, Ohio, describes it this way:

When faced with the problem of relocatable code when using subroutines . . . you can use a very useful routine in ROM. Essentially what it does is this:

```
POP  HL            ; Get return eddress to HL
JP   (HL)          ; Return to calling program
```

So after you call **000B** the PC is in HL. A relative call is a little more complicated:

```
CALL     00BH
LO       OE,0BH
ADD      HL,DE
PUSH     HL
LO       OE,NNNN ; Offset from first byte
                   pest JP (HL).
                   Use XOR A and SBC HL,OE
                   if the call is negative.
AOO      HL,OE
JP       (HL)
```

(Those interested in the various uses of this routine may write to Jerry at 8106 Quailwood Court, West Chester, Ohio 45069).

One could use the equivalent to such a ROM call in the program itself. This might be desirable. Certainly, if programmers had not learned it over the past two years, then the recent ROM changes (and expansions in the Model III) might dissuade overuse of calls to the Level II ROM.

5

How the System Expands

Unlike automobiles, refrigerators, or shovels, computers are hardly ever completely self contained. Even if their manufacturers pretend they are making a complete unit, the machines themselves seem to desire bursting forth from their shells, commanding us to create a tabletop electronic octopus.

The reasons almost sound metaphysical: it needs more memory; it needs communications capabilities; it needs mass storage; it needs hardcopy . . . to achieve these goals, expansion capabilities were made available for the TRS-80 by means of an electronic hodgepodge called an Expansion Interface.

The Radio Shack Expansion Interface

The Radio Shack interface originally consisted of eight major sections :

1. An extension of the keyboard's edge-card connector, initially reserved for a screen printer, but containing all the signals on the keyboard's connector.
2. Two groups of eight sockets, together with address decoding, to read and write two 16K banks of dynamic memory.
3. A decoded input/output latch for parallel printer control. A 'Centronics compatible' electronics scheme is used, with a separate edge-card connector dedicated to the printing task.
4. A set of decoded memory addresses and a LSI (large scale integration) chip for disk drive and input/output control. The disks are accessed through an independent edge-card connector.
5. A decoded output latch for dual cassette selection and control. One input and two output jacks are integral to this circuitry.
6. A decoded, input/output port for serial communications control, with accompanying terminal for an RS-232 circuit board. The RS-232 board is accessed via a separate edge-card connector.
7. A crystal and divider circuitry to provide disk access, real-time clock, and other interrupt functions.
8. Power supply circuitry.

If it seems like a lot of unrelated material to pack into a single box, then you're on the right track - the track that, for quite a while, meant trouble. The electronic clamor inside this box was to create a system-crashing din during the first year or so of expansion interface manufacturing.

The problems were manifested by memory crashes (return to MEMORY SIZE?, keyboard lockup, or, in a disk system, complete reboot and so on). There were several culprits, but the gangleader was the misconceived design itself. Putting all that material on a single board was inviting trouble, and the actual execution of the circuitry compounded it. The main difficulties

were memory refresh/select, noisy and dirty connectors, weak buffering lines, microphonics, and susceptibility to external interference.

The memory refresh/select lines were noisy and unreliable. The purpose of the refresh lines is to read the entire memory in intervals of two milliseconds or less. The memory-select lines provide the signals to select one of the 65,536 possible addresses when needed by the CPU.

In many computers, selecting a memory address is a fairly straightforward process. The CPU signals a memory request of some kind, and provides an address on the address bus. The selected memory responds by providing or accepting data according to the direction of the CPU. On the TRS-80, however, type 4116 dynamic memories are used. These memories do not have enough external pin connections to accept a complete memory address. Instead, hardware breaks the address into two parts, which are transferred sequentially.

Briefly, this is how it works. The address is sent out on the address bus. The CPU also provides a 'memory request' (MREQ) signal which triggers special circuitry. This special circuitry stands between the address lines and the dynamic memories. This circuitry produces a multiplex signal - MUX - which chooses the low seven bits of the address. It then sends those bits together with a 'row address strobe' - RAS - to the memories and reverses the MUX signal to choose the high seven bits of the address. Then the special circuitry sends those bits together with a 'column address strobe' - CAS - to the memories.

This sequence of operation provides all the address information needed by the dynamic memories to select an address. The three items most crucial for smooth memory action are the RAS, CAS and MUX signals, and as such, these should be clean, noise-free lines. Within the confines of the keyboard unit, this is the case. But once forced to travel through a cable (via two solder-coated edge connectors) into the expansion interface, the signals pick up some measure of noise. Once inside the expansion box, the noise is increased by the surrounding electronic din (remember that a separate crystal is onboard), and the requirement that these signals feed many other devices reduces their effectiveness. They become electronically tired, and memory access becomes erratic and susceptible to external electrical influences.

Thus, memory selection was impaired and memory refresh was not necessarily executed successfully in less than two milliseconds.

The next culprit in the expansion box was the lack of 'buffering'. In the *Technical Reference Handbook*, the author points out that among the requirements for hardware are that it :

> 4. *Contains a separate power supply.*
> 5. *Does not contain more than 1 LS TTL load on any one output from the Computer.*

Points 4 and 5 are very important, if you want to guarantee proper operation of your Computer.

Radio Shack, not taking its own advice, hangs *five* LS TTL loads on data line 0, and four on each additional data line. If an RS-232 board is installed, that becomes another load. The address lines feed as many as three devices. With a screen printer or other device connected to the expansion interface this load increases, respectively, at least once for each additional device attached!

The third system-crashing factor is an unusual one, avoided by good circuit board layout, but not always anticipated. This is covered by the rather unusual term *microphonics*. In other words, when the expansion box circuit board is tapped or vibrates, those vibrations are amplified and communicated throughout the entire circuitry by the power supply, data and address lines.

The keyboard unit can take a hefty bounce. If you're brave, give it a try by dropping it six or more inches. Chances are a running program won't crash. But rap sharply on the expansion box with the program running, and . . . you can guess. These strong pulses are not in the high-frequency range which the 'bypass' capacitors (the small disc capacitors scattered throughout the computer) can squelch; rather these are heavy, low-frequency surges which can be electronically interpreted as signal changes. Hence, the crash.

Finally, the electronics, being spread out in a plastic case, are subject to the electrical whims of the outside world. Seated directly below the video monitor, the expansion box is susceptible to any strong noises contributed by the monitor, or through the power lines and rebroadcast by the monitor's circuitry. Printer heads and motors, disk drive motors, and what have you all let the expansion box know they are operating. So it responds by crashing its sensitive and overworked memory circuits.

Several solutions have been created. The first was that bulge between expansion box and keyboard unit: the buffered cable. The second was the 'twisted pair' modification, another bulge between the boxes. The last was a

rethinking of the expansion circuitry and redesign of the board. The last was the only one that worked.

The idea behind the buffered cable was sound - to strengthen the overworked signal lines by having them feed a single integrated circuit each, and then have that integrated circuit feed the expansion box. Furthermore, 'termination resistors' could then be added, which work something like this: power supply lines contain bypass capacitors to squelch noise, but placing capacitors on the signal lines would slow down important signals as well. Instead, low-value resistors could make the signal lines 'hug' the power supply and ground lines, increasing their resistance to low-level, transient, electronic noises.

First installation of buffered cables were less than successful, partly because the three memory-select signals were very fast signals delayed too long by a combination of buffering and transmutation inside the expansion box. Thus, these lines were pulled outside the 40-pin cable via a three-pin DIN connector, separately terminated. This kept them up to speed, but isolated them from the accompanying noise.

Nevertheless, these modifications were only making up for difficulties inherent in the expansion box design, and could not improve the box's susceptibility to noise all around, or its microphonic tendencies.

The solution was to put the buffers on board the expansion interface itself, and redesign the board to reduce interference. New memory-select lines were created by the RAS line alone to eliminate noise in these signals, but the method used was to create problems concerning speed modifications (which, of course, Radio Shack did not authorize and could not consider in its redesign - see the way out of this problem later in this Chapter).

These difficulties, though, should be placed in perspective. When connectors are well cleaned, good memories are used to stock the expansion box, and the computer's environment kept clean, static-free and vibration-proofed, even the first, unbuffered systems work successfully. My own system (on which this book is being prepared) is a 48K, one-disk system with RS-232 board, printer, two modems, *Exatron Stringy Floppy*, two cassettes and home-brew interfaces - all connected to an *unbuffered* expansion box of early vintage. But it must be cared for. The designers were simply not prepared for the TRS-80's ultimate home and business environment.

One increase in reliability is not mentioned in the Radio Shack redesign. Electronic parts are 'derated' according to temperature. That is, as temperature increases, their performance decreases. Some circuits, like 74LS types, are strong and steady right to the limit; others, particularly dynamic memories, become flakey as the heat builds up. Thus, reliability of the expansion box can be improved by removing the two power supply transformers from the expansion box.

Solving the Ground Problem

I call this a ground problem, but it really refers to the microphonic tendency of the expansion board. The first and easiest solution is to remove and cushion the expansion circuit board. One principle of vibration-proofing is that when different materials are sandwiched together, a certain amount of sound and vibration energy is reflected back from the junction of the different materials.

Thus, all sources of potential vibration should be cushioned. Set a thick cloth (like terrycloth) on your computer desk, and a wooden baseplate atop that. On it, place a mat made up of several thin layers of plastic pad, rubber foam, and cloth to a thickness of about 1/4 to 1/2 inch. Assure that the keyboard unit and interface seat comfortably in them (you might drill shallow depressions in the wood for stability), but that there is some air space for cooling. Remove all the plastic doors which attach to the interface and discard them. In their place put rectangles, made of alternating layers of cork and styrofoam, which snuggle firmly between the connectors and the upper and lower walls of the case. See Figure 5-1.



Figure 5-1. Shockproofing diagram.

Other sources of vibration are the cables that attach to the expansion box. Rather than have cables vibrate and swing with a printer, or stretch when you readjust the position of a disk drive or modem, sandwich each one under a leather (or synthetic plastic, if you prefer) bridge, and screw



Photo 5-1. Photos on opening the expansion box. Screws are removed from bottom; note that like the CPU, a warranty-warning label may cover one screw.



Bottom is lifted off to reveal top of expansion circuit board. Screws holding circuit board are then removed.

the ends of this bridge through the cushion pad into the wooden base. When jostled, the cables should not move between the bridge and the expansion box.

Finally, avoid the possibility of stretching the keyboard/expansion box cable. The best way is to drill shallow depressions in the wood base, as noted earlier.

These are not specifically electronic hardware corrections, because only a thorough redesign of the expansion interface can truly cure these microphonics problems.

Expanding to 32K and 48K Memory

Memory expansion in the interface itself is quite simple. Remove power from the interface, disconnect cables, and lift out the power supply transformers. The latter action is necessary because the power supplies will only fall out anyway when the bottom comes off. Flip the expansion box over, and remove the six black Phillips screws. Lift off the bottom cover.

There are sixteen unfilled sockets on the board, reserved for memory expansion (see Photo 5-2. The *higher-numbered* sockets (Z-9 to Z-16 will be used for the first block of memory, for a 32K total RAM. The lower-numbered sockets expand the system to the complete 48K.

The memories to be used are type 4116, as used in the keyboard unit (see Chapter 4). There are some differences, though. Oddly, some sources claimed that slower memories seemed to work better in the older interfaces, but fast 250 nS RAMs are the most commonly available now. I have not come across an expansion box of any vintage that could not take fast RAMs like these, including my own, which dates to early 1978.

First, refer to Chapter 3's notes on handling static sensitive integrated circuits. Take each RAM and orient it with its notch or dot at the top facing in the same direction as the notch in the sockets (and in the same direction as the rest of the integrated circuits on the board). Fit each one of the first eight chips carefully in place, being sure that the pins slide into the sockets and neither buckle underneath the IC nor slip outside the socket edge. Press the memory chip gently but firmly in place.

Now, before installing another 16K memory block, test this group. Flip the expansion box over (the cover need not be installed), reconnect cables and power supply, and power up the expansion box. While holding (BREAK), power up the computer itself, and press (ENTER) in response to MEMORY SIZE. Now PRINT MEM, and a figure of 31956 will be displayed. If all is well, power down, remove cables, and

insert the remaining eight memory chips. Again restore cables and power, and go through the initialization procedure. Memory should now read 48340. Replace the cover and cover screws, and you're set with an expanded system.

Problems? If there are any, they will likely fall into these categories:

1. PRINT MEM returns 15572 or some figure much below the expected 32K value.
2. The system continuously crashes back to MEMORY SIZE? or just locks up. This happens most often while running any program.
3. The system just locks up with garbage on the screen at power-up.

Well, the last first. Don't forget to hold the (BREAK) key down at power-up in a non-disk system. The other two are tougher.

If PRINT MEM returns 15572, you might have installed the memory incorrectly. Keep booting (press the Reset button while holding down (BREAK)), and hitting (ENTER) in response to MEMORY SIZE? PRINT MEM, checking over and over. If a figure higher than 15572 is ever returned, you might have expansion box problems.

Try entering a number between 15580 and 32700 in response to MEMORY SIZE?. If it is ever accepted, chances are you've got the memory chips installed correctly. Try POKEing and PEEKing, like this :

```
POKE 25000,100 : PRINT PEEK(25000)
POKE 26000,103 : PRINT PEEK(26000)
```

and so on. If the value you POKEd is the same as what you PEEK at, the memory is there, but it's not acting reliably. Here are a few solutions (see also the expansion box general solutions above) :

1. Clean cables, connectors, etc., and shock-proof the unit.
2. Remove the buffered cable if you have one, and replace it with a regular one. *Before you do this*, open the expansion box and find pin #1 on the edge connector. Cut that trace, or remove the wire you see there. This is the 5-volt power supply to run the buffering box. The matching pin on the keyboard unit is a ground!
3. If you have a newer expansion box, make the high speed alteration noted above, although you shouldn't be having these problems with the new box.
4. You actually might have some flawed memory chips, though this is unlikely. Switch those in your keyboard unit with those in the expansion box, and see if the problem goes away (or the keyboard unit doesn't work now). Run the memory test (Chapter 3) to find out which chip(s) may be bad.



If RS-232 board is in place, the two screws holding it must also be removed.



Entire expansion card lifts out easily.



Photo 5-2. Expansion interface memory sockets. 32K memory fits into sockets Z1 through Z16. Oddly, Tandy engineers did not install power supply filter capacitors C54 and C55, nor are they included in the schematic drawing.

5. Make the small change to Z69 in the keyboard unit, as described in the 200% speed-up modification.

The options are few when dealing with an older expansion box. They will work, but you have to provide them with ideal conditions. Which points out the solution to the possible program crashes noted in problem number 3 above. Pamper the expansion interface when a program is running. Don't have the kids playing kick-the-cat near the computer, or the dog jumping about and thumping a large tail next to you, waiting to be fed. Keep the washers, driers, and mixers in the vicinity switched off.

Speeding Up Newer Expansion Boxes

Radio Shack's cures for the memory refresh/select difficulties in the expansion interface created a new problem for those who wish to increase the speed of the computer. All three select lines (RAS, CAS, and MUX) are not used in the revised expansion box; instead only RAS is used.

Technically, the RAS line is sent thrice through an inductance network which provides three differently delayed doppelgangers of the original signal. These are tweaked back into digital shape by a buffer circuit, and the three are labeled MRAS, MMUX, and MCAS. The ploy works.

Trouble is, these lines don't care about the speed of the central processing unit. Fast or slow, the false MMUX and MCAS signals trip along at a fixed rate after MRAS. The only cure is to somehow speed up that rate and buy fast, high-quality memory. The speedup is accomplished by *not* delaying the RAS to produce MRAS, and creating MMUX and MCAS in the old MRAS and MMUX positions, respectively. The faster memory (200 nS) is up to you.

To provide the speedup, you'll need to cut some traces and run some wires. Remember, this adjustment is for newer expansion boxes only – the ones that the sales clerk says "don't need the buffered cable". Here is the order :

1. Find Z37 and Z38.
2. Cut the trace leading from Z38, pin 9. Call the end furthest from Z38 'Trace A'.
3. Cut the trace leading from Z38, pin 8. Call the end furthest from Z38 'Trace B'.
4. Cut the trace leading from Z37, pin 4. Call the end furthest from Z37 'Trace C'.
5. Attach Trace A to Z38, pin 11.
6. Attach Trace B to Z37, pin 4.
7. Attach Trace C to Z38, pin 9.

The modification is complete. Close the box and power up again; the system should work normally (if not better as time goes by). Both higher speed modifications presented in Chapter 4 will work with these changes, so long as your memory is the faster, 200 nS type. If the memory seems at all unreliable, double-check your work. If the work is fine, then your memory may not be up to the change.

LNW, Microtek and Other Expansion Interfaces

The first of the TRS-80 products to be attacked, and rightly so, was the flakey expansion interface. By the time Radio Shack was offering its initial hopeless 'fixes', a trio of Californians were redesigning the box for their colleagues in a TRS-80 user group. This was to become the premier challenger to the expansion interface, the LNW System Expansion, priced at a mere $70 for the bare board, circuit diagrams, parts placement, and a few additions to the Tandy system.

The LNW System Expansion is essentially the Radio Shack expansion interface with a new

Using Those 4K Leftovers

Did you insist on keeping the 4K RAMs which were removed from the keyboard unit when your 16K RAMs were installed by Radio Shack? Or did you do the installation yourself? If so, you've got 4K of dynamic memory worth about $20 off the shelf. But the trouble is you can't use them in your expansion box, because it's set up for 16K memories only.

But, if you want to spend a bit of time and can't afford an expansion interface, you can extend that PRINT MEM to 19668! Almost everything is in place already, so all you need is an address decoder and multiplexer circuit.

The circuit presented below can be wire wrapped on a small board, and will provide that extra 4096 bytes. The cost? About $5 for circuits and sockets, another $5 for an edge connector (use the *Texas Instruments* wire wrap type sold by *Digi-Key*, part number C6-20), and some time.

When you begin to fill your expansion interface, though, you'll have to give up the 4K RAM extension, because the first block of 16K memory in the box takes those memory addresses.



Figure 5-3. 4K dynamic RAM add-on circuit.





Hefty power supply includes fuse and multiple heat sinks, unlike TRS model with inaccessible fuse and light heat sinks.

layout, on-board buffers (which appeared finally on Radio Shack's own product in the spring of 1980), standard RS-232, and noise-reducing passive bus termination. This last was of particular importance in making the LNW board noise-free and consequently crash-free.

As with the Radio Shack expansion, the LNW board has sockets for 32K additional RAM, but also suggests that sockets be used for all parts – good advice, especially since chips such as the open-collector buffers used in the disk line driver need occasional replacement.

This board is also modular in a way that the complete, boxed interface from Tandy could not be. Only as much as the user needs at one time may be installed. Thus, the $25 disk controller chip can be left out of the system until (or if) a disk drive is added; so also the disk's peripheral chips can be omitted. Where interrupts are not desired, the entire crystal controlled clock can be excluded. Less than $150 gets the user a bare-bones 32K memory expansion.

The trick to the LNW board is dexterity. This is not a project for total novices, because it involves extensive soldering and some



LNW Expansion compared with TRS-80 monitor. Board is 0approximately the same size as standard TRS expansion interface.



Communications are built into LNW expansion; TR1602 UART provides serial capabilities. Note clear marking of all parts, including an industry part number at the UART socket.



Virtually complete LNW board in use. User has added programmable baud rate generator (bottom right) in place of hard-wired jumpers recommended by LNW Research.

knowledge about what the parts look like. There is no Heathkit-style check-off list. You get a parts layout, schematics, and encouragement. But you also get a noise free, reliable expansion interface.

For those who plan to build (or have already built) the LNW board, a few changes might be in order. If you wish your reset button to work, you must not only make a change similar to that for the Radio Shack expansion box, but you must also change the values of the pull-up and pull-down resistors. Change the pull-up resistors on the data lines to 470 ohms, and the pull down resistors to 680 ohms. This will provide the desired 11111111 signal when the reset key is hit and the disk buffer-disable modification has been made.

To make the mod, turn to the expansion interface reset recovery presented in Chapter (?), and follow those same directions, but using the integrated circuit on the LNW board marked U19.

Special Section: Two Other 80s

The PMC-80.

As production of the TRS-80 Model I was winding down at Tandy, the rumored 'Hong Kong Copy' made its appearance in the United States, under the name PMC-80, and sold by Personal Microcomputers, Inc., of Mountain View, California.

I was personally ready to greet the PMC-80 with much skepticism, expecting a weaker TRS-80 with little to commend it and a lot to avoid. But, tacky advertising aside, the PMC-80 is a functional, satisfactorily designed product. In fact, because of the experience of the original '80 itself, this copy is probably better designed than Tandy's product. That's probably an indirect compliment to both Fort Worth's foresight and Microsoft's Level II BASIC, which the PMC-80 contains virtually byte for byte.

First, the obvious similarities :

1. Z-80 microprocessor running at 1.77 MHz.
2. 64 x 16 screen resolution, with 128 x 48 graphics.
3. Video monitor output compatible with the Radio Shack monitor.
4. Microsoft Level II BASIC in a 3-chip ROM set and standard type 4116 16K memory.



Photo 5-3. *The Z-80 CPU — Used in the PMC-80.*

And then, the differences :

1. Built-in cassette player with no level control necessary, with provision for two via a second cassette jack already in place.
2. Video RAMs are in sockets, all seven are installed for lower case use, and an industry-standard character generator is used. Lower case is not provided, but is available.
3. An oversized, well-ventilated power supply feeds the system.
4. Channel 3 RF video is provided, along with a connector cable and adaptor.
5. Keyboard has a cassette motor on/off control, but is missing clear and right-arrow keys. These can be installed by the user on some machines.



Complete PMC-80 system can include CPU unit with cassette, printer, expansion box, monitor, and disk drives. Photo courtesy of Personal Micro Computers, Inc.

6. An odd 32-character mode, selected differently (with a switch). Instead of alternate letters in video memory, the 'left half' of video memory is used. Normal CHR$(32) is shown instead as normal-size letters appearing alternately on the screen.

7. The keyboard types easily, with no evidence of keybounce.

8. The expansion connector is gold-plated, but the inter-board and keyboard connectors are just solid wires pushed into receptacles. Heavy duty relays are used for the dual-cassette I/O.

9. The gold-plated expansion connector, alas, is not a TRS-80 compatible 40-pin type. The PMC-to-TRS adaptor is an option.

Are the TRS-80 and PMC-80 software-compatible? From what I can tell after running both BASIC programs and machine language utilities employing calls to ROM: yes, with minor reservations. First of all, the missing clear and right arrow keys are a downright pain; users of programs such as Scripsit or the Penmod version of Electric Pencil are back in the good old days of having to add keys to the system to get these programs to work.

Major ROM calls, though, seem to be intact, so there's little worry about compatibility there. The only programs that seem to get lost are those that call inside routines, or that call partial routines in ROM. BASIC runs flawlessly, as do mixed BASIC/machine programs.



Inside the PMC-80. Keyboard, two electronics boards, cassette player, and power supply are attached to the baseplate. Multiconductor wire jumpers plug in place.



Keyboard connector attaches to main board via a removable cable, a distinct improvement from the permanent TRS-80 cable. Note Z-80 CPU underneath cable.



Hefty power supply provides drive for computer electronics as well as a separate supply for the cassette recorder. Fuse is user-replaceable, in a standard socket.

Other comments :

The video display is cleaner, and the letters are better formed, prettier, and with no touch of blurring, even on the inexpensive TRS-80 monitor. They are quite similar to the better quality characters of the TRS-80 Model III. The lowercase option was not installed in the unit I used, but since it uses the standard character generators and has a clean video output circuit, similar well formed letters can be expected.

Cassette input/output is sweet. Problem programs loaded easily with this system. The playback of the cassette deck is digitized with LM324 comparators instead of 3900 Norton amps, and so the digitization is more successful.

The overdesigned power supply shows every sign of providing plenty of surplus current. There is no need for power supply adjustment in this system, because in place of the adjustable 723 regulator used in the TRS-80, fixed 7812 and 7805 regulators are employed.

The unit, though heavier than the TRS-80, is more complete in the sense that it has a built-in cassette player and RF video output. For traveling, the PMC-80 makes much more sense, because a video monitor can be used in long sessions at home or office, and an ordinary television can be used at other times. The case is tacky, especially the fake walnut grain plasticoid sides, but then the down-to-business futura TRS-80 was no great aesthetic shakes, either. The keyboard is placed at a comfortable angle, and the added weight and size gives the unit a more responsive typing feel.

The LNW-80 Kit.

This is a welcome newcomer, providing the advantages of the Model I with LNW's well respected circuit board. As with their system expansion, this LNW board is sold naked. The user contributes the parts as required.



Under the keyboard is the complete electronics control.



CPU control card contains 3-chip Level II ROMs, 16K dynamic memory, and power supply. Circuit board design isn't pretty, but is very reliable.



Video display card includes 7-bit video memory (unlike original TRS-80 6-bit memory), industry-standard CGR-001 character generator, RF modulator, and sockets for video memory chips.

CPU Interruptus

The interrupt is a programmer's mystery tool. On large machines the interrupt controls are so sacred that they are available only to the system engineers. Without a password, assembler commands directed toward interrupts are generally ignored.

TRS-80 users might have in mind some dreams of the Z-80's interrupt power. They've heard of it. Allusions have been made to it. Yet because it operates outside familiar programming bounds, it is even now a mystery.

Furthermore, this may be one of those cases where the Tandy engineers seriously erred in the concept, (rather than in the design, which problems we know all too well). The inclusion of additional interrupt power could have been done for pennies.

Whatsis?

The activities of a computer program can be viewed in relative rather than real time. In other words, a computer performs its tasks in the order that the programmer has chosen, with a timing that is inherent to the oscillations of the computer's master clock. Change the spacing of those oscillations, and the absolute time – the time with respect to 'real' time – changes, yet the relative time within the computer program is still the same.

Unfortunately for timekeeping purposes, changing either the clock of the computer, or changing the way in which the computer handles its tasks, may actually cause a shift in the real time reported to the user. An interrupt, then, is electronic shoulder tapping, the ability of a device external to the microprocessor and its respective memory to demand the CPU's attention for imperative tasks. For example, an external pulsing clock says to the CPU, 'Okay, I don't care what you're doing, stop it now and take care of updating of the real-time clock.'

Such is the simplest use of an interrupt. And, for a change, the computer jargon term is true to its actual purpose. It interrupts the operation of the central processing unit, demanding attention.

An interrupt is akin to a ringing telephone. As long as you are within earshot, the ringing of the telephone interrupts your activity. Whether you choose to respond consciously to it is irrelevant to the actual interruption. If you can hear, and if you are within hearing range of the bell, it does

indeed influence the activities of your nervous system.

How you respond to that ringing telephone – whether you ignore it, whether you go to it and answer it, or whether you merely swear at it – is what might be called, in computer terms, 'servicing the interrupt'.

The Z-80 microprocessor contains a wide range of ways in which an interrupt may be acknowledged, received, or serviced. You respond to a knock, doorbell, telephone, child's cry, or gunshot with various levels of urgency. If more than one were to occur about the same time, you would be forced to mask out the one of lower priority and give your attention to the more pressing interruption.

Before describing the ways the Z-80 microprocessor might respond to an interrupt, it should be noted that an interrupt is uniquely different from the computer's usual input/output schemes, just as the ringing telephone or gunshot are considerably different from checking the color of a traffic signal as you approach it; inspecting the mailbox as you arrive home; or scratching the cat.

In these analogies, your ears most often serve as your human interrupt line. As long as they are 'in the circuit', they will interrupt you. You can close your eyes to the traffic signal, ignore the presence of the mailbox by averting your glance, or cold-shoulder the cat (at your own risk), but (lacking earflaps), sound will give you an appropriate kick in the eardrums.

Back to the Z-80's interrupt schemes. During a movie, were someone to yell "Fire!", chances are that everyone – barring suicides and existentialists – would respond to that interruption with their personal interrupt service routine. Most likely that routine would be to leave the theater quickly.

An equivalent reaction by the Z-80 is produced by a signal applied to its 'non-maskable interrupt' (NMI). This interrupt is always acknowledged. The CPU cannot ignore it. On the TRS-80, it is this interrupt which is activated when the Reset button is pressed.

The NMI is hard-wired into the system in such a way that we have no control over it, so that if these sentences were a program . . .

```
READY
>_
```

. . . and not only that: the execution of a HALT instruction produces a 'Halt Acknowledge' output signal which the Tandy Engineers have OR-gated with the NMI to ...

```
READY
>_
```

. . . yup, you guessed it.

Contrarily, the Z-80 has a maskable interrupt (INT). It is an interrupt line which, when activated, may either be ignored or acknowledged by the processor if the programmer has so specified.

Because their activities are not fixed, these maskable interrupts are the ones of interest to us. Although, as I've said, the Z-80 was designed with a wide range of interrupts, that wide range is not accessible to TRS-80 users because the Tandy engineers did not design the TRS-80 in a way that could make those interrupts available.

Nevertheless, here is a look at the Z-80 interrupt modes.

Mode 0. This mode allows the interrupting device to place a machine language instruction directly on the data bus. The CPU will then execute that command rather than the next instruction in the normal program flow. Designers of the Z-80 suggest that a restart (RST) instruction be used.

Restarts have been covered in *The Alternate Source* and other publications, but briefly, they are single byte subroutine calls especially designed for this kind of interrupt operation. Normally, subroutines require specification of a CALL instruction (CD) and two absolute address bytes. The RST instruction is a single byte command causing the CPU to stash the program counter on the stack and move to one of eight locations in low memory.

Mode 1. Upon interrupt, this mode forces the CPU to preserve the program counter and then move directly to location **38**.

(line to absorb indent)
Mode 2. This is considered the most powerful interrupt response mode of the Z-80 because "the programmer maintains a table of 16 bit starting addresses for every interrupt service routine . . . When an interrupt is accepted, a 16 bit pointer (is) formed to obtain the desired interrupt service routine address from the table. The upper 8 bits of this pointer (are) formed from the contents of the I register. The I register must have been previously loaded with the desired value by the programmer. The lower eight bits of the pointer must be supplied by the interrupting device...." (from Z-80 Technical Manual).

Before you permit excitement (or even a raised eyebrow) about the last interrupt mode, it should be pointed out that neither Mode 0 nor Mode 2 may be used on the TRS-80, for this hardware reason: in order to place any instruction or address on the data bus, it must be possible to configure the data bus as an input. Within the internal circuitry of the TRS-80 itself, the data bus is fully bidirectional. This is normal, because the data bus is in an *input-to-CPU* state whenever memory is being read or input intructions are being executed, and in an *output-from-CPU* state whenever information is being stored in memory or output instructions are taking place.

Unfortunately, only the data output is brought to the edge card of the TRS-80. There is no buffer wired to the edge card which is pointed *inward* to the CPU, activated when the IORQ signal is sent from the CPU during interrupt! Therefore it is impossible to place either an instruction or an address byte on the data bus from outside the computer.

(Of all the possible under-utilization of the Z-80's power in the TRS-80, this is to me the most discouraging. You can cure something like the stingy lack of an extra video bit for lower case, but adding a second set of buffers requires a true hardware hacker. You might as well build a new computer. *Aveatquevale*, Model I.)

Thus, the balance of this section will be concerned exclusively with interrupt Mode 1 (set by executing the command IM1). As noted, the execution of this instruction forces the CPU to address 38.

Address **38** has also been usurped by the TRS-80 designers by placing it in ROM (read only memory). Because the first act of the instruction at **38** (which incidentally is the last of the RST instructions) is to jump into RAM at **4012**, it can nevertheless be accessed easily.

With a Level II CPU unit alone, the edge-card connector is brought out so the interrupt line is present. However, if you are an expansion interface owner or disc user, then you should know that the interrupt itself is dominated by the expansion interface unit's clock, which places a constant 25-millisecond pulse on the interrupt line. Therefore, not only are interrupt modes 0 and 2 made unavailable by the TRS-80 design, but (unless you are willing to cut a trace) the presence of the expansion interface limits even the use of Mode 1.

Despite all these limitations (whew!), the 25 mS interrupt does allow options beyond just the real-time clock.

Which brings us to the reason the Z-80 has so many interrupt modes. The most powerful kind of interrupt places an instruction or address on the bus, directly influencing CPU activities every time it occurs, but only when it is needed. If the hardware is well designed, this means every interruption is essential, and is handled expeditiously.

On the other hand, 'polling' interrupts for service requests is wasteful. That is, when there is a single interrupt mode which all devices must use, then the CPU is forced to ask each one, 'Did you interrupt me? No? Well, did you interrupt me? No? Well then, did *you* interrupt me? No? Okay, then . . .', until it finds the culprit. It not only services it, but also checks the remainder of the devices in case other interrupts occurred simultaneously with the first, or during the interrupt service routine.

We are therefore limited not only to a single interrupt mode, but also to a required polling technique, because this 40-times-per-second pulse is coming through without cease. No real 'device' is asking for service, but the effete request is present nonetheless. Yet we can still use it. Here's how: when the interrupt comes through, the CPU sends a signal to the relatively few devices in our I/O scheme, and asks them, 'do you have any information?' If there's no information, the CPU will quickly beat a path back to normal program flow. If there is information, the CPU will service the interrupt.

Whysis?

You may wonder what type of situation — within the context of the humble TRS-80 itself — might require this interrupt, other than the familiar real-time clock. Let's take an example of flawed human interaction in TRS-80 programming: the *Electric Pencil.*

As any reasonably good typist knows, this 'text editing' program is infuriatingly slow at the end of lines, particularly at the bottom of the page. Not only must it move the word in progress to the next line, but also scroll all 1,024 characters up the screen. If you are nimble-fingered, you can lose characters during this process.

The interrupt system might be used in order to build a buffer of keys pressed. A good typist's fastest keystrokes ('the', 'is', etc.) can be less than 50 mS apart, or 20 characters per second. As the interrupt comes through from the expansion box 40 times each second, location 387F can be

examined by the CPU. If any key other than 'shift' is pressed, its presence can be sensed by looking at this location. If its presence is sensed, the key-scan routine can be initiated, and the key information and any successive keystrokes are stored until the line break and/or scrolling is completed.

In this way the keyboard may be 'scanned' quickly, not only during entry of text, but also during I/O, such as to tape. A keystroke buffer may be built during this process (since the keyscan need only be initiated if a key is pressed) between output bytes. The same is true of printing; the text can continue to be output to the printer while this activity is going on.

In fact, if a key were pressed during an I/O routine, it could be accepted into a buffer, and subsequently displayed when the next interrupt occurs. In effect, you would be time-sharing your TRS-80.

Light Bulbs

Aha! Time-sharing your TRS-80! (Light bulbs flicker on in millions of brain rooms). Although a 25-mS pulse does not allow totally transparent time-sharing, it allows enough of it for your TRS-80 to be able to service several user requests at a time, in different ways.

But first, here's a short routine to prove that the interrupt is really there. You can assemble this, or just POKE it into memory.

```
7F00 F3           DI                  ;Interrupts off
7F01 3E C3        LD       A,DC3H     :Get JP commend
7FD3 32 12 40     LD       (4012H),A  :Replece RET cmd
7FD6 21 14 7F     LD       HL,7F14H   ;Stert eervice
7FD9 22 13 40     LO       (4013H),HL ;Plece efter JP
7F0C 21 19 1A     LD       HL,1A19H   ;Commend level
7F0F E5           PUSH     HL         ;Reedy to returr
7F10 E0 56        IM       1          ;Set to Mode 1
7F12 FB           El                  ;Interrupts on
7F13 C9           RET                 ;Return to 1A19
```

The segment above is merely a setup routine, executed once. It disables interrupts during setup, places **C3** (a jump instruction) in place of **C9** (return) currently found at **4012**, the interrupt patch point in RAM. It then places the destination address (**7F14**) as the jump's operand. It pushes the return to BASIC or DOS onto the stack, sets interrupt Mode 1, enables interrupts, and returns (effectively jumping to **1A19**).

Note that after an EI (Enable Interrupts) instruction, acknowledgment of any interrupts is actually delayed until *after* the completion of the instruction following the interrupt enable. Here's the interrupt service routine itself :

```
7F14 F3           DI                  ;Interrupts off
7F15 F5           PUSH     AF         ;All of these
7F16 E5           PUSH     HL         ;   registers
7F17 D5           PUSH     DE         ;   will be used
7F1B C5           PUSH     BC         :   to do this
7F19 3A EC 37     LD       A,(37ECH)  ;Reed disc chip
7F1C 3A E0 37     LO       A,(37E0H)  ;Reset clock F/F
7F1F 21 11 01     LO       HL,0111H   ;Messege stert
7F22 11 25 3C     LO       DE,3C25H   :Displey spece
7F25 D1 1A DD     LD       BC,DD1AH   ;Messege length
7F2B E0 B0        LOIR                ;Displey it
7F2A C1           POP      BC         :Put ell these
7F2B 01           POP      OE         ;    registers
7F2C E1           POP      HL         ;    beck in
7F20 F1           POP      AF         ;    plece
7F2E FB           EI                  ;Interrupts on
7F2F C9           RET                 :Return whence
```

The instructions loading the accumulator from **37EC** and **37E0** accommodate the quirks of the TRS-80 hardware — the Z-80's interrupt acknowledge signal is not used in this hardware scheme. Instead, reading **37EC** (disk controller status) followed by reading **37E0** (real-time clock) resets a flip-flop used to signal input from disk controller and real-time clock, respectively. This must be done each time or the interrupt will continue to be 'on', forcing the routine ever back upon itself.

You may protect memory at 32512 if you wish, as this will prevent any accidental crashes while you're trying this demo program. Also note that if you have installed a disk-disable switch on your interface, this program may initially lock up. The lockup may be cured by momentarily flipping the disable switch on then off.

So what's the point of this? Only to show that no matter what BASIC (or machine language) program you are operating, including DOS, the sign-on message will remain in the upper-right corner of the screen. CLS, scrolling, even attempting to overwrite the area with text will have no apparent effect, because the interrupt takes priority. To disable it, put a RETurn instruction in place -

```
PDKE 16402,2D1
```

and to enable it, replace the return with a JUMP:

```
POKE 16402.195
```

Under DOS, the usual CMD"R" and CMD"T" instructions will have their intended effect. Re-initializing Level II BASIC or DOS from **0000** will wipe out the interrupt patch to **7F14**.

On to Something Useful

There are a few rules of thumb for using interrupts. First, the interrogation and service routines must be as short as possible, or else the main program will get little work done between interrupts. This means, alas, very few calls to

ROM; the ROM calls, although effective, often contain a level of detail and error-checking that may be beyond the absolute minimum needs of the service routine.

Second, every register to be used by the service routine must be preserved, usually on the stack, since there is no way of knowing which registers will be in action when an interrupt occurs. The only safe bet for ordinary BASIC programs using Level II alone is to alternate register pairs (by executing EX AF,AF' and EXX), since the alternates are not used in Level II. IX, however, must still be saved.

With these thoughts in mind, have a look at the listing below, which prints a more useful message onto the screen: the BASIC memory available at all times.

Listing 5-3. Free memory constant display.

```
7F00 F3          SETUP   OI                      ;
7F01A3E C3               LO      A,0C3H          ;
7F03 32 12 40            LO      (4012H),A       : Setup
7F06 21 14 7F            LO      HL,SERVE        ; routina
7F09 22 13 40            LO      (4013H),HL      ; similar
7F0C 21 19 1A            LO      HL,1A19H        ; to that
7F0F E5                  PUSH    HL              ; prasented
7F10 E0 56               IM      1               ; above
7F12 FB                  EI                      ;
7F13 C9                  RET                     ;
3C00             VIOEO   EQU     3C00H
40E8             STKBOT  EQU     40EBH
40FB             ARRTOP  EQU     40FBH
7F14 F3          SERVE   DI                      ; No interrupt
7F15 F5                  PUSH    AF              ;
7F16 E5                  PUSH    HL              ;
7F17 05                  PUSH    0E              ; Save all
7F18 C5                  PUSH    BC              ; ragisters to
7F19 00 E5               PUSH    IX              ; ba usad
7F1B FD E5               PUSH    IY              ;
7F10 3A EC 37            LO      A,(37ECH)       ; Clear FDC
7F20 3A E0 37            LO      A,(37E0H)       ; Clear F-F
7F23 21 69 7F            LO      HL,MESSG        ; Get "MEM="
7F26 11 36 3C            LO      0E,VIOEO+36H    ; Plece to go
7F29 01 05 00            LO      BC,5            ; Its Langth
7F2C E0 B0               LOIR                    ; Oisplay it
7F2E AF                  XOR     A               ; Claar carry
7F2F 2A E8 40            LO      HL,(STKBOT)     ; BASIC steck
7F32 E0 5B FB 40         LO      0E,(ARRTOP)     ; Array aree
7F36 E0 52               SBC     HL,0E           : Room left
7F3B 00 21 3B 3C         LO      IX,VIOEO+3BH    ; Place to go
7F3C F0 21 6E 7F         LO      IY,TENTAB       ; Tans-tabla
7F40 06 05               LO      B,5             ; No. digits
7F42 AF          LOOPO   XOR     A               ; Clear carry
7F43 F0 5E 00            LO      E,(IY+0)        ; 10000 lobyte
7F46 F0 56 01            LO      0,(IY+1)        ; 10000 hibyte
7F49 B7          LOOP1   OR      A               ; Set flag
7F4A E0 52               SBC     HL,0E           ; 1st diffnce.
7F4C 38 03               JR      C,JUMPO         ; If greatar
7F4E 3C                  INC     A               ; Additive div
7F4F 18 FB               JR      LOOP1           ; Oivida agein
7F51 19          JUMPO   A00     HL,0E           ; Was too much
7F52 C6 30               A00     A,30H           ; ASCII cnvrt.
7F54 00 77 00            LO      (IX+0),A        ; Oispley it
7F57 00 23               INC     IX              ; Next screan
7F59 F0 23               INC     IY              ; Move once,
7F5B FD 23               INC     IY              ; and again
7F50 10 E3               OJNZ    LOOPO           : Oo 5 digits
7F5F F0 E1               POP     IY              ;
7F61 00 E1               POP     IX              ; Rastore all
7F63 C1                  POP     BC              ; tha reg's
7F64 01                  POP     0E              ; ueed to do
7F65 E1                  POP     HL              : tha work
7F66 F1                  POP     AF              ;
7F67 FB                  EI                      ; Ints. okay
7F68 C9                  RET                     ; BASIC awaits
7F69 BF          MESSG   OEFB    BFH             ; Block
7F6A                     OEFM    'MEM='
7F6A 40      7F6B 45      7F6C 40      7F60   30
7F6E 10 27       TENTAB  OEFW    100000          ; Tens-tabla
7F70 E8 03               OEFW    010000          ; is usad for
7F72 64 00               OEFW    001000          ; division by
7F74 0A 00               OEFW    000100          ; subtraction
7F76 01 00               OEFW    000010          ;
7F00                     ENO     SETUP
```

The 19-byte interrupt setup routine is found as usual, followed by the 100-byte service subroutine. All registers are saved — IY is optional but may be used by other utilities — a message is displayed, and a calculation is made to determine free memory. This calculation is the bottom of the BASIC subroutine stack (referenced at **40E8**) minus the top of array space (referenced at **40FB**).

Following that is a short, five-digit binary-to-ASCII table lookup which, in 35 bytes, converts and displays the free memory.

This routine is especially useful because it can help identify the actual area causing out-of-memory errors at run time. Heavily nested calculations can push the BASIC stack well down into memory, which is then visible on the screen. Put the program in place, and then try this :

```
10 GOSUB 20
20 GOTO 10
```

Something Even More Useful

If you by chance have a printer which prints less than 40 characters per second, the following routine will speed up your BASIC programs. Otherwise, this routine will have little effect on your program speed (perhaps a two or three percent slowdown), but will allow a program to continue without 'locking up' while the printer is in action. It is called a 'spooler', a word which is based on an acronym mercifully forgotten.

When an LPRINT or LLIST is commanded, the spooler sends the characters to an in-memory buffer, and returns to the waiting program. Since 255 characters is the maximum string length, this buffer size is adequate; increasing it will be valuable only if the main program is highly interactive, involving user, screen, calculations and printer.

Normally, the LPRINT and LLIST routines send a character to the printer, and then check to see if the printer is 'busy'. In the meantime, the line printer routine is idle, performing no other work, and ignoring the BASIC program. Those of you with Teletypes know the discouraging feeling of waiting for hard copy.

Instead of waiting for the printer to output the entire number, word, or line before returning to the program, an interrupt service routine is used as a 'despooler'. When the 25-mS interrupt is generated, the despooler checks the 255-byte buffer to see if a printable character is present. If there is, the routine sends that character to the printer, advances the buffer, and returns to the program in progress. Also, if the printer is busy,

Listing 5-4. Print spooler.

```
                 001UU ; #######################################################
                 00110 ; THIS INTERRUPT SERVICE ROUTINES STORES UP TO 255 CHAR-
                 00120 ; ACTERS IN A BUFFER, WHERE THEY MAY THEN BE OUTPUT TO
                 00130 ; A PRINTER.  THIS SPOOLER CHECKS FOR CHARACTERS AT THE
                 00140 ; PRINTER ORIVER ROUTINE, INTERCEPTS THEM, STASHES THEM,
                 00150 ; ANO RETURNS TO THE MAIN PROGRAM WITHOUT OELAY.
                 00160 ; #######################################################
                 00170 ;
7E00             00180         ORG     7E00H
                 00190 ;
                 00200 ; #######################################################
                 00210 ; SETUP ROUTINE CREATES A BUFFER ANO PLACES ITS AOORESS,
                 00220 ; ALONG WITH A JUMP TO REPLACE THE NORMAL RET, AT 4012H
                 00230 ; #######################################################
                 00240 ;
7E00 F3          00250 SETUP   OI                       ; INT. OFF OURING SETUP
7E01 3EC3        00260         LD      A,OC3H           ; GET JUMP VALUE INTO A
7E03 321240      00270         LD      (4012H),A        ; PLACE INTO INT. VECTOR
7E06 AF          00280         XOR     A                ; CLEAR ACCUMULATOR
7E07 47          00280         LD      B,A              ; PUT 100 HEX INTO B
7E08 21BA7E      00300         LD      HL,BUFFER-1      ; HL JUST AHEAO OF BUFFER
7E0B 23          00310 CLEAR   INC     HL               ; NEXT POSITION IN BUFFER
7E0C 77          00320         LO      (HL1,A           ; PLACE ZERO INTO BUFFER
7E00 10FC        00330         OJNZ    CLEAR            ; OO IT FULL 256 TIMES
7E0F 213F7E      00340         LO      HL,SERVE         ; GET SERVICE ROUT. AOOR.
7E12 221340      00350         LD      (4013H1,HL       ; PLACE INTO INT. VECTOR
7E15 21237E      00360         LD      HL,SPOOL         ; GET SPOOL ROUTINE
7E1B 222640      00370         LO      (4026H1,HL       ; PLACE IN PRINTER ORIVER
7E1B 21191A      00380         LD      HL,1A19H         ; RETURN TO BASIC INTO HL
7E1E E5          00390         PUSH    HL               ; PLACE ON STACK
7E1F E056        00400         IM      1                ; SET INTERRUPT MOOE
7E21 FB          00410         EI                       ; INTERRUPTS READY TO GO
7E22 C9          00420         RET                      ; BACK TO BASIC READY
                 00430 ;
                 00440 ; #######################################################
                 00450 ; SPOOL ROUTINE STARTS HERE ANO INTERCEPTS PRINTER ORIVER
                 00460 ; #######################################################
                 00470 ;
7E23 F3          00480 SPOOL   OI                       ; INT. OFF OURING SPOOL
7E24 E5          00490         PUSH    HL               ; SAVE HL REGISTER
7E25 79          00500         LD      A,C              ; GET CHARACTER INTO A
7E26 F5          00510         PUSH    AF               ; SAVE CHAR. TO PRINT
7E27 21BC7E      00520         LO      HL,BUFFER+1      ; POINT TO BUFFER START
7E2A FB          00530         EI                       ; INTERRUPTS BACK ON NOW
7E2B 7E          00540 LOOP2   LD      A,(HL)           ; GET BUFFER VALUE
7E2C A7          00550         ANO     A                ; IS IT A CHAR. OR ZERO?
7E20 20FC        00560         JR      NZ,LOOP2         ; WAIT IN LOOP IF FULL
7E2F F3          00570         OI                       ; INTERRUPTS BACK OFF
7E30 06F0        00580         LD      B,OFOH           ; GET PRESENT BUFFER SIZE
7E32 23          00590 LOOP3   INC     HL               ; GET NEXT BUFFER POS'N
7E33 7E          00600         LO      A,(HL)           ; BRING VALUE INTO A
7E34 A7          00610         ANO     A                ; TEST FOR CHAR. OR ZERO
7E35 2002        00620         JR      NZ,SAVEIT        ; FOUNO FREE SPACE - GO
7E37 10F9        00630         OJNZ    LDOP3            ; SEARCH THROUGH BUFFER
7E39 2B          00640 SAVEIT  OEC     HL               ; BACK OFF ONE POSITION
7E3A F1          00650         POP     AF               ; RESTORE CHAR. TO PRINT
7E3B 77          00660         LD      (HL1,A           ; PUT IT IN BUFFER
7E3C E1          00670         POP     HL               ; RESTORE FORMER VALUE
7E30 FB          00680         EI                       ; INTERRUPTS BACK ON
7E3E C9          00690         RET                      ; BACK TO MAIN ROUTINE
                 00700 ;
                 00710 ; #######################################################
                 00720 ; INTERRUPT SERVICE ROUTINE FIRST SAVES REGISTERS, THEN
                 00730 ; RESETS INTERRUPT FLIP-FLOPS IN E/I.  PRINTER STATUS
                 00740 ; IS EXAMINEO, ANO THE ROUTINE EXITEO IF PRINTER BUSY.
                 00750 ; #######################################################
                 00760 ;
7E3F F3          00770 SERVE   OI                       ; INT. OFF OURING OESPOOL
7E40 F5          00780         PUSH    AF               ; SAVE VALUE IN ACCUM.
7E41 E5          00790         PUSH    HL               ; SAVE VALUE IN HL
7E42 05          00800         PUSH    OE               ; SAVE VALUE IN OE
7E43 C5          00810         PUSH    BC               ; SAVE VALUE IN BC
7E44 00E5        00820         PUSH    IX               ; SAVE VALUE IN IX
7E46 00212540    00830         LO      IX,4025H         ; PRINTER CONTROL BLOCK
7E4A 3AEC37      00840         LD      A,(37ECH1        ; RESET INT. FLIP-FLOP
7E40 3AE037      00850         LU      A,(37E0H)        ; RESET INT. FLIP-FLOP
7E50 3AEB37      00860         LD      A,(37EBH)        ; GET PRINTER STATUS TO A
7E53 E6F0        00870         ANO     OFOH             ; MASK OUT LOW BITS
7E55 FE30        00880         CP      30H              ; SEE IF PRINTER IS BUSY
7E57 205A        00890         JR      NZ,OUT           ; GO OUT IF PRINTER BUSY
                 00900 ;
                 00910 ; #######################################################
                 00920 ; WHEN PRINTER IS REAOY, BUFFER IS MOVEO UP, THE CHAR-
                 00930 ; ACTER IS TESTEO, ANO PRINTEO IF A VALIO CHARACTER.
                 00940 ; IF IT IS CARRIAGE RETURN, FORM FEEO, LINE FEEO, ETC.,
                 00950 ; APPROPRIATE TESTS ARE MAOE IN THE PRINTER CONTROL BLOCK
                 00960 ; #######################################################
                 00970 ;
7E59 21B97F      00980         LO      HL,BUFFER+OFEH   ; GET NEXT TO LAST CHAR.
7E5C 11BA7F      00990         LD      OE,BUFFER+OFFH   ; GET NEXT CHAR. IN QUEUE
7E5F 01FF00      01000         LO      BC,OFFH          ; GET TOTAL BUFFER SIZE
7E62 E0BB        01010         LOOR                     ; MOVE IT UP ONE POS'N
```

Listing Continued .

it returns to the program immediately.

A ten-character-per-second (cps) printer like a Teletype is 'busy' for 100,000 microseconds for each character. In that time, a BASIC program might perform many calculations. Selectrics type a maximum of 15 cps, which is also time-consuming.

The program will not necessarily benefit in time with faster printers, but the waiting period will be eliminated in favor of a more interactive program overall.

The following listing is uncommented, as the bulk of the interrupt explanations have already been presented. The spooler is entered from BASIC via LLIST and LPRINT, either of which moves directly to the printer driver address referenced at 4026 and 4027. This is replaced with the address of the spooler. The character to be printed is delivered to the printer driver in the C register. The spooler searches through the buffer for the first non-zero value and places the character to be printed immediately before that. (If your system requires nulls after a carriage return, you can back up the appropriate number of places in the buffer).

Upon interrupt, the despooler saves registers and loads the IX register with 4025, the start of the printer device control block. This block contains line and page information, which is used to determine if paging has been completed, and how line feeds, carriage returns, and form feeds will be handled. It is functionally identical to the driver in ROM, except that it takes its characters from the spooler's buffer instead of directly from the Level II routines.

If the printer is not busy, then, the character is sent to the printer address at 37E8. Following is the complete routine, including setup, spool, and despool.

All of the interrupt programs presented in this article depend on the expansion interface for their 25 mS clock pulses. However, a simple rectified and shaped 16.66 mS pulse, which will work fine with all of these routines, can be created using the 60 Hz output of a 6.3-volt, low-current filament transformer, resistor, and 7414 Schmitt trigger.

The complete circuit for a printer decoder is available from Radio Shack as *'Printer Cable Service Manual'*.

Continued Listing

```
7E64 3ABA7F   01020         LO      A,(BUFFER+0FFH) ; GET QUEUE CHAR TO PRINT
7E67 A7       01030         ANO     A               ; TEST TO SEE IF ZERO
7E6B 2B49     01040         JR      Z,OUT           ; GO OUT IF NONE LEFT
7E6A FE0B     01050         CP      0BH             ; CHECK IF TOP OF FORM
7E6C 280A     01060         JR      Z,TEST1         ; TEST IF CHAR. IS ONE
7E6E FE0C     01070         CP      0CH             ; TEST IF CHAR = F.F.
7E70 201F     010B0         JR      NZ,TEST2        ; NEXT TEST IF NOT
7E72 AF       01090         XOR     A               ; CLEAR ACCUMULATOR
7E73 00B603   01100         OR      (IX+3)          ; GET LINES PRINTEO
7E76 2B19     01110         JR      Z,TEST2         ; OUT IF VALUE = 0
7E7B 007E03   01120 TEST1   LO      A,(IX+3)        ; GET LINES PRINTEO
7E7B 009604   01130         SUB     (IX+4)          ; GET LINES PER PAGE
7E7E 47       01140         LD      B,A             ; PUT LINES LEFT IN B
7E7F 3AEB37   01150 LOOPA   LD      A,(37EBH)       ; GET PRINTER STATUS
7EB2 E6F0     01160         ANO     0F0H            ; MASK OUT LOW BITS
7EB4 FE30     01170         CP      30H             ; CHECK STATUS BITS
7EB6 20F7     011B0         JR      NZ,LOOPA        ; LOOP IF PRINTER BUSY
7EBB 3E0A     01190         LO      A,0AH           ; GET LINE FEEO CHAR.
7E8A 32EB37   01200         LO      (37EBH),A       ; SENO IT TO PRINTER
7EB0 10F0     01210         DJNZ    LOOPA           ; DO IT TILL FDRM IS FED
7EBF 1B1E     01220         JR      EXIT            ; GO OUT WHEN OONE
7E91 47       01230 TEST2   LD      B,A             ; STASH CHAR. IN B REG.
7E92 3AEB37   01240 LDOPB   LO      A,(37EBH)       ; GET PRINTER STATUS
7E95 E6F0     01250         ANO     0F0H            ; MASK OUT LOW BITS
7E97 FE30     01260         CP      30H             ; CHECK STATUS BITS
7E99 20F7     01270         JR      NZ,LOOPB        ; LOOP TILL PRINTER REAOY
7E9B 7B       01280         LO      A,B             ; GET CHAR. BACK INTO A
7E9C 32EB37   01290         LO      (37EBH),A       ; SENO IT TO PRINTER
7E9F FE00     01300         CP      00H             ; CHECK IF CARRIAGE RET.
7EA1 2010     01310         JR      NZ,OUT          ; IF NOT THEN GO OUT
7EA3 003404   01320         INC     (IX+4)          ; ELSE INC. LINES COUNTER
7EA6 007E04   01330         LO      A,(IX+4)        ; GET NEW LINES COUNTER
7EA9 00BE03   01340         CP      (IX+3)          ; CHECK WITH LINES/PAGE
7EAC 79       01350         LO      A,C             ; GET CHARACTER BACK TO A
7EA0 2004     01360         JR      NZ,OUT          ; GO IF NOT PAGE ENO
7EAF 00360400 01370 EXIT    LO      (IX+4),0        ; RESET PAGE LINES TO 0
              013B0 ;
              01390 ; #######################################################
              01400 ; REGISTERS ARE RESTORED AND THE ROUTINE IS EXISTED.  THE
              01410 ; LAST 255 BYTES OF SPACE ARE RESERVEO FOR PRINTER BUFFER
              01420 ; #######################################################
              01430 ;
7EB3 00E1     01440 OUT     POP     IX              ; RESTORE IX REGISTER
7EB5 C1       01450         POP     BC              ; RESTORE BC REGISTER
7EB6 01       01460         POP     0E              ; RESTORE 0E REGISTER
7EB7 E1       01470         POP     HL              ; RESTORE HL REGISTER
7EBB F1       0148D         PDP     AF              ; RESTDRE AF REGISTER
7EB9 FB       01490         EI                      ; INTERRUPTS BACK ON
7EBA C9       01500         RET                     ; BACK TO MAIN ROUTINE
00FF          01510 BUFFER  0EFS    255             ; 0EFINE 255-CHAR. BUFFER
7FBA 00       01520         0EFB    00              ; ENO BUFFER WITH 0 BYTE
              01530 ;
              01540 ; #######################################################
7E00          01550         ENO     SETUP
00000 TUTAL ERRORS
29420  TEXT AREA BYTES LEFT


6UFFER 7EBB 01510   00300 00520 009B0 00990 01020
CLEAR  7E0B 00310   00330
EXIT   7EAF 01370   01220
LOOP2  7E2B 00540   00560
LOOP3  7E32 00590   00630
LOOPA  7E7F 01150   011B0 01210
LOOPB  7E92 01240   01270
OUT    7EB3 01440   00B90 01040 01310 01360
SAVEIT 7E39 00640   00620
SERVE  7E3F 00770   00340
SETUP  7E00 00250   01550
SPOOL  7E23 004B0   00360
TEST1  7E7B 01120   01060
TEST2  7E91 01230   010B0 01110
```

6

More Hardware Modifications

By now your TRS-80 is an electronic intimate. In this chapter, some significant (and some sophisticated) hardware modifications will be made. A few of these are simple, and their value is not immediately obvious. Others involve major work (such as the high-resolution graphics), but the results are exciting and very rewarding.

Making Halt Work

Let's start with an easy one. The HALT instruction is a useful command. It isn't exceptional, but you will find that time spent idling in loops waiting for an interrupt is easier when the HALT instruction is used. In fact, its main advantage comes when the Z-80 microprocessor is used in interrupt-based systems. Where program work is being done, the HALT instruction is not particularly meaningful; but where program operations are suspended except for interrupts, it is very useful.

When HALT is executed on the Z-80, the processor simply ceases program counter operation and executes NOPs in order to continue memory refresh. That is, the Z-80 outputs a fetch (the M1 or machine cycle one signal) which – together with a refresh address on the address bus – constitutes enough information to keep the memory active. The information received during the fetch is ignored by the CPU, which continues to execute NOPs until an interrupt is received. It then exits the NOP state and services the interrupt.

Whenever the HALT instruction is executed, a halt-acknowledge signal (HALT, active low) is output on pin 18. In the TRS-80, pin 18 is tied to an input of NAND gate Z53. The other input of Z53 is tied high through a 10K resistor, but can be pulled low when the Reset button is pressed. In other words, either a Reset or a HALT will redirect the CPU to the address of the non-maskable interrupt (NMI), where it will continue execution from either 'READY' or DOS reboot.

By cutting loose pin 18 of the CPU (Z40), and tying Z53 pin 2 high, with a 4.7K ohm resistor, the HALT instruction will operate as intended by the Z-80's designers. Memory will continue to be refreshed, as the 4116s' refresh cycle depends on RAS (row address strobe), which will be output as usual by Z72.

Cut the trace running from Z40, pin 18. Attach a 4.7K ohm resistor from Z53 pin 2, to Z53 pin 14. The modification is complete.

A Real Break

Later in this Chapter is a power-on monitor, which will give more importance to the minor change described here. The TRS-80 does not have a true 'break' function that resets the CPU to its power-up condition. It can be simulated by entering SYSTEM followed by /0, or by pressing the Reset button on a disk system.

This change is quite simple. Locate Z53, a 74LS132 NAND gate, which feeds (through Z52) the system reset pin of the Z-80 microprocessor. When the power is turned on, capacitor C42 takes time to charge, holding the processor in its reset mode for a few milliseconds. When the capacitor charges completely, the input to Z53 is held high by resistor R47.

Run a wire from pins 12 and 13 of Z53, through a 1K resistor, to one end of a SPST (single pole single throw) normally open pushbutton switch. The other end of the switch goes to ground (which can be found at Z53, pin 7). When this switch is pressed, the Z53 sees a low signal, and resets the processor to address 0000. A resistor is used in series so that C42 is not overexerted by shorting directly to ground.

Be sure to mount this button well out of the way; for disk systems, it's as fatal as the Reset button. For Level II it means MEMORY SIZE? and the loss of any program in memory.

Stuck Relays

There are two ways to fix a stuck relay: bang it until it unstucks, or replace it. The many published fixes to tape recorders, or additional external circuitry, simply don't take into consideration any changes you might make to your tape system; nor to the possibility you may take your CPU with you when you work elsewhere.

A replacement relay is available from *Lab Service, Inc., Box 383, Hustisford, Wisconsin 53034.* Unlike the relay normally installed in the TRS-80, it is reliable, low power and has gold contacts. I have installed this unit in my computer, and run the high current motor of a CTR-41 through 100,000 operations continuously over the course of a week. Neither the CTR-41 nor the relay failed.

The cassette relay is mounted just behind the jacks for power, video and cassette. It is a cylinder approximately the size of the *LSI* replacement relay, but in most TRS-80s it contains six leads instead of four.

Using solder-wick and a hot soldering iron, heat the solder connections and draw off excess solder. While doing this, slide a thin flat blade under the relay. Take care not to move the nearby small video trimmer potentiometers. Use the blade as a lever, lifting the old relay off the board. Apply very gentle pressure to this lever, and alternately melt the three solder connections on each side of the relay. Do not use force that might crack the board or lift solder traces from the board.

When one side of the relay is completely free, grasp it with your hand and pull *gently,* while heating the remaining three connections on the opposite side of the relay. It will eventually pull free.

Remove excess solder from the holes with the solder-wick. Use a fine splinter to open the eyes of the holes, if all the solder does not flow into the solder-wick.

Now examine the circuit board, noting that on the end of the relay position nearest the computer's connection jacks there are two otherwise unused connections; no circuit traces run out from these points. Look at the relacement relay, noting that it has four wires, three on one side and one on the other. Orient it above the board so that the unused holes match the end of the relay with the single wire. This wire feeds into the center of the trio of holes.

Carefully insert the relay in place; if you have properly cleaned out the connection holes, the new relay wires will slide in, barely protruding from the opposite side of the board. You may have to bend them just a bit in order to get them to feed through.

Once the wires are in place, apply a very small amount of solder, and secure the relay on the board. Check carefully for solder splashes, shorts or cracks, and clean or repair them. Such a check is doubly important here because the relay driver circuit (unlike most other circuits in the TRS-80) cannot handle a short circuit for very long.

Refit the boards and covers of the computer together, replace the power and cassette cables; then put the cassette player into its play position, and enter this program:

```
10 PRINT#-1," "
20 FOR N = 1 TO 500 : NEXT
30 GOTO 10
```

This program will turn the cassette player on and off at regular intervals. If it does not work properly, double check all connections, especially the orientation of the relay, and try again. This fix should eliminate any further concern over a sticking relay causing skipped data or missed program loads.

High Resolution Graphics

Now for the biggie. In the past few years, there has been quite a bit of excitement generated by the idea of high-resolution graphics. Reasonably representative images can be drawn with them, and animation is considerably more exciting; especially when compared with the extremely high resolution of the type used in the latest generation of coin-operated video games. The Apple computer was advertised with a heavy emphasis on their high resolution, hard as it is to work with. The new Radio Shack Color Computer also offers several modes of resolution.

The following project can either stand alone as a plug-in peripheral, or be integrated as part of the TRS-80 keyboard unit. In either case, the specifications are:

1. Resolution of 384 dots wide by 192 dots deep.
2. Full compatability with all current software.
3. Simultaneous use *and overprint* of normal TRS-80 alphanumerics *and graphics.*
4. Addressing using six bits in contiguous memory blocks of 768 bytes each; sixteen total memory blocks are used.

The hardware involved in this project, including power supply and miscellaneous hardware, will be under $100 (probably closer to $70 by the time you read this), yet will compete easily with any high-resolution add-on for the TRS-80.

On the negative side, this project will involve a great deal of wire wrapping or soldering, and will eat up one chunk of 16K memory address space when it is used. It will not actually compete with or replace the top memory block in the expansion box (there is no electronic conflict) but will be addressed from **C000** to **FFFF**. Alternatively, it may be addressed from **8000** to **BFFF**. In either case, you do not need the expansion box to run this memory.

The TRS-80 screen has 1,024 locations in a grid of 64 characters across by 16 lines down. Within each of these grid elements are blocks 2 pixels by 3 pixels (a pixel is a 'picture element') for the familiar coarse graphics mode accessed with SET and RESET. If you turn the contrast fully down and reduce the brightness of the screen, the individual dots which make up the graphic and alphanumeric characters can be seen with a sharp eye; a magnifying glass will make the dots very clear.

In order to produce a complete screen line of letters, the locations in video memory are handed to a circuit which actually accesses them twelve times – once for each pass the electron beam makes horizontally. At each pass, a row of dots corresponding to part of the whole line of letters is shifted out to the video beam. Each dot (or 'undot') then turns the beam on or off for the tiny fraction of a second it takes to sweep across 1/384th of the screen.

The point is clear: an electronic event takes place for every dot on every line of the screen. This means that it is possible to create an individual, addressable electronic event for each screen dot.

The process might work like this:

1. Devise a circuit whose timing characteristics are identical to the video timing of the usual TRS-80 circuits.
2. Instead of addressing the same video memory on twelve consecutive screen lines, have the addressing select *different* memory for each line.
3. Have the contents of that memory filled by the TRS-80, and displayed on the same or a different monitor. The add-on has its own video circuitry, but can be displayed on the same monitor because step 1 specifies that the timing characteristics must be identical to those in the TRS-80. It's like an auto with 4-wheel drive, where all wheels are capable of working together; or a dual-capstan tape recorder, where both capstans pull the tape to ensure steady contact with the playback head.

The circuit shown opposite presents the complete high-resolution circuitry. There are two ways of building this circuit since the areas shaded in grey *are already present within the TRS-80.* If you wish, you can solder directly to those circuits inside the computer, saving yourself some parts and perhaps a bit of time. Otherwise, the entire circuit can be built separately.



Figure 6-1. Complete high resolution circuit.



Figure 6-1b. High resolution memory.



Figure 6-1c. High resolution power supply.



Figure 6-2. Hires clock circuit.

Figure 6-2 is the clock. The 10.6445 MHz crystal is the same one used in the TRS-80; Radio Shack sells it for $3.95, on special order. A small trimmer capacitor is included so that the frequency of the high resolution board can be aligned identically to that in the computer.

Figure 6-3 is the master video countdown chain and timing circuitry, also nearly identical to that inside the TRS-80. There are a few exceptions. The logic necessary for 32 characters per line is not present (it is not needed in high resolution mode, although the normal alphanumerics may be displayed in 32-character mode simultaneously with the hi-res graphics screen). Also, the four outputs of Z6 do not feed any latches or character generators; instead, they become the line of dots addresses for high resolution memory. Identical (top and side) screen blanking is used.

Figure 6-1. is the high-resolution memory itself. The familiar 4116 type, 16K dynamic memories are used in this circuit (250 nS or less is essential), but with a difference. The hi-res board must generate its own memory refresh, yet hand over control to the TRS-80 when it needs to select memory into which it will write information. Thus, Z20 multiplexes the on-board refresh/select (MRAS, MCAS, MMUX) with the TRS-80 select (CRAS, CCAS, CMUX).

The switch is made by the simultaneous presence of addresses 14 and 15 on the address bus.

On-board refresh/select is generated by the clock in combination with two flip-flops (Z3a/b), producing select in this order:

1. Z2 pin 8, selects the lowest portion of the address; as such, it is the fastest changing memory select signal.

2. Two clock cycles later, Z2 pin 11, produces a signal which will be gated by Z9 and inverted to produce MRAS (row address strobe).

3. One clock cycle later, MMUX goes high, produced by the clocking of Z3a.

4. One clock cycle later, MRAS is continued as Z2 pin 11 goes low by Z2 pin 9 going high. The transition is simultaneous and virtually invisible.

5. At that time, MCAS is produced when Z3b is clocked low at the NOT Q output.

6. Memory data is stable at this time, and two clock cycles later, LATCH is issued by Z1e, latching the data into Z16 for its trip through shift register Z17.

Figure 6-3 shows the creation of horizontal and vertical synchronization signals, and the horizontal and vertical screen positioning controls. This circuitry again is identical to that in the TRS-80, as is Figure 6-4 , the video mixing circuitry.

There is only one critical construction area in the device, and that is the circuitry surrounding the 10.6445 MHz crystal (Z16, R4-5, C1). The wires in this area must be very short, and all the parts clustered together. Capacitor C1 should be the only part of the circuit responsible for tuning the crystal's frequency, not random capacitance



Figure 6-3. Master video circuit.



Figure 6-4. The video mixing circuitry.

introduced by a haphazard bunch of wires.

Other than the wire layout near the crystal, construction is time-consuming but straightforward. I recommend wire wrapping the entire circuit; use different colors for data, address, video, ground, etc., so that troubleshooting will be simplified.

The completed circuit will have these external controls:

1. **Power**. Three voltages, +5, -5, and +2 are necessary. -5 volts must be present first and last.

2. **Mixing**. This controls the intensity of the high-resolution board with respect to the TRS-80 alphanumerics and graphics.

3. **Fine tuning**. This adjusts the frequency of the 10.6445 MHz crystal to that of the TRS-80. Occasional adjustments will be necessary with temperature changes.

4. **Vertical and horizontal positioning**. These control the placement of the image on the screen; it should coincide with the alphanumeric screen normally produced by the TRS-80.

5. **Input**. This accepts a cable running from the TRS-80 video jack, which would normally attach to the video monitor.

6. **Output**. This accepts a cable from the video monitor, and provides an output which mixes the TRS-80 alphanumerics and graphics with the high-resolution dots.

To use the device, attach a 5-pin DIN cable between the TRS-80 video jack and the input jack hi-res board. Connect the video monitor to the output jack of the hi-res board, then attach a 40-pin edge connector from the TRS-80 to the hi-res board. Turn the mixing control fully countercockwise (Hi-Res Out). Power up the hi-res board, and then the rest of the system in normal order.

As usual, MEMORY SIZE? should appear; if so enter 49152 (for a 48K computer). The system should operate as usual. Enter the following program:

```
10 FOR X = 15360 TO 16383
20 POKE X,129
30 NEXT
40 FOR X = -16384 TO 0
50 POKE X,175
60 NEXT
70 GOTO 70
```

The screen will fill with small graphics blocks. There will be a pause of almost a minute while the rest of the program is running. Put an AM radio next to the computer to determine when the program is complete. Now bring the mixing control of the hi-res board clockwise until dots, herringbone, jitter and/or other interference appears on the screen. This is a good sign.

If you have a stable enough screen to see the alternating dot patterns produced by the hi-res board, then adjust the horizontal and vertical positioning controls, if necessary, to center the image with that of the TRS-80. To remove the jitter and herringbone adjust the fine tuning control.

Now your screen should display an alternating pattern of TRS-80 graphics, along with an overlay of thin vertical lines of hi-res graphics dots. If you have any difficulty getting this pattern, or if there are any other problems, refer to the troubleshooting section.

Use of the Hi-Res board is simple. Addresses from C000 through C03F contain the information to create the first line of dots, addresses C040 through C07F contain the second line, etc. A contiguous block of memory from C000 through C2FF is used for the first twelve lines of dots. But since the display is twelve lines, and not sixteen, the addressing takes a jump in order to be compatible with the familiar 64 x 16 normal screen display. Thus, addresses C300 through C3FF are not used, and the second group of 12 dot lines begins at address C400 and continues

through C6FF. Here is a full memory map of the Hi-Res board:

Hi-Res Board Memory Map

C000 - C03F	Group 1, Line 1, Screen Line 1
C040 - C07F	Group 1, Line 2, Screen Line 2
C080 - C08F	Group 1, Line 3, Screen Line 3
C0C0 - C0FF	Group 1, Line 4, Screen Line 4
C100 - C13F	Group 1, Line 5, Screen Line 5
C140 - C17F	Group 1, Line 6, Screen Line 6
C180 - C18F	Group 1, Line 7, Screen Line 7
C1C0 - C1FF	Group 1, Line 8, Screen Line 8
C200 - C23F	Group 1, Line 9, Screen Line 9
C240 - C27F	Group 1, Line 10, Screen Line 10
C280 - C28F	Group 1, Line 11, Screen Line 11
C2C0 - C2FF	Group 1, Line 12, Screen Line 12
C400 - C43F	Group 2, Line 1, Screen Line 13
C440 - C47F	Group 2, Line 2, Screen Line 14
	⋮
C680 - C68F	Group 2, Line 11, Screen Line 23
C6C0 - C6FF	Group 2, Line 12, Screen Line 24
C800 - CAFF	Group 3, Lines 1 - 12 Screen Lines 25 - 36
CC00 - CEFF	Group 4, Lines 1 - 12 Screen Lines 37 - 48
D000 - D2FF	Group 5, Lines 1 - 12 Screen Lines 49 - 60
D400 - D6FF	Group 6, Lines 1 - 12 Screen Lines 61 - 72
D800 - DAFF	Group 7, Lines 1 - 12 Screen Lines 73 - 84
DC00 - DEFF	Group 8, Lines 1 - 12 Screen Lines 85 - 96
E000 - E2FF	Group 9, Lines 1 - 12 Screen Lines 97 - 108
E400 - E6FF	Group 10, Lines 1 - 12 Screen Lines 109 - 120
E800 - EAFF	Group 11, Lines 1 - 12 Screen Lines 121 - 132
EC00 - EEFF	Group 12, Lines 1 - 12 Screen Lines 133 - 144
F000 - F2FF	Group 13, Lines 1 - 12 Screen Lines 145 - 156
F400 - F6FF	Group 14, Lines 1 - 12 Screen Lines 157 - 168
F800 - FAFF	Group 15, Lines 1 - 12 Screen Lines 169 - 180
FC00 - FEFF	Group 16, Lines 1 - 12 Screen Lines 181 - 192

Only six bits of each byte are used (the least significant six); thus, six one-bit-wide, memory chips are used in the circuit. The bits fit into their respective lines and memory addresses as follows:



Before continuing, clear out the hi-res memory with:

```
FOR X = -16384 TO 0 : POKE X,0 : NEXT
```

Drawing simple lines is an easy process; for a horizontal one, just enter:

```
FOR X = -12288 TO -12224 : POKE X, 63 : NEXT
```

A vertical one is produced by stepping through groups:

```
5  CLS                               : REM KILL ALPHANUMERICS
10 FOR Y = -16352 TO 0 STEP 1024     : REM STEP THROUGH GROUPS
20 FOR X = Y TO Y+(12*64) STEP 64    : REM STEP THROUGH LINES
30 POKE X,1 : NEXT X                 : REM SET ONE PIXEL
40 NEXT Y                            : REM TO NEXT LINE GROUP
50 GOTO 50                           : REM KEEP DISPLAY INTACT
```

Diagonal lines are more complicated, because more than two sets of increments must be specified; but simple diagonals can be created. For diagonals and variable-width lines, change listing to read as follows:

```
10 INPUT Q : INPUT R : CLS
20 FOR Y = -16352 TO 0 STEP 1024
30 FOR X = Y TO Y+(12*64) STEP 64+Q
40 POKE X,(R AND 63) : NEXT X
50 NEXT Y
60 GOTO 60
```

For serious graphics, assembly language programming is the only way real speed can be achieved. This is a very 'custom' type of programming, and only the simplest of subroutines will be presented here. For drawing circles, ellipses, and curves the functions will have to be stored in a look-up table and calculated. Listing 6-1 is an assembly listing to draw graphic lines on the screen, given a set of coordinates.



```
                00100 ; ######################################################
                00110 ; ROUTINE TO ORAW HORIZONTAL ANO VERTICAL LINES FR. BASIC
                00120 ; ######################################################
                00130 ;
C000            00140 HIRES   EQU     0C000H          ; START OF HIRES GRAFIX
0A7F            00150 XFER    EQU     0A7FH           ; VARIABLE XFER ROUTINE
                00160 ;
7F00            00170         ORG     7F00H           ; SOMEWHERE IN MEMORY
                00180 ;
                00190 ; ######################################################
                00200 ; SUBROUTINE TO OETERMINE THE CORRECT BASIC USR(X) CALL
                00210 ; ######################################################
                00220 ;
7F00 C07F0A     00230 ENTRY   CALL    XFER            ; GET VALUE FROM BASIC
7F03 7C         00240         LO      A,H             ; GET MSB INTO ACCUM.
7F04 B5         00250         AOO     A,L             ; AOO LSB FROM HL PAIR
7F05 A7         00260         ANO     A               ; TEST IF IT IS ZERO
7F06 280B       00270         JR      Z,PCLS          ; CLEAR SCREEN ROUTINE
7F0B FE01       00280         CP      1               ; TEST IF IT IS ONE
7F0A 2815       00290         JR      Z,PHORIZ        ; HORIZONTAL LINE ON 1
7F0C FE02       00300         CP      2               ; TEST IF IT IS A TWO
7F0E 2B30       00310         JR      Z,PVERT         ; VERTICAL LINE ON 2
7F10 C39719     00320         JP      1997H           ; SN? ERROR IF NOT 1,2,3
                00330 ;
                00340 ; ######################################################
                00350 ; SUBROUTINE TO CLEAR THE SCREEN IN HIGH-RESOLUTION MOOE
                00360 ; BASIC FORMAT:  M=USR(A).  A MUST ALWAYS BE ZERO.
                00370 ; ######################################################
                00380 ;
7F13 AF         00390 PCLS    XOR     A               ; GET CHARACTER TO WRITE
7F14 F5         00400         PUSH    AF              ; SAVE THAT CHARACTER
7F15 2100C0     00410         LO      HL,HIRES        ; GET BEGINNING OF HI-RES
7F1B F1         00420 PCLEAR  POP     AF              ; RESTORE ZERO CHARACTER
7F19 77         00430         LO      (HL),A          ; PUT IT IN PLACE IN MEM
7F1A F5         00440         PUSH    AF              ; SAVE CHARACTER AGAIN
7F1B 7C         00450         LO      A,H             ; GET MSB OF CURRENT LOC.
7F1C B5         00460         OR      L               ; GET LS8 ANO TEST PAIR
7F10 20F9       00470         JR      NZ,PCLEAR       ; LOOP BACK FOR NEXT
7F1F F1         00480         POP     AF              ; GET STACK BACK IN SHAPE
7F20 C9         00490         RET                     ; BACK TO CALLING ROUTINE
                00500 ;
                00510 ; ######################################################
                00520 ; SUBROUTINE TO ORAW A HORIZONTAL LINE.  BASIC FORMAT:
                00530 ; POKEN,B:C1=INT(C/6):C2=C-C1*6:POKEN+1,C1:POKEN+2,C2:
                00540 ; 01=INT(0/6):02=0-01*6:POKEN+3,01:POKEN+4,02:M=USR(1)
                00550 ;
                00560 ; B=LINE NUMBER (0-11, 16-27, 32-43, 48-59. 64-75, B0-91,
                00570 ;         96-107, 112-123, 128-139. 144-155, 160-171, 176-
                00580 ;         187. 192-203, 20B-219. 224-235, 240-251
                00590 ; C=ORIGINATION POSITION (0-3B3).
                00600 ; D=OESTINATION POSITION (0-383). C MUST BE LARGER THAN 0
                00610 ; ######################################################
                00620 ;
7F21 0021B97F   00630 PHORIZ  LO      IX,N            ; POINT TO THE STORAGE
7F25 C06E7F     00640         CALL    FINOER          ; GET STARTING POSITION
7F28 3ABC7F     00650         LO      A,(N+3)         ; GET VALUE AT "N+3"
7F2B 4F         00660         LO      C,A             ; PLACE IN MSB OF BC
7F2C AF         00670         XOR     A               ; CLEAR ACCUM TO ZERO
7F20 47         00680         LO      B,A             ; PLACE IN LSB OF BC
7F2E E5         00690         PUSH    HL              ; SAVE START LOC'N
7F2F 05         00700         PUSH    OE              ; READY FOR XFER BACK
7F30 E1         00710         POP     HL              ; TRANSFERREO BACK
7F31 09         00720         AOO     HL,BC           ; PERFORM THE AOOITION
7F32 E5         00730         PUSH    HL              ; REAOY FOR TRANSFER
7F33 01         00740         POP     OE              ; ANO GET INTO OESTIN'N
7F34 E1         00750         POP     HL              ; RESTORE ORIGINAL VALUE
7F35 3AB87F     00760         LO      A,(N+2)         ; GET VALUE AT "N+2"
7F38 86         00770         OR      (HL)            ; AOO TO CURRENT LOC'N
7F39 77         00780         LO      (HL),A          ; ANO PUT INTO PLACE
7F3A 23         00790         INC     HL              ; NEXT SCREEN POSITION
7F3B AF         00800 LOOP1   XOR     A               ; CLEAR ACCUM TO ZERO
7F3C 3A3F00     00810         LD      A,(03FH)        ; VALUE TO FILL 8YTE
7F3F E052       00820         S8C     HL,OE           ; PERFORM SUBTRACTION
7F41 2804       00830         JR      Z,HOROUT        ; OUT OF ROUTINE
7F43 77         00840         LO      (HL).A          ; PUT BYTE IN PLACE
7F44 23         00850         INC     HL              ; GET NEXT SCREEN POS'N
7F45 1BF4       00860         JR      LOOP1           ; GO BACK FOR NEXT FILL
7F47 3A807F     00870 HOROUT  LO      A,(N+4)         ; GET BACK FINAL 8YTE
7F4A B6         00880         OR      (HL)            ; AOO TO VALUE ON SCREEN
7F4B 77         00890         LO      (HL),A          ; PUT IT ON THE SCREEN
7F4C C9         00900         RET                     ; ANO BACK TO BASIC
                00910 ;
                00920 ; ######################################################
                00930 ; SUBROUTINE TO ORAW A VERTICAL LINE.  48K RAM IN PLACE.
                00940 ; BASIC FORMAT:
                00950 ; POKEN,B:C1=INT(C/6):C2=C-C1*6:POKEN+1,C1:POKEN+2,C2
                00960 ; 01=INT(0/6):02=0-D1*6:POKEN+3,01:POKEN+4.02:M=USR(2)
                00970 ;
                00980 ; E=HORIZONTAL POSITION (0-255)
                00990 ; F=LINE NUMBER (SEE HORIZONTAL LINE, ABOVE)
                01000 ; G=LINE NUMBER (SEE HORIZONTAL LINE, ABOVE)
                01010 ; ######################################################
                01020 ;
7F40 0021897F   01030 PVERT   LO      1X,N            ; POINT TO THE STORAGE
```

Listing 6-1. Hires demonstration program. *Listing Continued*

Without TRS-80 memory parallel to that in the hi-res board, it is not possible to read the contents of the high-resolution memory directly. The contents must be stored in some form elsewhere. When the high 16K block is in place in the expansion box, however, six bits of each byte are identical to those on the screen. Ideally, the entire block of high resolution memory (16K by 6 bits) and TRS-80 memory (16K by 8 bits) should be cleared out by POKEing 0 in place first. Then an in-computer image of the high resolution screen can be maintained at all times.

Another interesting mode of using the high resolution board is with a separate screen. Normal alphanumerics can appear on the TRS-80 monitor, while the high-resolution graphics can be presented on a parallel screen. This way, the table calculations and information reported can be displayed on the computer's monitor for reference. The high-resolution screen will be unaffected by anything done by the TRS-80 unless its memory is being specifically written to. Not only can action games of the Startrek type be more interesting and challenging — with visuals and info displayed on different screens — but for experimentation and analysis, the high-resolution display is unbothered by program changes.

To use this mode, merely leave your TRS-80 monitor plugged into the computer. Then send the video information in the hi-res board to another video monitor, or to an ordinary television set via an RF modulator.

Troubleshooting

With a complicated project like this, there is a good chance that the system will not work perfectly the first time. The main problems together with their causes and solutions are outlined below.

1. The screen keeps tearing or jittering no matter what setting the fine tuning is on. If the fine tuning has no effect at all, it may be defective. Replace it. If the tuning gets better, but can't quite pull it in, you can put another capacitor in parallel to increase the capacitance, or replace the crystal (in either the hi-res board or the TRS-80) with one better matched to the other.
2. The high-resolution graphics cannot be changed, remaining the same as when the power was turned on. The memory write circuits are not working properly. Check the memory-select wiring at Z20; the write

Continued Listing

```
7F51 C06E7F   01040          CALL    FINOER           ; GET SCREEN START BYTE
7F54 E5       01050          PUSH    HL               ; SAVE THE START VALUE
7F55 0021BC7F 01060          LO      IX,N+3           : POINT TO THE TABLE
7F59 C06E7F   01070          CALL    FINOER           ; ANO OO THE WORK
7F5C E5       010B0          PUSH    HL               ; REAOY VALUE TO TRANSFER
7F50 01       01090          POP     OE               ; ANO TRANSFER TO OEST'N
7F5E E1       01100          POP     HL               ; RESTORE START POSITION
7F5F 014000   01110          LO      BC,40H           ; SCREEN BYTE LINE OFFSET
7F62 AF       01120          XOR     A                ; CLEAR CARRY FLAG
7F63 3ABB7F   01130          LO      A,(N+2)          : GET BYTE FROM STORAGE
7F66 77       01140 LOOP2    LO      (HL),A           : STASH IT ON SCREEN
7F67 09       01150          AOO     HL,BC            : MOVE UP ON THE SCREEN
7F6B E052     01160          SBC     HL,OE            : CHECK IF OONE YET
7F6A 20FA     01170          JR      NZ,LOOP2         : BACK IF NOT OONE
7F6C 77       011B0          LO      (HL),A           ; PUT LAST BYTE IN
7F60 C9       01190          RET                      : BACK TO BASIC
              01200 ;
              01210 ; #######################################################
              01220 ; FINOER SUBROUTINE LOCATES PROPER BYTE WITHIN HIRES AREA
              01230 ; #######################################################
              01240 ;
7F6E 2100C0   01250 FINOER   LO      HL,HIRES         : GET HI-RESOLUTION SCRN
7F71 007E00   01260          LO      A,(1X)           ; GET START 8YTE OFFSET
7F74 47       01270          LO      8,A              : PLACE IN B REGISTER
7F75 AF       01280          XOR     A                ; CLEAR THE CARRY FLAG
7F76 CB1B     01290          RR      B                : OIVIOE BY TWO ANO ...
7F7B CB19     01300          RR      C                ; ... ROTATE IN OROER ...
7F7A CB1B     01310          RR      B                ; ... ACTUALLY TO ...
7F7C CB19     01320          RR      C                ; ... MULTIPLY BY 64
7F7E 09       01330          AOO     HL,BC            ; MAKE NEW SCREEN POS'N
7F7F E5       01340          PUSH    HL               ; REAOY IT FOR TRANSFER
7FB0 01       01350          POP     OE               ; TRANSFER TO OESTIN'N
7FB1 007E01   01360          LO      A,(IX+1)         ; GET START BIT OFFSET
7FB4 4F       01370          LO      C,A              : PLACE IN MSB OF BC
7FB5 AF       013B0          XOR     A                ; CLEAR ACCUM TO ZERO
7FB6 47       01390          LO      B,A              ; PLACE IN LSB OF BC
7FB7 09       01400          AOO     HL,BC            : GET NEW START BIT
7FBB C9       01410          RET                      ; BACK TO CALLING ROUTINE
              01420 ;
7FB9          01430 N        EQU     $                ; MOMORY STORAGE POS'NS
              01440 ;
06CC          01450          ENO     06CCH            : BACK TO BASIC
00000 TOTAL ERRORS
30026  TEXT AREA BYTES LEFT


ENTRY  7F00 00230
FINOER 7F6E 01250   00640 01040 01070
HIRES  C000 00140   00410 01250
HOROUT 7F47 00870   00830
LOOP1  7F3B 00B00   00860
LOOP2  7F66 01140   01170
N      7FB9 01430   00630 00650 00760 00B70 01030 010B0 01130
PCLEAR 7F1B 00420   00470
PCLS   7F13 00390   00270
PHORIZ 7F21 00B30   00290
PVERT  7F40 01030   00310
XFER   0A7F 00150   00230
```

lines to the memory (Z11); and the write line from the computer (from edge card pin 13).

3. The high-resolution graphics keep changing without writing to them. The memory-select circuits may be selecting write for both read and write; check Z11. More likely, the memory refresh/select circuitry is miswired; check Z9a and Z3.

4. When creating lines of graphics, the dots do not appear in the correct place. This indicates the memory data and /or address lines are miswired; check the lines from the computer (pins 4-7, 9-11, 17-18, 20, 22, 24-28, 30-32, 34-36, 38 and 40), making sure they are in the correct order. Also check each memory circuit to be sure the address lines (pins 4-7, 10-13, and 15) are parallel in each memory IC. Finally, be sure Z4 correctly feeds Z10; Z5 correctly feeds Z11; Z6 correctly feeds Z12; and Z7 correctly feeds Z13. These four circuits are the memory count/multiplex circuits. Also check that Z10, 11, 12 and 13 correctly feed Z18 and 19.

5. No graphics are produced. This is a tough one. The fault could lie with

(a) the clock formed by Z1a-c

(b) the memory refresh circuits Z9b and Z3

(c) latch and shift registers Z16 and Z17

(d) memory circuits Z21 to Z26

(e) video output formed by Z30, Q1 and Q2.

Check the screen display carefully, because if any of these sections are working (except the video output) the screen will be affected in some way, even if it is minor. If herringbone or some tearing is present when the fine tuning is adjusted, then the video output and sync circuits are probably okay. Also, be sure that the mixing control is not turned fully counterclockwise (TRS-80 on, hi-res off).

6. The computer crashes to MEMORY SIZE? or otherwise acts problematically. The hi-res board has no effect on the computer. No data is written to the computer from the hi-res board at any point; it only receives information. If the computer crashes, then faulty wiring is likely.



Photo 6-1. Hi-Res graphics example.

Replace BASIC ROMs

In the past few years, more and more TRS-80 users have asked me the question, "I don't need BASIC because I do all my work in machine language. How can I use that space for my own routines and language in ROM?". The answer is simple: replace your ROMs with 2716 (2K x 1 byte), 2732 (4K x 1 byte) or 2764 (8K by 1 byte) EPROMs.

The process is electronically simple. The Level II (or Level I) ROMs are removed, and a board containing the new *and old* ROMs is inserted at the edge connector. This board, then, can select either ROMs at the flick of a switch – exactly like the Apple's 'softcards' do it.

This section will present a circuit to use 2716 EPROMs and any other ROMs together and, as a bonus, a way to hand control of your TRS-80 over to another *microprocessor!* The power of such processors as the 6502, 6800 series, the 8060 (SC/MP) and others then becomes available to the TRS-80 user. Together with the appropriate bootstrap and executive programs in ROM, the TRS-80 can act with the strengths of almost any language and almost any processor.

There is no secret to adding ROM. The area from 0000 to 37C0 is free to use, and some of that method has already been presented. Figure 6-5 presents the circuitry that will handle seven 2716 EPROMs, switchable with the 3-chip Level II ROM set.

The real trick is making another processor available to the TRS-80's hardware. This other processor must be able to:

- access memory and peripherals in the TRS-80 memory map
- address at least 32K of memory
- be able to move its software stack anywhere in memory
- refresh the 4116 dynamic memories.

Of these restrictions, the last two are the trickiest. Without also placing RAM on this outboard device, the 6502 cannot be used, because it requires its stack in page 1 (0100-01FF) and many of its fastest (and hence most advantageous) instructions are limited to page 0 (0000-00FF).



IC	TYPE	+5V	GND
Z1–Z7	2716	24	12
Z8	74LS138	16	8
Z9	74LS00	14	7

Figure 6-5. Circuit for replacing BASIC ROMs.

1. REMOVE DIP SHUNT Z3.
2. ALL SEVEN 2716'S ARE CONNECTED IN PARALLEL EXCEPT PIN 18.

However, the refresh requirement is the most severe. Because the RAS-only refresh is controlled within the TRS-80, and its signals are killed when the processor is removed, the entire refresh process must be handled outside the computer by chips which were not designed for dynamic memory support.

Before turning to the details, you may be asking "How can control be wrested from the Z-80?". The answer is found in the line marked TEST. This input line is present on pin 23 of the TRS-80 bus, and when brought low, causes all address lines (A0-A15), all data lines (D0-D7), read (RD), write (WR), input (IN), output (OUT), row address strobe (RAS), column address strobe (CAS) and memory select multiplex (MUX) to be put into three-state condition. This provides a wide-open computer bus for the outside world.



POWER UP TO MONITOR AT 3000 H.
MONITOR MUST EXECUTE :

```
3000     C30330     JP   3003H
3003     AF         XOR  A
3004     D300       OUT  (0),A
```

Figure 6-6. Modification needed for power-up monitor.

Power-Up Monitor

From my programmer (but not my user!) point of view, entering BASIC immediately upon power-up, or reset, is inconvenient and sometimes maddening. Rather, I would prefer a jump to a monitor of the type which can be found on the Ohio Scientific microcomputers: instead of MEMORY SIZE?, the user is presented with 'D/C/W/M?', which means 'Disk reboot, Cold start in BASIC (MEMORY SIZE?), Warm start in BASIC (READY), or Machine Language Monitor?'.

The user can exit from BASIC to the monitor and back at any point without jumping to a program-creaming MEMORY SIZE? The cold start serves that purpose, and is almost always by choice.

There is such a possibility on the TRS-80, so long as two conditions are met:

1. A machine language monitor is resident, preferably in ROM.

2. The restart from 0000 is redirected from BASIC to that machine language monitor, and/or the NMI located at 0066 is redirected to that machine language monitor. This latter configuration preserves the last location of the program counter on the stack for examination.

The first requirement is easy to meet, and is in my opinion the most logical use of a ROM memory addition.

```
              00100 ; ########################################################
              00110 ; POWER-UP PROGRAM FOR USE INOEPENOENTLY (WITHOUT BASIC
              00120 ; ROMS IN PLACE) OR IN CONJUNCTION WITH EXIT ANO RE-ENTRY
              00130 ; TO BASIC UP RESET TO 0000 (BEFORE OISC SYSTEM REBOOT).
              00140 ; ########################################################
              00150 ;
401A          00160 KPLACE  EQU     401AH           ; RAM STORAGE FOR STROKE
3000          00170         ORG     3000H           ; MONITOR ENTRY POINT
              001B0 ;
              00190 ; ########################################################
              00200 ; OPTIONAL SCREEN-CLEAR.  IF THE EXIT CONOITION OF THE
              00210 ; SCREEN IS IMPORTANT, THEN ELIMINATE CLEARING PROCESS
              00220 ; ########################################################
              00230 ;
3000 F3       00240         OI                      ; KILL THE INTERRUPTIONS
3001 E073E242 00250         LO      (42E2H),SP      ; SAVE STACK POINTER
3005 31E042   00260         LO      SP,42E0H        ; GET NEW STACK POINTER
300B F5       00270         PUSH    AF              ; SAVE REGISTERS FOR
3009 C5       002B0         PUSH    BC              ;       LATER OISPLAY
300A 05       00290         PUSH    OE              ;       OURING THE
300B E5       00300         PUSH    HL              ;       MONITOR ENTRY
300C 21003C   00310 CLS     LO      HL,3C00H        ; BEGINNING OF SCREEN
300F 11013C   00320         LO      OE,3C01H        ; NEXT POSITION ON SCREEN
3012 01FF03   00330         LO      BC.3FFH         ; NUMBER OF SCREEN POS'NS
3015 3620     00340         LO      (HL),20H        ; PRINT SPACE 1ST POS'N
3017 E0B0     00350         LOIR                    ; 0O IT FOR WHOLE SCREEN
              00360 ;
              00370 ; ########################################################
              003B0 ; OISPLAY OISK/MONITOR/WARM START/USER ROUTINE MESSAGE
              00390 ; ########################################################
              00400 ;
3019 219732   00410         LO      HL,MSG01        ; GET FIRST MESSAGE
301C 11C03C   00420         LD      OE,3CC0H        ; GET OISPLAY POSITION
301F C0BF32   00430         CALL    OISPLY          ; ANO OISPLAY ON SCREEN
3022 C0C331   00440 MENU    CALL    INPUT           ; GET INPUT FROM KEYBOARO
3025 FE63     00450         CP      63H             ; IS IT A LETTER "C"?
3027 2B13     00460         JR      Z,COLO          ; GO TO COLOSTART ROUTINE
3029 FE64     00470         CP      64H             ; IS IT A LETTER "O"?
302B CA0000   004B0         JP      Z,0000          ; GO TO OISK REBOOT
302E FE60     00490         CP      60H             ; IS IT A LETTER "M"?
3030 2B30     00500         JR      Z,MONTOR        ; GO TO MACHINE MONITOR
3032 FE75     00510         CP      75H             ; IS IT A LETTER "U"?
3034 2822     00520         JR      Z,USER          ; GO TO USER ROUTINE
3036 FE77     00530         CP      77H             ; IS IT A LETTER "W"?
303B 2B2A     00540         JR      Z,WARM          ; GO TO BASIC WARMSTART
303A 1BE6     00550         JR      MENU            ; LOOP BACK IF NONE
              00560 ;
              00570 ; ########################################################
              005B0 ; COLOSTART ROUTINE OUPLICATES LEVEL II ACTION TO 0075H.
              00590 ; STACK POINTER NOT RESET HERE BECAUSE COLOSTART OOES IT.
              00600 ; ########################################################
              00610 ;
303C F3       00620 COLO    OI                      ; INTERRUPTS TURNEO OFF
3030 AF       00630         XOR     A               ; CLEAR ACCUMULATOR
303E 03FF     00640 CLEAR   OUT     (0FFH),A        ; BEGIN WRITE-PORT LOOP
3040 210206   00650         LO      HL,0602H        ; GET COMMUNICATION BLOCK
3043 110040   00660         LO      OE,4000H        ; GET COMMUNICATION AREA
3046 013600   00670         LO      BC,0036H        ; GET SIZE OF COMM. BLOCK
3049 E0B0     006B0         LOIR                    ; BLOCK MOVE COMM. AREA
304B 30       00690         OEC     A               ; A = A-1 (A=0 AT START)
304C 30       00700         OEC     A               ; A = A-1 (FE, FC, F0...)
3040 20EF     00710         JR      NZ,CLEAR        ; CLEAR ALL EVEN PORTS
304F 0627     00720         LO      B,27H           ; GET 39 VAR. LOCATIONS
3051 12       00730 LOOP1   LD      (OE),A          ; BEGIN SETTING UP CHARS
3052 13       00740         INC     OE              ; GET NEXT MEM POS'N
3053 10FC     00750         OJNZ    LOOP1           ; LOOP THROUGH THEM ALL
3055 C37500   00760         JP      0075H           ; REST OF BASIC STARTUP
              00770 ;
              007B0 ; ########################################################
              00790 ; USER ENTRY ROUTINE REQUIRES THAT A TWO-BYTE AOORESS B
              00B00 ; STOREO IN MEMORY AT 40BE/40BF (16526/16527), <=USR(0)>
              00B10 ; ########################################################
              00B20 ;
305B E1       00B30 USER    POP     HL              ; BEGIN TO CLEAR THE
3059 01       00B40         POP     OE              ;       STACK OF ALL
305A C1       00B50         POP     BC              ;       REGISTERS PUSHEO
305B F1       00B60         POP     AF              ;       AT ENTRY POINT
305C E07BE242 00B70         LD      SP,(42E2H)      ; GET ORIGINAL STACK PTR
3060 2ABE40   00BB0         LO      HL,(40BEH)      ; GET USR(0) ENTRY POINT
3063 E9       00B90         JP      (HL)            ; ANO JUMP TO IT
              00900 ;
              00910 ; ########################################################
              00920 ; WARM START ROUTINE RESTORES STACK BEFORE GOING TO BASIC
              00930 ; ########################################################
              00940 ;
3064 E1       U0950 WARM    POP     HL              ; RESTORE ALL REGISTERS
3065 01       00960         POP     OE              ;       PUSHEO ON STACK
3066 C1       00970         POP     BC              ;       WHEN MONITOR
3067 F1       009B0         POP     AF              ;       WAS ENTEREO
306B E07BE242 00990         LO      SP,(42E2H)      ; GET ORIGINAL STACK PTR
306C C3CC06   01000         JP      06CCH           ; GO TO BASIC WARMSTART
              01010 ;
```

Listing 6-2. Power-up monitor program.

How Interpreters Work

The concept of computer languages is far too complex for a single section, a single chapter or even a single book. They run from easy, messy, but capable languages like BASIC through hard and messy languages like FORTRAN, to neat, structured, but obtuse languages like Pascal and LISP. In between are pseudo BASICs like BASEX, plus a whole range of compiled languages and hybrid self-definers like FORTH.

All these languages have one thing in common: they must eventually be broken into subroutines which operate in the machine language of the host processor. Compiled languages are broken into these subroutines when the program is written, but the bulk of material installed in small computers is accessed most easily by means of interpreters – executing one statement at a time, during a program's run.

How does a computer get to the information to be interpreted or compiled? Here's a short rundown of how an interpreter does its work; compilers are similar, but they won't be covered here.

Once a program has been constructed (and the method varies from machine to machine) it is in place for the computer to evaluate and execute. The process that follows is consistent with most interpreters:

Once a program has been constructed, and the method varies from machine to machine, it is in place for the computer to evaluate and execute. The process that follows is consistent with most interpreters:

1. Upon an execution command, the interpreter identifies the start of the program.

2. The first command from the program is obtained. The interpreter compares this command, byte for byte, against a table of legitimate commands. In some interpreters, the commands are stored as full words; in others, they are tokenized. When a valid entry is found in the command table, this stage of interpretation is complete. If a valid entry is not found, the routine is exited, usually via a loop which can be intercepted by extensions to the interpreter.

```
                 01020 ; ####################################################
                 D1D30 ; MACHINE LANGUAGE MONITOR IS SIMPLE, DISPLAYING REGISTER
                 D1D40 ; CONOITIONS AT ENTRY, AND ACCEPTING MEMORY CHANGES.  ALL
                 0105D ; REGISTERS ARE RESTOREO UPON EXIT FROM THIS ROUTINE.
                 0106D ; ####################################################
                 0107D ;
3D6F 21D632      01080 MONTOR  LD      HL,MSG02          ; GET REGISTER OISPLAY
3D72 11CD3C      D1D9D         LD      DE,3CC0H          ; GET SCREEN POSITIDN
3D75 COBF32      D110D         CALL    DISPLY            ; DISPLAY THE MESSAGE
3D7B 11DD30      0111D         LD      OE,300DH          ; GET SCREEN PDSITION
3D78 ED4BE242    D112D         LD      BC,(42E2H)        ; GET STACK POINTER PDS'N
307F C5          D113D         PUSH    BC                ; GET VALUE READY TO XFER
3DBD E1          D1140         PDP     HL                ; TRANSFER BYTES TD HL
3DB1 CD1731      D115D         CALL    WORDER            ; CDNVERT & DISPLAY BYTE
3084 00E5        01160         PUSH    IX                ; GET IT REAOY TO USE
3DB6 E1          D1170         PDP     HL                ; ANO DD IT WITH IT
3087 CD1731      011B0         CALL    WOROER            ; CONVERT & OISPLAY 8YTES
30BA FDE5        D1190         PUSH    IY                ; GET IT REAOY TO USE
3DBC E1          D1200         PDP     HL                ; AND DD IT WITH IT
3DBD C01731      01210         CALL    WOROER            ; CONVERT & OISPLAY IT
3D9D 2A0E42      0122D         LD      HL,(420EH)        ; POINT TO AF STACK VALUE
3D93 CD1731      D123D         CALL    WOROER            ; CDNVERT & OISPLAY BYTE
3D96 2A0C42      01240         LD      HL,(420CH)        ; POINT TO 8C STACK VALUE
3099 C01731      D12S0         CALL    WORDER            ; CDNVERT & OISPLAY 8YTE
309C 2A0A42      D1260         LD      HL,(420AH)        : POINT TO OE STACK VALUE
3D9F CD1731      01270         CALL    WDRDER            ; CONVERT & OISPLAY 8YTE
30A2 2ADB42      01280         LD      HL,(42D8H)        ; POINT TO HL STACK VALUE
30AS C01731      01290         CALL    WOROER            ; CDNVERT & OISPLAY BYTE
30AB ED5F        01300         LD      A,R               ; GET R REGISTER INTO A
30AA 67          D1310         LD      H,A               ; GIVE IT FOR CONVERSION
30AB EDS7        D1320         LD      A,I               ; GET I REGISTER INTO A
30A0 6F          0133D         LD      L,A               ; GIVE IT FOR CONVERSION
3DAE C01731      D1340         CALL    WOROER            ; CCNVERT & DISPLAY BYTE
3D81 118030      013SD         LO      OE,3080H          ; GET NEW VIOEO POSITION
30B4 08          01360         EX      AF,AF'            ; TRANSFER OTHER VALUE
30B5 FS          0137D         PUSH    AF                ; READY TO XFER TD HL
30B6 E1          013B0         PDP     HL                ; EFFECT TRANSFER TO HL
3087 DB          D1390         EX      AF,AF'            ; RETURN DRIGINAL VALUE
3DBB CD1731      D140D         CALL    WDRDER            ; CDNVERT & DISPLAY BYTE
3DBB D9          D141D         EXX                       ; TRANSFER BC, DE, HL
308C ES          01420         PUSH    HL                ; FIRST SLIP BC ON STACK.
3080 05          01430         PUSH    OE                ; THEN PUSH OE THERE,
3DBE CS          01440         PUSH    8C                ; AND THEN THE LAST ONE.
3D8F D9          014SD         EXX                       ; TRANSFER REGISTERS 8ACK
30C0 E1          D146D         PDP     HL                ; GET VALUE ALL READY
30C1 C01731      0147U         CALL    WOROER            ; CONVERT & OISPLAY BYTE
30C4 E1          D1480         POP     HL                ; GET OE VALUE READY
30CS C01731      01490         CALL    WORDER            ; CONVERT & OISPLAY 8YTE
30CB E1          D1S00         POP     HL                ; GET HL VALUE READY
30C9 C01731      D1510         CALL    WOROER            ; CONVERT & OISPLAY 8YTE
30CC 11DD3F      0152D CHECK   LO      DE,3F00H          ; GET NEW SCREEN POS'N
30CF CD1731      D1530         CALL    WOROER            ; CONVERT & OISPLAY 8YTE
30D2 1C          01S40         INC     E                 ; 8UMP SCREEN POSITION
30D3 7E          01SS0         LO      A,(HL)            ; GET VALUE FROM MEMORY
3004 C02431      01560         CALL    HEXASC            ; ANO OISPLAY IT IN ASCII
                 01S70 ;
                 D1S80 ; ####################################################
                 D1S90 : AODRESS MOD ROUTINE GETS KEY8OARO VALUE & LOOPS BACK
                 01600 ; ####################################################
                 01610 ;
3007 CDC331      0162D AODMOD  CALL    INPUT             ; GET VALUE FROM KEY8OARO
300A FE21        01630         CP      '!'               ; TEST FIRST IF EXECUTE
30DC 2832        01640         JR      Z,EXEC            ; OUT IF EXECUTE COMMANO
30DE FE2F        016S0         CP      '/'               ; TEST SECONO IF OATA
30ED CA6E31      01660         JP      Z,OATMOO          : OUT IF OATA MOO CDMMAND
3DE3 FE2A        0167D         CP      '*'               ; TEST THIRD IF RET MENU
3DE5 CADC3D      D16BD         JP      Z,CLS             ; DUT TO MENU IF A STAR
30E8 FE30        01690         CP      '0'               ; SEE IF <0 CHARACTER
3DEA 38EB        01700         JR      C,AODMDD          ; LDOP BACK IF <0 CHAR.
3DEC FE67        01710         CP      67H               : SEE IF >F CHARACTER
3DEE 30E7        D172D         JR      NC,ADDMOO         ; LOOP 8ACK IF >F CHAR.
30F0 FE3A        01730         CP      ':'               ; SEE IF <9 CHARACTER
3DF2 3804        01740         JR      C,NUMBER          ; GO TO NUMBER ROUTINE
3DF4 FE61        017S0         CP      61H               ; SEE IF >A CHARACTER
30F6 38DF        01760         JR      C,ADDMOO          ; LOOP 8ACK IF <A & >9
30F8 21D43F      0177D NUMBER  LD      HL,3F04H          ; GET AODRESS SCREEN POSN
30F8 11033F      01780         LO      OE,3F03H          ; GET NEXT SCREEN POS'N
30FE D1D300      D179D         LD      8C.3              ; GET THREE TOTAL POS'NS
3101 ED80        01800         LOIR                      ; ANO MOVE THEM OVER
3103 2B          0181D         OEC     HL                ; REPOSITION TD LAST CHAR
3104 FE60        01820         CP      60H               : COMPARE TO L.C. ALPHA
31D6 3802        01830         JR      C,ZIP8Y           ; IF NUMBERIC, THEN SKIP
3108 0620        01840         SU8     20H               ; ELSE CONVERT TO U.CASE
31DA 77          D18S0 ZIP8Y   LO      (HL),A            ; OISPLAY NEW CHARACTER
3108 C04331      0186D NUM2    CALL    ASCHEX            ; CONVERT OISPLAY TO HL
310E 188C        01870         JR      CHECK             ; ANO LOOP 8ACK FOR MORE
3110 21063F      01880 EXEC    LO      HL,3F06H          ; POINT HL TO AOORESS
3113 C04331      D1890         CALL    ASCHEX            : ANO CDNVERT TO HEX
3116 E9          0190D         JP      (HL)              ; HL CONTAINS AOORESS
                 0191D ;
                 D1920 ; ####################################################
                 01930 ; SU8ROUTINE RESPONSIBLE FOR CONVERTING & OISPLAYING TWO-
                 D1940 ; BYTE WDRDS DELIVERED TD IT IN THE HL REGISTER.
```

Listing Continued . . .

3. If the command is identified as a legitimate one, a subroutine is called which executes the command. That subroutine in turn may further examine the command line for operands and conditions, incrementing and decrementing pointers in its search for required, and valid, information. Further subroutines are entered as necessary to evaluate and put to use this additional information. In-memory variables and pointers are set up, modified, and accessed by all subroutines, usually from a master table which defines variable types and syntax conditions. Transcendental functions are also accessed via tables within the interpreter itself. Error checking is done at all points.

4. When the execution of each subroutine is completed, it returns to the calling program. Eventually, all subroutines have returned to their upper level of subroutine 'nesting'. Then the execution routine finds itself re-entered, positioned at the next executable point in the program, where the execution process is repeated.

5. The execution routine may, depending on the language, find itself repositioned in the program out of normal execution sequence. On the other hand, some languages have an inherent structure which disallows any repositioning, demanding an inviolable first-to-last execution sequence. In these latter interpreters, repositioning will be interpreted as an error condition.

6. If any information, commands, program order or program syntax is incorrect, an error handling routine is entered, usually by direct jump rather than subroutine call. Normally, this routine prepares and presents an error message. It returns the program from execution level, arbitrarily cancelling any nested execution subroutines by readjusting stack pointers and other variable information. This readjustment is necessary to avoid unsettling the user-interactive command-level routine, and causing the processor to lose its way in a complex of incomplete subroutines.

7. Upon completion of all program statements, the program is returned from execution level to command level. Some interpreters allow commands to be entered, interpreted, and executed from a command buffer, without actually entering a program execution condition.

Continued Listing

```
              01950 ; ########################################################
              01960 ;
3117 1C       01970 WORDER  INC     E               ; BUMP DE REGISTER ALONG
3118 1C       01980         INC     E               ; SOME MORE BUMPING ...
3119 1C       01990         INC     E               ; ... AND SOME MORE OF IT
311A 7C       02000         LD      A,H             ; GET FIRST BYTE OF IT
311B CD2431   02010         CALL    HEXASC          ; CONVERT & DISPLAY BYTE
311E 7D       02020         LD      A,L             ; GET SECOND BYTE OF IT
311F CD2431   02030         CALL    HEXASC          ; CONVERT & DISPLAY BYTE
3122 1C       02040         INC     E               ; AND POSITION SCREEN
3123 C9       02050         RET                     ; AND BACK TO CALLER
              02060 ;
              02070 ; ########################################################
              02080 ; HEXADECIMAL TO ASCII CONVERSION FOR TWO-BYTE WORDS
              02090 ; ########################################################
              02100 ;
3124 F5       02110 HEXASC  PUSH    AF              ; SAVE BYTE IN AF REG.
3125 E6F0     02120         AND     0F0H            ; AND MASK OUT LOW NYBBLE
3127 0F       02130         RRCA                    ; BEGIN ROTATING BIT ...
3128 0F       02140         RRCA                    ; ... IN ORDER TO TEST...
3129 0F       02150         RRCA                    ; ... THE LOW NYBBLE ...
312A 0F       02160         RRCA                    ; ... ALL BY ITSELF.
312B CD3931   02170         CALL    HXAC            ; BYTE RANGE EVALUATION
312E 12       02180         LD      (DE),A          ; DISPLAY ON THE SCREEN
312F 1C       02190         INC     E               ; AND MOVE TO NEXT POS'N
3130 F1       02200         POP     AF              ; RESTORE ORIGINAL BYTE
3131 E60F     02210         AND     0FH             ; AND MASK OUT HIGH BITS
3133 CD3931   02220         CALL    HXAC            ; RANGE EVALUATION ROUT.
3136 12       02230         LD      (DE),A          ; AND DISPLAY ON SCREEN
3137 1C       02240         INC     E               ; MOVE TO NEXT VIDEO POSN
3138 C9       02250         RET                     ; AND BACK TO CALLER
              02260 ;
              02270 ; ########################################################
              02280 ; HEX-ASCII RANGE EVALUATION FOR 0 TO 9 AND A TO F AREAS
              02290 ; ########################################################
              02300 ;
              02310 ;
3139 FE0A     02320 HXAC    CP      0AH             ; CHECK AGAINST 10 DEC.
313B 3003     02330         JR      NC,NEXTX        ; IF >10 THEN ALPHA CHAR
313D C630     02340         ADD     A,30H           ; ELSE NUMERIC - CONVERT
313F C9       02350         RET                     ; AND BACK TO CALLER
3140 C637     02360 NEXTX   ADD     A,37H           ; ALPHABETIC - CONVERT
3142 C9       02370         RET                     ; AND BACK TO CALLER
              02380 ;
              02390 ; ########################################################
              02400 ; ASCII TO HEXADECIMAL CONVERSION FOR TWO-BYTE WORDS
              02410 ; ########################################################
              02420 ;
              02430 ;
3143 CD6331   02440 ASCHEX  CALL    ACHX            ; RANGE EVALUATION ROUT.
3146 4F       02450         LD      C,A             ; SAVE PART OF CONVERSION
3147 2B       02460         DEC     HL              ; AND GET NEXT BYTE
3148 CD5B31   02470         CALL    LLLLS           ; EXECUTE LEFT ROTATES
314B B1       02480         ADD     A,C             ; AND ADD TO MAKE BYTE
314C 4F       02490         LD      C,A             ; SAVE IT BACK IN C REG.
314D 2B       02500         DEC     HL              ; AND MOVE TO NEXT BYTE
314E CD6331   02510 AX2     CALL    ACHX            ; DO RANGE EVALUATION
3151 47       02520         LD      B,A             ; AND SAVE IT IN B REG.
3152 2B       02530         DEC     HL              ; GET FINAL BYTE READY
3153 CD5B31   02540         CALL    LLLLS           ; AND EXECUTE LEFT ROTATE
3156 B0       02550         ADD     A,B             ; CREATE COMPLETE BYTE
3157 47       02560         LD      B,A             ; AND SAVE IT IN B REG.
3158 C5       02570         PUSH    BC              ; GET 2 BYTES TO XFER
3159 E1       02580         POP     HL              ; TRANSFER TO HL REGISTER
315A C9       02590         RET                     ; AND BACK TO CALLER
315B CD6331   02600 LLLLS   CALL    ACHX            ; EVALUATE RANGE OF CHAR
315E 07       02610         RLCA                    ; BEGIN LEFT ROTATES ...
315F 07       02620         RLCA                    ; ... WHICH WILL POS'N...
3160 07       02630         RLCA                    ; ... BYTE READY FOR ...
3161 07       02640         RLCA                    ; ... CONVERSION.
3162 C9       02650         RET                     ; AND GO BACK TO CALLER
3163 7E       02660 ACHX    LD      A,(HL)          ; GET BYTE FROM SCREEN
3164 FE40     02670         CP      40H             ; CHECK AGAINST ALPHA
3166 3003     02680         JR      NC,NEXTZ        ; IF NUMERIC THEN JUMP
3168 D630     02690         SUB     30H             ; ELSE NUMBER TO HEX
316A C9       02700         RET                     ; AND BACK TO CALLER
316B D637     02710 NEXTZ   SUB     37H             ; THEN IT'S ALPHA TO HEX
316D C9       02720         RET                     ; AND BACK TO CALLER
              02730 ;
              02740 ; ########################################################
              02750 ; ROUTINE TO ACCEPT DATA FOR INPUT TO DISPLAYED MEMORY
              02760 ; LOCATIONS, WITH EXIT TO MENU UPDATE OR MEMORY INCREMENT
              02770 ; ########################################################
              02780 ;
316E CDC331   02790 DATMOD  CALL    INPUT           ; GET CHAR. FROM KEYBRD.
3171 FE2E     02800         CP      '.'             ; IS IT A PERIOD?
3173 CAB031   02810         JP      Z,ADEXIT        ; IF SO, EXIT TO ADDR MOD
3176 FE0D     02820         CP      0DH             ; IS IT A CARRIAGE RET?
3178 282F     02830         JR      Z,NEXTD         ; IF SO, GO TO NEXT DATA
317A FE30     02840         CP      '0'             ; BEGIN TESTING FOR RANGE
317C 38F0     02850         JR      C,DATMOD        ; BACK IF <0 CHARACTER
317E FE67     02860         CP      67H             ; CHECK AGAINST LC ALPHA
3180 30EC     02870         JR      NC,DATMOD       ; IF >F THEN GO BACK
```

Listing Continued . . .

It was natural that Radio Shack would choose an inexpensive storage medium, cassettes, to accompany their low cost microcomputer. Because ordinary cassette players are audio devices, the tape saving and loading routines were designed to be slow but sure. With care, the CTR series of recorders can be as reliable as any other storage system designed for the TRS-80.

The weakness of the tape process comes from the obvious mismatching of an audio device, of very limited precision, with a digital device of unyielding high-precision. Portable cassette recorders are intended to reproduce audio signals with a reasonable level of fidelity. What constitutes a reasonable level of fidelity is disputable, and only a person with a true tin ear would not be able to pick out a portable player, from amongst a group of high fidelity tape decks.

But even with this 'reasonable' fidelity, much of what we recognize as harmonies and instrumentation is perceptible only because we already have an acculturated comprehension of sound; and this directly influences what we believe we are hearing. Our minds, in conjunction with our ears - average, fill in, smooth over and forgive minuscule failings. We have internal mechanisms which remember our experiences.

The cassette load/save system consists of seven major elements:

1. **Serialization.**
The individual bytes of computer data are converted into a stream of individual bits. This is a completely digital process, and the timing is provided by the computer.

2. **Audio Processing.**
The signal is converted into a 'digital audio' wave for recording on tape decks of unknown polarity. In other words, a digital, one to zero, signal is converted to an audio, one to minus one to zero, signal. In this way, an 'upside down' signal looks the same to a computer as the original.

3. **Recording.**
The signal goes through the tape recorder's electronics, and is recorded on a thin strip of magnetic tape. The audio electronics round the wave's edge, and the limitations of the tape contribute noise to the signal.

Continued Listing

```
31B2 FE3A     028B0          CP      ':'           ; TEST FOR NUMERIC >9
31B4 3B04     0289D          JR      C,INOATA      ; IF <9 THEN GET OATA
31B6 FEB1     D2900          CP      61H           ; TEST FOR ALPHA <A
31BB 3BE4     D2910          JR      C,OATMOO      ; IF <A THEN GO BACK
31BA 210A3F   02920 INOATA   LO      HL,3F0AH      ; READY THE SCREEN PTR.
31B0 F5       0293D          PUSH    AF            ; SAVE VALUE FROM KEYBRO
31BE 7E       02940          LD      A,(HL)        ; GET LOWER ASCII NYBBLE
31BF 32093F   D2950          LD      (3F09H),A     ; ANO PUT IN HIGH POS'N
3192 F1       D296D          POP     AF            ; RESTORE VALUE FROM KBO
3193 FE60     02970          CP      60H           ; CHECK AGAINST LC ALPHA
3195 3B02     029B0          JR      C,ZIPZY       ; IF LC, THEN SKIP PAST
3197 D620     0299D          SUB     20H           ; ELSE CDNVERT TO U.C.
3199 77       03000 ZIPZY    LO      (HL),A        ; ANO OISPLAY ON SCREEN
319A CD4E31   D3D1D          CALL    AX2           ; SINGLE BYTE CDNVERSION
3190 7C       03020          LO      A,H           ; SAVE ONE 8YTE IN A REG.
319E F5       03D30          PUSH    AF            ; SAVE THAT NOW ON STACK
319F 21063F   03040          LO      HL,3F06H      ; POINT HL TO SCREEN POSN
31A2 C04331   0305D          CALL    ASCHEX        ; EVALUATE AOORESS THERE
31A5 F1       03060          POP     AF            ; RESTORE VALUE TO SHOW
31A6 77       03070          LD      (HL),A        ; ANO PUT ON THE SCREEN
31A7 1B07     03DBD          JR      EXIT1         ; NDW GD OUT ANO STORE
31A9 21063F   03090 NEXTO    LO      HL,3F06H      ; POINT HL TO SCREEN POSN
31AC C04331   03100          CALL    ASCHEX        ; CONVERT ADDRESS TO HEX
31AF 23       03110          INC     HL            ; HOVE OVER TO NEXT POSN
31B0 11003F   03120 EXIT1    LD      OE,3F00H      ; POINT OE AOOR. OISPLAY
31B3 C01731   03130          CALL    WOROER        ; ANO CONVERT/OISPLAY IT
31B6 1C       03140          INC     E             ; GO TO NEXT SCREEN POSN
31B7 7E       0315D          LO      A,(HL)        ; GET VALUE FROM HEHORY
31BB C02431   03160          CALL    HEXASC        ; ANO CONVERT FOR OISPLAY
31BB 1BB1     03170          JR      DATMOO        ; ANO BACK FOR SOME MORE
31B0 21063F   031BD AOEXIT   LO      HL,3F06H      ; POINT TO PRESENT AOOR.
31C0 C30B31   0319D          JP      NUM2          ; AND BACK TO UPOATE HENU
              0320D ;
              03210 ; ##########################################################
              03220 ; COHPLETE KEYBOARO ROUTINE BELOW HAY BE CALLEO BY NOT
              03230 ; ONLY THE MONITOR ROUTINES, BUT ANY ROUTINES NEEOING AN
              03240 ; UPPER/LOWER CASE, AUTOREPEAT, BEEP ORIVER.  FOR FURTHER
              03250 ; OESCRIPTION, SEE SUPPLEMENT TO CHAPTER ON KEYBOARO I/O
              03260 ; ##########################################################
              0327D ;
31C3 213640   03280 INPUT    LO      HL,4036H      ; SAME AS LII 8UFFER
31C6 01013B   03290          LO      BC,3B01H      ; FIRST KEYBOARD ROW
31C9 1600     03300          LO      0,0           ; COUNTER FDR COLUMNS
31CB 0A       03310 KEYPRS   LD      A,(BC)        ; RETRIEVE ROW CDNTENTS
31CC 5F       03320          LD      E,A           ; SAVE IT TEMPORARILY
31CD A3       03330          AND     E             ; SET FLAGS FDR TESTING
31CE 201B     03340          JR      NZ,STRDKE     ; NOT ZERO IF KEY PRESSED
3100 77       D3350          LD      (HL),A        ; SAVE CURRENT VALUE
3101 14       03360 RECHEK   INC     D             ; INCREMENT ROW COUNTER
3102 2C       03370          INC     L             ; INCREMENT STORAGE AOOR.
31D3 CB01     033B0          RLC     C             ; GET NEXT KEYBOARD CDL.
31D5 79       03390          LD      A,C           ; GET VALUE INTD ACCUM.
31D6 06B0     03400          SUB     B0H           ; LAST ROW IS 3BBD HEX
31DB 20F1     U341D          JR      NZ,KEYPRS     ; NEXT CHECK IF NDT DONE
310A 0607     03420          LD      B,7           ; COUNTER OF KEYBRD ROWS
310C 20       03430 CLRMEM   OEC     L             ; START COUNTING BACKWARO
310D B6       03440          ADO     A,(HL)        ; AND AOD IT UP IN ACCUM.
310E 10FC     03450          OJNZ    CLRMEM        ; ANO DD IT FOR 7 RDWS
31E0 A7       U3460          ANO     A             ; TEST FOR ANY KEY DOWN
31E1 3E00     03470          LO      A,0           ; A=0, FLAGS ARE INTACT
31E3 C0       034B0          RET     NZ            ; BACK IF KEYS IN USE
31E4 321A40   03490          LD      (KPLACE),A    ; ELSE DELAY GETS RESET
31E7 C9       03500          RET                   ; AND GD BACK ANYWAY
31E8 A6       03510 STRDKE   ANO     (HL)          ; CHECK KEYSTROKE STORAGE
31E9 2B1B     0352D          JR      Z,FOUND       ; NEW KEY IF NDT SAME DNE
31EB 3A1A4D   D353D          LD      A,(KPLACE)    ; NEW CHECK SPECIAL STDRE
31EE 3C       03540          INC     A             ; LET STDRE = STORE + 1
31EF 321A40   03550          LD      (KPLACE),A    ; AND PUT IN 8ACK THERE
31F2 FEFF     03560          CP      0FFH          ; CHECK IF IT IS AT END
31F4 2B0B     0357D          JR      Z,OECA        ; IF SO, THEN HDLO THERE
31F6 C5       03580          PUSH    BC            ; SAVE ROW CDUNTER REG.
31F7 06FF     U3590          LD      B,0FFH        ; GET DELAY VALUE INTD B
31F9 10FE     03600 TMWSTE   DJNZ    TMWSTE        ; AND DELAY JUST A BIT
31FB C1       03610          POP     BC            ; RESTDRE RDW CDUNTER
31FC 1803     03620          JR      RECHEK        ; ANO 8ACK TO CHECK NEXT
31FE 3D       U3630 DECA     OEC     A             ; LET A = A - 1 (STDRE)
31FF 321A40   03640          LD      (KPLACE),A    ; AND PUT IT IN STORAGE
3202 7B       03650          LD      A,E           ; GET KEYBOARD BYTE BACK
32U3 73       03660 FOUND    LD      (HL),E        ; STDRE IT IS STRDKE AREA
3204 7A       03670          LD      A,0           ; GET RDW CDUNTER FRDM D
32U5 07       036B0          RLCA                  ; AND BEGIN PRDCESS DF...
32U6 07       03690          RLCA                  ; ...CDNVERTING IT...
3207 D7       03700          RLCA                  ; ...TQ AN DFFSET VALUE
320B 57       03710          LD      D,A           ; ANO PUT IT BACK IN 0
3209 0E01     03720          LD      C,1           ; GET NUMBER DNE READY
320B 79       03730 BACKUP   LD      A,C           ; ACCUM. HAS C FDR MASK
320C A3       03740          AND     E             ; TEST IF C = KEYSTRDKE
320D 2005     03750          JR      NZ,ARDUND     ; IF NDT, THEN GD ARDUND
320F 14       03760          INC     D             ; ELSE 0 = ROW + COLUMN
3210 CB01     03770          RLC     C             ; C SET TD NEXT CDLUMN
3212 1BF7     037B0          JR      BACKUP        ; GO BACK ANO TEST AGAIN
3214 3AB03B   03790 AROUND   LD      A,(3BBDH)     ; GET SHIFT ROW FOR TEST
3217 47       D3BDD          LD      B,A           ; AND SAVE IT IN B REG.
```

Listing Continued

4. Storage.
The tape sits on the shelf, affected by temperature and humidity, where its oxide coating may 'creep'. The tape may stretch or buckle or warp, and its upper and lower edges may become slightly feathered.

5. Playback.
The recorded signal, including warps, dropouts, feathering, creep and noise, is fed to the playback electronics. This audio circuit contributes further noise, providing a purely low grade audio signal to the computer.

6. Digital Processing.
The signal is received, its top and bottom edges are squared, and it is returned to the one to zero digital state. The timing is provided by the recorded tape in cooperation with timing loops provided by the computer.

7. De-Serialization.
A completed group of bits is assembled into an 8 bit byte for use by the CPU in determining synchronization, type of program, loading location, etc.

An oscilloscope representation of a digital signal being generated during the CSAVE routine is shown below. The signal changes from one to zero very crisply, spending only a few nanoseconds (not visible at all on the photo) in the transition area between one and zero. This true digital signal is measured just before the audio processing section sent to the cassette.



The audio processing is actually no more than a digital signal whose polarity is reversed. Two outputs of a latch are tied together, and as one goes high, the other is forced low. Between pulses, the signal floats to the middle. This is done by data bits 0 and 1 of Z59, which are alternately switched by the CPU during CSAVE. The digital signal as it leaves the cassette port is shown in the second photograph.

The sharp edges of the signal have been ever so slightly blurred, partly due to the capacitance

Continued Listing

```
3218 7A        03810          LD     A,0          ; GET ROW COUNTER BACK
3219 C640      03820          ADO    A,40H        ; ANO CONVERT TO ASCII
3218 FE60      03830          CP     60H          ; IS IT UP/LW/GRAFIX/CTRL
3210 3016      03840          JR     NC,JUMP1     ; GO OUT IF GRAPHICS
321F S7        03BS0          LD     0,A          ; SAVE PARTLY CONVERTEO
3220 3A403B    03B60          LD     A,(3B40H)    ; GET VALUE FOUNO 7TH ROW
3223 E610      03870          ANO    10H          ; CHECK IF OOWN ARROW
322S 2009      03B80          JR     NZ,CNTROL    ; IF SO, PROOUCE CONTROL
3227 7A        03B90          LD     A,0          ; ELSE GET VALUE BACK
3228 C80B      03900          RRC    8            ; 8 BUMPS INTO CARRY FLAG
322A 3830      03910          JR     C,GOAWAY     ; IF CARRY, THEN SHIFT
322C C620      03920          A00    A,20H        ; IF NOT THEN LOWER CASE
322E 1839      03930          JR     GOAWAY       ; ANO GET OUT OF ROUTINE
3230 7A--      03940 CNTROL   LO     A,0          ; IF CONTROL COOE, GET IT
3231 0640      03950          SU8    40H          ; GET RIO OF ASCII MASK
3233 1B34      03960          JR     GOAWAY       ; ANO GET OUT OF ROUTINE
323S 0670      03970 JUMP1    SU8    70H          ; THE 8ALANCE OF THE
3237 3010      039B0          JR     NC,JUMP2     ;    ROUTINE 8ELOW UP TO
3239 C640      03990          A00    A,40H        ;    THE BEEP SECTION IS
323B FE3C      04000          CP     3CH          ;    VIRTUALLY IOENTICAL
3230 3B02      04010          JR     C,JUMP3      ;    TO THE KEYBOARO
323F EE10      04020          XOR    10H          ;    OETERMINATION SUB-
3241 CB08      04030 JUMP3    RRC    B            ;    ROUTINE FOUNO IN
3243 3024      04040          JR     NC,GOAWAY    ;    RCH.  THIS ENTIRE
3245 EE10      04050          XOR    10H          ;    ROUTINE IS REPEATEO
3247 1820      04060          JR     GOAWAY       ;    BEOAUSE IT CAN
3249 07        04070 JUMP2    RLCA                ;    SERVE AS AN EXACT
324A CB0B      040B0          RRC    B            ;    REPLACEMENT FOR
324C 3000      04090          JR     NC,JUMP4     ;    THE LEVEL II 8ASIC
324E 21S932    04100 JUMP4    LD     HL,TABLET    ;    ROUTINES WHEN (IF)
3251 4F        04110          LD     C,A          ;    THE ROMS HAVE 8EEN
3252 0600      04120          LO     8,0          ;    REMOVED, REPLACEO,
32S4 09        04130          A00    HL,BC        ;    OISABLEO, ETC.
3255 7E        04140          LO     A,(HL)       ;    SEE KEY8OARO ROUTINE
3256 1811      04150          JR     GOAWAY       ;    RUNOOWN ELSEWHERE
32S8 3C--      04160          INC    A            ;    IN THIS BOOK......
3259 0000      04170 TABLET   OEFW   0000H        ; CARR. RET. / CARR. RET.
3258 1F1F      041B0          OEFW   1F1FH        ; CLEAR SCRN / CLEAR SCRN
3250 0101      04190          OEFW   0101H        ; 8REAK KEY / 8REAK KEY
325F S81B      04200          OEFW   18S8H        ; EOIT ESCAPE / UP ARROW
3261 0A00      04210          OEFW   000AH        ; NO CHANGE / LINEFEEO
3263 0818      04220          OEFW   180BH        ; BACKSP. LINE / BACKSP.
326S 0919      04230          OEFW   1909H        ; 32-CHAR MOOE / HOR TAB
3267 2020      04240          OEFW   2020H        ; SPACE / SPACE
3269 S7        04250 GDAWAY   LO     0,A          ; SAVE VALUE IN 0 REG.
326A 018001    04260          LO     8C,180H      ; OEBOUNCE VALUE ANO
3260 0B        04270 OELAYS   OEC    BC           ;    IMPLEMENTEO AT THIS
326E 7B        042B0          LO     A,8          ;    POINT FOR ACTUAL
326F 81        04290          OR     C            ;    KEY8OARO SCAN WHEN
3270 20F8      04300          JR     NZ,OELAYS    ;    CHARACTERS ARE
3272 7A        04310          LD     A,0          ; GET STOREO VALUE BACK
3273 FS        04320          PUSH   AF           ; SAVE ACCUM. & FLAGS
3274 0640      04330          LD     B,40H        ; GET BEEP LENGTH VALUE
3276 3A3040    04340          LD     A,(4030H)    ; GET STATUS OF SCREEN
3279 E6F0      043S0          ANO    0F0H         ; MASK SCREEN CHANGE
327B 67        04360          LO     H,A          ; STORE MSB IN H REG.
327C F602      04370          OR     2            ; SET BIT 1 TO BE ON
327E 6F        04380          LD     L,A          ; STORE ALT. MSB IN L REG
327F 70        04390 8EEPER   LO     A,L          ; GET ALT. MSB TO OUTPUT
3280 03FF      04400          OUT    (0FFH),A     ; ANO OUTPUT RISING WAVE
3282 7C        04410          LO     A,H          ; GET NORMAL MSB CHAR.
3283 03FF      04420          OUT    (0FFH),A     ; ANO OUTPUT FALLING WAVE
3285 CS        04430          PUSH   BC           ; SAVE NOTE LENGTH VALUE
3286 0640      04440          LO     B,40H        ; GET FREQUENCY OELAY
328B 10FE      04450 FREQCY   OJNZ   FREQCY       ; ANO WAIT A LITTLE WHILE
328A C1        04460          POP    BC           ; NOW RESTORE LENGTH VAL.
3288 10F2      04470          OJNZ   8EEPER       ; ANO GO BACK THAT LENGTH
3280 F1        04480          POP    AF           ; RESTORE ORIGINAL CHAR.
328E C9        04490          RET                 ; ANO BACK TO CALLER
               04500 ;
               04510 ; ##################################################
               04520 ; ROUTINE 8ELOW TAKES SIMPLE MESSAGES ANO OISPLAYS THEM
               04530 ; ##################################################
               04540 ;
328F 7E        04SS0 OISPLY   LO     A,(HL)       ; GET FIRST MSG CHARACTER
3290 A7        04560          ANO    A            ; TEST IF 0 OR CHARACTER
3291 CB        04570          RET    Z            ; BACK TO CALLING ROUTINE
3292 12        045B0          LO     (OE),A       ; OISPLAY THE CHARACTER
3293 23        04SB0          INC    HL           ; GET NEXT MSG CHARACTER
3294 13        04600          INC    OE           ; GET NEXT OISPLAY POS'N
3295 18F8      04610          JR     OISPLY       ; ANO TEST NEXT CHARACTER
               04620 ;
               04630 ; ##################################################
               04640 ; MESSAGES FOR OISPLAY FOLLOW.  IN A STRIPPEO SOFTWARE
               04650 ; MONITOR CONFIGURATION, THESE MESSAGES MAY BE ELIMINATEO
               04660 ; ANO OISPLAY PARAMETERS CHANGED ELSEWHERE IN THE LISTING
               04670 ; ##################################################
               04680 ;
3297 3C        04690 MSG01    OEFM   '<C>OLOSTART, <O>ISKBOOT, <M>ONITOR, '
32BB 3C        04700          OEFM   '<U>SERJUMP, <W>ARMSTART? '
3204 BF        04710          OEFB   BFH
3205 00        04720          OEFB   00
3206 5A        04730 MSG02    OEFM   'ZBO REGISTERS AT MONITOR ENTRY: '
```



introduced by the cables and tape input. This is the first (and least significant) step in the extensive route of signal degradation.

```
32F6 20        04740          OEFM   '                                        '
3316 53        04750          OEFM   'SP=        IX=        IY=        AF=     '
3336 42        04760          OEFM   '8C=        OE=        HL=        RI=     '
33S6 41        04770          OEFM   'ALTERNATE REGISTERS AT MONITOR E'
3376 4E        047B0          OEFM   'NTRY (NOT USEO IN LEV II 8ASIC):'
3396 41        04790          OEFM   'AF=        BC=        OE=        HL=     '
33B8 20        04800          OEFM   '                                        '
3306 SS        04810          OEFM   'USE PERIOO (.) TO ENTER AN AOORE'
33F6 53        04820          OEFM   'SS, SLASH (/) TO ENTER OATA.  TO'
3416 45        04830          OEFM   'EXIT TO MONITOR MENU, TYPE STAR '
3436 28        04840          OEFM   '(*), TO EXECUTE AT AOORESS SHOWN'
3456 4F        048S0          OEFM   'ON SCREEN, TYPE EXCLAMATION POIN'
3476 54        04860          OEFM   'T (!)                                   '
3496 00        04870          OEFB   00
3497           04880 XXXXXX   EQU    $
               04890 ;
0000           04900          ENO

ACHX    3163 02660   02440 02S10 02600
AODMOO  3007 01620   01700 01720 01760
AOEXIT  3180 03180   02810
AROUNO  3214 03790   03750
ASCHEX  3143 02440   01B60 01890 030S0 03100
AX2     314E 02S10   03010
8ACKUP  3208 03730   037B0
BEEPER  327F 04390   04470
CHECK   30CC 01S20   01B70
CLEAR   303E 00640   00710
CLRMEM  310C 03430   034S0
CLS     300C 00310   01680
CNTROL  3230 03940   03B80
COLO    303C 00620   00460
DATMOO  316E 02790   01660 028S0 02870 02910 03170
OECA    31FE 03630   03S70
OELAYS  3260 04270   04300
OISPLY  328F 045S0   00430 01100 04610
EXEC    3110 01B80   01640
EXIT1   31B0 03120   03080
FOUNO   3203 03660   03520
FREQCY  3288 04450   04450
GOAWAY  3269 042S0   03910 03930 03960 04040 04060 04150
HEXASC  3124 02110   01560 02010 02030 03160
HXAC    3139 02320   02170 02220
INOATA  318A 02920   02890
INPUT   31C3 032B0   00440 01620 02790
JUMP1   323S 03970   03B40
JUMP2   3249 04070   039B0
JUMP3   3241 04030   04010
JUMP4   324E 04100   04090
KEYPRS  31CB 03310   03410
KPLACE  401A 00160   03490 03530 035S0 03640
LLLLS   3158 02600   02470 02540
LOOP1   3051 00730   0075U
MENU    3022 00440   00S50
MONTOR  306F 010B0   00500
MSG01   3297 04690   00410
MSG02   3206 04730   01080
NEXTO   31A9 03090   02830
NEXTX   3140 02360   02330
NEXTZ   31EB 02710   02680
NUM2    3108 01860   03190
NUMBER  30FB 01770   01740
RECHEK  3101 03360   03620
STROKE  31E8 03510   03340
TABLET  32S9 04170   04100
TMWSTE  31F9 03600   03600
USER    3058 00B30   00520
WARM    3064 00950   00540
WOROER  3117 01970   011S0 011B0 01210 01230 01250 01270 01280
                     01340 01400 01470 01490 01510 01530 03130

XXXXXX  3497 048B0
ZIPBY   310A 018S0   01830
ZIPZY   3199 03000   029B0
```

The worst signal abuse takes place during the taping process. The reasonably digital signal is recorded with the poor electronics of a portable tape recorder, and the sharp-edged waves are rounded off by the natural limitations of the tape itself; examine Photo 6-4. Also visible in the photo are residual noise (tape hiss) and the high-frequency recording bias signal.

There is also an unexpected interreaction between the computer's output wiring and some tape recorders that produces a low-pitched hum, called a ground loop. The good data signal can ride on this ground-loop hum to result in sensitive volume settings — too high or low a volume during playback will cause the top or bottom of the digital waveform to travel out of the range of the digital processing.

This digital processing redeems quite a bit of the audio signal, turning it back into a usable digital waveform much of the time. Photo 6-5 shows the results of the reshaping process; it's a fairly good signal that the CPU finally receives and must interpret as data.

Now the names and descriptions of the seven CLOAD culprits:

1. Head misalignment. This is the main cause of bad loads, because misalignment severely cuts the essential high frequencies. The CTR-80 already has a provision for adjust-rw00ing the playback head. If you have a CTR-41 (or other recorder), drill a hole directly over the playback head adjustment screw (under
1. Head misalignment. This is the main cause of bad loads, because misalignment severely cuts the essential high frequencies. The CTR-80 already has a provision for adjusting the playback head. If you have a CTR-41 (or other recorder), drill a hole directly over the playback head adjustment screw (under the letters ERY in 'battery' on the CTR-41 face plate), and adjust with a small Phillips screwdriver.

2. Speed variations. This one is not obvious, but note that a five percent variation in recorder speed can cause a bad load, especially with long BASIC lines during CLOAD.

3. Bad tape. There is no reason to use low-grade tape, just as there is no reason to buy the best audio tape. Get a good commercial grade, and standardize with it.

4. Dirty head. Clarity and volume are cut down when the head is dirty. Clean it and all parts that contact the tape with isopropyl alcohol.

5. Starting too soon. The beginning of most tape — especially leaderless tape — is often slightly crumpled, and data can be lost right at the start. Count off ten seconds.

6. Magnetized head. Those who depend on cassettes will use the machine often, and the head will build up residual magnetism. Obtain a cassette demagnetizer (degausser) and use it often.

7. Software. Early Level II BASIC ROMs have problems because the timing loops were not written ideally for low-grade audio use. These can be upgraded with new ROMs or the Radio Shack XRX cassette modification. Note, however, that removal of the XRX modification is necessary for use with high/low speed hardware modifications (except the Archbold 1981-82 kit).



Photo 6-4. Rounded-off digital signal with tape hiss.



Photo 6-5. Reshaped wave that the CPU finally sees.

NOTES

7

Controlling the World

The world is out there, waiting to be controlled by your TRS-80. Really. Most of the partly-mechanized daily routine that you find yourself doing by hand might be connected to the '80. Not that it should be, mind you, but it could be. You could successfully operate a clothes washer and drier, a dishwasher, an automatic furnace, an air conditioner, or many other electromechanical devices; turn lights, televisions, and radios on and off, as well as replace your ordinary wake-up alarm; dial the phone, or answer it in a synthetic voice; even act as a digital burglar alarm. But would you really want to?

Admittedly, microprocessors are making their way into more and more appliances, including such diverse items as automobile engines and electric razors. But remember that the TRS-80 is a spectacular *general-purpose* device; although it might do all sorts of control work, it's best suited to applications calling for a large library of different electronic tasks, most with crucial human interaction. Aside from machine - oriented tasks like word processing, calculating, and printing, then, these applications include (generally speaking) measurement, signalling, and cloning.

Measurement involves the evaluation of a real-world occurrence in real time: checking temperature, counting events, comparing relative amounts of light or voltage or sound. Some of these measurements, like counting events, are inherently digital – an event (say, a person walking through a door) either is taking place or it isn't. A door is closed or it's open. And so on. Other measurements are relative or quantitative, consisting of small increments or continuous change, such as the pressure, the rate of flow, or the quantity of water in a pipe.

Signalling is somewhat the opposite of measurement: a user is informed when some activity has been completed, or when a particular condition in the environment has been reached – including such things as the completion of a mailing list sort or someone breaking and entering.

Cloning is a rather odd phrase, but it's what I would like to call the computer's ability to create precise duplicates of some target object or activity. If that sounds a bit too philosophical, then think of it this way: the computer is fast, which means if it is given a task, it can complete it quickly. The computer is capable of calculating the parameters of its task with enormous accuracy. And finally, the computer works in minute, definable, and identical increments. Simply stated, we can command a computer to do work which, barring glitches and bugs, will be identical every time.

This last concept is the reason microprocessors have become the favored design tools for machining, measurement, and even the creation of music. Jigs wear out, so that tolerances change; but computer programs can be self-correcting. Measuring devices can go out

of alignment: again, computers can be programmed to cross-check and correct these errors. And finally, where electronic design has been sloppy as a result of inaccuracies in the electronic parts themselves (such as in synthesized music), computers can provide the advantages of precise replication where it was not possible before.

The general approach to discrete, digital events is discussed in Chapter (?), where input/output ports are presented. The hardware of interfacing digital inputs and outputs to electrical appliances and other 'real-world' devices is brilliantly described in *TRS-80 Interfacing* (Volumes 1 and 2 — see Bibliography; especially check Volume 2, Chapter 1).

This Chapter will present a few real-world interfacing projects, but will touch only lightly on the theory involved. If you plan to put together your own interfaces, turn to the references cited. Beyond that, here are some rules of thumb before you begin considering interfacing schemes or parts purchases:

Output Interfacing

TTL-level integrated circuits of the type used in your TRS-80 are capable of driving (running) little more than other TTL circuits like themselves or an occasional light-emitting diode (LED). Don't hook your computer expansion card onto any home-made electronic board unless it has TTL inputs; consider the computer's bus to be its most delicate hardware.

For interfacing purposes, integrated circuit peripheral drivers are great. Use them to light small bulbs, turn on miniature relays, and to operate other low-voltage applications needing only limited current. Type 75452 is reliable and cheap, and takes abuse; it's the circuit used by the TRS-80 to run the video dot output and cassette relay. For LEDs, use individual transistors or the inexpensive type 500, 501 and 502 digit and segment drivers.

Isolation of hazardous voltages is essential for external equipment running from your computer. Consider anything plugged into house current to be potentially hazardous, because there's nothing like a power surge or unexpected short circuit to fry your '80 and maybe you too. Use opto-isolators and — or high-current relays for running electric stoves or even AC light bulbs.

Always read the specifications of both the equipment you plan to interface and the device that's going to do the interfacing. Look for:

- Average voltage and maximum voltage of the interfacing device, and operating voltage of the equipment to be run; the figure is given in volts (V), direct current volts (VDC), or alternating current volts (VAC). The interfacing device must always have a rating higher than the equipment to be run.
- Average current and surge current of the the interfacing device, and operating current of the equipment to be run; the figure is given in amps (A) or milliamps (mA). The interfacing device must always have a rating higher than the equipment to be run.
- Isolation voltage of the interfacing device. This device must have a rating roughly 67 percent higher than the equipment to be run.

Actually, interfacing peripheral equipment is one of the easiest things you can do with your TRS-80. Below is a simple schematic; it shows one latched output line from the computer, and how it might drive:

(a) an LED
(b) a relay
(c) an ordinary house lamp
(d) a motor
(e) a high-voltage circuit.

You wouldn't want to use this single line to do all these things, but you might want to combine the LED, house lamp, and motor. That way you could have an indicator near the computer that the motor is on, a bright lamp outside a building to indicate the motor is on, and the motor itself would go on.

The point of this schematic is that it can be tapped at any point on the line of parts shown; use the parts only as far as you need them:

Input Interfacing

Counting events or determining occurrences has an easier group of rules: TTL level signals can interface right to other TTL devices with no work; just don't connect outputs together.

Other on-off signals are interfaced with a device or group of devices which can shape the incoming signal into a neat, tight square wave, at TTL level. Such a device is called a Schmitt trigger, and is available as type 7414 for a few cents.

If the signal is in the range of 4 to 7 volts, the Schmitt trigger will transform it to a fast-moving digital signal. If the signal occurs very often or is erratic or unstable in its rising voltage, then



Figure 7-1. Methods for interfacing the TRS-80.

additional hardware or very tolerant software must be used. Use optical isolators to feed the computer or relays for interfacing higher voltages.

For AC input, the signal may be transformed to about 3 to 6 volts, rectified to DC and filtered only if the signal is slow-moving (once a minute or so). Then the signal can be fed to a Schmitt trigger to the computer interface. Otherwise, the AC information can only be transformed to a lower voltage and its pulses (60 per second if it is ordinary house current) counted either by hardware or software. Don't interface AC if you can avoid it, because it can be a genuine pain in the bytes. Instead, have the AC run a fast relay and identify when the relay turns on and off.

National Semiconductor

A to D, D to A

DAC0808, DAC0807, DAC0806 8-bit D/A converter

general description

The DAC0808 series is an 8-bit monolithic digital-to-analog converter (DAC) featuring a full scale output current settling time of 150 ns while dissipating only 33 mW with ±5V supplies. No reference current (I_{REF}) trimming is required for most applications since the full scale output current is typically ±1 LS8 of 255 I_{REF}/256. Relative accuracies of better than ±0.19% assure 8-bit monotonicity and linearity while zero level output current of less than 4 μA provides 8-bit zero accuracy for $I_{REF} \geq 2$ mA. The power supply currents of the DAC0808 series are independent of bit codes, and exhibits essentially constant device characteristics over the entire supply voltage range.

The DAC0808 will interface directly with popular TTL, DTL or CMOS logic levels, and is a direct replacement for the MC1508/MC1408. For higher speed applications, see DAC0800 data sheet.

features

- Relative accuracy: ±0.19% error maximum (DAC0808)
- Full scale current match: ±1 LSB typ
- 7 and 6-bit accuracy available (DAC0807, DAC0806)
- Fast settling time: 150 ns typ
- Noninverting digital inputs are TTL and CMOS compatible
- High speed multiplying input slew rate: 8 mA/μs
- Power supply voltage range: ±4.5V to ±18V
- Low power consumption: 33 mW @ ±5V

block and connection diagrams



Dual-In-Line Package



TOP VIEW

typical application



$$V_O = 10V\left(\frac{A1}{2} + \frac{A2}{4} + \ldots \frac{A8}{256}\right)$$

FIGURE 1. ±10V Output Digital to Analog Converter

ordering information

ACCURACY	OPERATING TEMPERATURE RANGE	ORDER NUMBERS*					
		D PACKAGE (D16C)		J PACKAGE (J16A)		N PACKAGE (N16A)	
8-bit	−55°C ≤ T_A ≤ +125°C	DAC0808LD	LM1508D-8	DAC0808LJ	LM1508J-8		
8-bit	0°C ≤ T_A ≤ +75°C			DAC0808LCJ	LM1408J-8	DAC0808LCN	LM1408N-8
7-bit	0°C ≤ T_A ≤ +75°C			DAC0807LCJ	LM1408J-7	DAC0807LCN	LM1408N-7
6-bit	0°C ≤ T_A ≤ +75°C			DAC0806LCJ	LM1408J-6	DAC0806LCN	LM1408N-6

*Note. Devices may be ordered by using either order number.

application hints

REFERENCE AMPLIFIER DRIVE AND COMPENSATION

The reference amplifier provides a voltage at pin 14 for converting the reference voltage to a current, and a turn-around circuit or current mirror for feeding the ladder. The reference amplifier input current, I_{14}, must always flow into pin 14, regardless of the set-up method or reference voltage polarity.

Connections for a positive voltage are shown in *Figure 7*. The reference voltage source supplies the full current I_{14}. For bipolar reference signals, as in the multiplying mode, R15 can be tied to a negative voltage corresponding to the minimum input level. It is possible to eliminate R15 with only a small sacrifice in accuracy and temperature drift.

The compensation capacitor value must be increased with increases in R14 to maintain proper phase margin; for R14 values of 1, 2.5 and 5 kΩ, minimum capacitor values are 15, 37 and 75 pF The capacitor may be tied to either V_{EE} or ground, but using V_{EE} increases negative supply rejection.

Figure 7-2. National Semiconductor data sheet example.

Signals from photocells and similar resistive devices can be fed through Wein bridges or merely fed into an operational amplifier. Again, the references such as *TRS-80 Interfacing* and *Engineer's Notebook* contain plenty of details on interfacing on-off signals.

D-to-A and A-to-D Conversion

Although some human events occur in on-off groups, most of life is pliable, elusive, and relative. It works by image and analogy, not by counting. It is an analog world, and the computer is a digital device. Faced with this dilemma, two important groups of electronic circuits have been developed: the digital-to-analog converter (D/A converter) and the analog-to-digital converter (A/D converter).

The first class accepts a parallel digital input a given number of bits wide, and converts that to individual steps. For N steps, the number of distinct voltages or currents is 2 to the power N. The greater the number of bits, the lesser the relative size of the steps, to the point where the distinction between steps becomes insignificant. For an ordinary 8-bit data bus such as that on the TRS-80, the available voltage can be divided into 256 parts; for five-volt circuitry, this is 0.0195 volts per step, starting at zero. If greater accuracy is essential, then 12-bit converters can be used (at greater expense), fed by one and one-half bytes of data from the computer. This provides 4,096 steps at 0.0012 volts per step. The most common 8-bit type is the DAC0808 (National Semiconductor) or the MC1408L8 (Motorola); data sheets are found in an Appendix.

With present technology, conversion from analog signals to digital ones is much more

absolute maximum ratings (T_A = 25°C unless otherwise noted)

Power Supply Voltage	
V_{CC}	5.5 V_{DC}
V_{EE}	−16.5 V_{DC}
Digital Input Voltage, V5−V12	−10 V_{DC} to +18 V_{DC}
Applied Output Voltage V_O	−11 V_{DC} to +18 V_{DC}
Reference Current, I_{14}	5 mA
Reference Amplifier Inputs, V14, V15	V_{CC}, V_{EE}

Power Dissipation (Package Limitation)	
Cavity Package	1000 mW
Derate above T_A = 25°C	6.7 mW/°C
Operating Temperature Range	
DAC0808L	$-55°C \le T_A \le +125°C$
DAC0808LC Series	$0 \le T_A \le +75°C$
Storage Temperature Range	−65°C to +150°C

electrical characteristics

(V_{CC} = 5V, V_{EE} = −15 V_{DC}, V_{REF}/R14 = 2 mA, DAC0808L, T_A = −55°C to +125°C, DAC0808LC, DAC0807LC, DAC0806LC, T_A = 0°C to +75°C, and all digital inputs at high logic level unless otherwise noted.)

	PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
E_r	Relative Accuracy (Error Relative to Full Scale I_O)	*(Figure 4)*				%
	DAC0808L (LM1508-8), DAC0808LC (LM1408-8)				±0.19	%
	DAC0807LC (LM1408-7), (Note 1)				±0.39	%
	DAC0806LC (LM1408-6), (Note 1)				±0.78	%
	Settling Time to Within 1/2 LSB (Includes t_{PLH})	T_A = 25°C (Note 2), *(Figure 5)*		150		ns
t_{PLH}, t_{PHL}	Propagation Delay Time	T_A = 25°C, *(Figure 5)*		30	100	ns
TCI_O	Output Full Scale Current Drift			±20		ppm/°C
MSB	Digital Input Logic Levels	*(Figure 3)*				
V_{IH}	High Level, Logic "1"		2			V_{DC}
V_{IL}	Low Level, Logic "0"				0.8	V_{DC}
MSB	Digital Input Current	*(Figure 3)*				
	High Level	V_{IH} = 5V		0	0.040	mA
	Low Level	V_{IL} = 0.8V		−0.003	−0.8	mA
I_{15}	Reference Input Bias Current	*(Figure 3)*		−1	−5	μA
	Output Current Range	*(Figure 3)*				
		V_{EE} = −5V	0	2.0	2.1	mA
		V_{EE} = −15V, T_A = 25°C	0	2.0	4.2	mA
I_O	Output Current	V_{REF} = 2.000V, R14 = 1000Ω, *(Figure 3)*	1.9	1.99	2.1	mA
	Output Current, All Bits Low	*(Figure 3)*		0	4	μA
	Output Voltage Compliance	$E_r \le 0.19\%$, T_A = 25°C				
	Pin 1 Grounded,				−0.55, +0.4	V_{DC}
	V_{EE} Below −10V				−5.0, +0.4	V_{DC}
SRI_{REF}	Reference Current Slew Rate	*(Figure 6)*		8		mA/μs
	Output Current Power Supply Sensitivity	$-5V \le V_{EE} \le -16.5V$		0.05	2.7	μA/V
	Power Supply Current (All Bits Low)	*(Figure 3)*				
I_{CC}				2.3	22	mA
I_{EE}				−4.3	−13	mA
	Power Supply Voltage Range	T_A = 25°C, *(Figure 3)*				
V_{CC}			4.5	5.0	5.5	V_{DC}
V_{EE}			−4.5	−15	−16.5	V_{DC}
	Power Dissipation					
	All Bits Low	V_{CC} = 5V, V_{EE} = −5V		33	170	mW
		V_{CC} = 5V, V_{EE} = −15V		106	305	mW
	All Bits High	V_{CC} = 15V, V_{EE} = −5V		90		mW
		V_{CC} = 15V, V_{EE} = −15V		160		mW

Note 1: All current switches are tested to guarantee at least 50% of rated current.

Note 2: All bits switched.

Note 3: Range control is not required.

application hints (Continued)

A negative reference voltage may be used if R14 is grounded and the reference voltage is applied to R15 as shown in *Figure 8*. A high input impedance is the main advantage of this method. Compensation involves a capacitor to V_{EE} on pin 16, using the values of the previous paragraph. The negative reference voltage must be at least 4V above the V_{EE} supply. Bipolar input signals may be handled by connecting R14 to a positive reference voltage equal to the peak positive input level at pin 15.

When a DC reference voltage is used, capacitive bypass to ground is recommended. The 5V logic supply is not recommended as a reference voltage. If a well regulated 5V supply which drives logic is to be used as the reference, R14 should be decoupled by connecting it to 5V through another resistor and bypassing the junction of the 2 resistors with 0.1 μF to ground. For reference voltages greater than 5V, a clamp diode is recommended between pin 14 and ground.

If pin 14 is driven by a high impedance such as a transistor current source, none of the above compensation methods apply and the amplifier must be heavily compensated, decreasing the overall bandwidth.

OUTPUT VOLTAGE RANGE

The voltage on pin 4 is restricted to a range of −0.6 to 0.5V when V_{EE} = −5V due to the current switching methods employed in the DAC0808.

The negative output voltage compliance of the DAC0808 is extended to −5V where the negative supply voltage is more negative than −10V. Using a full-scale current of 1.992 mA and load resistor of 2.5 kΩ between pin 4 and ground will yield a voltage output of 256 levels between 0 and −4.980V. Floating pin 1 does not affect the converter speed or power dissipation. However, the value of the load resistor determines the switching time due to increased voltage swing. Values of R_L up to 500Ω do not significantly affect performance, but a 2.5 kΩ load increases worst-case settling time to 1.2 μs (when all bits are switched ON). Refer to the subsequent text section on Settling Time for more details on output loading.

OUTPUT CURRENT RANGE

The output current maximum rating of 4.2 mA may be used only for negative supply voltages more negative than −7V, due to the increased voltage drop across the resistors in the reference current amplifier.

ACCURACY

Absolute accuracy is the measure of each output current level with respect to its intended value, and is dependent upon relative accuracy and full-scale current drift. Relative accuracy is the measure of each output current level as a fraction of the full-scale current. The relative accuracy of the DAC0808 is essentially constant with temperature due to the excellent temperature tracking of the monolithic resistor ladder. The reference current may drift with temperature, causing a change in the absolute accuracy of output current. However, the DAC0808 has a very low full-scale current drift with temperature.

The DAC0808 series is guaranteed accurate to within ±1/2 LSB at a full-scale output current of 1.992 mA. This corresponds to a reference amplifier output current drive to the ladder network of 2 mA, with the loss of 1 LSB (8 μA) which is the ladder remainder shunted to ground. The input current to pin 14 has a guaranteed value of between 1.9 and 2.1 mA, allowing some mismatch in the NPN current source pair. The accuracy test circuit is shown in *Figure 4*. The 12-bit converter is calibrated for a full-scale output current of 1.992 mA. This is an optional step since the DAC0808 accuracy is essentially the same between 1.5 and 2.5 mA. Then the DAC0808 circuits' full-scale current is trimmed to the same value with R14 so that a zero value appears at the error amplifier output. The counter is activated and the error band may be displayed on an oscilloscope, detected by comparators, or stored in a peak detector.

Two 8-bit D-to-A converters may not be used to construct a 16-bit accuracy D-to-A converter. 16-bit accuracy implies a total error of ±1/2 of one part in 65,536, or ±0.00076%, which is much more accurate than the ±0.019% specification provided by the DAC0808.

MULTIPLYING ACCURACY

The DAC0808 may be used in the multiplying mode with 8-bit accuracy when the reference current is varied over a range of 256:1. If the reference current in the multiplying mode ranges from 16 μA to 4 mA, the additional error contributions are less than 1.6 μA. This is well within 8-bit accuracy when referred to full-scale.

A monotonic converter is one which supplies an increase in current for each increment in the binary word. Typically, the DAC0808 is monotonic for all values of reference current above 0.5 mA. The recommended range for operation with a DC reference current is 0.5 to 4 mA.

SETTLING TIME

The worst-case switching condition occurs when all bits are switched ON, which corresponds to a low-to-high transition for all bits. This time is typically 150 ns for settling to within ±1/2 LSB, for 8-bit accuracy, and 100 ns to 1/2 LSB for 7 and 6-bit accuracy. The turn OFF is typically under 100 ns. These times apply when $R_L \le 500\Omega$ and $C_O \le 25$ pF.

Extra care must be taken in board layout since this is usually the dominant factor in satisfactory test results when measuring settling time. Short leads, 100 μF supply bypassing for low frequencies, and minimum scope lead length are all mandatory.

complicated. Most commonly used is a technique which compares the input voltage to known voltages inside the converter. When a match is found, a binary version of the input condition is fed to the computer bus. This process is slow when compared to computer speeds, and such devices usually have start-of-conversion and end-of-conversion signals so the computer will not receive false data by attempting to read the converter's information during the conversion process. The commonly used 8-bit type is ADC0800 (National Semiconductor); see the Appendix.

Music and Sound Effects

There are other ways of producing sound using the TRS-80 which do not involve exclusively software. The software-only approach may be capable of producing sound effects, but in the TRS-80 configuration it cannot provide any spatial effects (it is monaural only), nor can it offer a large variety of textures. For these, the TRS-80 user must turn to a little extra hardware.

Simplest among the extra hardware is a latched output address. The information written to the address appears at the output of the latch. Write to the address fast enough, and sound is produced, because the latch acts as a kind of electronic window to that single memory location. Feed that digital activity through a few resistors to blend the sounds, and run that to a stereo amplifier. Voila! Spatial sound.

The circuit presented here contains an 8-bit latch (Z1), and address decoder (Z3, Z4 and Z4, mapped to 4FFF), and three-state output buffer (Z2). The computer data is latched into Z1 when WRite to 4FFF appears at Z3/4/5. Depending on the data at Z1, any or all of the four buffers in Z2 may be turned on or off.



IC	TYPE	+5V	GND
Z1	74LS374	20	10
Z2	74LS125	14	7
Z3	74LS30	14	7
Z4	74LS30	14	7
Z5	74LS02	14	7

Figure 7-3. Simple sound synthesis circuit



Figure 7-4. Alternate decoding scheme.

An alternate decoding (**8FFF**) is provided, and is recommended for some of the musical selections presented. The selections include my own arrangement of 'God Rest Ye Merry Gentlemen', first presented in the Christmas 1980 issue of *80 Microcomputing*; and 'Your California', a suite by David Gunn, originally composed for viola duo. The latter group is written for use with the *Exatron Stringy-Floppy*, and will continuously repeat the four parts of the suite.

There are two versions of the software; both are identical, except that the second is a two-voice program intended for pieces such as 'Your California'. Because the TRS-80 is slow (1.77 MHz) and the Z-80 is slow (an enormous number of machine cycles per instruction when compared with other microprocessor families), four-part music will reproduce in the low register. The two-part music is much more satisfying musically.

Figure 7-5. Music notation for people.



Figure 7-6. The same music for the computer.

```
10 REM * CLEARING SPACE FOR PROGRAM CHAINING SEQUENCE
20 POKE16634,PEEK(16634)+16 : REM * SIMPLE VARIABLE POINTER
30 CLEAR50 : REM * CLEAR STRING SPACE AND RESET POINTERS
40 @LOAD3 : REM * BRING NEXT PROGRAM IN FROM STRINGY FLOPPY
```

```
10 OUT254,2 : CLS : PRINT"READING.." : REM * OUT254,2 = HISPEED
20 X = 24578 : REM * THIS IS MEM. POSITION OF VOICE NUMBER ONE
30 READ A : IF A = 999 THEN 50 ELSE POKE X,A : REM * EXIT @ 999
40 X = X + 4 : GOTO 30 : REM * VOICE APPEARS EVERY 4 MEM LOC'NS
50 X = 24579 : REM * THIS IS MEM. POSITION OF VOICE NUMBER TWO
60 READ A : IF A = 999 THEN 80 ELSE POKE X,A : REM * PITCH POKE
70 X = X + 4 : GOTO 60 : REM * VOICE APPEARS EVERY 4 MEM LOC'NS
80 X = 24576 : REM * THIS IS THE BEGINNING VALUE FOR DURATIONS
90 READ A : IF A = 999 THEN 110 ELSE POKE X,A*2 : REM * RHYTHMS
100 X = X + 4 : GOTO 90 : REM * NOTICE RHYTHM MULTIPLIER ABOVE
110 RESTORE : REM * THIS GETS THE DATA POINTER BACK TO START
120 X = 24577 : REM * THESE LOCATIONS USED FOR SUBTLE DURATIONS
130 READ A : IF A = 999 THEN 150 ELSE POKE X,1 : REM * RHYTHMS
140 X = X + 4 : GOTO 130 : REM *  NO CHANGE IN LSB TIMING ABOVE
150 POKE X,0 : POKE X+4,0 : POKE X+8,0 : REM * MUSIC END CODE
160 OUT254,3 : POKE 16526,96 : POKE 16527,143 : M=USR(0) :CLEAR
170 @LOAD4 : REM * PLAY NORM SPEED. USR CALL, CLEAR, LOAD NEXT
180 DATA0,0,0,0,0,0,0,0,22,26,30,30,30,30,30,34,34,34,0,0,0,0,0
190 DATA20,16,13,14,14,14,14,14,15,15,15,0,0,0,0,0,0,20,18,18
200 DATA18,18,24,0,24,0,24,0,24,0,24,24,24,0,24,0,24,24,0,24,0
210 DATA24,24,0,24,0,24,24,24,24,0,24,0,24,24,0,24,0,24,0,24,0
220 DATA22,22,18,18,16,16,14,14,13,13,12,13,13,13,14,19,27,19
230 DATA13,13,14,19,27,19,13,0,16,0,20,0,22,0,24,0,24,0,24,0,24
240 DATA0,20,16,13,14,14,20,16,13,0,16,0,16,0,16,12,12,12,12,13
250 DATA15,15,15,15,18,21,21,21,21,16,16,0,16,0,16,16,0,16,0,16
260 DATA17,15 : REM * end of page one for voice one
270 DATA20,21,24,26,0,0,0,0,0,22,26,30,30,30,30,30,34,34,34,0,0
280 DATA0,24,0,24,24,24,24,0,24,0,24,24,0,24,0,24,0,0,0,20,18
290 DATA18,18,18,24,0,24,0,24,0,21,0,22,0,18,0,30,30,32,0,24,0
300 DATA24,0,24,0,24,0,26,21,16,16,16,16,16,16,16,16,16,999
310 REM * THIS IS THE END OF THE PITCH SEQUENCE FOR VOICE ONE
320 DATA24,0,24,0,24,0,24,0,24,24,24,0,24,0,24,24,0,24,0,24,0
330 DATA24,0,24,24,24,24,0,24,0,24,24,0,24,0,24,24,0,24,0,26,26
340 DATA0,26,0,27,0,27,0,27,0,40,0,22,26,30,30,30,30,30,34,34
350 DATA34,0,0,0,0,0,0,20,16,13,14,14,14,14,14,15,15,15,15,0,0
360 DATA0,0,27,30,32,36,40,20,18,36,40,20,18,36,40,20,18,18,36
370 DATA36,40,20,18,18,36,36,40,0,30,0,26,0,32,0,27,0,27,0,30
380 DATA0,40,0,22,22,22,26,30,34,34,34,0,24,0,24,0,24,24,0,24
390 DATA0,24,24,0,24,0,24,24,0,24,0,24,26,26,26,26,22,30,30,30
400 DATA30,32,32,32 : REM * end of page one for voice two
410 DATA32,32,32,0,0,24,0,24,0,24,24,24,0,24,0,24,24,0,24,0,24
420 DATA0,0,20,16,13,14,14,14,14,14,15,15,15,0,0,0,24,0,26,26
430 DATA0,26,0,27,0,27,0,30,0,30,0,32,32,32,32,32,0,0,0,34,0
440 DATA34,0,34,0,34,0,32,28,24,24,26,24,26,24,26,28,26,999
450 REM * this is the conclusion of the score for voice two
460 DATA10,2,2,2,10,2,2,2,4,4,2,2,2,2,8,2,2,2,2,10,2,2,2,3,3,3
470 DATA2,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2,2,2,2,10,2,2,2,10,2,2,2
480 DATA4,4,2,2,2,2,8,2,2,2,2,8,2,2,2,2,3,3,3,2,2,2,2,8,2,2,2,2
490 DATA10,2,2,2,4,4,4,4,8,8,8,8,8,8,8,8,8,8,4,4,4,4,8,8,4,4,4
500 DATA4,10,2,2,2,10,2,2,2,10,2,2,2,10,2,2,2,3,3,3,8,8,3,3,3
510 DATA8,10,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2,2,2,2,8
520 DATA2,2,2,2,8,8,8 : REM * end of page one for durations
530 DATA8,8,16,8,8,10,2,2,2,4,4,2,2,2,2,8,2,2,2,2,10,2,2,2,3,3
540 DATA3,2,2,2,2,8,2,2,2,2,10,2,2,2,8,2,2,2,2,10,2,2,2,10,2,2
550 DATA2,10,2,2,2,2,2,4,8,10,2,2,2,10,2,2,2,4,4,8,8,1,1,1,1,3
560 DATA6,20,999 : REM * end of score for durations; end score
```

Listing 7-1. Examples of music programs.

More Music

Naturally, there is much more to the creation of music by computer than the mere sounding of tones; the appearance of commercial music-generation peripherals for the TRS-80 attests to that. But though they may be well-designed pieces of electronics, composers and others serious about producing listenable music tend to look for richer sounds and more flexible ways to change that sound.

There are several ways to do this. The simplest is the tone generator with a tempered scale, capable of producing chordal sounds (consisting of three or more pitches sounding simultaneously). The tone color is limited to a fixed palette, and they are suitable for making elementary music. I refer to these generically as 'organs' because their tone colors usually give the illusion of organ stops. Most TRS-80 compatible music boards are simplified variations on the basic electronic organ, using integrated circuit chips like the General Instrument AY-3-8910 and the Texas Instrument SN76489.

A second group of electronic instruments creates music by constructing waveforms from a pre-assigned table of values. Thus, tone color, pitch, and volume can be altered by the selection of parameters in the table. This is digital synthesis in an elementary form, just one step beyond the simple software tone generation presented earlier in this Chapter. The TRS-80 is not capable of operating either with enough speed or electronic flexibility for digital synthesis.

Peripheral to the digital synthesis of tones is the electronic creation of vocal sounds. Texas Instruments, Votrax and other integrated circuits use a complex algorithm called 'linear predictive coding' to select from a known subset of human vocal sounds. Although somewhat convincing voices can be produced this way, mere intelligibility is the least significant criterion in music. Until (and if) predictive devices are developed for a wide array of musical sound, they have no application for producing music.

The most popular electronic music makers for more than a decade have been the analog synthesizers. Traditional oscillators create a sound which can be mutated and transformed until its color is right. These synthesizers were never conceived in computer-compatible terms, but companies such as *PAIA* have for the past few years offered hybrid analog-digital systems where the computer is used as a super-sequencer,

keeping the notes in order for storage and playback.

There are several reasons why I suggest interfacing analog synthesizers to the TRS-80. First, analog synthesizers are cheap. Small, capable machines can be picked up for the cost of a TRS-80, and kits are sold by *PAIA* and others for less than $100. Surplus synthesizers are also available (*Moog, Buchla, PBI, Putney*, and others of early 1970's vintage) at low cost. All of these will take on new musical life when interfaced to the TRS-80.

Second, if you are a performing musician, it's likely you're looking for a musical instrument, and it's in that area where the analog synthesizer is still champion. They are performance instruments, not electronic widgets. And with a computer interface, they remain stand-alone performance instruments, but with computer assistance where it is wanted.

Figure 7-7 presents the circuit for a 2- to 32-voice analog synthesizer interface. The basic circuit contains a data-line buffer (Z1), a buffer for the most used addresses (Z4), a port decoder and a voice-pair selector (Z2/Z3). In a fully expanded system, sixty-four ports (port 64 to port 127) are used to provide thirty-two voltage outputs, sixty-four envelopes, with sixty-four additional control lines.



IC	TYPE
Z1	81LS95
Z2	74LS154
Z3	74LS00
Z4	74LS04
Z5	INS8255
Z6	MC1408L8
Z7	MC1408L8
Z8	74LS123
Z9	74LS123
Z10	LM324

Z3, Z4: GND PIN 7, VCC PIN 14
Z10: GND PIN 11, VCC PIN 4

Figure 7-7. TRS-80 to voltage-controlled synthesizer interface.

```
10 OUT 254,2 : CLS : PRINT"READING.." : REM OUT254,2 = HISPEED
20 X = 24578 : REM * THIS IS MEM. POSITION OF VOICE NUMBER ONE
30 READ A : IF A = 999 THEN 50 ELSE POKE X,A : REM * PITCH POKE
40 X = X + 4 : GOTO 30 : REM * VOICE APPEARS EVERY 4 MEM LOC'NS
50 X = 24579 : REM * THIS IS MEM. POSITION OF VOICE NUMBER TWO
60 READ A : IF A = 999 THEN 80 ELSE POKE X,A : REM * PITCH POKE
70 X = X + 4 : GOTO 60 : REM * VOICE APPEARS EVERY 4 MEM LOC'NS
80 X = 24576 : REM * THIS IS THE BEGINNING VALUE FOR DURATIONS
90 READ A : IF A = 999 THEN 110 ELSE POKE X,A*2 : REM * RHYTHMS
100 X = X + 4 : GOTO 90 : REM * NOTICE RHYTHM MULTIPLIER ABOVE
110 RESTORE : REM * THIS GETS THE DATA POINTER BACK TO START
120 X = 24577 : REM * THESE LOCATIONS USED FOR SUBTLE DURATIONS
130 READ A : IF A = 999 THEN 150 ELSE POKE X,1 : REM * RHYTHMS
140 X = X + 4 : GOTO 130 : REM * NO CHANGE IN LSB TIMING ABOVE
150 POKE X,0 : POKE X+4,0 : POKE X+8,0 : REM * MUSIC END CODE
160 OUT254,3 : POKE 16526,96 : POKE 16527,143 : M=USR(0) :CLEAR
170 @LOAD4 : REM * pLAY NORM SPEED, USR CALL, CLEAR, LOAD NEXT
180 DATA0,0,0,0,0,0,0,0,22,26,30,30,30,30,30,34,34,34,0,0,0,0,0
190 DATA20,16,13.14,14,14,14,14,15,15,15,0,0,0,0,0,0,20,18,18
200 DATA18,18,24,0,24,0.24,0,24,0,24,24,24,0,24,0,24,24,0,24,0
210 DATA24,24,0,24,0,24,24,24,24,0,24,0,24,24,0,24,0,24,0,24,0
220 DATA22.22,18,18,16,16,14,14,13,13,12,13,13,13,14,19,27,19
230 DATA13.13,14,19,27,19,13,0,16,0,20,0,22,0,24,0,24,0,24,0
240 DATA24,0,20,16,13,14,14,20,16,13,0,16,0,16,0,16,12,12,12,12
250 DATA13,15,15,15,15,18,21,21,21,21,16,16,0,16,0,16,16,0,16,0
260 DATA16,17,15 : REM * END OF PAGE ONE FOR VOICE ONE
270 DATA20,21,24,26,0,0,0,0,0,22,26,30,30,30,30,30,34,34,34,0,0
280 DATA0,24,0,24,24,24,24,0,24,0,24,24,0,24,0,24,0,0,0,20,18
290 DATA18,18,18,24,0,24,0,24,0,21,0,22,0,18,0,30,30,32,0,24,0
300 DATA24,0,24,0,24,0,26,21,16,16,16,16,16,16,16,16,16,999
310 REM END OF PAGE TWO FOR VOICE ONE
320 DATA24,0,24,0,24,0,24,0,24,24,24,0,24,0,24,24,0,24,0,24,0
330 DATA24,0,24,24,24,24,0,24,0,24,24,0,24,0,24,24,0,24,0,26
340 DATA26,0,26,0,27,0,27,0,27,0,40,0,22,26,30,30,30,30,30,34
350 DATA34,34,0,0,0,0,0,0,20,16,13,14,14,14,14,14,15,15,15,15
360 DATA0,0,0,0,27,30,32,36,40,20,18,36,40,20,18,36,40,20,18,18
370 DATA36,36,40,20,18,18,36,36,40,0,30,0,26,0,32,0,27,0,27,0
380 DATA30,0,40,0,22,22,22,26,30,34,34,34,0,24,0,24,0,24,24,0
390 DATA24,0,24,24,0,24,0,24,24,0,24,0,24,26,26,26,26,22,30,30
400 DATA30,30,32,32.32 : REM * END OF PAGE ONE FOR VOICE TWO
410 DATA32,32,32,0,0,24,0,24,0,24,24,24,0,24,0,24,24,0,24,0,24
420 DATA0,0,0,20,16,13,14,14,14,14,14,15,15,15,0,0,0,24,0,26,26
430 DATA0,26,0,27,0,27,0,30,0,30,0,32,32,32,32,32,0,0,0,34,0,34
440 DATA0,34,0,34,0,32,28,24,24,26,24,26,24,26,28,26,999
450 REM * END OF PAGE TWO FOR VOICE TWO
460 DATA10,2,2,2,10,2,2,2,4,4,2,2,2,2,8,2,2,2,2,10,2,2,2,3,3,3
470 DATA2,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2,2,2,2,10,2,2,2,10,2,2,2
480 DATA4.4,2,2,2,2,8,2,2,2,2,8,2,2,2,2,3,3,3,2,2,2,2,8,2,2,2,2
490 DATA10,2,2,2,4,4,4,4,8,8,8,8,8,8,8,8,8,8,4,4,4,4,8,8,4,4,4
500 DATA4,10,2,2,2,10,2,2,2,10,2,2,2,10,2,2,2,3,3,3,8,8,3,3,3
510 DATA8,10,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2
520 DATA2,2,2,8,8,8 : REM * END OF PAGE ONE OF RHYTHMS
530 DATA8,8,16,8,8,10,2,2,2,4,4,2,2,2,2,8,2,2,2,2,10,2,2,2,3,3
540 DATA3,2,2,2,2,8,2,2,2,2,10,2,2,2,8,2,2,2,2,10,2,2,2,10,2,2
550 DATA2,10,2,2,2,2,2,4,8,10,2,2,2,10,2,2,2,4,4,8,8,1,1,1,1,3
560 DATA6,20,999 : REM * END OF RHYTHMS PAGE TWO AND END PIECE
```

Each pair of voices is managed by programmable peripheral interface Z5, which provides two 8-bit outputs to digital-to-analog converters Z6 and Z7, offering one-part-in-256 accuracy. Remaining from Z5 are eight control lines for envelope, etc. Optionally, six of these remaining control outputs can be used for voltage control of volume or filtering (see Figure 7-7), which can be used with less resolution (one part in 64) than that needed for pitch control.

Figure 7-8 is the power supply, which is similar to others in this book with the exception of the LM340-8, providing eight volts as a reference to the digital-to-analog converters.

The output of the D/A converters Z6 and Z7 is in the range of 0 volts to 4.98 volts, which should be more than adequate to drive most synthesizers across their full range. The envelope triggers provided by Z8 and Z9, however, may need tweaking depending on the type of synthesizer you are using. Some synthos require a negative-going pulse, and others need a positive-going one; likewise, some synthos trigger on the rising or falling *edge* of the wave, while other envelopes will sustain as long as the level of the trigger signal remains high or low. Thus, the resistance and capacitance values given for Z8 and Z9 may have to be changed for sustained envelope triggers, or Z8 and Z9 might be eliminated completely if the envelope is edge-triggered. If you don't have specs on your synthesizer, build the trigger circuit up, then down, until it works for your machine.



*A ZENER DIODE WITH CURRENT LIMITING MAY BE USED.

Figure 7-8. Power supply for the synthesizer interface.

```
10 OUT254,2 : CLS : PRINT"READING.." : REM * OUT254,2 = HISPEED
20 X = 24578 : REM * THIS IS MEM. POSITION OF VOICE NUMBER ONE
30 READ A : IF A = 999 THEN 50 ELSE POKE X,A : REM * EXIT @ 999
40 X = X + 4 : GOTO 30 : REM * VOICE APPEARS EVERY 4 MEM LOC'NS
50 X = 24579 : REM * THIS IS MEM. POSITION OF VOICE NUMBER TWO
60 READ A : IF A = 999 THEN 80 ELSE POKE X,A : REM * PITCH POKE
70 X = X + 4 : GOTO 60 : REM * VOICE APPEARS EVERY 4 MEM LOC'NS
80 X = 24576 : REM * THIS IS THE BEGINNING VALUE FOR DURATIONS
90 READ A : IF A = 999 THEN 110 ELSE POKE X,A*2 : REM * RHYTHMS
100 X = X + 4 : GOTO 90 : REM * NOTICE RHYTHM MULTIPLIER ABOVE
110 RESTORE : REM * THIS GETS THE DATA POINTER BACK TO START
120 X = 24577 : REM * THESE LOCATIONS USED FOR SUBTLE DURATIONS
130 READ A : IF A = 999 THEN 150 ELSE POKE X,1 : REM * RHYTHMS
140 X = X + 4 : GOTO 130 : REM * NO CHANGE IN LSB TIMING ABOVE
150 POKE X,0 : POKE X+4,0 : POKE X+8,0 : REM * MUSIC END CODE
160 OUT254,3 : POKE 16526,96 : POKE 16527,143 : M=USR(0) :CLEAR
170 @LOAD6 : REM * PLAY NORM SPEED, USR CALL, CLEAR, LOAD NEXT
180 DATA0,0,0,0,0,0,0,0,25,29,31,29,3,0,0,0,0,20,16,13,14,14,14
190 DATA14,14,15,15,15,0,0,0,0,0,0,20,18,18,18,18,24,0,24,0,24
200 DATA0,24,0,24,24,24,0,24,0,24,24,0,24,0,24,24,0,24,0,24,24
210 DATA24,24,0,24,0,24,24,0,24,0,24,0,24,0,22,22,18,18,16,16
220 DATA14,14,13,13,12,13,13,13,14,19,27,19,13,13,14,19,27,19
230 DATA13,0,16,0,20,0,22,0,24,0,24,0,24,0,24,0,12,12,12,12,13
240 DATA15,15,15,15,18,21,21,21,21,16,16,0,16,0,16,16,0,16,0,16
250 DATA17,15 : REM * END OF PAGE ONE FOR VOICE ONE
260 DATA3,140,3,22,26,30,30,30,30,30,34,34,34,0,0,0,24,0,24,24
270 DATA24,24,0,24,0,24,24,0,24,0,24,0,0,0,20,18,18,18,18,24,0
280 DATA24,0,24,0,21,0,22,0,18,0,30,30,32,0,24,0,24,0,24,0,24,0
290 DATA26,21,16,16,16,16,16,16,16,16,16,999 : REM * END P2V1
300 DATA24,0,24,0,23,3,135,1,1,42,0,24,0,24,0,24,24,24,24,0,24
310 DATA0,24,24,0,24,0,24,24,0,24,0,26,26,0,26,0,27,0,27,0,27,0
320 DATA40,0,22,26,30,30,30,30,30,34,34,34,0,0,0,0,0,0,20,16,13
330 DATA14,14,14,14,14,15,15,15,15,0,0,0,0,27,30,32,36,40,20
340 DATA18,36,40,20,18,12,140,140,13,3,40,20,18,18,36,36,40,0
350 DATA30,0,26,0,32,0,27,0,27,0,30,0,40,0,22,22,22,26,30,34,34
360 DATA34,0,24,0,24,0,24,24,0,24,0,24,24,0,24,0,24,24,0,24,0
370 DATA24,26,26,26,26,22,30,30,30,30,32,32,32 : REM * END P1V2
380 DATA32,32,32,0,0,24,0,24,0,24,24,24,0,24,0,24,24,0,24,0,24
390 DATA0,0,0,20,16,13,14,14,14,14,14,15,15,15,0,0,0,24,0,26,26
400 DATA0,26,0,27,0,27,0,30,0,30,0,32,32,32,32,32,0,0,0,34,0,34
410 DATA0,34,0,34,0,32,28,24,24,26,24,26,24,26,28,26,999
420 REM * END OF PAGE TWO FOR VOICE TWO
430 DATA10,2,2,2,10,2,2,2,4,4,2,2,2,2,8,2,2,2,2,10,2,2,2,3,3,3
440 DATA2,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2,2,2,2,10,2,2,2,10,2,2,2
450 DATA4,4,2,2,2,2,8,2,2,2,2,8,2,2,2,2,3,3,3,2,2,2,2,8,2,2,2,2
460 DATA10,2,2,2,4,4,4,4,8,8,8,8,8,8,8,8,8,8,4,4,4,4,8,3,11,5,4
470 DATA10,2,2,2,10,2,1,1,10,2,2,2,10,2,2,2,3,3,3,8,8,3,3,3,8
480 DATA10,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2,2,2,2,8,2,2
490 DATA2,2,8,8,8 : REM * END OF PAGE ONE OF RHYTHMS
500 DATA8,8,16,8,8,10,2,2,2,4,4,2,2,2,2,8,2,2,2,2,10,2,2,2,3,3
510 DATA3,2,2,2,2,8,2,2,2,2,10,2,2,2,8,2,2,2,2,10,2,2,2,10,2,2
520 DATA2,10,2,2,3,13,5,9,2,2,2,12,10,2,2,2,4,4,8,8,1,1,1,1,3,6
530 DATA20,999 : REM * END PAGE TWO OF RHYTHMS AND END PIECE
```

Synthesizer Interface Port Addressing

Port Number (Decimal)	Port Number (Hex)	Port Function
64	40	Pitch Control Voice 1
65	41	Pitch Control Voice 2
66	42	Envelopes 1 a/b and 2 a/b Extra Lines 1 a/b and 2 a/b
67	43	Port Control Voices 1 – 2
68	44	Pitch Control Voice 3
69	45	Pitch Control Voice 4
70	46	Envelopes 3 a/b and 4 a/b Extra Lines 3 a/b and 4 a/b
71	47	Port Control Voices 3 – 4
72	48	Pitch Control Voice 5
73	49	Pitch Control Voice 6
74	4A	Envelopes 5 a/b and 6 a/b Extra Lines 5 a/b and 6 a/b
75	4B	Port Control Voices 5 – 6
76	4C	Pitch Control Voice 7
77	4D	Pitch Control Voice 8
78	4E	Envelopes 7 a/b and 8 a/b Extra Lines 7 a/b and 8 a/b
79	4F	Port Control Voices 7 – 8
.	.	.
.	.	.
.	.	.
.	.	.
124	7C	Pitch Control Voice 31
125	7D	Pitch Control Voice 32
126	7E	Envelopes 31 a/b and 32 a/b Extra Lines 31 a/b and 32 a/b
127	7F	Port Control Voices 31 – 32

Table 7-1. Synthesizer interface port addressing.

Using the synthesizer interface is straightforward. Plug the interface into the TRS-80 expansion connector, and run shielded microphone cable from the voltage outputs of the interface to the voltage inputs (marked 'control in', 'voltage in', 'VCO control', 'external in', or something similar) on the synthesizer. Then run either parallel speaker wire or shielded cable from the interface envelope (positive-going edge) to the synthesizer's envelope inputs. The integrated circuits running from the interface are not balanced for long lines; if you plan to use more than a dozen feet of cable, place 7417 open-collector buffers at each control output from the interface, so:



```
10 OUT254,2:CL5:PRINT"READING..."
12 X=24578
15 REA0A:IFA=999THEN30ELSEPOKEX,A:X=X+4:GOT015
30 X=24579
35 REA0A:IFA=999TNEN50ELSEPOKEX,A:X=X+4:GOT035
50 X=24576
55 REA0A:IFA=999THEN80EL5EPOKEX,A*2:X=X+4:GOT055
80 RE5TORE:X=24577
80 REA0A:IFA=999THEN97EL5EPOKEX,1:X=X+4:GOT090
97 OUT254,3:POKEX+4,0:POKEX+8,0:POKE16526,96:POKE16527,143:N=USR(0):CLEAR
98 @LOA03
100 OATA20,20,20,20,20,20,20,18,20,19,17,17,17,17,17,15
110 OATA24,24,21,27,26,27,27,27,30,27,30,27,0,0,20,21,20,19,17
120 OATA16,16,27,24,40,48,48,44,40,36,30,26,26,18,18,14,13
130 OATA11,9,9,9,12,11,12,10,21,21,27,27,28,27,26,24
140 OATA28,28,28,27,24,19,17,17,20,13,13,18,16,20,21,21,24,22,22,22,20
150 OATA19,18,36,27,30,30,28,36,19,19,20,20,13,13,22,22,24,24,17,15,15
160 OATA14,27,24,21,20,21,16,14,13,11,10,13,18,24
170 OATA32,32,32,32,32,32,32,32,32,32,32,32,32,30,27,40,38,38,28,28,26,24,24
180 OATA20,20,20,20,20,20,20,18,20,19,17,17,17,17,17,15
190 OATA24,24,21,27,26,27,27,27,30,27,27,24,22,32,32,24,22
200 OATA34,34,32,42,42,38,38,34,30,24,22,20,14,14
210 OATA13,13,14,16,18,18,18,17,16,20,22,26,27,27,27,30,24,18
220 OATA17,17,17,17,18,16,14,13,19,22,26,27,27,27,34,28,26,22,22,22
230 OATA24,24,20,30,38,38,40,36,42,42,42,44,54,68,68,68,68,48,52,44,40,34,34,36
240 REN ENO OF PAGE 1
250 OATA38,44,32,32,34,40,28,28,30,36,26,27,32,22,24,30,32,36,38,42,40,36
260 OATA40,40,38,44,32,32,34,40,28,28,36,32,27,27,27,24,21
270 OATA20,20,20,20,20,20,20,18,20,19,17,17,17,17,17,15,24,26,27,30,32,34,36,0
280 OATA40,0,0,0,0,0,0,0,0,999
290 REN ENO OF PAGE 2
300 OATA60,52,48,40,34,36,42,60,52,48,48,40,34,36,42,42
310 OATA60,52,48,48,40,34,36,42,42,60,52,52,48,40,34,34,36,36,42
320 OATA54,52,42,36,30,32,38,54,54,52,52,42,36,30,32,38,38
330 OATA54,52,42,36,30,30,32,38,54,52,42,36,36,30,32,38
340 OATA48,44,38,32,32,27,27,28,28,34,48,44,44,38,38,32,32,27,28,34,34
350 OATA48,48,44,44,38,32,32,27,28,34,48,44,44,38,38,32,32,27,27,28,34
360 OATA36,36,36,36,52,52,52,64,64,84,68,68,68,68
370 OATA68,80,60,54,42,48,40,44,52,40,54,40,57,72,76,78,44,52,57,64,48,40,54,57
380 OATA60,57,48,40,34,36,42,60,57,48,48,40,34,36,42,42
380 OATA60,57,48,48,40,34,36,42,42,64,68,76,76,48,36,40,40
400 OATA40,57,54,48,60,64,42,52,52,52,48,54,60,68
410 OATA76,72,60,52,42,44,54,54,76,76,72,72,60,52,42,44,44,54
420 OATA40,42,52,60,60,72,72,68,68,57,57,40,42,52,52,60,60,72,68,57
430 OATA36,38,38,44,44,54,54,64,64,60,52,52,36,36,38,44,54,54,64,64,60,80,52,52
440 REH ENO OF PAGE 1
450 OATA54,54,54,72,48,48,48,64,42,42,40,38,38,38,52,52,34,34,34,34,44,44
460 OATA30,28,27,27,27,36,24,24,24,32,21,20,19,28,42,68,68
470 OATA60,57,48,40,34,38,42,60,57,48,48,40,34,36,42,42
480 OATA60,57,48,44,42,0,0,0,40,0,0,0,0,0,0,0,0,0,0,0,0,0,989
490 REM ENO OF PAGE 2
500 OATA8,8,8,8,8,8,8,8,8,4,4,8,8,8,4,4
510 OATA8,8,4,4,8,8,8,4,4,8,4,4,8,8,4,4,4,4,8
520 OATA8,8,8,8,8,8,8,4,4,4,4,8,8,8,8,4,4
530 OATA8,8,8,8,4,4,8,8,8,8,8,4,4,8,8,8
540 OATA8,8,8,4,4,4,4,4,4,8,8,4,4,4,4,4,4,8,8,4,4
550 OATA4,4,4,4,8,4,4,8,8,8,8,4,4,4,4,4,4,4,4,8,8
560 OATA8,8,8,8,8,8,8,8,8,8,8,8,8,8
570 OATA4,4,4,4,4,4,4,4,4,4,4,4,4,4,8,8,8,4,4,4,4,8,4,4
580 OATA8,8,8,8,8,8,8,8,8,4,4,8,8,8,4,4
590 OATA8,8,4,4,8,8,8,4,4,8,8,4,4,8,8,8,8
600 OATA8,8,8,8,8,8,8,8,8,8,8,8,8
610 OATA8,8,8,8,8,8,4,4,4,4,4,4,8,8,8,4,4,8
620 OATA8,8,8,4,4,4,4,4,4,4,4,8,8,4,4,4,4,8,8,8
630 OATA8,4,4,4,4,4,4,4,4,8,4,4,4,4,8,8,4,4,4,4,4,4,4,4
640 REH ENO OF PATE
650 OATA4,4,8,8,4,4,8,8,4,4,8,4,4,8,4,4,4,4,4,4,4,4
660 OATA8,8,4,4,8,8,4,4,8,8,8,8,8,8,8,4,4
670 OATA8,8,8,8,8,8,8,8,8,4,4,8,8,8,4,4,8,8,8,8,8,4,4,8
680 OATA8,8,8,8,8,8,8,8,999
```

```
10 GOSU8 650 : REM * THE TUNING SECTION IS RETRIEVEO FIRST
20 OEFINT V, A, 8, C, O, T, X, Y, P, N : REM * INTEGERS ALL
30 V1 = 64 : REM * VOICE ONE USES OUTPUT LOCATION 64
40 V2 = 65 : REM * VOICE TWO USES OUTPUT LOCATION 65
50 EN = 66 : REM * ENVELOPE TRIGGER USES OUTPUT LOCATION 66
60 TN = 32 : REM * TRIGGER TURNEO ON WITH VALUE 32
70 TF = 0  : REM * TRIGGER TURNEO OFF WITH VALUE 0
80 CT = 67 : REM * 8255 PIA CONTROL REGISTER AT LOCATION 67
90 PT = 128 : REM * PORT OUTPUT ONLY OEFINEO BY VALUE 128
100 NN = 200 : REM * NUMBER OF NOTES OEFINEO BY VALUE 200
110 OIM V1(2,500) : REM * ARRAY OF NOTES ANO THEIR OURATIONS
120 OIM V2(2,500) : REM * ARRAY OF NOTES ANO THEIR OURATIONS
130 X=1 : REM * TEMPORARY COUNTER ONLY
140      REAO V1(1,X) : REM * REAO VOICE ONE
150      REAO V1(2,X) : REM * REAO OURATION ONE
160      IF V1(2,X) = 0 THEN 170 ELSE X = X + 1 : GOTO 140
170 X=1 : REM * TEMPORARY COUNTER ONLY
180      REAO V2(1,X) : REM * REAO VOICE TWO
190      REAO V2(2,X) : REM * REAO OURATION TWO
200      IF V2(2,X) = 0 THEN 210 ELSE X = X + 1 : GOTO 180
210 A=1 : 8=1 : C=1 : D=1 : X=1 : Y=1 : Q=0 : R=2
220 OUT CT,PT : OUT V1,255 : OUT V2,255
230 G = V1(R,X) : H = V2(R,Y) : GOSU8 330 : GOSU8 350
240 G = G - A : IF G <= Q THEN 250 ELSE 270
250 X = X + A : GOSU8 330 : G = V1(R,X)
260 GOTO 280
270 FOR W = 1 TO 14 : NEXT
280 H = H - A : IF H <= Q THEN 290 ELSE 310
290 Y = Y + A : GOSU8 350 : H = V2(R,Y)
300 GOTO 320
310 FOR W = 1 TO 14 : NEXT
320 IF X > 200 THEN 210 ELSE 240
330 IF V1(A,X) = Q THEN 340 ELSE OUT ÉN,TN : OUT EN,TF :
    OUT V1,V1(A,X) : RETURN
340 FOR W = 1 TO 2 : NEXT : RETURN
```

Listing Continued . . .

Once the connections are made, run the following few lines, an envelope test:

```
10  OUT 67,128            : REM  SET 8255 PORT
20  A$=INKEY$             : REM  SCAN KEYBOARO
30  IF A$="" THEN 20      : REM  LOOP IF NO KEY
40  OUT 66,1              : REM  ENVELOPE ON SHOT
50  OUT 66,0              : REM  ENVELOPE OFF SHOT
60  GOTO 20               : REM  LOOP AS NEEOEO
```

The envelope should be triggered each time you touch a key on the TRS-80. If the envelope does not trigger, move the interface connection to the negative-going envelope, and try again. If the envelope is still not working, increase the values for C3 or R5, which are found at pins 14 and 15 of Z8. This will lengthen the trigger cycle, and should handle any synthesizer input. Again, try both the positive and negative envelopes.

Now disconnect the envelope trigger, and patch the envelope out of the synthesizer. Try the following program which creates a series of fast-rising whoops if the digital-to-analog converter is working properly:

```
10  OUT 67,128            : REM  SET UP 8255 PORT
20  INPUT"TIME OELAY";N   : REM  GET INTERNOTE OELAY
30  FOR X = 0 TO 255      : REM  SET TO RUN ALL NOTES
40  OUT 64,X              : REM  SENO VOLTS TO SYNTHO
50  FOR Y = 1 TO N        : REM  SET UP TIMING LOOP
60  NEXT : NEXT           : REM  TIME, GET NEXT NOTE
70  GOTO 20               : REM  8ACK FOR NEXT OELAY
```

Each time you run through the program to the INPUT statement, increase the value for the time delay; the whoops will slow until you can hear a series of discrete pitches. If you have a two-voice synthesizer (or to test the second voice of the interface), connect the voltage output from voice 2, and use OUT 71,128 to set the port and OUT 68,X for the data.

If the pitches fall instead of rise, then your synthesizer responds to a higher voltage as a *lower* pitch, and any music routines you write will have to take this into account. If this is the case, before you run change line 60 to read:

```
60 OUT 66,32 : OUT 66,0 : OUT 64,(255-ML(1,PH))
```

Finally, run Listing 7-4, a rendition of keyboard prelude 23 from Johann Sebastian Bach's Well-Tempered Clavier.

Continued Listing

```
350 IF V2(A,Y) = Q THEN 350 ELSE OUT EN,TN : OUT EN,TF :
    OUT V2,V2(C,Y) : RETURN
360 FOR W = 1 TO 2 : NEXT : RETURN
370 0ATA81,4,105,2,102,2,87,4,114,4,102,4,120,2.117,2.132,4,126
380 0ATA4,90,4,96,6,93,2,96,4,123,2,117,2,123,4,132,8,138,2,111
380 0ATA2,117,2,132,2,129,2,132,2,138,4,144,2,135,2,138,4,138,4
400 0ATA108,4,123,4,87,4,117,4,93,4,96.2,90.2,87,2,84,2,87,12
410 0ATA108,4,102,12,132,4,129,4,138,4,135.4,129,4,123,4,111,2
420 0ATA120,2,123,4,87,4,108,4,75,2,81,2,87,4,108,2,105,2,108
430 0ATA2,132,2,138,2,123,2,126,4,111,4.96,4,99,4.87,4,90,8,93
440 0ATA8,102,8,105,8,108,4,132,4,93,4,138,4,81,4,105,2,102,2
450 0ATA87,4,114,4,102.4,120.2,117,2,132,4,126,4,90,4,87,2,90,2
460 0ATA96,2,102,2,96,2,102,2,105,2,87,2.93,2,129,2,132,2,126,2
470 0ATA123,2,126,2,120,2,117,2,111,2,105,2,102.2,111,2,108,2
480 0ATA111,2,120,2,117,2,111,4,138,2,117.2,123,4,121,2,105,2
490 0ATA132,2,126,2,120,2,117,2,111.4,132,2,129,2,132,4,102,4
500 0ATA81,4,87,2,90,2,96,2,99,2,96.2,117,2,111,2,108,2,111.4
510 0ATA114,4,111,16,0,0,0,36,81,4,105,2,102.2,87.4,114,4,102
520 0ATA4,120,2,117,2,132,4,126.4.90,4,96.6.93,2,96,4,123,2,117
530 DATA2,123,4,132,8,138,2,111,2,117,2.132,2,129,2,132,2,138,4
540 0ATA144,2,135,2,138.4,138,4,108,4,123.4,87,4.117,4.93,4,96
550 0ATA2,80.2,87,2,84,2,87,12,108,4,102.12,132,4,129,4.138,4
560 0ATA135,4,129,4,123,4,111,2,120,2,123.4,87,4,105,4,75,2,81
570 0ATA2,87,4,108,2,105,2.108,2,132,2,128,2,123,2,126,4,111,4
580 0ATA96,4,99,4,87,4,90.8,93,8,102,8,105,8,108,4,132,4,93,4
590 0ATA138,4,81,4,105,2,102,2,87,4,114,4,102,4,120,2,117,2,132
600 0ATA4,126,4,90,4,87,2,90,2.95,2,102,2,95.2,102,2.105,2,87.2
610 DATA93,2,129,2,132,2,126,2.123,2,126,2,120,2,117,2,111,2
620 0ATA105,2,102,2,111,2,108,2,111,2,120,2.117,2,111,4,138,2
630 0ATA117,2,123,4,141,2,105,2,132,2,126,2.120,2,117,2,111,4
640 0ATA132,2,129,2,132,16,0,0 : REH * ENO OF TWO VOICES
850 REM * THE TUNING SECTION PROOUCES OCTAVE PITCHES
660 OUT 67,128 : REM * SET UP THE 8255 PIA FOR ACTION
670 OUT 64,3 : OUT 65,3 : FOR N = 1 TO 1000 : NEXT
680 OUT 64,39 : OUT65,38 : FOR N = 1 TO 1000 : NEXT
680 OUT 64,75 : OUT 65,75 : FOR N = 1 TO 1000 : NEXT
700 OUT 64,111 : OUT65,111 : FOR N = 1 TO 1000 : NEXT
710 OUT 64,147 : OUT 65,147 : FOR N = 1 TO 1000 : NEXT
720 A$ = INKEY$ : IF A$ = "" THEN 670 ELSE RETURN
```

```
10 CL6 : PRINTCHR$(23) "- GENERALIZEO MU5IC PROGRAM -"
20 PRINT : PRINT : PRINT "OENNI5 8ATHORY KIT5Z. HAY 1979"
30 FOR X = 1 TO 1000 : NEXT : CLEAR : CLS
40 PRINT"THERE ARE 539 NOTES IN 8ACH PRELUOE NO. 23" : 0 = 639
60 0OTO 400 : REM * MOVE TO TUNINO ROUTINE 8EFORE PLAYINO PIECE
80 OIM ML(2,0+50) : REM * EXTRA 8YTES 5ET ASIOE FOR LONGER WORK
70 PRINT : PRINT"NOW REAOING";0;"NOTES FROM NOTE/RHYTHH OATA."
80 FOR PH = 1 TO 0 : REM * PM 5PECIFIES PITCH & OURATION ARRAY
90 FOR NT = 1 TO 2 : REM * NT SPECIFIE5 THE TWO ARRAY ELEMENT5
100 REAO ML(NT,PH) : REM * EACH PITCH ANO RHYTHM FILLS ARRAY
110 NEXT NT,PH : REM * REAO ENTIRE ARRAY OF 639 NOTES & RHYTHMS
120 INPUT "PRESS ENTER TO START PIECE";Z : REM * WAIT FOR START
130 FOR PH = 1 TO Q : REM * REAO ARRAY LOOP TO PLAY 8ACK MUSIC
140 OUT 55,32 : OUT 68,0 : REM * ENVELOPE TRIGGER ON THEN OFF
150 OUT 64,ML(1,PH) : REM * THEN 5ENO PITCH TO O/A CONVERTER
160 FOR X = 1 TO ML(2,PH) : NEXT : REM * ARRAY OURATION OELAY
170 NEXT PM : REM * ANO CONTINUE UNTIL ALL NOTES ARE PLAYEO OUT
180 INPUT "PRESS ENTER TO PLAY AGAIN";Z : REM * OPTIONAL REPEAT
180 GOTO 120 : REM * ANOTHER PIECE HAY 8E AOOEO ANO RUN MERE
200 OATA89,31,80,31,117,31,90,31,66,31,90.31,111,31,90,31,69,
     31,80,31,117,31,90,31,54,31,102,31,126,31,102,31,60,31,
     81,31,105,31,81,31,54,31,81,31,102,31,81,31,60,31,81,31,
     105,31,81,31,45,31,90,31,117,31,90,31
210 OATA48,31,88,31,98,31,69,31,45,31,69.31,90,31,69,31,48,31,
     69,31,86,31,88,31,33,31,81,31,105,31,81,31,39,31,81,31,84,
     31,81,31,33,31,81,31.95,31,81,31,30,31,75,31,90,31,75,31,
     18,31,65,31,84,31,66,31
220 OATA68,31,81,31,90,31,81,31,54,31.69,31.81,31,69,31.45,31,
     54,31,59,31,54,31,33,31,45,31,54,31,45,31.24,31,45,31,51,
     31,57,31,60,31,66,31,69,31,75,31,69,31,60,31,66,31,69,31,
     75,31,81,31,87,31,80,31
230 OATA75,31,87,31,98,31,87,31,60,31,75,31,87,31,75,31,51,31,
     80,31,75,31,60,31,39,31,51,31,60,31.51,31,30,31,51,31,54,
     31,60,31,68,31,72,31,75.31,81,31,75,31,66,31.72,31,75.31,
     81,31,87,31,90,31,86,31
240 OATA81,31,90,31,102,31,90,31,66,31,81,31,90,31,81,31,54,31,
     88,31,81,31,86,31,45,31,54,31,66,31,54.31,33,31,54.31,81,
     31,54,31,24,31,54,31,69,31,54,31,30,31.54.31,75,31,54,31,
     19,31,54,31,84,31,54,31
250 OATA33,31,54,31,81,31,54,31,24,31,54,31,69,31,54,31,30,31,
     54,31,75,31,54,31,18,31,54,31,84,31,54,31,33,31,54,31,81,
     31,54,31,36,31,80,31,90,31,50,31,39,31,50,31,87,31,50,31,
     42,31,68,31,88,31,56,31
260 OATA45,31,86,31.80,31.66,31,9.31,69,31,102,31,69,31,15,31,
     89,31,85,31,58,31,51,31,75,31,105,31,75,31,54,31,75,31,
     102,31,75,31,18,31,81,31,111,31,81.31,24,31,81,31,105,31,
     91,31,80,31,87,31,117,31,87,31
270 OATA88,31,75,31,81,31,87,31,90,31,96,31,102,31,105,31,111,
     31,105,31,102,31,96,31,90,31,84,31,81,31,75,31,81,31,69,
     31,88,31,60,31,54,31.48,31,45,31,39,31,33,31,39,31,45,31,
     38,31,33,31,30,31,24,31,18,31
280 OATA15,31,75,31,105,31,75,31,18,31,75,31,102,31,75,31,9,31,
     88,31,102,31,88,31,15,31,69,31,96,31,69,31.18,31,66,31.96,
     31,66,31,30,31,66,31,80,31,66,31,33,31.60,31,90,31.60,31,
     39,31,50,31,87,31,80,31
290 OATA18,31,75,31,80,31,75,31,66.31,90,31,75,31,66,31,54,31,
     88,31,75,31,68,31,54,31,75,31,56,31,54,31,39,31,54,31,51,
     31,45,31,38,31,33,31,30,31,24,31,18,31,30,31,39,31,54,35,
     88,39,75,42,84,45,93,48
300 OATA8,250,46,15,54,15,89,15,81,15,99,15,105,15,117,15,128,
```

Continued Listing

```
     200,45,15,54,15,69,15,91,15,99,15,106,15,117,15,126,50,36,
     15,45,15,80,15,85,15,108,15,117,15,126,131,132,31,135,31,
     132,31,126,31,120,31,117,31,120,31
310 OATA126,31,123,31,117,31,111,31,108,31,111,31,117,31,111,
     31,108,31,102,31,86,31,102,31,108,31,102,31,98,31,80,31,
     84,31,81,31,75,31,68,31,63,31,60,31,54,31,48,31,45,31,39,
     31,38,31,30,34,24,37,18,40,12,44,8,48,3,250
320 OATA39,15,48,15,60,15,75,16,96,15,111,15,120,200,39,15,48,
     15,50,15,75,15,98,15,105,15,111,15,120,50,54,15,66,15,75,
     15,90,15,102,15,111,15,120,131,54,31,38,31,45,31,48,31,54,
     31,60,31,86,31,69,31
330 OATA68,31,80,31,54,31,80,31,58,31,89,31,75,31,81,31,75,31,
     69,31,66,31,68,31,75,31,81,31,84,31,80,31,84,31,81,31,75,
     31,81,31,84,31,80,31,88,31,102,31,105,31,111,31,117,31,
     120,34,126,37,132,40,138,44,125,48
340 OATA141,250,33,15,45,15,54,15,89,15,80,15,102,15,105,15,
     117,200,33,15,45,15,54,15,88,15,80,15,102,15,105,15,117,
     50,48,15,80,16,88,16,84,15,96,15,106,15,117,250,51,15,80,
     15,68,15,85,15,106,15,114,200,51,15,60,15,75,15,88,15,106
350 OATA15,111,50,54,15,88,15,75,15,84,15,80,15,102,15,111,250,
     102,15,111,31,102,31,90,31,84,31,80,31,102,31,111,31,102,
     31,111,31,102,31,80,31,84,31,80,31,102,31,111,31,129,31,
     126,31,120,31,114,31,111,31,105,31,102,31,88,31
360 OATA102,31,90,31,102,31,111,31.120,31,128,31,138,31,147,31,
     141,83,111,31,114,31,102,31,105,31,87,31,18,15,38,15,48,
     15.54,15,75,15,80,15,105,15,111,125,81,125,18,15,39,15,48,
     15.54,15,84,16,80,15,102,115,111,031,54,125,80,125
370 OATA33,15.45,15,54,16,63,15,81,15,90,15,105,250,81,31,90,
     31,81.31,88,31,56,31.88,31,81,31,80,31,81,31,80,31,81,31,
     68,31,68,31,68,31,81,31,80,31,108,31,89,31,80,31,81,31,72,
     31,66,31,54,31.81,31
380 OATA60,15,84.15,81,15,84,15,81,16,84,125,81,31.76,31,81,31,
     84,31,81,31,75,31,88,31,66,31,58,31,75,31,89,31,88,31,80,
     31,54,31,60,31,55,31,50,31,54,31,48,31,45,31,48,31,54,31,
     48,31.45,31,39,31,33,31,30,31
390 OATA33,31,45,31,54,31,45,31,45,31,54,31,89,31,54,31,54,31,
     69,31,81,31.89,31,59,31,81,31,80,31.81,31,81,31,90,31,105,
     31.90,31,80,31,105,31,117,33,105,35,105,37,117,39,126,42,
     117,45,141.150
400 REM * * * * * * * * TUNING SECTION FOLLOWS * * * * * * * *
410 PRINT"THIS IS THE TUNING SECTION -- OUTPUT IS 3, 38, 75."
420 PRINT"HOLO SPACE 8AR TO 8EGIN REAOINO 8ACH PRELUOE OATA."
430 OUT 64,3 : FOR X = 1 TO 500 : NEXT : REM * OUTPUT LOW C
440 OUT 64,39 : FOR X = 1 TO 500 : NEXT : REM * NEXT OCTAVE
450 OUT 64.75 : FOR X = 1 TO 500 : NEXT : REM * NEXT OCTAVE
460 OUT 54,111 : FOR X = 1 TO 500 : NEXT : REM * NEXT OCTAVE
470 OUT 64,147 : FOR X = 1 TO 500 : NEXT : REM * TOP OCTAVE
480 A$ = INKEY$ : IF A $ = "" THEN 480 : REM * CHECK KEY8OARO
480 OUT 58,255 : REM * HOPE THAT VERY TOP NOTE I6 INAUOI8LE
500 GOTO 60 : REM * NOW RETURN TO MAIN MUSIC REAOINO ROUTINE
```

Listing 7-4. Johann Sebastion Bach.

8

P/N	SIGNAL NAME	DESCRIPTION
1	RAS*	Row Address Strobe Output for 16-Pin Dynamic Rams
2	SYSRES*	System Reset Output, Low During Power Up Initialize or Reset Depressed
3	CAS*	Column Address Strobe Output for 16-Pin Dynamic Rams
4	A10	Address Output
5	A12	Address Output
6	A13	Address Output
7	A15	Address Output
8	GND	Signal Ground
9	A11	Address Output
10	A14	Address Output
11	A8	Address Output
12	OUT*	Peripheral Write Strobe Output
13	WR*	Memory Write Strobe Output
14	INTAK*	Interrupt Acknowledge Output
15	RD*	Memory Read Strobe Output
16	MUX	Multiplexor Control Output for 16-Pin Dynamic Rams
17	A9	Address Output
18	D4	Bidirectional Data Bus
19	IN*	Peripheral Read Strobe Output
20	D7	Bidirectional Data Bus
21	INT*	Interrupt Input (Maskable)
22	D1	Bidirectional Data Bus
23	TEST*	A Logic “0” on TEST* Input Tri-States A0-A15, D0-D7, WR*, RD*, IN*, OUT*, RAS*, CAS*, MUX*
24	D6	Bidirectional Data Bus
25	A0	Address Output
26	D3	Bidirectional Data Bus
27	A1	Address Output
28	D5	Bidirectional Data Bus
29	GND	Signal Ground
30	D0	Bidirectional Data Bus
31	A4	Address Bus
32	D2	Bidirectional Data Bus
33	WAIT*	Processor Wait Input, to Allow for Slow Memory
34	A3	Address Output
35	A5	Address Output
36	A7	Address Output
37	GND	Signal Ground
38	A6	Address Output
39	GND	Signal Ground
40	A2	Address Output

NOTE: *means Negative (Logical “0”) True Input or Output



Mates with AMP P/N 88103-1 Card Edge Connector or Equivalent

Figure 8-1. TRS-80 edge card connector.

Adding to the System

In this Chapter we will explore several hardware projects to expand the TRS-80's capabilities :

A parallel printer interface for keyboard units without an expansion interface.

An expansion of system RAM and ROM in a 'reserved' block in the memory map.

Bank selection of RAM and ROM in that 'reserved' blank area, and a memory expansion that includes bank selected RAM.

A programmable input/output port device and a companion interrupt I/O board.

Battery backup and real time clock.

Parallel Printer Interface

Perhaps the simplest addition to the keyboard unit is a printer interface. Radio Shack sells a complete cable for this purpose, but building one is both less expensive and more enlightening.

When an LLIST or LPRINT command is entered, the computer enters a subroutine which plucks each character to be printed, checks its value, and converts it if necessary. Line feeds, for example, are converted to carriage returns, and form feeds are converted to the proper number of line feeds according to the value in the printer's device control block.

The final value is written to an address, almost exactly as if it were being stored in memory. The hardware decodes that memory

address and sends the character along parallel data lines to the printer. The printer then sends a 'busy' signal to the memory address. The LPRINT or LLIST routines read this busy signal, wasting time until the printer is ready. When the busy signal turns off, the next character is plucked, converted and sent to the printer. The process continues until all characters are printed.

There are disadvantages to this system; among them the fact that the printing process 'hangs up' the computer for the duration. This can easily be avoided in an interrupt-driven system (see Supplement to Chapter 5), and even modified in a less successful way as a background routine to the keyboard scan. But the overall process is simple, requiring neither sophisticated hardware nor complex software.

Figure 8-1 presents the complete circuit for a printer interface board. It consists of three sections :

1. An address decoder for 37E8, the printer location.



IC	TYPE	+5V	GND
Z1	74LS30	14	7
Z2	74LS260	14	7
Z3	74LS00	14	7
Z4	74LS123	16	8
Z5	74LS377	16	8
Z6	74LS367	16	8

Figure 8-2. Parallel printer interface.

2. An 8-bit output buffer for sending characters to the printer.
3. An input buffer for checking the status of the printer (busy or out of paper).

The address decoder is formed by Z 1 and Z 2 evaluating the address lines in conjunction with RD (read) or WR (write) signals from the computer. If WR is sent, buffer Z 6 is activated, sending a character to the printer. If RD is sent, buffer Z 6 is activated, sending the status of the printer to the CPU.

Power-up the TRS-80, and go through the input sequence. If this process does not act normally, *turn the computer off immediately* and recheck the wiring. If all is normal, it's time for a printer test. Turn the printer on (don't be surprised by a return to MEMORY SIZE? if your printer is an older, electrically noisy one). The simplest way to test the printer interface is to load any program and LLIST it. The printer should spring to life, printing a complete list. If there are problems, they will probably be among the following :

No characters printed at all; computer immediately (or after a short pause) returns to ready.

Characters are being sent to the memory address, but not being received by the printer. Therefore, no 'busy' is being received, and the computer dumps all its characters as fast as it can.

> **Solution** : check wiring of the port address, wiring to the output buffer select line, and see that the board has both power and ground wires connected.

No characters printed at all; computer immediately locks up :

Characters are being sent to the memory address, but if none are printed, they are not being received by the printer. The computer is seeing a constant 'busy' signal, and thus is waiting in a loop.

> **Solution** : check wiring of the port address, wiring to the input buffer from the printer, and see that the printer is enabled (if it has an enable function).

Intermittent but regular characters (every third or fifth or fiftieth character, for example) are being printed.

Characters are being sent through to the printer, but no handshake ('busy') is being received by the computer.

> **Solution** : check wiring of the input buffer select line, and the wiring from the printer's busy signal. Some printers may not have a busy signal; see box for suggestions.

A single character is printed, then printing stops and the computer locks up.

A constant busy is being received by the computer, and it is waiting in a loop for the busy signal to terminate.

> **Solution** : check for ground shorts in the printer's busy line, or shorts to ground at the input buffer.

Incorrect characters are printed, and none or any of the above symptoms are present.

The data lines are incorrectly wired to the printer or to the board's output buffer. The printer may be wired for complement ASCII.

> **Solution** : check the wiring of the data lines for reversed wires, either at the computer or printer end. If all is well, enter the following short program :

```
10 FOR X = 65 TO 91
20 Y = NOT X ANO 255
30 POKE 14312,Y
40 FOR N = 1 TO 100
50 NEXT : NEXT
```

Listing 8-1. Printer interface test routine.

This program produces the complement of the letters from A to Z. If the correct letters are printed this time, replace Z 5 with an inverting buffer, type 81LS96.

Talking with the World – The Computer as Boss

The TRS-80 has remarkable skills for controlling the world around it. Four BASIC commands (POKE, PEEK, INP, and OUT) and their machine language equivalents (LD register, LD memory, IN register, OUT port) are the software conversational tools by which the computer makes its wishes known.

Only one dilemma remains: very little hardware was provided with the TRS-80 to use these powerful features. Just a single port (255) was hard-wired in place, and it is limited to controlling cassette functions and video display size. Memory mapped input/output was left exclusively to the expansion interface. And even then then, only for a printer, dual cassette, RS-232 and disks. In each case, no uncommitted user ports or memory addresses were provided.

Fortunately, creating such input/output (I/O) is not difficult. There are two very effective ways to accomplish it:

1. Using inexpensive, separate logic devices that can be dedicated to their interfacing tasks. The TRS-80 Technical Reference Handbook describes such simple hardware in its 'coffee pot' scenario.
2. Using more costly programmable interface devices (such as the INS8255 peripheral interface adaptor) for handling more flexible, general purpose I/O.

In either case, the input/output device must be identifiable by the computer, which means it must somehow be located. It is assigned a port number or a memory address. But what does this number mean, and how does it work? I have often used the analogy of the key in the lock, because it so well describes the way the electronics can open the doors to the world outside its case.

Figure 8-3 shows a simple-minded lock and key. It is simple minded because there are no fine graduations in the height of the tumblers – the 'pins' either rise to a single height, or are not present at all. In the computer, these pins are really voltages, represented by numbers.

In other words, the higher voltage can be called a 'one', and the lower voltage can be considered a 'zero'. In this way, the key number code shown in Figure 8-3 might look like this :

ON	ON	OFF	ON	ON	OFF	OFF	OFF
1	1	0	1	1	0	0	0

The sample key's code (binary 1101 1000) works out to the hexadecimal value **D8**, or the decimal equivalent 216 (refer to Chapter 2 for details on binary, decimal, and hexadecimal numbers). The 'key' is the value that the computer will output; the 'tumblers' are the hardware which will unlock when this key is inserted.

Below is the schematic of a general purpose 'tumbler' which can be adjusted to open to any electronic key. As noted in Chapter 2, the triangles are buffers which protect the TRS-80 electronic hardware from overexertion. Once again, the triangle with the 'not' circle at its point is an inverting buffer, which reverses the value of any signal placed at its input.



Figure 8-3. Lock-and-key illustration.



Figure 8-4. Unconnected buffer diagram.

This is very elementary – it will be improved on later – but it is the central scheme of digital operation. Real tumblers must all be lifted to a point so they are in line with the edge of the lock's cylinder. Electronically, the same thing must take place. To turn the electronic cylinder, all the binary input values must be lifted (or depressed) to the same value before the electronic lock will click open.

**:

Using Exclusive-OR for decoding

Resistor 1K ohms to Ground; Switch to Plus Volts

Switch Position	Input Value	Output Value
OFF (gate sees 0)	0	0
ON (gate sees 1)	0	1
OFF (gate sees 0)	1	1
ON (gate sees 1)	1	0

Resistor 1K ohms to Plus Volts; Switch to Ground

Switch Position	Input Value	Output Value
OFF (gate sees 1)	0	1
ON (gate sees 0)	0	0
OFF (gate sees 1)	1	0
ON (gate sees 0)	1	1

****

Table 8-1. Using exclusive-OR for decoding.



Figure 8-6. Improved port decoding for port addresses.

Figure 8-5 is the schematic for an elementary interface circuit. Z1 and Z2 form the tumblers, and Z3 is the cylinder.

There is another way to produce the same effect as Z1 and Z2, and no rewiring or jumpering is necessary. To do it, you can use one or two 74LS86 exclusive OR gates. Exclusive OR is a remarkable electronic function which states :

> *If two input signals are alike, the evaluated result will be set to zero. If two input signals are different, the evaluated output will be set to one.*

Here's how that might work electronically. One input of an exclusive OR gate is attached to a switch and a resistor. The resistor is attached to ground, with the switch connected to the positive voltage line. When the switch is off, the input looks like a zero. When the switch is on, the lower resistance of the switch makes the input of the gate see a one.

Therefore, with the switch off, a signal coming into the second input of the gate would cause a one output when it is a one. With the switch on, a signal coming into the second input of the gate would cause a zero output when it is a one. Refer to Table 8-1.

By using eight exclusive OR gates (two type 74LS86 circuits) and an 8 position DIP (dual inline package) switch, any one of the 256 possible ports can be selected. The circuit below (Figure 8- 6) shows how Z1 and Z2 in Figure 8- 5 can be replaced with a switch and the 74LS86's to select the port. Thus, jumpering and soldering from the original Z1 and Z2 can be avoided.

Now, before putting these ports to use, it's time to turn to the other type of input/output device – the programmable interface adaptor. The previous I/O device costs perhaps $5 to create. The central integrated circuit to the programmable I/O port itself costs about $8, but it offers some extra features and easier wiring.

The INS8255 is a single integrated circuit capable of providing three complete input/output ports. Each port can act as an input or output, and that condition can be changed via programming. This is how it is done: using a decoder similar to that designed above, a 'chip select' is formed.

When the 8255 receives the chip select, it examines its two address line connections. Two address lines can be configured four ways (00, 01, 10, 11), and so can select one of the three I/O



IC	TYPE	+5V	GND
Z1,Z3,Z4	81LS95	20	10
Z2	81LS96	20	10
Z5,Z6	74LS75	5	12
Z7	74LS30	14	7
Z8	74LS02	14	7

Figure 8-5. Elementary interface.



DC Electrical Characteristics

$T_A = 0°C$ to $+70°C$; $V_{CC} = +5\,V \pm 5\%$; $V_{SS} = 0\,V$

Symbol	Parameter	Min	Typ.	Max.	Unit	Test Conditions
V_{IL}	Input Low Voltage			0.8	V	
V_{IH}	Input High Voltage	2.0			V	
V_{OL}	Output Low Voltage			0.4	V	$I_{OL} = 1.6\,mA$
V_{OH}	Output High Voltage	2.4			V	$I_{OH} = -50\,\mu A$ ($-100\,\mu A$ for D B Port)
I_{OH}[1]	Darlington Drive Current		2.0		mA	$V_{OH} = 1.5\,V$, $R_{EXT} = 390\,\Omega$
I_{CC}	Power Supply Current		40		mA	

NOTE:

1 Available on 8 pins only of ports B and C Selected randomly

AC Electrical Characteristics

$T_A = 0°C$ to $+70°C$; $V_{CC} = +5V \pm 5\%$, $V_{SS} = 0V$

Symbol	Parameter	Min.	Typ.	Max.	Unit	Test Conditions
t_{WW}	Pulse Width of $\overline{WR}$	400			ns	
t_{DW}	Time D.B. Stable before $\overline{WR}$	50			ns	
t_{WO}	Time D.B. Stable after $\overline{WR}$	35			ns	
t_{AW}	Time Address Stable before $\overline{WR}$	20			ns	
t_{WA}	Time Address Stable after $\overline{WR}$	20			ns	
t_{CSW}	Chip Select on to $\overline{WR}$	20			ns	
t_{WB}	Delay from $\overline{WR}$ to Output			500	ns	
t_{RP}	Pulse Width of $\overline{RD}$	405			ns	
t_{IR}	$\overline{RD}$ Set-Up Time	10			ns	
t_{HR}	Input Hold Time	100			ns	
t_{RO}	Delay from $\overline{RD} = 0$ to System Bus			295	ns	
t_{RH}	Delay from $\overline{RD} = 1$ to System Bus			150	ns	
t_{HZ}	$\overline{RD} = 0$ to TRI-STATE® of Bus Drivers	10		150	ns	
t_{AR}	Time Address Stable before $\overline{RD}$	50			ns	
t_{CSR}	Time $\overline{CS}$ Stable before $\overline{RD}$		70		ns	
t_{AK}	Width of $\overline{ACK}$ Pulse	500			ns	
t_{ST}	Width of $\overline{STB}$ Pulse	500			ns	
t_{PS}	Set-Up Time for Peripheral	60			ns	
t_{PH}	Hold Time for Peripheral	180			ns	
t_{RA}	Hold Time, Address Bus Trailing Edge to $\overline{RD}$	0			ns	
t_{RC}	Hold Time for $\overline{CS}$ after $\overline{RD} = 1$	5			ns	
t_{AD}	Address Bus Valid to Data Valid			400	ns	
t_{KO}	Time from $\overline{ACK} = 1$ to Output Floating	20		480	ns	
t_{WO}	Time from $\overline{WR} = 1$ to $\overline{OBF} = 0$			650	ns	
t_{AO}	Time from $\overline{ACK} = 0$ to $\overline{OBF} = 1$			450	ns	
t_{SI}	Time from $\overline{STB} = 0$ to IBF			450	ns	
t_{RI}	Time from $\overline{RD} = 1$ to IBF = 0			360	ns	
t_{ACS0}	Address Bus Valid to $\overline{CS}$	0			ns	
t_{ACS1}	Address Change to $\overline{CS}$ OFF	0			ns	

2

Figure 8-7. 8255 configuration (control).



National Semiconductor

November 1980

INS8255 Programmable Peripheral Interface

General Description

The INS8255 is a programmable peripheral interface contained in a standard, 40-pin dual-in-line package. The chip, which is fabricated using N-channel silicon gate technology, functions as a general-purpose parallel input/output interface in National Semiconductor's 8080 microcomputer family. The functional configuration of the INS8255 is programmed by the system software so that normally no external logic is required to interface peripheral devices.

The INS8255 has three basic modes of operation that can be selected by the system software. In the first mode (Mode 0), the INS8255 provides simple input and output operations for three 8-bit ports. Data is simply written to or read from a specified port (Port A, B or C) without the use of "handshaking" signals. In the second mode (Mode 1), the INS8255 enables the transfer of input/output data to or from a specified 8-bit port (Port A or B) in conjunction with strobes or "handshaking" signals. Ports A and B use the lines of Port C in this mode to generate or accept the "handshaking" signals with the peripheral device. In the third mode (Mode 2), the INS8255 enables communications with a peripheral device or structure via one bidirectional 8-bit bus port (Port A). "Handshaking" signals are provided over the lines of Port C in this mode to maintain proper bus flow discipline.

Features

- Outputs Source 1 mA at 1.5 Volts
- 24 Programmable Input/Output Pins
- Direct Bit Set/Reset Capability
- TTL Compatible
- Reduces System Component Count
- MICROBUS™* Compatible

INS8255 MICROBUS Configuration

Typical Diagram of MODE 0 operation. The 8 bit ports A, B, C are defined by the user's program to be either an input or an output from/to the peripherals.

*Trademark, National Semiconductor Corp

© 1980 National Semiconductor Corp

µPG-FL5M110/Printed in U S A

Figure 8-8. 8255 configuration (data).

ports, or – and this is the remarkable part – the 8255's internal *control register*. The 8255 is a smart chip!

When the control register has been selected, the 8255 can be programmed – its ports may be defined as input or output, and other combinations of actions can be selected. The various possibilities are shown in Figure 8-7 and 8-8.

Three Real-Time Clock/Calendars

Telling the time and date is a legitimate concern of computer users, not only for keeping documents in order, but also for observing and controlling experiments. Until recently, the only type of real-time clock available was the one built into the expansion interface, which disk and Level III users could access with the TIME$ command.

The principle of that clock is simple: forty times each second, a pulse is sent from the expansion box to the TRS-80 keyboard unit, where it is applied to the interrupt (INT) line. The computer responds by temporarily setting aside its other processing activities in order to update the seconds, minutes, and hours. When the user asks for the TIME$, the computer checks the area of memory in which this updated information is stored, and sends it to the current display device.

The clocks presented in this section all use the TIME$ function, but avoid certain problems associated with the expansion box TIME$ function. First and foremost, it eliminates the need for the expansion box itself, and the special software to use the 25-millisecond interrupt.

Without disk, this special software must be loaded for every session, reloaded if an inadvertent reset should occur, updated should the computer be turned off, and disabled at every CLOAD and CSAVE. Though convenient in a disk system, this type of approach is more of an annoyance in a Level II system.

There are, however, two distinct advantages to an interrupt-based system for timekeeping: the hardware is simple and cheap to create, and in certain ways the clock pulses generated by the power line are more accurate than crystal-controlled clocks. The power line, because it is linked into a large network of generating systems, must maintain a virtually absolute synchronization over the long term. Short duration lags and leads in the 60-cycle pulses may appear, but the percentage of error over weeks, months, and years is virtually nil.

Time updating from a simple pulse train can be complicated, too, because seconds, minutes and hours, days, weeks, months and years aren't very 'decimal' in their counting. 59 seconds plus one second is one hour and zero seconds. 23 hours and one hour is one day and zero hours. You get the idea. So the software to update a pulse-based calendar needs special math, charts, and tables to keep the time and date in its electronic mind.



Figure 8-9. Interrupt-driven RTC (one second).

```
                 00100 ; ##################################################
                 00110 ; THIS ROUTINE WILL USE THE ONE-SECOND INTERRUPT CREATED
                 00120 ; BY A HARDWARE ADDITION TO DO TIMEKEEPING.  THIS IS
                 00130 ; TRANSPARENT TO BASIC.  NOTE THAT THIS IS NOT INCLUDED
                 00140 ; IN THE SLASH (/) FUNCTIONS CALLED BY THE CUSTOM
                 00150 ; INTERPRETER, AND THUS RETURNS ON ITS OWN TO BASIC ROM.
                 00160 ; ##################################################
                 00170 ;
7EC0             00180         ORG     7EC0H           ; CHANGE TO RELOCATE
                 00190 ;
                 00200 ; ##################################################
                 00210 ; PATCH INTO DOS TIME$ ERROR LOCATION AND CHANGE IT
                 00220 ; ##################################################
                 00230 ;
7EC0 F3          00240 ENTRY   DI                      ; DISABLE ACTIVE INTRPTS.
7EC1 210E7E      00250         LD      HL,START1       ; ENTRY OF TIME$ PROGRAM
7EC4 227741      00260         LD      (4177H),HL      ; REPLACE ?L3 ERROR MSG.
7EC7 21A07F      00270         LD      HL,START2       ; START OF "CMD" PROGRAM
7ECA 227441      00280         LD      (4174H),HL      ; REPLACE ?L3 ERROR MSG.
7ECD 3EC3        00290         LD      A,0C3H          ; GET "JUMP" COMMAND
7ECF 321240      00300         LD      (4012H),A       ; INSERT INT. PATCH POINT
7ED2 214C7F      00310         LD      HL,SERVE        ; INTERRUPT SERV. ROUTINE
7ED5 221340      00320         LD      (4013H),HL      ; INT. PATCH FROM 0038H
7ED8 ED56        00330         IM      1               ; SET INTERRUPT MODE #1
7EDA FB          00340         EI                      ; ENABLE INTERRUPT LINE
7EDB C3CC06      00350         JP      06CCH           ; RETURN TO BASIC "READY"
                 00360 ;
                 00370 ; ##################################################
                 00380 ; PATCH TO INTERCEPT ?L3 ERROR AND CHECK LINE'S SYNTAX
                 00390 ; ##################################################
                 00400 ;
7EDE D7          00410 START1  RST     10H             ; HOUSEKEEP SPACE, ETC.
7EDF E5          00420         PUSH    HL              ; SAVE BASIC LINE POINTER
7EE0 3E11        00430         LD      A,11H           ; LENGTH OF TIME$ ITSELF
7EE2 CD5728      00440         CALL    2857H           ; ROM STRING SPACE SETUP
7EE5 2A0440      00450         LD      HL,(4004H)      ; LOCATION TO FIND TIME$
7EE8 114340      00460         LD      DE,SECOND+2     ; POINT DE TO HOURS POS'N
7EEB CD187F      00470         CALL    DISPLY          ; CONVERT, PLACE IN TIME$
7EEE 363A        00480         LD      (HL),3AH        ; PUT COLON INTO TIME$
7EF0 23          00490         INC     HL              ; BUMP TIME$ POINTER
7EF1 1B          00500         DEC     DE              ; SET DE TO MINS. POS'N
7EF2 CD187F      00510         CALL    DISPLY          ; CONVERT, PLACE IN TIME$
7EF5 363A        00520         LD      (HL),3AH        ; PUT COLON INTO TIME$
7EF7 23          00530         INC     HL              ; BUMP TIME$ POINTER
7EF8 1B          00540         DEC     DE              ; SET DE TO SECS. POS'N
7EF9 CD187F      00550         CALL    DISPLY          ; CONVERT, PLACE IN TIME$
7EFC 3620        00560         LD      (HL),20H        ; PUT SPACE INTO TIME$
7EFE 23          00570         INC     HL              ; BUMP TIME$ POINTER
7EFF 114540      00580         LD      DE,SECOND+4     ; POINT DE TO MON. POS'N
7F02 CD187F      00590         CALL    DISPLY          ; CONVERT, PLACE IN TIME$
7F05 362F        00600         LD      (HL),2FH        ; PUT SLASH INTO TIME$
7F07 23          00610         INC     HL              ; BUMP TIME$ POINTER
7F08 1B          00620         DEC     DE              ; SET DE TO DAYS POS'N
7F09 CD187F      00630         CALL    DISPLY          ; CONVERT, PLACE IN TIME$
7F0C 362F        00640         LD      (HL),2FH        ; PUT SLASH INTO TIME$
7F0E 23          00650         INC     HL              ; BUMP TIME$ POINTER
7F0F 114640      00660         LD      DE,SECOND+5     ; POINT DE TO YEARS POS'N
7F12 CD187F      00670         CALL    DISPLY          ; CONVERT, PLACE IN TIME$
7F15 C38428      00680         JP      2884H           ; FINISH DISPLAY IN ROM
                 00690 ;
                 00700 ; ##################################################
                 00710 ; FIND VALUES IN TIME LOCATIONS AND CONVERT TO ASCII
                 00720 ; ##################################################
                 00730 ;
7F18 1A          00740 DISPLY  LD      A,(DE)          ; GET VALUE INTO ACCUM.
7F19 CD407F      00750         CALL    NIBBLE          ; SEPARATE INTO 4 BITS
7F1C 47          00760         LD      B,A             ; VALUE INTO B FOR TEST
7F1D AF          00770         XOR     A               ; CLEAR A FOR USE IN LOOP
7F1E 04          00780         INC     B               ; DUMMY INCREMENT ...
7F1F 05          00790 LOOP    DEC     B               ; DECREMENT TO TEST FOR 0
7F20 2805        00800         JR      Z,LEAVE         ; UPPER NIBBLE NOW AT 0
7F22 C616        00810         ADD     A,16H           ; A=A+16 ...HEX-DEC CONV.
7F24 27          00820         DAA                     ; DEC.ADJ.: 16 BECOMES 10
7F25 18F8        00830         JR      LOOP            ; LOOP TILL CONV. DONE
7F27 47          00840 LEAVE   LD      B,A             ; SAVE VALUE BACK IN B
7F28 79          00850         LD      A,C             ; GET LOW NIBBLE BACK
7F29 FE0A        00860         CP      0AH             ; IS IT GREATER THAN 10?
7F2B 3804        00870         JR      C,CLEAN         ; NO WORK IF LESS THAN 10
```

Listing 8-2. Interrupt-driven RTC (one second).

Figure 8-9 is a one-pulse-per-second clock that triggers the keyboard unit's interrupt line. Because this clock and the expansion box would compete for that line, this circuit cannot be used in a complete TRS-80 system. But it is a $5 project, and an inexpensive clock add-on for 16K systems alone.

It consists of five integrated circuits. One regulates the voltage, the second (Z2) takes the sine-wave-shaped signals from the 6.3-volt power transformer and converts them to a sharp-edged digital signal. Z3 and Z4 divide the 60 Hz signal into a one-pulse-per-second signal. Finally, Z5 provides the 1 Hz interrupt signal.

When the interrupting signal is accepted by the TRS-80, an 'interrupt acknowledge' signal is sent back to Z5. There is an important purpose to this action; it turns the interrupt signal off. Why? When the computer receives the interrupt, it sets aside its present software activities to 'service' the interrupt. Unless the interrupting flip-flop is reset, the computer, upon completing the interrupt service routine, will think the previous interrupt is a *new* interrupt, and it will keep updating the time and date.

Software to run this clock is presented in Listing 8-2. It patches into the TIME$ and CMD locations, and accepts time and date in the following format (use spaces and punctuation exactly as shown):

```
CMD"09:15:22 05/18/81"
```

The program checks for correct syntax of the set-time command line, but doesn't verify actual times or dates. So, until the clock is next updated, it will display whatever bizarre time and date you may have set it to!

To print the time and date, enter PRINT TIME$. You may use TIME$ just as you would any other strings, including with PRINT, LPRINT, MID$, LEFT$, RIGHT$, concatenation, and other string manipulation. A complete description of these programs is in the supplement to this chapter.

```
7F20 060A      00880          SUB     0AH            ; REOUCE IT TO 0 THRU 5
7F2F C610      00890          AOO     A,10H          ; NOW AOO CARRY BIT
7F31 80        00900 CLEAN    AOO     A,B            ; CREATE A OECIMAL RESULT
7F32 27        00910          OAA                    ; OEC. AOJ. THE TOTAL
7F33 C0407F    00920          CALL    NIBBLE         ; SEPARATE INTO 4 BITS
7F36 C630      00930          AOO     A,30H          ; CONVERT NIBBLE TO ASCII
7F38 77        00940          LO      (HL),A         ; PLACE VALUE INTO TIHE$
7F39 23        00950          INC     HL             ; BUMP TIHE$ PTR. BY ONE
7F3A 79        00960          LO      A,C            ; GET VALUE SAVEO IN C
7F38 C630      00970          ADD     A,30H          ; CONVERT NI8BLE TO ASCII
7F30 77        00980          LO      (HL),A         ; PLACE VALUE INTO TIHE$
7F3E 23        00990          INC     HL             ; BUHP TIME$ PTR. BY ONE
7F3F C9        01000          RET                    ; BACK TO 00 PUNCTUATION
               01010 ;
               01020 ; #######################################################
               01030 ; SU8ROUTINE TO CONVERT A 8YTE ANO SAVE IT AS TWO NIBBLES
               01040 ; #######################################################
               010S0 ;
7F40 FS        01060 NIBBLE   PUSH    AF             ; SAVE THE BYTE BRIEFLY
7F41 E60F      01070          ANO     0FH            ; MASK OUT THE HIGH BITS
7F43 4F        01080          LO      C,A            ; SAVE LOW NIBBLE IN C
7F44 F1        01090          POP     AF             ; GET THE WHOLE BYTE BACK
7F4S 1F        01100          RRA                    ; HOVE THE BYTE RIGHT...
7F46 1F        01110          RRA                    ; ... TWO PLACES ...
7F47 1F        01120          RRA                    ; ... THREE PLACES ...
7F48 1F        01130          RRA                    ; UNTIL MSB BECOHES LSB
7F49 E60F      01140          ANO     0FH            ; HASK OUT THE HIGH BITS
7F48 C8        011S0          RET                    ; NIBBLES NOW IN A & C
               01160 ;
               01170 ; #######################################################
               01180 ; INTERRUPT SERVICE ROUTINE IS ENTEREO AT 1-S CLOCK PULSE
               01190 ; #######################################################
               01200 ;
4041           01210 SECONO   EQU     4041H          ; LOCATION TO STORE TIHE$
7F4C F3        01220 SERVE    OI                     ; OON'T BOTHER ME NOW!
7F40 FS        01230          PUSH    AF             ; SAVE ACCUM. & FLAGS
7F4E E5        01240          PUSH    HL             ; SAVE HL REGISTER PAIR
7F4F 05        01250          PUSH    OE             ; SAVE OE REGISTER PAIR
7FS0 3A4540    01260          LO      A,(SECONO+4)   ; GET CURRENT MONTH VALUE
7FS3 SF        01270          LO      E,A            ; SAVE HONTH VALUE IN E
7F54 1600      01280          LO      0,0            ; LET 0=0. REASON FOLLOWS
7F56 214140    01290          LO      HL,SECONO      ; START AT SECONOS POS'N.
7FS8 34        01300          INC     (HL)           ; SECONOS = SECONOS + 1
7FSA 7E        01310          LO      A,(HL)         ; GET REAOY TO COMPARE
7FS8 FE3C      01320          CP      600            ; IS IT 60 SECONOS?
7F50 3824      01330          JR      C,OUT          ; OONE IF NOT 60 SECONOS
7FSF C0887F    01340          CALL    TICTOC         ; AOVANCE TIME SU8ROUTINE
7F62 FE3C      013S0          CP      600            ; IS IT 60 HINUTES?
7F64 3810      01360          JR      C,OUT          ; OONE IF NOT 60 MINUTES
7F66 C0897F    01370          CALL    TICTOC         ; AOVANCE TIHE SUBROUTINE
7F69 FE18      01380          CP      240            ; IS IT 24 HOURS?
7F88 3816      01390          JR      C,OUT          ; OONE IF NOT 24 HOURS
7F60 C0897F    01400          CALL    TICTOC         ; AOVANCE TIHE SUBROUTINE
7F70 E5        01410          PUSH    HL             ; SAVE REGISTER BRIEFLY
7F71 21937F    01420          LO      HL,LOOKUP      ; OAYS-IN-MONTH TABLE
7F74 19        01430          AOO     HL,OE          ; REHEM8ER OE?  SEE A8OVE
7F7S BE        01440          CP      (HL)           ; IS IT LAST OAY OF HONTH
7F76 E1        01450          POP     HL             ; GET REGISTER 8ACK NOW
7F77 380A      01460          JR      C,OUT          ; OONE IF NOT LAST OAY
7F79 C08F7F    01470          CALL    TIKTOK         ; AOVANCE OATE SUBROUTINE
7F7C FE00      01480          CP      130            ; IS IT 12 MONTHS?
7F7E 3803      01490          JR      C,OUT          ; OONE IF NOT 12 HONTHS
7F80 C08F7F    01500          CALL    TIKTDK         ; AOVANCE OATE SU8ROUTINE
7F83 01        01510 OUT      POP     OE             ; RESTORE OE REGISTERS
7F84 E1        01S20          POP     HL             ; RESTORE HL REGISTERS
7F8S F1        01530          POP     AF             ; RESTORE ACCUM. & FLAGS
7F86 FB        01540          EI                     ; GET CLOCK TICKING AGAIN
7F87 E040      01SS0          RETI                   ; BACK FROH THE INTERRUPT
               01560 ;
               01570 ; #######################################################
               01580 ; AOVANCE TIME/OATE & RETRIEVE NEW VALUE SU8ROUTINES
               01S90 ; #######################################################
               01600 ;
7F88 AF        01610 TICTOC   XOR     A              ; CLEAR ACCUM. TO ZERO
7FBA 77        01620 FINISH   LO      (HL),A         ; HRS, HIN, OR SEC = 0
7FBB 23        01630          INC     HL             ; MOVE TO NEXT POSITION
7FBC 34        01640          INC     (HL)           ; TIME = TIHE + 1 (CARRY)
7FB0 7E        016S0          LO      A,(HL)         ; SET UP TO TEST VALUE
7FBE C9        01660          RET                    ; BACK TO COHPLETE TEST
7F8F 3E01      D1670 TIKTDK   LO      A,1            ; A = 1 FOR DAY OR MONTH
7F91 18F7      D1680          JR      FINISH         ; DTHER RDUTINE DDES WDRK
               D1690 ;
               D1700 ; #######################################################
               D1710 ; THIS IS THE OAYS-IN-A-MDNTH LDDKUP TABLE - NO LEAP YEAR
               01720 ; #######################################################
               01730 ;
7F93 00        01740 LOOKUP   OEF8    00             ; OUHMY 8YTE, 8UT THEN...
7F94 20        01750          OEF8    320            ; THIRTY OAYS HATH
7F95 10        01760          OEF8    29D            ;        SEPTEH8ER,
7F96 20        D177D          DEF8    32D            ; APRIL, JUNE, ANO
7F97 1F        01780          OEF8    31D            ;        NDVEH8ER:
7F88 20        D1790          OEF8    32D            ; ALL THE REST HAVE
7F98 1F        01800          OEF8    310            ;        THIRTY-DNE,
7F9A 20        D181D          DEF8    32D            ; 'CEPT FE8RUARY, ANO
7F98 2D        01820          OEF8    32D            ;        THERE'S 8EEN ALL
7F9C 1F        01830          OEF8    310            ;        TOO MUCH TALK
7F9D 20        D184D          OEF8    320            ;        A8DUT THE HYRIAO
7F9E 1F        D185D          DEF8    310            ;        PRETIOIGITATIONS
7F8F 2D        D1860          OEF8    32D            ;        USING THAT MONTH
               01870 ;
               D188D ; #######################################################
               D1890 ; "CMD" PATCH CHECKS PARAHETERS, SYNTAX, ANO SETS TIHE
               01900 ; #######################################################
```

The second and third clocks for the TRS-80 are similar in concept, but different in execution. That difference has only to do with manufacturing quality of the specifiedclock-calendar chip, the MSM5832 (available from *Digi-Key Corporation* and *Hobbyworld Electronics* — see Appendix). This clock-calendar has been designed to interface with microcomputers instead of the familiar red LED readouts. A 32.768 KHz crystal is required for its operation (also sold by the above suppliers).

It provides time in hours (12 or 24), minutes and seconds; month, day, year (leap year as well) and day of the week. It has timing signal outputs for interrupt use, which will not be used in this circuit. A battery backup will keep it in time when the TRS-80 is turned off. Two complete circuits are presented in Figure 8-10 and Figure 8-11

Why two circuits? Because the MSM5832 is a relatively slow electronic circuit, and, depending on the quality of the production run used for the chip you purchase, it may or may not be fast enough to interface directly with your TRS-80!

For a slower chip, you will need to use intermediate logic to latch onto the clock information in *its* own good time, and feed it to the TRS-80 as the computer's signals speed past. For this job, the INS8255 (as recommended by *OKI*, manufacturers of the MSM5832) is used. As noted above, the 8255 is a peripheral interface adapter, which sets up a private, latched bus between itself and the clock chip. Clock information is sent via Port A. The clock chip's address lines are selected through Port B, and other timekeeping features are selected through Port C.

The 8255 will be placed in the TRS-80 memory map at **37D0** through **37D2**, below the cassette/ disk latches, and above the Level II operating system. Z1 and Z2 in Figure 8- 10 decode that address group, and pins 8 and 9 of the 8255 (Z3) are used to select the specific address among those.

The last circuit, Figure 8- 11, places the MSM5832 directly into the TRS-80 memory map without use of the 8255 interface chip. Because the MSM5832 has four address lines, it is decoded differently from the 8255, but occupies the same general area (**37D0** to **37DF**).

Wiring all these clocks is a simple procedure because there are few parts. All can be soldered or wire wrapped, though sockets are virtually essential for the 8255 and MSM5832 chips. The latter is a static-sensitive chip, and should be



Figure 8-10. MSM5832 with 8255 port chip RTC.



IC	TYPE	+5V	GND
Z1	74LS30	14	7
Z2	74LS260	14	7
Z3	74LS04	14	7
Z4	MSM5832	1	13

Figure 8-11. MSM5832 direct to bus RTC.



REF. OCT. '80
80 MICROCOMP
P. 23

```
                D191D ;
7FAD 11434D     0192D START2  LD      DE,SECDND+2       ; PDINT DE TD HOURS PDS'N
7FA3 7E         D193D         LO      A,(HL)            ; CHAR AT LINE PDINTER
7FA4 FE22       D1940         CP      22H               ; IS IT A QUDTE MARK?
7FA6 204A       01950         JR      NZ,DTHERS         ; CHECK FDR CMDT OR CMOR
7FAB CD0B7F     D196D         CALL    CDNVRT            ; READ/CDNV. ASCII HR.
7FAB FE3A       0197D         CP      3AH               : IS IT A CDLDN?
7FA0 C29719     019BD SYNERR  JP      NZ,1997H          : GO TO ?SN ERROR ROUTINE
7FBD CDDB7F     D1990         CALL    CDNVRT            ; REAO/CONV. ASCII MIN.
7FB3 FE3A       D20DD         CP      3AH               ; IS IT A CDLDN?
7FB5 20F6       D201D         JR      NZ,SYNERR         ; SYNTAX ERRDR IF NDT :
7FB7 C00B7F     D2020         CALL    CONVRT            : REAO/CDNV. ASCII SEC.
7FBA FE20       D2D3D         CP      2DH               ; IS IT A SPACE?
7FBC 20EF       02040         JR      NZ,SYNERR         : SYNTAX ERROR IF NOT
7FBE 11454D     D2D5D         LD      DE,SECDND+4       ; PDINT DE TD MDNTH PDS'N
7FC1 CDDB7F     D2D6D         CALL    CDNVRT            ; READ/CDNV. ASCII MDN.
7FC4 FE2F       02070         CP      2FH               ; IS IT A SLASH?
7FC6 20E5       D208D         JR      NZ,SYNERR         ; SYNTAX ERROR IF NOT /
7FCB C00B7F     02D90         CALL    CDNVRT            ; READ/CDNV. ASCII DAY
7FCB FE2F       0210D         CP      2FH               ; IS IT A SLASH?
7FC0 200E       D2110         JR      NZ,SYNERR         : SYNTAX ERRDR IF NOT /
7FCF 11464D     D2120         LD      DE,SECDND+5       : PDINT DE TD YEARS PDS'N
7FD2 CDDB7F     D213D         CALL    CDNVRT            : READ/CDNV. ASCII YEAR
7FD5 FE22       D214D         CP      22H               ; IS IT A QUDTE MARK?
7FD7 2DD1       D215D         JR      NZ,EXIT           ; DDNE IF A QUDTE MARK
7F09 23         D2160         INC     HL                ; BUMP PDINTER PAST QUOTE
7FDA C9         02170 EXIT    RET                       : BACK TD BASIC
                D21BD :
                D219D ; ##################################################
                D22DD ; CDNVERT ASCII TD HEX AND PDKE INTO CLDCK TIME$ LDCATIDN
                D221D ; ##################################################
                D2220 :
7F0B 23         D2230 CDNVRT  INC     HL                : BUMP LINE PTR. BY DNE
7FDC 7E         D224D         LO      A,(HL)            ; GET CHARACTER IN LINE
7FD0 0630       D225D         SUB     3DH               ; CONVERT ASCII TO HEX
7FDF 3C         0226D         INC     A                 ; MAKE A BE AT LEAST 1
7FED 47         D227D         LD      B.A               : SAVE THAT VALUE IN B
7FE1 3EF6       D22BD         LD      A,0F6H            ; A= 1DD HEX MINUS 10 DEC
7FE3 C6DA       D229D MULT    ADD     A,DAH             ; MULTIPLY BY AOOITION
7FE5 10FC       D23DD         DJNZ    MULT              ; I.E., A = B TIMES 10
7FE7 47         D231D         LO      B,A               ; SAVE THAT VALUE IN B
7FEB 23         D2320         INC     HL                : BUMP LINE PTR. BY DNE
7FE9 7E         D233D         LD      A,(HL]            ; GET CHARACTER IN LINE
7FEA D63D       D234D         SUB     3DH               ; CDNVERT ASCII TD HEX
7FEC BD         D235D         ADD     A,B               ; A = (B * 1D) + A
7FE0 12         02360         LO      (OE].A            ; TIME IS SET, PUT IN OE
7FEE 1B         02370         OEC     DE                : BUMP OE TD NEXT PLACE
7FEF 23         02380         INC     HL                ; BUMP LINE PTR. BY ONE
7FF0 7E         02390         LO      A,(HL)            : GET CHARACTER IN LINE
7FF1 C9         D240D         RET                       : RETURN FDR FURTHER TEST
7FF2 FE52       0241D OTHERS  CP      52H               ; IS IT CMDR (CLDCK DFF)?
7FF4 2DD3       D2420         JR      NZ.NEXT           ; NDPE, TRY FDR CMOT
7FF6 F3         0243D         OI                        : TURN DFF THE CLDCK
7FF7 23         D244D         INC     HL                ; BUMP LINE PTR. BY ONE
7FFB C9         D245D         RET                       ; BACK TO BASIC PRDGRAM
7FF9 FE54       D246D NEXT    CP      54H               ; IS IT CMOT (CLDCK ON)?
7FFB 2D80       0247D         JR      NZ,SYNERR         ; NDPE. MUST BE ERRDR
7FFD FB         D24BD         EI                        ; TURN DN THE CLDCK
7FFE 23         0249D         INC     HL                ; BUMP LINE PTR. BY DNE
7FFF C9         D25DD         RET                       ; BACK TD BASIC PRDGRAM
                D251D :
                D252D ; ##################################################
7ECD            D253D         END     ENTRY
ODDDD TDTAL ERRDRS
```



MSM5832 clock board contains only 4 integrated circuits, some resistors, and a crystal. Power supply is external, and includes rechargeable batteries for backup.

handled carefully (see Chapter 4 for details). Use wires as short as possible in the area where the crystal is located, and triple-check all connections before applying the power. The MSM5832 is a delicate circuit, and at $9 a shot, worth the trouble to check your work. The circuits are connected to the computer via standard edge-card connectors.

Edge Card Connectors: What's Up?

The 40 pin bus of the TRS-80 is a non-standard animal to begin with, and is not particularly logical in its pin assignments. What makes things more frustrating than merely locating the position of the pins, is trying to figure out which way is up.

The edge card of the TRS-80, when viewed from its edge, has pin 1 located at the top left – a logical place. Naturally, because the CPU and expansion unit face each other, the entry to the expansion interface is the mirror image of this design. Yet its top left pin is also called 'pin 1'! So pin 1 (TRS-80) leads to pin 39 (expansion box).

It gets stickier than this, however. When you are building projects, it's likely you won't be doing it with professionally etched edge cards, but rather with headers and wires and cables of various kinds which you assemble yourself. So when you get your 40 pin edge connector to hook onto the TRS-80, notice –

– the numbering of the pins on the connector, which, if industry standards are used, has pin 1 marked on the opposite side, like the expansion box.

– the outside wire, which may either lead to pin 1 or pin 2, depending on the manufacturer.

– the orientation of the connecting header, which may reverse the process one more time.

To be absolutely sure, use a meter to determine the path all the way from the computer edge card to the final connector when it is mounted on the project. It's best to mount the header or connector first, identify its pins with a meter, mark them and *then* begin work wire wrapping or soldering.

To use the MSM5832 clock with the 8255 interface adaptor, you will need to refer to both chips' programming information. Figure 8-(?), earlier in this chapter, contains the 8255 programming parameters. Figure 8-(?) shows how the clock's registers are set up.

At first, this process may appear confusing. What is being done? Three semi-intelligent electronic devices are being taught to talk to one another. The TRS-80 knows it wants to read and write to memory. The 8255 is that memory. But the 8255 has a mind of its own, and that mind can only be controlled by selecting its control register, telling it what purpose each of its three ports is to serve, and then reading and writing those ports. Finally, the MSM5832 also has a mind of its own. It will neither report nor accept the time until it is told what aspect of the time is needed, and that too is done via a control register.

Figure 8-(?) is a flow chart which describes the process, and Listing 8-(?) is a BASIC program which fairly well describes the steps needed to access the MSM5832 chip, 'way down the chain.

```
10 CLS : CLEAR 150 : REM * CRUOE 8UT SERVICEA8LE CLOCK PROGRAM
20 FOR X = 0 TO 6 : REAO OW$(X) : NEXT : REM * ARRAY OF OAYS
30 OATA M O N O A Y,T U E S O A Y,W E O N E S O A Y
40 OATA T H U R S O A Y,F R I O A Y,S A T U R O A Y,S U N O A Y
50 PRINT "ENTER HOURS ANO MINUTES, PLUS AM OR PM INOICATION."
60 INPUT "USE FORMAT 0,3,5,8,P (= 3:58 P.M.)";H0,H1,M0,M1,P$
70 INPUT "12-HOUR OR 24-HOUR CLOCK (ANSWER 12 OR 24)";C$
80 IF P$ = "P"  THEN H0 = H0 + 4 : REM * 8IT 3 INOICATES P.M.
90 IF C$ = "24" THEN H0 = H0 + 8 : REM * 8IT 4 FOR 24 HOURS
100 PRINT "OAY OF THE WEEK (ENTER 1 TO 7.  MONOAY IS 1.)"
110 INPUT OW : OW = OW - 1   : REM * CLOCK'S MONOAY IS ZERO
120 PRINT "MONTH, OAY ANO YEAR IN FORMAT 0,3,3,1,8,0 (3/31/80)"
130 INPUT M2,M3,00,01,Y0,Y1 : REM * LEAP YEAR TEST IN NEXT LINE
140 LY = Y0 + 10 * Y1 : IF LY/4 = FIX (LY/4) THEN 00 = 00 + 4
150 POKE 14291,128 : REM * SET UP 8255 CHIP PORTS
160 POKE 14290,80  : REM * SET UP CLOCK TO REAO TIME ANO OATE
170 Q = 14289      : REM * THIS IS CLOCK AOORESS REGISTER
180 POKE Q,2  : POKE Q-1,M1 : POKE Q,3  : POKE Q-1,M0
190 POKE Q,4  : POKE Q-1,H1 : POKE Q,5  : POKE Q-1,H0
200 POKE Q,6  : POKE Q-1,OW : POKE Q,7  : POKE Q-1,01
210 POKE Q,8  : POKE Q-1,00 : POKE Q,9  : POKE Q-1,M3
220 POKE Q,10 : POKE Q-1,M2 : POKE Q,11 : POKE Q-1,Y1
230 POKE Q,12 : POKE Q-1,Y0 : REM * TIME ANO OATE INFO SET
240 POKE 14291,144 : CLS : REM * OISPLAY SU8ROUTINE FOLLOWS
250 PRINT @ 0, ""; : REM * OISPLAY IS ON TOP LINE OF SCREEN
260 POKE 14290,32  : REM * SET UP CLOCK TO WRITE TIME AND DATE
270 POKE Q,6  : PRINT OW$ (PEEK (Q-1) AND 15)",  ";
280 POKE Q,10 : PRINT PEEK (Q-1) ANO 15; CHR$(8);
290 POKE Q,9  : PRINT PEEK (Q-1) ANO 15: "/";
300 POKE Q,8  : PRINT PEEK (Q-1) ANO 3;  CHR$(8);
310 POKE Q,7  : PRINT PEEK (Q-1) ANO 15; "/";
320 POKE Q,12 : PRINT PEEK (Q-1) ANO 15: CHR$(8);
330 POKE Q,11 : PRINT PEEK (Q-1) ANO 15; " -- ";
340 POKE Q,5  : PRINT PEEK (Q-1) ANO 3;  CHR$(8);
350 POKE Q,4  : PRINT PEEK (Q-1) ANO 15: ":";
360 POKE Q,3  : PRINT PEEK (Q-1) ANO 15: CHR$(8);
370 POKE Q,2  : PRINT PEEK (Q-1) ANO 15; ":";
380 POKE Q,1  : PRINT PEEK (Q-1) ANO 15; CHR$(8);
390 POKE Q,0  : PRINT PEEK (Q-1) ANO 15;
400 POKE Q,5  : IF (PEEK (Q-1) ANO 4) = 0 THEN PRINT " A. M.";
410           : IF (PEEK (Q-1) ANO 4) = 4 THEN PRINT " P. M.";
420 IF (PEEK(14312) ANO 128) = 0 THEN 500 ELSE 250
430 REM       : THIS ROUTINE IS MUCH LONGER THAN IT NEEO 8E,
440 REM       : 8UT IS SET UP FOR CLARITY, NOT EFFICIENT USE
450 REM       : OF MEMORY.  IT IS EASIER TO USE THE MACHINE
460 REM       : LANGUAGE SUBROUTINE FOR THIS CLOCK CIRCUIT.
500 A$ = "" : FOR X = 15360 TO 15424 : A$ = A$ + CHR$(PEEK(X) )
510 NEXT : LPRINT A$ : GOTO 250
```

Listing 8-3. BASIC program for MSM5832/8255.

```
                00100 ; ##################################################
                00110 ; MACHINE LANGUAGE CLOCK PROGRAM FOR MSM5832 CLOCK 80ARO
                00120 : ATTACHED TO THE TRS-8D AT ADDRESS 14288 TO 14300, USING
                00130 ; THE "TIME$" FUNCTION.  THIS ROUTINE IS TRANSPARENT TO
                00140 ; 8UT IS NOT CALLED 8Y THE CUSTOM INTERPRETER.  HENCE,
                001S0 : IT OPERATES INOEPENDENTLY FROM THE INTERPRETER PATCH.
                00160 ; ##################################################
                00170 ;
7ED0            00180          ORG     7ED0H               ; CHANGE TO RELOCATE
                00190 ;
                00200 ; ##################################################
                00210 ; PATCH INTO DOS TIME$ ERROR LOCATION AND CHANGE IT
                00220 ; ##################################################
                00230 :
7ED0 210F7E     00240 ENTRY    LD      HL.START1           : START OF TIME$ PROGRAM
7E03 227741     002S0          LD      (4177H).HL          ; PATCH TIME$ ?L3 ERROR
7E06 218F7E     00260          LD      HL,START2           ; START OF "CMD" PROGRAM
7E09 227441     00270          LD      (4174H).HL          ; PATCH CMD ?L3 ERROR
7E0C C3CC06     00280          JP      06CCH               : 8ACK TO A 8ASIC "READY"
                00290 ;
                00300 ; ##################################################
                00310 : THIS IS THE 8EGINNING OF TH "TIME$" PATCH TO READ TIME.
                00320 ; ROUTINE INTERCEPTS ?L3 ERROR AND CHECKS LINE'S SYNTAX.
                00330 : ##################################################
                00340 :
7E0F D7         003S0 START1   RST     10H                 ; 8ASIC HOUSEKEEPING
7E10 ES         00360          PUSH    HL                  ; SAVE 8ASIC LINE POINTER
7E11 3E18       00370          LD      A,18H               ; LENGTH OF TIME$
7E13 CDS728     00380          CALL    28S7H               ; ROM STRING SPACE SETUP
                00390 ;
                00400 ; ##################################################
                00410 : SET UP RAM SPACE AND GET CLOCK CHIP READY TO READ TIME
                00420 ; ##################################################
                00430 :
7E16 2A040      00440          LD      HL,(4004H)          : LOCATION TO STORE TIME$
7E19 FD210037   004S0          LD      IY,3700H            ; CLOCK MEMORY ADDRESS
7E1D FD36D390   00460          LD      (IY+3),90H          : SET UP 82S5 CHIP PORTS
7E21 CD6A7F     00470          CALL    DELAY               ; WAIT FOR SLOW MSMS832
7E24 FD36D220   00480          LD      (IY+2).20H          ; SET UP CLOCK TO READ
7E28 CD6A7F     00490          CALL    DELAY               : WAIT FOR SLOW MSMS832
                00S00 ;
                00S10 ; ##################################################
                00S20 ; CLOCK IS READY TO READ ... NOW READ AND CREATE STRING.
                00S30 ; DAY OF THE WEEK IS ALPHA8ETIC AND WILL 8E DONE FIRST.
                00S40 ; ##################################################
                00SS0 ;
```

Listing 8-4. Assembly program for MSM5832/8255.

Eliminating the 8255 by using the second circuit means only one set of electronic parts must be taught to speak to each other. The TRS-80 can probe right into the MSM5832 control register to select which aspect of the time and date it wishes.

Each of the machine language programs presented in Listings 8-(?) and 8-(?) use the TIME$ and CMD commands to set and recall the time. To set the time and date, enter :

```
CMO"MON 03/14/49 02:29 PM"
```

Notice that this differs from the interrupt driven clock (Listing 8-(?)) in that the day of the week and morning – afternoon indicators must be given. Remember to use the punctuation and spacing exactly as printed here. As with the interrupt clock, PRINT TIME$ returns the time and date, and this TIME$ can be used and manipulated just as any other string.

A complete description of these programs is given in the Supplement to this Chapter.

```
7E28 F0360106 00560         LD      (IY+1),6        ; POINT TO DAY OF WEEK
7E2F C06A7F   00570         CALL    DELAY           ; WAIT FOR SLOW MSM5832
7E32 F07E00   00580         LD      A,(IY+0)        ; GET DUMMY VALUE INTO A
7E35 C06A7F   00590         CALL    DELAY           ; WAIT FOR SLOW CHIP (!)
7E38 F07E00   00600         LD      A,(IY+0)        ; GET DAY OF WEEK VALUE
7E38 E607     00610         AND     07H             ; MASK OFF UNUSED BITS
7E30 11757F   00620         LD      DE,TABLE        ; POINT DE TO DAY TABLE
7E40 3C       00630         INC     A               ; IT MUST BE AT LEAST 1
7E41 30       00640 LOOP1   DEC     A               ; IS ACCUMULATOR ZERO?
7E42 2807     00650         JR      Z,XLOOP         ; GO OUT OF TABLE LOOP
7E44 0603     00660         LD      B,3             ; NUMBER OF CHARS PER DAY
7E46 13       00670 LOOP2   INC     DE              ; MOVE PAST EACH CHAR
7E47 10F0     00680         DJNZ    LOOP2           ; DO IT TILL AT NEXT DAY
7E49 18F6     00690         JR      LOOP1           ; CHECK FOR NEXT DAY
              00700 ;
              00710 ; ##################################################
              00720 ; VALUE FOR DAY IS FOUND ... NOW TURN IT INTO LETTERS
              00730 ; ##################################################
              00740 ;
7E48 0E03     00750 XLOOP   LD      B,3             ; NUMBER OF CHARS TO GET
7E40 1A       00760 YLOOP   LD      A,(DE)          ; CHARACTER TO TRANSFER
7E4E 77       00770         LD      (HL),A          ; XFER DAY NAME TO TIME$
7E4F 23       00780         INC     HL              ; NEXT LOCATION IN TIME$
7E50 13       00790         INC     DE              ; NEXT LOCATION IN TABLE
7E51 10FA     00800         DJNZ    YLOOP           ; LOOP BACK FOR NEXT CHAR
7E53 3620     00810         LD      (HL),20H        ; PUT SPACE AFTER DAY
7E55 23       00820         INC     HL              ; BUMP TIME BUFFER AGAIN
              00830 ;
              00840 ; ##################################################
              00850 ; DAY OF WEEK IS DONE ... NOW GET MONTH, DAY, AND YEAR
              00860 ; ##################################################
              00870 ;
7E56 1E30     00880         LD      E,30H           ; HEX TO ASCII DIFFERENCE
7E58 1608     00890         LD      D,11            ; MONTH HI PORT + 1
7E5A 062F     00900         LD      B,2FH           ; SLASH ("/") CHARACTER
7E5C 0E0F     00910         LD      C,0FH           ; MASK UNUSED PORT BITS
7E5E C0557F   00920         CALL    FILLER          ; GET MONTH HIGH VALUE
7E61 C0557F   00930         CALL    FILLER          ; GET MONTH LOW VALUE
7E64 70       00940         LD      (HL),B          ; LOAD SLASH INTO TIME$
7E65 23       00950         INC     HL              ; BUMP TIME BUFFER BY ONE
7E66 0E03     00960         LD      C,3             ; MASK UNUSED CLOCK BITS
7E68 C0557F   00970         CALL    FILLER          ; GET DAY HIGH VALUE
7E68 0E0F     00980         LD      C,0FH           ; MASK UNUSED CLOCK BITS
7E60 C0557F   00990         CALL    FILLER          ; GET DAY LOW VALUE
7E70 70       01000         LD      (HL),B          ; PUT SLASH INTO TIME$
7E71 23       01010         INC     HL              ; BUMP TIME BUFFER BY ONE
7E72 16DD     01020         LD      D,13            ; YEAR HIGH VALUE + 1
7E74 C0557F   01030         CALL    FILLER          ; GET YEAR HIGH VALUE
7E77 C0557F   01040         CALL    FILLER          ; GET YEAR LOW VALUE
7E7A 3620     01050         LD      (HL),20H        ; VALUE FOR A SPACE
7E7C 23       01060         INC     HL              ; BUMP TIME BUFFER BY ONE
              01070 ;
              01080 ; ##################################################
              01090 ; MONTH, DAY, YEAR DONE - NOW GET HOURS, MINUTES, SECONDS
              01100 ; ##################################################
              01110 ;
7E70 1605     01120         LD      D,5             ; HOURS HIGH VALUE
7E7F F07201   01130         LD      (IY+1),D        ; SET UP CLOCK CHIP PORT
7E82 C06A7F   01140         CALL    DELAY           ; DELAY FOR 8255 CHIP
7E85 F07E00   01150         LD      A,(IY+0)        ; DUMMY VALUE INTO ACC.
7E88 C06A7F   01160         CALL    DELAY           ; DELAY AGAIN FOR CHIP!
7E88 F07E00   01170         LD      A,(IY+0)        ; GET HOURS HIGH VALUE
7E8E F5       01180         PUSH    AF              ; SAVE THIS FOR AM/PM
7E8F 14       01190         INC     D               ; ACCOMMODATE SUBROUTINE
7E90 0E03     01200         LD      C,3             ; MASK UNUSED CLOCK BITS
7E92 C0557F   01210         CALL    FILLER          ; GET HOURS HIGH VALUE
7E95 0E0F     01220         LD      C,0FH           ; MASK UNUSED CLOCK BITS
7E97 C0557F   01230         CALL    FILLER          ; GET HOURS LOW VALUE
7E9A 363A     01240         LD      (HL),3AH        ; PUT A COLON IN TIME$
7E9C 23       01250         INC     HL              ; BUMP THE STRING ALONG
7E90 0602     01260         LD      B,2             ; NUMBER MINUTE/SEC LOOPS
7E9F C0557F   01270 MINSEC  CALL    FILLER          ; GET,CONVERT,SAVE VALUE
7EA2 C0557F   01280         CALL    FILLER          ; GET,CONVERT,SAVE VALUE
7EA5 363A     01290         LD      (HL),3AH        ; VALUE FOR A COLON
7EA7 23       01300         INC     HL              ; BUMP TIME BUFFER BY ONE
7EA8 10F5     01310         DJNZ    MINSEC          ; GO BACK FOR MIN/SEC
7EAA 28       01320         DEC     HL              ; BACK UP TO LAST COLON
7EAB 3620     01330         LD      (HL),20H        ; CHANGE TO STRING END
              01340 ;
              01350 ; ##################################################
              01360 ; HOURS, MINUTES, SECONDS ARE DONE ... NOW FIGURE AM/PM
              01370 ; ##################################################
              01380 ;
7EA0 23       01390         INC     HL              ; BUMP TIME BUFFER BY ONE
7EAE F1       01400         POP     AF              ; GET BACK HOUR HI VALUE
7EAF CB57     01410         BIT     2,A             ; CHECK AM/PM INDICATOR
7E81 2804     01420         JR      Z,MORNNG        ; MORNING IF BIT 2 = 0
7E83 3650     01430         LD      (HL),50H        ; PUT LETTER "P" IN PLACE
7E85 1802     01440         JR      NEXT            ; JUMP PAST LETTER A
7E87 3641     01450 MORNNG  LD      (HL),41H        ; PUT LETTER "A" IN PLACE
7E89 23       01460 NEXT    INC     HL              ; BUMP TIME BUFFER BY ONE
7E8A 3640     01470         LD      (HL),40H        ; PUT LETTER "M" IN PLACE
7EBC C3842B   01480         JP      2884H           ; BACK TO BASIC ACTIVITY
              01490 ;
              01500 ; ##################################################
              01510 ; THIS IS THE BEGINNING OF THE "CMD" PATCH TO SET TIME
              01520 ; CHECK FOR TIME SETTING PARAMETERS AND SYNTAX
              01530 ; ##################################################
              01540 ;
7E8F 7E       01550 START2  LD      A,(HL)          ; CHAR AT LINE POINTER
7EC0 FE22     01560         CP      22H             ; IS IT A QUOTE MARK?
7EC2 C29719   01570         JP      NZ,1997H        ; ?SN ERROR IF NO QUOTE
```

Bank Selecting Machine Language in ROM

Warning: Before you begin construction of anything in this section, read the rest of the chapter! You might want to construct the complete ROM/RAM bank select system.

Seriously, one of the most exciting aspects of the TRS-80 is its blank area in the memory map. This has been partially used in this chapter to install a real time clock. It can also be used to select machine language programs or data burned into ROMs. At the time of this book's publication, the cost of a 2K erasable, programmable, read only memory (EPROM) is less than $8. A year earlier, when these memories were $27 or more, this project would not have been practical. Now it is.

In quantities of 100, these EPROMs are less than $5, which means, by using this project, direct access to over 200K of memory is possible for less than $500. But one or two of such memories are just as valuable.

But first, what is an EPROM? How is it used? An EPROM, as its name suggests, is a memory which the user can program and reprogram as necessary. It is programmed with an EPROM programmer, and erased with ultraviolet light. It maintains its contents with the power off, just like the Level II ROMs themselves. It is used in a way even simpler than the way the TRS-80's RAM memory is used, and in this is found its great advantage: it needs but power, address and data lines to make its data available to the CPU.

By using a decoded output port, one of a bank of these memories may be selected for use. Here is an example; I might want to load a special machine language monitor program. I know that program is located in ROM #26 in my ROM bank. I can command something like –

```
OUT 31,26    <ENTER>
SYSTEM       <ENTER>
/12288       <ENTER>
```

– and my program will be loaded and active. Only the time for three entries has been spent; not even the time of the disk access. And, beyond that, no RAM memory need be used!

A complete circuit for a ROM select bank is presented in Figure 8-14. Each of the lines marked 'to ROM' will select one of 256 possible ROMs!



Figure 8-14. Bank-selected ROMs.



Figure 8-15. Bank-selected ROM/RAM.

```
7ECS 23        01SB0          INC    HL              ; BUMP LINE PTR. BY ONE
7EC6 ES        01590          PUSH   HL              ; SAVE THE LINE POINTER
7EC7 11757F    01600          LO     OE,TABLE        ; GET TABLE OF OAY NAHES
7ECA 0E00      01610          LO     C,0             ; THIS WILL BE COUNTER
7ECC 0603      01620 OYLOOP   LO     B,3             ; NUMBER OF CHARS IN DAY
7ECE E1        01630          POP    HL              ; GET LINE POINTER BACK
7ECF ES        01640          PUSH   HL              ; SAVE AGAIN FOR LOOP USE
7E00 1A        016S0 FINOIT   LD     A,(OE)          ; GET 1ST CHAR DF STRING
7E01 A7        0166D          ANO    A               ; EASY WAY TO SET A FLAG
7E02 2B09      01670          JR     Z,ERROR1        ; VALUE = 0 ... ?SN ERROR
7E04 BE        016B0          CP     (HL)            ; CHECK IT AGAINST TABLE
7EDS 2B0A      01690          JR     Z,GOTONE        ; GET REAOY FOR NEXT CHAR
7E07 13        01700 LOOP4    INC    OE              ; RUN PAST VALUES FOR OAY
7E0B 10F0      0171D          OJNZ   LOOP4           ; BY RUNNING B TO ZERO
7E0A 0C        01720          INC    C               ; NEXT OAY - BUHP COUNTER
7E08 1BEF      01730          JR     OYLODP          ; BACK TO NEXT OAY LODP
7E00 E1        01740 ERROR1   PDP    HL              ; CLEAR STACK OF HL REG.
7E0E C39719    D17S0 ERROR2   JP     1997H           ; GO TO ?SN ERROR HESSAGE
7EE1 23        01760 GOTONE   INC    HL              ; GET NEXT CHAR FROH LINE
7EE2 13        0177D          INC    OE              ; BUMP TABLE VALUE ALONG
7EE3 10EB      017B0          OJNZ   FINOIT          ; KEEP GOING TILL OONE
               01790 ;
               01BD0 ; ##################################################
               01B10 ; NUHERICAL VALUE FOR OAY IS IN C - PUT IT IN MSMSB32
               01B20 ; ##################################################
               0183D ;
7EE5 F1        D184D          POP    AF              ; CLEAR STACK DF HL VALUE
7EE6 F036D3B0  01BSD          LD     (IY+3),8DH      ; SET UP 8255 TD WRITE
7EEA C06A7F    01860          CALL   OELAY           ; THAT #&!*% SLOW M5M5832
7EED FD36D2S0  D1B70          LD     (IY+2),5DH      ; CLOCK CHIP WRITE VALUE
7EF1 CD6A7F    01B8D          CALL   OELAY           ; HOW SLOW IS IT?!?
7EF4 79        01B90          LO     A,C             ; GET OAY OF WEEK VALUE
7EFS F0360106  01900          LO     (IY+1),6        ; READY TO WRITE OAY
7EF9 C06A7F    D1910          CALL   OELAY           ; WAIT (YAWN) TD WRITE
7EFC F077D0    D1920          LD     (IY+0),A        ; WRITE OAY TO CLOCK
               01930 ;
               0194D ; ##################################################
               019S0 ; DAY IS WRITTEN - FINO HDNTH, OAY, YEAR ANO WRITE THEH
               01960 ; ##################################################
               01970 ;
7EFF 1608      D19BD          LO     D,11            ; VALUE FOR HDNTH + 1
7F01 CD377F    0199D          CALL   TIHSET          ; WRITE HDNTH TO CLOCK
7F04 CD377F    02000          CALL   TIMSET          ; WRITE OAY TO CLOCK
7F07 16DD      02010          LO     0,13            ; VALUE FDR YEAR +1
7FD9 CD377F    02D20          CALL   TIHSET          ; WRITE YEAR TO CLOCK
7FDC 16D5      02D3D          LD     D,5             ; SET TO HOURS HIGH VALUE
7F0E C01A7F    D204D          CALL   AHDRPH          ; WRITE HOURS TO CLOCK
7F11 C0377F    020S0          CALL   TIHSET          ; WRITE MINUTES TD CLOCK
7F14 0604      02060          LO     B,4             ; NUMBER OF CHARS LEFT
7F16 23        02070 SNEAK    INC    HL              ; BUHP LINE POINTER
7F17 10F0      020B0          OJNZ   SNEAK           ; LOOP PAST "PM" & QUOTES
7F19 C9        02DBD          RET                    ; BACK TO BASIC PROGRAH
               0210D ;
               02110 ; ##################################################
               02120 ; CHECK FOR AH DR PH INOICATION ANO WRITE THAT VALUE
               D213D ; ##################################################
               02140 ;
7F1A 23        02150 AMORPM   INC    HL              ; BUMP LINE TO NEXT CHAR.
7F1B ES        02160          PUSH   HL              ; SAVE CURRENT LINE PTR.
7F1C D5        D217D          PUSH   DE              ; SAVE DTHER VALUES IN OE
7F10 1106D0    021B0          LO     OE,6            ; HOW MANY SPACES TO MOVE
7F20 19        02190          AOO    HL,OE           ; FINO AH OR PM IN LINE
7F21 7E        02200          LO     A,(HL)          ; GET CHARACTER FROH LINE
7F22 FE41      D2210          CP     41H             ; SET FLAG IF CHAR. = "A"
7F24 3E04      02220          LO     A,4             ; GET PM INDICATDR REAOY
7F26 2001      02230          JR     NZ,EVENNG       ; ZERO FLAG NDT SET IF PM
7F2B AF        0224D          XOR    A               ; CLEAR PH INOICATDR
7F29 01        022S0 EVENNG   POP    OE              ; RESTORE VALUES TO OE
7F2A E1        02260          POP    HL              ; GET ORIGINAL LINE PTR.
7F2B 0602      D2270          LO     B,2             ; SET UP 8 AS TIHSET LOOP
7F20 4F        022B0          LO     C,A             ; SAVE AM/PH INDICATOR
7F2E 7E        02290          LO     A,(HL)          ; GET VALUE FROM LINE
7F2F 0630      02300          SUB    30H             ; STRIP ASCII HASK
7F31 3BAA      02310          JR     C,ERROR1        ; ERROR IF LESS THAN 0
7F33 B1        D2320          ADD    A,C             ; ADD AM/PM 8IT TD VALUE
7F34 C3417F    02330          JP     MIOOLE          ; SUBROUTINE FINISHES JOB
               02340 ;
               0235D ; ##################################################
               02360 ; TIHE SETTING SUBRDUTINE CHECKS LINE FDR SYNTAX
               02370 ; ##################################################
               023BD ;
7F37 1E3D      0239D TIHSET   LO     E,30H           ; CDNVERTS ASCII TO HEX
7F39 D6D2      02400          LO     8,2             ; LOOP TWICE FOR 2 OIGITS
7F3B 1S        D2410 ZLOOP    OEC    D               ; BUMP CLOCK AOORESS PORT
7F3C 23        D2420          INC    HL              ; GET NEXT CHAR FROM LINE
7F30 7E        02430          LO     A,(HL)          ; HDVE IT TD ACC. TD TEST
7F3E 93        02440          SUB    E               ; STRIP OFF ASCII VALUE
7F3F 389C      024S0          JR     C,ERRDR1        ; ERRDR IF LESS THAN 0
7F41 FE0A      D246D HIDOLE   CP     0AH             ; CHECK IF GREATER THAN 9
7F43 3D98      02470          JR     NC,ERROR1       ; ERROR IF GREATER THAN 9
7F45 F07201    024B0          LO     (IY+1),0        ; OPEN PORT TO CLOCK
7F48 C06A7F    024BD          CALL   OELAY           ; THE USUAL CMOS WAIT
7F48 FD77DD    D2500          LD     (IY+0),A        ; WRITE VALUE TD CLOCK
7F4E C06A7F    02510          CALL   OELAY           ; WAIT! WAIT! WAIT!!!!!
7F51 10E8      02520          OJNZ   ZLDOP           ; DO IT FOR 2 OIGITS
7FS3 23        D253D          INC    HL              ; 8UMP PAST / : DR SPACE
7F54 C9        D254D          RET                    ; 8ACK TO MAIN PROGRAM
               02550 ;
               02560 ; ##################################################
               D2S70 ; GET VALUE, CDNVERT TD ASCII, AND SAVE IN TIHE$ 8UFFER
               D258D ; ##################################################
               02590 :
```

Actually, the bank-select ROM idea is only one part of a larger possibility — blocks of ROM and/or RAM placed interchangeably. Ideally the additional RAM would be available in higher memory, but the TRS configuration is so locked into its memory map that expansion in high memory would require major reconfiguring of the memory and refresh circuits. With that in mind, then, all this expansion will be dedicated to the free area located at **3000** to **37E0**.

This memory addition is an application of a 'Read-Only-RAM' concept. Simply stated, the memory write (WR) line to read/write memory is disabled by the user in order to outline an area of protected, but not permanently programmed, memory. Machine language programs under development can be emulated with this system. Crucial software can be embedded in crash-proof RAM, and the occasional nuisance of a program gone wild will not affect data in this area.

The inclusion of bank selection in this area permits the use of interchangeable, and constantly on-line, blocks of ROM, RAM, and protected RAM. In Figures 8-16 and 8-17, the ROMs used, as before, are 2716 EPROMs, and the RAMs are of the static variety. Two designs of the circuit are shown: one uses 2114 static RAMs, which are 1K by 4 bits wide; the other uses 4118 static RAMs, each a full 1K by 8 bits wide. The former memories are considerably less expensive, but the latter are easier to wire in a wire-crazy bank select scheme like this one.

As before, output port 31 has been chosen for the memory, and each 2K block is selected by the value output through port 31. Furthermore, RAM data in the unselected blocks remains intact, ready to use whenever a different value is output through port 31.

The bank-selected ROM may be used for the most part as any other memory, with one very interesting exception: routines in *different* ROMs may not call or jump to each others' routines in the normal way. Instead, two special routines must be used.

The jump routine is the simplest: the ROM's position in the bank must be identified, the jump prepared and the OUT statement commanded. The easiest way to do this is shown in Listing 8-7); the AF and HL registers are saved on the stack, then AF is loaded with the location of the routine (which it must obtain from a table of some sort identical in each ROM). Following that, the HL register pair is loaded with the jump address, and the OUT (1F),A command is then

```
7F55 15       02600 FILLER  OEC     0                   ; BUMP CLOCK PORT AOORE55
7F56 F07201   02610         LO      (IY+1).0            ; POINT TO VALUE WANTEO
7F59 C06A7F   02620         CALL    OELAY               ; THAT OL' SLOW M5M5832
7F5C F07E00   02630         LD      A,(IY+0)            ; GET OUMMY VALUE INTO A
7F5F C06A7F   02640         CALL    OELAY               : WAIT AGAIN! 5LOW CHIP
7F62 F07E00   02650         LO      A,(IY+0)            ; NOW GET VALIO VALUE
7F65 A1       02660         AND     C                   ; MA5K UNU5EO 8IT5
7F66 B3       02670         AOO     A,E                 : MAKE IT AN A5CII VALUE
7F67 77       02680         LO      (HL),A              ; PUT VALUE INTO 8UFFER
7F6B 23       02690         INC     HL                  ; NEXT 8UFFER PO5ITION
7F68 C9       02700         RET                         ; BACK TO MAIN PROGRAM
              02710 ;
              02720 ; #######################################################
              02730 : THIS I5 A SETUP WHICH CALL5 A OELAY SU8ROUTINE IN ROM
              02740 ; #######################################################
              02750 ;
7F6A C5       02760 OELAY   PUSH    BC                  : 5AVE 8C REGISTER PAIR
7F6B F5       02770         PU5H    AF                  : 5AVE AF REGISTER PAIR
7F6C D1D1DD   D278D         LD      BC,1                ; DELAY FDR MSM5832 CHIP
7F6F C06000   02790         CALL    0060H               : HERE I5 ROUTINE IN ROM
7F72 F1       02B00         POP     AF                  ; GET AF REGI5TER5 8ACK
7F73 C1       02810         POP   ' 8C                  ; GET 8C REGI5TER5 8ACK
7F7,4 C9      02B20         RET                         ; BACK TO MAIN PROGRAM
              02830 :
              02840 ; #######################################################
              02850 : THIS I5 THE LOOKUP TA8LE OF OAYS OF THE WEEK
              02860 ; #######################################################
              D2870 ;
7F75 40       02880 TA8LE   OEFM    'MON'
              02890 :
7F78 54       02900         OEFM    'TUE'
              02910 ;
7F78 57       02920         DEFM    'WEO'
              02930 ;
7F7E 54       02940         OEFM    'THU'
              02950 ;
7FB1 46       02960         DEFM    'FRI'
              0297D ;
7F84 53       02980         DEFM    'SAT'
              02990 ;
7F87 53       D3000         OEFM    '5UN'
              03010 ;
7F8A 00       03020         OEF8    0
              0303D ;
              03040 : #######################################################
7EDD          03D5D         ENO     ENTRY
0DDD0 TOTAL ERRDRS
```

executed, which switches ROMs. The proper jump address is still in HL, so a simple JP (HL) effects the jump.

```
                 ; ROUTINE BEING LEFT MUST PROVIOE THIS
                 ; INFORMATION TO AF ANO HL REGISTERS
..ZZZZ           LO      (ZZZZ),A        ; SAVE AF VALUES
..YYYY           LO      (YYYY),HL       ; SAVE HL VALUES
3ENN             LO      A,NN            ; NEW ROM BANK NUMBER
21NNNN           LO      HL,NNNN         ; JUMP AOORESS
C3WWWW           JP      XFER1           : MAKE ROM TRANSFER
                 ; ALL ROMS CDNTAIN THE FOLLOWING IOENTICAL
                 ; 8YTES AT THE 5AME ADORESSE5 IN ROM
031F     XFER1   OUT     (1F),A          ; SWITCHES ROMS
E9               JP      (HL)            ; JUMPS TO ROUTINE
..ZZZZ           LD      (ZZZZ),A        ; NOT USEO IN JUMP
..XXXX           LO      A,(XXXX)        ; NOT USEO IN JUMP
031F             DUT     (1F),A          ; NOT USEO IN JUMP
C9               RET                     ; NOT USEO IN JUMP
                 ; ALL ROUTINES BEING ENTEREO MUST PROVIOE
                 ; THE FOLLOWING RESTORATION COOING
..ZZZZ           LD      HL,(ZZZZ)       ; RESTORE HL VALUES
..YYYY           LO      A,(YYYY)        ; RESTORE AF VALUES
```

Listing 8-6. Accessing multiple ROMs (jumps).

Calling a subroutine in another ROM is more complicated, but still can be done. Listing 8-(?) shows how it might be achieved.

```
                 ; ROUTINE 8EING LEFT MUST PROVIOE THIS
                 ; INFORMATION IN AF ANO HL REGI5TERS
..ZZZZ           LO      (ZZZZ),A        ; SAVE AF OATA
..YYYY           LO      (YYYY),HL       ; SAVE HL OATA
OB1F             IN      A,(1F)          ; GET RDM BANK NUMBER
..XXXX           LO      (XXXX),A        ; SAVE ROM BANK NO.
21NNNN           LO      HL,NNNN         ; GET CALL AOORESS
COWWWW           CALL    XFER2           ; MAKE ROM TRANSFER
                 ; THE FOLLOWING CALLING ROUTINE MUST BE
                 ; PLACEO IN ALL ROMS AT IOENTICAL LOCATION
031F     XFER2   OUT     (1F),A          ; SWITCH ROMS
E9               JP      (HL)            ; ENTER ROUTINE
..ZZZZ   BACK    LO      (ZZZZ),A        ; SAVE AF OATA
..XXXX           LO      A,(XXXX)        ; GET OLO ROM NO.
D31F             OUT     (1F),A          ; TRANFER BACK
C9               RET                     ; BACK TO CALLER
                 ; THE CALLEO ROUTINE MUST MAKE THE
                 ; FOLLOWING IOENTIFICATIONS
..YYYY           LO      HL,(YYYY)       ; GET SAVEO OATA
..ZZZZ           LO      A,(ZZZZ)        ; GET SAVEO OATA
                 ; EXECUTE SUBROUTINE FOUNO HERE
                 ; PERFORM FOLLOWING STEPS WHEN THE
                 ; 5UBROUTINE IS COMPLETE ANO MUST RETURN
C3 VVVV          JP      BACK            ; GO TO XFER ROUTINE
```

Listing 8-7. Accessing multiple ROMs (calls).

This bank-select method is only one of many options which may be selected to move from one ROM to another; as you can see, three bytes of RAM (marked ZZZZ, YYYY and WWWW in the listings) are needed to store information between transfers. Although this process may initially seem unwieldy, a ROM-resident operating system in each one, together with cautious programming, will provide a remarkably transparent system expansion.



Figure 8-16. Bank-selected 4118 ROM/RAM.



IC	TYPE	+5V	GND
Z1	74LS30	14	7
Z2	74LS02	14	7
Z3	74LS00	14	7
Z4	74LS00	14	7
Z5	74LS125	14	7
Z6–9	2114	18	9
Z10	2716	24	12

Figure 8-17. ROM/RAM addition without bank-select.





Completed ROM/RAM addition with power supply on board.

```
                 DD1DD ; MEMDRY SIDECAR TEST TAPE (C) 1981 D. 8. KITSZ
                 DD11D ;
3CDD             DD12D           DRG     3CDDM
3CDD 2A          DD13D           DEFM    '** LOADING 2K RAM TEST TAPE '
3C1C 2D          DD140           DEFM    '— D. 8. KITSZ, SEPTEM8ER 1981 **'
3DDD             DD15D           DRG     3DDDM
3DDD 2A          DD16D M1        DEFM    '********************************'
3D2D 2A          DD17D           DEFM    '********************************'
3D40 2D          DD18D M2        DEFM    '————————— TESTING "READ-ONLY'
3D6D 2D          DD19D           DEFM    '-RAM" MEMDRY AREA ——————————'
3D8D 54          DD2DD M3        DEFM    'THIS SCREEN HAS 8EEN LOADED DIRE'
3DAD 43          DD21D           DEFM    'CTLY FROM THE MEMDRY SIDECAR. IF'
3DCD 41          DD22D M4        DEFM    'ALL CHARACTERS ARE CDRRECT IN TH'
3DED 49          DD23D           DEFM    'IS MESSAGE, AND IT HAS LOADED DN'
3100 54          00240 M5        OEFM    'THE SCREEN NORHALLY, THEN THIS F'
312D 49          DC25D           DEFM    'IRST TEST DF YOUR MEMDRY SIDECAR'
3140 49          0026D M6        DEFM    'IS COMPLETED.  8ELDW IS SHOWN A '
316D 43          DD27D           DEFM    'CDMPLETE CHARACTER SET AVAILA8LE'
318D 54          D028D M7        OEFM    'TD YOUR TRS-8D:                 '
31A8 2D          DD29D           DEFM    '                                '
31CD DDD1        DD3DD M8        DEFW    D1DDH
31C2 D2D3        DD31D           DEFW    D3D2H
31C4 0405        DD32D           DEFW    D5D4H
31C6 D6D7        DD33D           DEFW    D7D6M
31C8 D8D9        DD340           DEFW    D9D8H
31CA DAD8        DD35D           DEFW    D8DAH
31CC DCDD        DD36D           DEFW    DDDCM
31CE DEDF        0D37D           DEFW    DFDEH
31DD 1D11        DD38D           DEFW    111DM
31D2 1213        DD39D           DEFW    1312H
31D4 1415        DD40D           DEFW    1514H
31D6 1617        DD41D           DEFW    1716H
31D8 1819        DD42D           DEFW    1918H
310A 1A18        DD43D           DEFW    181AH
31DC 1C1D        DD440           DEFW    1D1CH
31DE 1E1F        DD45D           DEFW    1F1EH
31ED 2D21        DD46D           DEFW    212DM
31E2 2223        DD47D           DEFW    2322M
31E4 2425        DD48D           DEFW    2524H
31E6 2627        DD49D           DEFW    2726H
31E8 2829        00500           OEFW    2928H
31EA 2A28        DD51D           DEFW    282AM
31EC 2C2D        DD52D           DEFW    2D2CH
31EE 2E2F        DD53D           DEFW    2F2EH
31FD 3D31        DD540           DEFW    313DM
31F2 3233        DD55D           DEFW    3332M
31F4 3435        DD56D           DEFW    3534M
31F6 3637        DD57D           DEFW    3736M
31F8 3839        DD58D           DEFW    3938H
31FA 3A38        DD59D           DEFW    383AH
31FC 3C3D        DD6DD           DEFW    3D3CH
31FE 3E3F        DD61D           DEFW    3F3EH
32DD 4041        DD62D M9        DEFW    4140M
32D2 4243        DD63D           DEFW    4342H
32D4 4445        DD640           DEFW    4544M
32D6 4647        DD65D           DEFW    4746M
32D8 4849        DD66D           DEFW    4948M
32DA 4A48        0D67D           DEFW    484AH
32DC 4C4D        DD68D           DEFW    4D4CM
32DE 4E4F        DD69D           DEFW    4F4EH
321D 5D51        DD7DD           DEFW    515DM
3212 5253        DU71D           DEFW    5352H
3214 5455        DD72D           DEFW    5554H
3216 5657        DD73D           DEFW    5756H
3218 5859        DD740           DEFW    5958H
321A 5A58        DD75D           DEFW    585AH
321C 5C5D        DD760           OEFW    5D5CH
321E 5E5F        00770           DEFW    5F5EH
322D 6061        DD78D           DEFW    616DH
3222 6263        DD79D           OEFW    6362H
3224 6465        DD8DD           DEFW    6564H
3226 6667        DD81D           DEFW    6766H
3228 6869        DD82D           DEFW    6968M
322A 6A88        0083D           DEFW    686AH
322C 6C60        DD840           DEFW    6D6CH
322E 6E6F        DD85D           OEFW    6F6EH
3230 7071        DD86D           DEFW    717DH
3232 7273        DD87D           DEFW    7372M
3234 7475        DD88D           DEFW    7574H
3236 7677        0D89D           DEFW    7776M
3238 7879        DD9DD           DEFW    7978H
323A 7A78        DD91D           DEFW    787AH
323C 7C7D        DD92D           DEFW    7D7CM
323E 7E7F        DD93D           DEFW    7F7EH
3240 8D81        DD940 M1D       DEFW    818DM
3242 8283        DD95D           DEFW    8382M
3244 8485        DD96D           DEFW    8584M
3246 8687        D097D           DEFW    8786H
3248 8889        DD98D           DEFW    8988H
324A 8A88        DD990           DEFW    888AH
324C 8C8D        D1DDD           DEFW    8D8CH
324E 8E8F        D1D1D           DEFW    8F8EH
```

Listing Continued . . .

Remember also that the ROMs do not need to call each other directly. Instead, you may want to establish a lookup and transfer table in RAM, that acts like this :

1. User is in BASIC.
2. OUT 31,0 is entered to select the master ROM.
3. SYSTEM is entered, followed by /12288.
4. The master ROM (ROM #0) may be programmed to reset MEMORY SIZE and relocate a bank of patch points into RAM.
5. The master ROM, having completed its work the way Level II does at power up, returns to a READY in BASIC.
6. The routines are now all ready to use.

In summary, the ROM, RAM and bank-select systems can extend the horizons of your TRS-80 in unique ways. A project for people afflicted with cerebral palsy is developing a system whereby patients, doctors, or nurses need not be concerned if the TRS-80 crashes at some point, or the power is removed. Instead of loading tapes or fumbling with disks that may get damaged through handling or erratic power, these people need only use their bank-selected ROMs to reinstate and activate the machine language programs which drive specially made hardware. This hardware permits them to communicate with and use the computer with great ease.

Without the bank-select feature, however, the 8K control programs would have to be reloaded regularly, at a cost of time and patience, plus the risk of damage, loss or failure.

Continued Listing

```
3250 8091     01020        OEFW   9180H
3252 9293     01030        OEFW   9382H
3254 8485     01040        OEFW   B5B4H
3256 8687     01050        OEFW   9796H
3258 9889     01060        OEFW   88B8H
325A 8A88     01070        OEFW   989AH
325C 8C90     01080        OEFW   808CH
325E 8E8F     01080        OEFW   8F8EH
3260 A0A1     01100        OEFW   0A1A0H
3262 A2A3     01110        OEFW   0A3A2H
3264 A4A5     01120        OEFW   0A5A4H
3266 A6A7     01130        OEFW   0A7ABH
3268 A8A8     01140        OEFW   0A8A8H
326A AAAB     01150        OEFW   0ABAAH
326C ACA0     01160        OEFW   0ADACH
326E AEAF     01170        OEFW   0AFAEH
3270 8081     01180        OEFW   08180H
3272 82B3     01190        OEFW   0B382H
3274 8485     01200        OEFW   08584H
3276 8687     01210        OEFW   08786H
3278 8889     01220        OEFW   08988H
327A BA88     01230        OEFW   088BAH
327C 8C80     01240        OEFW   0808CH
327E 8E8F     01250        OEFW   08F8EH
3280 C0C1     01260 M11    OEFW   0C1C0H
3282 C2C3     01270        OEFW   0C3C2H
3284 C4C5     01280        OEFW   0C5C4H
3286 C6C7     01290        OEFW   0C7C6H
3288 C8C9     01300        OEFW   0C9C8H
328A CAC8     01310        OEFW   0C8CAH
328C CEC0     01320        OEFW   0C0CEH
328E CECF     01330        OEFW   0CFCEH
3290 0001     01340        OEFW   00100H
3282 0203     01350        OEFW   00302H
3294 0405     01360        OEFW   00504H
3286 0607     01370        OEFW   00706H
3288 0809     01380        OEFW   00908H
329A 0A08     01390        OEFW   00BDAH
328C DC00     01400        OEFW   0000CH
329E 0E0F     01410        OEFW   00F0EH
32A0 E0E1     01420        OEFW   0E1E0H
32A2 E2E3     01430        OEFW   0E3E2H
32A4 E4E5     01440        OEFW   0E5E4H
32A6 E6E7     01450        OEFW   0E7E6H
32A8 E8E9     01460        OEFW   0E8E8H
32AA EAE8     01470        OEFW   0E8EAH
32AC ECE0     01480        OEFW   0E0ECH
32AE EEEF     01490        OEFW   0EFEEH
3280 F0F1     01500        OEFW   0F1F0H
3282 F2F3     01510        OEFW   0F3F2H
3284 F4F5     01520        OEFW   0F5F4H
3286 F6F7     01530        OEFW   0F7F6H
3288 F8F8     01540        OEFW   0F9F8H
328A FAFB     01550        OEFW   0F8FAH
328C FCF0     01560        OEFW   0F0FCH
328E FEFF     01570        OEFW   0FFFEH
32C0 20       01580 H12    OEFM   '                                '
32E0 20       01590        OEFM   '                                '
3300 57       01600 M13    OEFM   'WHEN YOU HAVE VERIFIEO THAT ALL '
3320 43       01610        OEFH   'CHARACTERS HAVE BEEN TRANSFERREO'
3340 43       01620 H14    OEFM   'CORRECTLY TO THE SCREEN, PRESS T'
3360 48       01630        OEFH   'HE <ENTER> KEY TO CONTINUE......'
3380 20       01640 M15    OEFM   '                                '
33A0 20       01650        OEFM   '                                '
33C0 2A       01660 H16    OEFM   '********************************'
33E0 2A       01670        OEFM   '********************************'
3400 2A       01680 M1A    OEFM   '********************************'
3420 2A       01690        OEFH   '********************************'
3440 20       01700 H28    OEFH   '-------------- TESTING "READ-ONLY'
3460 2D       01710        OEFH   '-RAM" HEHORY CONT'0 -------------'
3471 54       01720 M3A    OEFH   'THIS SECONO SCREEN OF CHARACTERS'
3491 20       01730        OEFM   ' IS FOUNO IN THE SECONO GROUP OF'
3481 32       01740 M4A    OEFH   '2K RANDOH ACCESS MEHORY CHIPS IN'
3401 20       01750        OEFH   ' THE MEMORY SIOECAR.  THE SCREEN'
34F1 53       01760 M5A    OEFH   'SHODLO BE AS CLEAN AS THE FIRST '
3511 4F       01770        OEFH   'ONE WITH THE EXCEPTION OF AN 000'
3531 47       01780 M6A    OEFM   'GROUP OF CHARACTERS PRINTED IHME'
3551 44       01780        OEFM   'OIATELY BELOW THIS LINE --      '
3571 20       01800 M7A    OEFM   '    '
3575 211640   01810 ENTRY  LD     HL,4016H
357B 36E3     01820        LO     (HL),0E3H
357A 23       01830        INC    HL
3578 3603     01840        LD     (HL),03H
3570 210030   01850 BACKUP LO     HL,3000H
3580 11003C   01860        LD     0E,3C00H
3583 010004   01870        LD     8C,400H
3586 E0B0     01880        LDIR
3588 3A4038   01890 LDOP1  LD     A,(3840H)
3588 A7       01900        ANO    A
368C 28FA     01910        JR     Z,LOOP1
368E CDA436   01920        CALL   OELAY
3581 2634     01930        LD     H,34H
3593 163C     01940        LO     0,3CH
```

Listing Continued . . .

Romplus and Other ROM Extenders

There are simpler methods of adding ROM to the TRS-80, where some of the work has already been done for you. The *Micro 80 Computer Club of Ontario* (in care of *Brian Harron*, 67-3691 Albion Road, Ottawa, Ontario K1T 1P2) has produced their Romplus board, capable of handling two 2708 1K ROMs or one 2716 2K ROM. It fits inside the keyboard, and only requires soldering three integrated circuits in place on the board, plus sockets for the ROMs.

Computer Accessory Technology (1307 Bagley Drive, Kokomo, Indiana 46901) has also developed a small board which contains a single 2716 EPROM and an address decoder. It comes caseless, but has a power supply and plugs direcly into the TRS-80 edge-card connector. A set of programmed ROMs is available which include utilities of different kinds.



Personal Micro Computers (475 Ellis Street, Mountain View, California 94043) makes the REX-80 ROM extender, which is similar to the C.A.T. board, but comes with case and power supply, plus edge connector and cable. They also provide programmed ROMs. About $50 for the device, $25 for the ROMs.

Finally, *The Peripheral People* (P.O. Box 524, Mercer Island, Washington 98040), offers the Memory Sidecar ROM/RAM addition, which I designed, and is identical to the ROM/RAM addition presented in this book, without any bank-select features. The complete unit is $149, and a blank board is $25.

Continued Listing

```
3595 0604     01950        LO     8,4H
3597 E080     01960        LOIR
3599 3A4038   01970 LOOP2  LD     A,(3840H)
359C A7       01980        ANO    A
3580 28FA     01990        JR     Z,LOOP2
359F COA435   02000        CALL   OELAY
35A2 1809     02010        JR     BACKUP
35A4 010040   02020 OELAY  LO     8C,4000H
35A7 08       02030 LOOP3  OEC    8C
35A8 78       02040        LD     A,8
35A9 81       02050        OR     C
35AA 20F8     02060        JR     NZ,LOOP3
35AC C9       02070        RET
35A0 20       02080        OEFM   '    '
3581 2D       02090 M8A    OEFM   '--------------------------------'
3501 2D       02100        OEFM   '--------------------------------'
35F1 20       02110 M9A    OEFM   '    - WHICH IS THE ACTUAL BLOCK'
3611 20       02120        OEFM   ' OF MACHINE COOE THAT IS RUNNING'
3631 54       02130 M1OA   OEFM   'THIS TEST PROGRAM.  TO EXIT THIS'
3651 20       02140        OEFM   ' ROUTINE,  YOU MUST PRESS RESET.'
3871 54       02150 M11A   OEFM   'TO REPEAT THE TEST SEQUENCE, PRE'
3691 53       02160        OEFM   'SS THE <ENTER> KEY.             '
3681 20       02170 M12A   OEFM   '                                '
3601 20       02180        OEFM   '                                '
36F1 54       02190 M13A   OEFM   'THE UNUSUAL LINES SEEN HERE ARE '
3711 41       02200        OEFM   'A REPRESENTATION OF MEMORY SPACE'
3731 55       02210 M14A   OEFM   'USEO 8Y THE TRS-80 TO CONTROL TH'
3751 45       02220        OEFM   'E OISK ORIVES ANO CASSETTE PORT:'
3771 20       02230        OEFM   '                                '
3791 20       02240        OEFM   '                                '
3781 20       02250        OEFM   '                                '
3C40          02260        ORG    3C40H
3C40 2A       02270        OEFM   '** LOAOING 2K RAM TEST TAPE COM'
3C5F 50       02280        OEFM   'PLETE. CONTROL TAKEN 8Y TEST **'
4016          02290        ORG    4016H
4016 7535     02300        OEFW   ENTRY
3575          02310        ENO    ENTRY
00000 TOTAL ERRORS
29944  TEXT AREA 8YTES LEFT


8ACKUP 3570 01850   02010
OELAY  35A4 02020   01920 02000
ENTRY  3575 01810   02300 02310
LOOP1  3588 01890   01910
LOOP2  3599 01970   01990
LOOP3  35A7 02030   02060
M1     3000 00160
M10    3240 00940
M10A   3631 02130
M11    3280 01260
M11A   3671 02150
M12    32C0 01580
M12A   3681 02170
M13    3300 01600
M13A   36F1 02190
M14    3340 01620
M14A   3731 02210
M15    3380 01640
M16    33C0 01660
M1A    3400 01680
M2     3040 00180
M28    3440 01700
M3     3080 00200
M3A    3471 01720
M4     30C0 00220
M4A    3481 01740
M5     3100 00240
M5A    34F1 01760
M6     3140 00260
M6A    3531 01780
M7     3180 00280
M7A    3571 01800
M8     31C0 00300
M8A    3581 02090
M9     3200 00620
M9A    35F1 02110
```

A Front Panel Monitor

The first personal computers were a hobbyist's dream and a user's nightmare. These large boxes of electronic boards were programmed by hand, one byte at a time. The operation of the processor was stopped, an address was selected, and a byte programmed — all by using nearly 30 switches.

The TRS-80 is a far cry in size, speed, power, and convenience from these early machines (but don't forget that 'early' means 1974!). Yet there was an advantage in these early machines that the TRS-80 and its kin don't have: the front panel display. The front panel not only contained the multiple switches, but also a bank of LEDs so the user could view the contents of memory, registers, etc. (see Photo 8-2.).

The front panel is not an entirely obsolete concept, and can be remarkably valuable when your machine language programs sprint for the exit when you're not looking. Since the front panel visually monitors addresses and data, it provides somewhat of a window opening on the computer's activities.

The front panel can tell you if the machine is caught up in a deadly tight loop, if it is still processing (have you ever waited while the computer sorted string data?), or if it is operating in the area you expect it to. You can follow peripheral accesses like printers and disk, sound output routines and special devices you may have created.

Figure 8-18 presents the circuit for the micro front panel. It is no more than a group of latches which are activated by certain conditions – you may select any combination of input, output, read or write signals to trigger the LED displays. 16 LEDs monitor the address, and eight monitor the data.

The latches are triggered on an upswing of any signal line that is switched into the select gate; the gate may be switched off entirely, leaving the last latched address displayed on the LEDs.

Ideally, the front panel can be created from subminiature, 'grain of wheat' LEDs, and mounted directly in the TRS-80 case and soldered in place. Alternatively, it may be connected when needed by a standard 40 conductor cable. Method of construction is not critical, and can use soldering and wire wrap.



Photo 8-1. DEC front panel.

When using the micro front panel, you'll notice that much of the activity, particularly memory reads, run by very fast. It can't be helped. Because the TRS-80 uses dynamic memory which must be refreshed every few thousandths of a second (see description earlier in this chapter), the instruction clock cannot be stopped. Thus, you'll have to get used to the fast operation, noting from the intensity of the LEDs the frequency with which an area of memory is accessed. The monitor is remarkably useful when running diagnostic routines, because it points out whether there are any obvious signal line flaws. If the diagnostic program is a tight loop (most are – see chapter 10), then the activities of the computer's signal lines will become very obvious on the micro front panel.

In any case, it's easy to build and nifty to watch – very instructive to see how the computer accesses disks, for example, or how one data line pulses during cassette input/output.



Photo 8-2. Micro front panel.

Micro front panel monitor shows data and address lines from read, write, input, or output conditions.



Micro front panel can be plugged directly into the edge card or put at the end of a connector cable, as shown here.



Figure 8-18. Micro front panel.

NOTES

9

Keeping It Safe: Mass Storage

Mass storage for computer programs and data has evolved from the days of punched paper tape and punch cards to present systems involving magnetic disk storage and bubble memories.

For microcomputer users, mass storage presents a unique problem: slow and apparently unreliable tape systems are inexpensive but frustrating, whereas fast disk-based systems seem transparent, trouble free, and expensive. Both of these generalizations border on myth.

What are the true advantages and disadvantages of the competing systems? This chapter will cover them in some detail, but briefly, here they are:

1. Cassette tape is a slow to medium speed storage medium (500 bits per second is normal for the TRS-80, with systems capable of transferring data at more than 3000 bits per second).
2. Tape is an inexpensive storage medium (3/1000 of a cent per bit), and is available across the counter. The hardware is pre-configured on the TRS-80, and the operating system (such as it is) is in ROM. Total system cost, including several boxes of blank cassettes, is under $100.
3. Tape is a reliable storage medium, where good materials are used and care is taken. In a properly aligned system using low-noise, high-output cassettes, my own tests showed an average of one loading failure in 2.5 million bits.
4. Higher speed tape loaders add to the cost of the tape electronics, reducing their attractiveness, but increasing their speed and often their reliability where marginally recorded tapes are present.
5. Tape storage is sequential access, except where special digital tape systems are used. A program, once in the process of being loaded, is not tried again and again should a bit failure occur. Data storage problems are compounded, with double-dumping almost a requirement, and sequential conception and operation of programs essential.
6. The tape operating system is an essential part of the language, except where outboard devices (such as *Fastload* and similar systems) are used. Thus, it cannot be changed without adding a non-transparent, RAM-resident patch to the operating system.
7. Disk systems are capable of fast transfer rates (125,000 bits per second is possible), but the orientation towards records, directories, and other internal checking and referencing systems creates an effective transfer rate of 10,000 bits per second or less.
8. Disk systems contain built-in error checking and re-try routines. Thus, although data transfer errors occur as frequently as errors on cassette tape (if not more so), the random-access and retry capabilities make them appear error free

except where disks have been physically damaged, written over in error, or demagnetized. The apparent reliability is very high.

9. Disk systems are comparatively costly in their original hardware configuration, their operating systems, and their medium. However, the storage cost of the medium is comparable to that of cassette tape, at about 2/1000 of a cent per bit. The initial hardware investment is higher, requiring disk control ($300 for an expansion box or similar controller) and the drive ($350 or more, with quality increasing with price), and an operating system ($25 to $250, again depending on needs). An initial investment in disk storage, including a box of disks, can begin at $750 and end in the multiple thousands.

10. System flexibility is increased greatly, as the disk's operating system and BASIC language additions overlay each other as needed, and appear almost transparent to system operation. However, the plethora of disk operating systems and approaches limits the interchangeability of information from one TRS-80 to another with a different operating system.

11. Intermediate and hybrid systems are available that encompass some of the features of both standard tapes and disks. Foremost among these is the Exatron Stringy-Floppy endless-loop tape cartridge system. Its operating system is ROM-resident, its transfer rate is 7,200 bits per second.

12. The Stringy-Floppy is probably the most reliable mass storage system under adverse environmental conditions, putting it above tape and far beyond the sensitive (some say temperamental) disk systems. This aspect more than any other probably justifies its consideration as serious mass storage. Based on hi-tech, laboratory models, the ESF is a scaled-down scientific storage system.

13. Like tape, access using the ESF is sequential, but the endless loop makes pseudo-random access possible. With short tapes and programs less than 8K bytes, actual load/save time is faster than disk.

14. Cost of this system is less than disk ($250 for the hardware, $3 for the medium, an endless-loop 'wafer'), and the cost of storage is less than all other complete systems (about 1/1000 of a cent per bit). To be competitive with dropping disk prices, I expect to see the hardware cost drop.

15. Although less fragile than disks (and higher in quality of the magnetic surface), the ESF wafers, because they use thin tape on a tiny, endless-loop hub, can be damaged by the tape binding or pulling from the housing. Unlike the larger cassettes, the tape cannot be successfully reinstalled in the housing, and unlike disks, the undamaged material on the wafer cannot be recovered.

This chapter will present a tour through the available mass storage systems (except tape – see Supplements to Chapters 3(?) and 6(?)), describe the construction of a paper tape reader, and present the construction and operation of a tape storage device using 8-track cartridges.

Disk Drives

Disk drives come in a variety of sizes, shapes and formats. Among those are floppy disks in 5-inch and 8-inch sizes; removable and permanent hard disks; and permanently housed Winchester drives. Miscellaneous variants of all kinds are for sale or under development.

The most popular system for the TRS-80 is the 5-inch floppy disk system. The drive contains a platter which spins the magnetic disk inside its cardboard sleeve, a record/playback head to read the data, and a stepping motor to move the head from concentric track to track. The data is recorded using sharp digital pulses without any sort of audio recording considerations such as high-frequency bias. DC 'trim erase' is used to remove previously recorded data just ahead of the write head.

A single indexing hole near the center hub is used to inform the drive electronics and control software of the disk's position inside the paper sleeve. Other than this hole and a write-protect notch in the top edge of the paper case, there is no other information available to the drive and control software from a blank disk. It must be formatted, which is the process of embedding magnetic information on the disk for later use by the disk operating system.

The information needed for the original Radio Shack specifications included the magnetic outlining of 35 concentric tracks on the disk, and the separation of those 35 tracks into ten discontinuous bands each, called sectors.



Figure 9-1. Disc and disk system format.

Details of the system by which information is recorded on the disk can be found in the *TRSDOS 9 Disk BASIC Reference Manual*, and *TRS-80 Disk 9 Other Mysteries*. In summary, the original Radio Shack specifications called for a disk containing 35 tracks of 10 sectors of 256 bytes each, for a total of 83,060 available bytes (89,600 are actually recorded, but several thousand are reserved for directory and other information – again, see the references above for details).

Drive manufacturers and software authors immediately began modifying the Radio Shack standards. 40, 77 and 80 tracks could be used, and nearly a dozen different disk operating systems (DOS) made their appearance: the original TRSDOS from Radio Shack (versions through 2.3 now issued); NEWDOS, an updated and corrected version of TRSDOS, sold by Apparat; NEWDOS/80, a complete re-write incompatible with the others; VTOS (now issued through versions 4.0), written by the original author of TRSDOS; MicroDOS and its successor OS/80, a stripped-down, efficient, minimal DOS which is growing larger and hence less attractive; DBLDOS, a Percom entry that operates its double-density (80-track) hardware option; DOSPLUS in single- and double-density versions, a wide-ranging program by Micro Systems Software; CP/M, supposedly a standard DOS for microcomputers, but available only in modified form for the TRS-80; and many special operating systems to load and run protected software.

Choosing a disk operating system is outside the range of this book, to be sure. Incompatibilities ride rampant over the bytes of the TRS-80 computer; the consistent, convenient, accessible Level II ROM gives way under disk control to the whims of software authors and entrepreneurs, good and bad. It might seem like I'm knocking DOSes; I'm not, because it's truly a customizer's dream. But a problem arises when trying to deal with customization: to begin with, a disk operating system *is* a kind of customization. Hence, it becomes almost impossible to customize one further without being forced to provide versions for every popular DOS. There are too many, and they change quickly . . . to patch them invites problems, ill will, and frustration.

On the other hand, a disk system is ideal for customizing the TRS-80, because, once you have selected the operating system, you may modify and change it, making it your own. In a sense, that is how Apparat created NEWDOS – as a series of patches and improvements to TRSDOS, and in fact it originally required that disk users already own a copy of TRSDOS.

Inside A Disk Drive

The insides of a disk drive seem incredibly simple. In fact, they are. It is only the precision of alignment needed and a few expensive parts which bring the cost so high. The drive consists of an electronic control board which is capable of communicating with the controlling computer, in this case the TRS-80, through a disk controller chip (FDC – see below). There is a motor which spins the disk, and in most inexpensive drives this motor is connected through a drive belt to the disk hub. The motor speed of 300 rpm must be accurate to within five percent; three percent deviation from normal is reasonable, and most drives are capable of a 1.5 percent long-term deviation. The disk is inserted in the housing and held in place by a cone and pressure plate which fit around the hub, and clamp gently but firmly to the disk's center area.

When the door to the drive is closed, the pressure plate moves into place, and the disk is brought into contact with the read/write head. A properly seated disk will present the indexing opening to a light sensor, so that as it spins inside the paper envelope, the index hole will open the light beam as it passes by.

A stepping motor is capable of moving precisely to one position on its axis, on command. This type of motor is used to position a magnetic read/write head on the disk track to be read. The motor is fast and precise, and the assembly which it moves is carefully machined so there is virtually no up-down play in the head. Opposite the head is a pressure pad which forces the disk

to maintain contact with the head, albeit separated from the head by a few microinches.

The head itself is usually of the glass-ferrite variety; it has an extremely smooth, highly polished surface that will not damage the disk, and a very long life that exceeds 20,000 hours of continuous head-to-disk contact. It is capable of handling the high write currents generated by the digital circuitry, and virtually immune to electronic noise in its vicinity.

In the TRS-80 system, the disk drive itself accepts and sends certain pieces of information. They are:

1. A 4-bit drive select indicator sent to the drive; only the drive hard-wired to accept this signal will respond. In the TRS-80 system, this wiring is done in the cable itself.
2. A motor-on signal, which turns on the 300 rpm hub motor.
3. A track-to-track stepping signal and a stepping direction signal.
4. A write-enable signal and a stream of written data.
5. A stream of written data sent by the drive.
6. A write-protect signal to prevent writing to write-protected disks. Most drives will not respond to a write signal, and this write-protect signal is sent so the software can report a write-protected condition.
7. An index pulse to indicate where the disk is currently located in its rotation.
8. A track-zero indicator to identify when the disk head has reached the outermost track on the disk. This is used to locate tracks, relocate tracks or reposition the head, and on initial access to identify the head position.

Except for the drive-select signals, the disk controller chip is responsible for managing all these lines. In the TRS-80, a type 1771 controller is used, manufactured by *Western Digital.* A complete data sheet is provided with the Expansion Interface service manual from Radio Shack.

The author at work.

This controller has eight data input/output lines (DAL0 to DAL7) to the computer, an interrupt output to signal its need for service (INTRQ), read and write enables (RE and WE), and a two-bit address select (A0 and A1). These last are used to select the register that will send or receive data on the DAL lines:

A1	A0	RE	WE
0	0	Status Register	Command Register
0	1	Track Register	Track Register
1	0	Sector Register	Sector Register
1	1	Data Register	Data Register

****



Photo 9-1. Pictorial tour (6) of disk drive.
Front door of disk drive controls mechanism to steady the disk as well as a switch to indicate that the door is closed.

In the TRS-80, the chip is always selected (CS) because the buffering of data is taken care of by Z33, Z37 and Z38 in the expansion box. The Data Request signal (DRQ) is not used, nor are the three-phase motor signals (PH3 and 3PM), and the track-greater-than-43 signal (TG43). These signals would be present were a more sophisticated disk drive capability intended by Radio Shack in future versions of the TRS-80.

The clock input is provided by the separate oscillator in the expansion interface. Three voltages are needed (+12, +5, and -5), plus ground.

Test, disk initialization (DINT), and write-fault lines (WF) are not used, nor are the infamous external data separation (XTDS) and external data clock (FD CLOCK) lines. Disk data are separated by clock pulses, and high accuracy demands unfailing differentiation between the clock pulses and the data pulses. The Percom data separator plugs into the controller chip socket and makes use of XTDS and FD CLOCK.

The head-load output (which determines whether the read/write head is in place against the disk) is not used, because software controls the timing between motion of the read-write head. Head-load timing (HLT) and READY are both connected via external logic to the TRS-80, where software determines when the drive and read/write head should be ready to read or write. The remaining disk controller signals lead to and from the disk drive itself, and are identical to those listed in the description of the drive signals.



Circuit card contains disk read/write circuitry, motor stepping control, and computer interfacing. Computer connector and termination resistors are seen at lower right.



Opposite side from control card is the drive motor with speed strobe disk, and a window revealing the shaft of the head stepping motor.



Removing the control circuit card reveals a heavy cast frame to hold the disk in place. In center is the cone that fits through the disk; to the right is a pressure pad.



The drive with a disk in place. Cone fits through disk and clamps it in place. Head and index hole light emitter are on the other side of the disc; pressure pad and light sensor are on this side.

Close-up of read/write head and pressure pad. White square is glass ferrite head surface, vertical stripe is the head's read/write surface. Pressure pad moves into place when the disc's front door is closed.



Close-up of positioning sensor. Index hole of a disk allows light to pass from LED emitter to sensor (top center).



Hefty disk drive power supply handles motor drive current and powers the electronics.

A Heavy Dose of DOSes

On the software side, the number of disk operating systems for the Model I continues to increase. Most include 'Level III BASIC', the usual copying and formatting capabilities, but have been expanded to include more than that. For a complete description of the features of competing DOSes, refer to the March 1981 issue of 80 Microcomputing. Among the special features of the most prominent DOSes:

TRSDOS. AUTO, ATTRIB, CLOCK, COPY, DATE, DEVICE, DIR, DUMP, KILL, FREE, LIB, LIST, LOAD, PRINT, PROT, RENAME, TIME, VERIFY. Also BASIC, BASIC2, DEBUG, TRACE. Level III BASIC functions. Details are found in the TRSDOS manual, and other DOSes include all of these commands in some way or other.

NEWDOS+. Adds COPY, JKL screen print, DIRCHECK directory verification, LMOFFSET tape load offset module, EDTASM with modifications, SUPERZAP for modifying disk contents, LEVEL 1 located in RAM, DISASSEM, LV1DSKSL disk save/load for Level I. CMD"DOS COMMAND NAME" to execute from BASIC, and several commands to re-enter BASIC from DOS.

NEWDOS/80. CHAIN, HIMEM protection from DOS, JKL, MINIDOS don't-distrub-memory DOS, MDBORT for killing MINIDOS, PDRIVE setup for multiple drive types, PURGE for killing file groups, SYSTEM to create special commands, SUPERZAP, LMOFFSET, LEVEL 1, ASPOOL print spooler, DIRCHECK.

VTOS. BOOT software reset, BUILD a group of auto-excute programs, CHAIN to execute them, MEMORY, PURGE, RUN for non-VTOS systems, SYSTEM , XFER disk copy program, PATCH disk modification routine, VTCOMM communications utility, KSR terminal program, ROUTE for changing the destination of data, SET for a user device program, SPOOL, RESET to cancel device setup, LINK for devices, FILTER to be used with device routing, ALLOC setting up disk space in advance.

DOSPLUS. Adds BOOT, BUILD, CLEAR a directory file, DO group of auto-exeute programs, FORMS to set up the printer driver , a different variant of FREE, PAUSE for user input in auto-execute routines, RS232 for a report on that status, PURGE, DISKZAP for modifying disk information, CLRFILE for zeroing a file, COPY1 copying utility, CRUNCH space compression for BASIC, TRANSFER program copier.

ULTRADOS. CLEAR for zeroing memory, DEAD for zeroing memory, TOPMEM for setting DOS-protected memory, CMD"C" compression routine, CMD"DOS COMMAND NAME" which executes from BASIC, CMD"O" file buffer allocation, CMD"X" to return to BASIC from DOS, cross referenced listing of variables and line numbers, renumbering from BASIC, shorthand command keystrokes.

A Garden Full of Varieties

The available variety of disk drives is growing. Not only are the capabilities of standard 5-inch drives being stretched (to run 40, 77 and 80 track densities), but 8-inch systems and hard-disk systems are being introduced for the lowly TRS-80. Among them:

Manufacturer	Model/Type	Price	Comments
Minifloppy (5-inch) Disc Systems			
Access	AFO-100	$315	40 tracks; Tandon?
Aerocomp	40-1	$350	40 tracks; double-density
	80-1	$460	80 tracks; double-density
	80-2	$460	40 tracks; double-sided; double density.
	160-2	$600	80 tracks; double-sided; double density.
CPU Shop	CCI-100	$315	40 tracks; Percom?
	CCI-200	$430	80 tracks; Percom?
MPI	8/51	$320	40 tracks; 5 ms track -to-track; auto-eject; double-density head.
	8/81	$425	80 tracks; 3 ms track -to-track; auto-eject; double-density head.
Micropolis	MCP1027	$300	35 tracks, single head
	MCP1037	$700	35 tracks, dual head
	MCP1027-2	$440	77 tracks, single head
	MCP1037-2	$800	77 tracks, dual head
Percom	TFO-100	$350+	40 tracks
	TFO-200	$650+	77 tracks
Pertec	FD200	$380	40 tracks
Shugart	SA-400	$330	35 tracks
	SA-410	$340	40 tracks
Siemens	FDD 100-5	$275	40 tracks, double density
Tandon	———	$...	40 tracks
TEAC	———	$300	40 tracks
	———	$400	80 tracks
Vista	V-80	$400	40 tracks
	V-800	$600	80 tracks
	V-8800	$775	160 tracks

The Exatron Stringy-Floppy

In between tape systems and disk systems is an unusual device. I only say 'in between' because the name Stringy-Floppy implies that it somehow is a tapelike version of a floppy disk device. In fact, it is not, for two major reasons: it is a unique, high reliability, high endurance storage medium; and it does not (at least in its TRS-80 configuration) contain formatting, sectoring, or record-keeping of the type used for disks.

The *Exatron Stringy-Floppy* (ESF) consists of a small DC motor which uses a tiny plastic belt to drive a capstan, exactly as in a cassette player. The motor's speed, however, is set to 10.5 inches per second, quite a bit faster than cassette, 8-track, or even open-reel. Thus, even though the tape itself is only 1/16 of an inch wide, reasonable data recording can be expected.

In the TRS-80 version, the ESF does not use any standard method of recording. A separate sequence is used to prepare, or 'verify' an endless-loop tape wafer than that which is used to record data. Both methods use a variety of bi-phase recording, in which the bit being read or recorded depends on the polarity of the bit just written or read.



Photo 9-2. Pictorial tour (6) of ESF system.

Exatron Stringy-Floppy placed next to Microconnection modem. Both are compact, light devices.

This makes the ESF reliable in spite of a motor speed which varies more than ten percent in either direction of its ideal speed. It also means the ESF can work under harsh conditions which might otherwise throw a standard clock/data system far off.

Programs are recorded on the ESF in a continuous stream, preceded by a leader and followed by information to assist the software in locating the next available blank program space. Programs and data may be read in any order, but must be written in ascending numerical order.

The ESF operating system is contained in a read only memory which resides in the unassigned memory area on the Model I (3000 to 37C0); thus, it is always available and relatively crash-free. It does use a few bytes of RAM, however, and must also patch into the Level II BASIC parameters in low memory.

The wafer itself is available only from *Exatron*, and is based on the wafers used in industrial applications. It consists of a length of high-output digital recording tape, highly polished. This is wound on a small hub, lubricated, and spliced into an endless-loop. A reflective splice is used to determine end-of-tape (EOT/BOT), and is viewed through a window at the top of the wafer.

The wafers may be write-protected by affixing a reflective-tape dot on the wafer. This is read by the operating system before the drive is activated. The ESF operating system consists of these commands:

@LOADx Load a program; **x** is the program number, and is optional. An error in the load



ESF 'rubber band' drive is not as reliable as disk drives, but software is capable of handling greater variations in speed. Small DC motor replaced by a direct-drive type in later versions, say Exatron officials.

terminates the process and the error (parity or checksum) is reported to the user.

@SAVEx Saves a BASIC program; the **x** is the program number, and is required. The program is verified, and any saving errors are reported.

@SAVEx,r,s,t Saves a block of memory; **x** is the program number, **r** is the starting address, and **s** is the length of the block. These are required. The **t** is an optional entry address. All numbers are in decimal. The block is verified, and any saving errors are reported.

@NEWx Verifies a wafer. When **x** is used, the wafer is cleared and verified from that program to the end splice. Available byte count is reported.

Fastload, TC-8, and Other Systems

Most other alternatives to disk systems involve using standard cassettes for high-speed saving and loading. Among these are Fastload, manufactured by *Personal Microcomputers, Inc.*; TC-8, or the 'Poor Man's Floppy', made by *JPC Systems*; and the Beta-80, made by *Meca Technology*.

The advantage to the standard cassette is simple: cost and availability. Unlike disks, they are able to take some measure of abuse, and can be replaced without regret over the expense. And unlike Exatron wafers (or disks, for that matter), they can be purchased if necessary in the local grocery. Furthermore, cassette tape technology has progressed further than disk technology, providing better surfaces, adhesion, and signal-to-noise ratio. Disks are still in the dark ages of reproduction compared to audio tape.



Control card of ESF contains drive electronics, tape read/write circuitry, and 2716 EPROM containing the ESF operating system. Power supply is underneath the card.

Fastload is a ROM-based operating system combined with a hardware detection and shaping circuit. A modified CTR-41 is used, where the fast-forward button and play button can be locked down. The circuit then can read a standard 500-baud tape in the fast-forward mode quite reliably at about 8000 baud. Debounce, audible beep, and key repeat are included with the operating system.

Although I have not examined the schematics for Fastload, its carefully designed circuit board, with voltage regulator heat-sinked to the case, attest to a cautious, probably over-designed system. The loading system is put into operation by typing SYSTEM (ENTER), /12288 (ENTER); optional debounce/beep/repeat can be added as well.

When in operation, Fastload uses the single LOAD command in Level II, and is compatible with disk-based computers by using a SYSTEM call. The 500-baud load and save are left undisturbed. Fastload is well-designed, and reasonably reliable. If your original tapes have audible 'bumps' when played at high speed, however, they may not load easily with this system. Commercial tapes, or those recorded by the user on virgin cassettes, load easily and extremely fast. 'Bumpy' tapes, however, do not load well, and have to be re-recorded.

One of the other disturbing features of Fastload is its tendency to give a 'READY' message even when a BASIC program has been loaded incorrectly. Granted, it is almost impossible to be sure a BASIC program has loaded well because, in its normal CSAVE format, no checksums have been provided. But the user should be sure to list the program before expecting it to run. SYSTEM loads, on the other hand, present checksum error messages on bad loads. Fastload costs $188 assembled; a modified CTR-41 is $95.

TC-8, or the Poor Man's Floppy, both saves and records at high speed. It is provided in kit form; assembly can be completed in a few hours. Like Fastload, the TC-8 plugs into the edge connector, but the software is RAM-resident. The standard CTR-80 tape recorder is used, and a two-wire swap is shown to make the CTR-41



Photo 9-3. Fastload device.

Instead of a small heat sink, Fastload power supply regulator is sinked to the entire metal case. Insulators around regulator show attention to detail.



Photo 9-4. Fastload circuit card.

Circuit card for Fastload shows extremely conservative design, with careful attention to grounding and possible noise sources. DIP resistor package is used in place of separate resistors, and the operating system is contained in a 2716 EPROM. Since less than 1K of the EPROM is used for the operating system, the remainder may be programmed by the user with utilities.

run properly (its high current tended to fuse motor relays together on the TRS-80).

Since it is both a record and save device, the TC-8 contains fifteen separate commands, including SAVE (BASIC programs only) and PUT (machine language blocks); LOAD BASIC programs next or by name; LOAD? for verification; LOADN to position the tape; comparable GET commands for machine language programs; RUN as a load-and-go command; RSET for cassette motor on; OPEN, CLOSE, PRINT, and INPUT for file management; and KILL to eliminate file management.

The software can be reconfigured, relocated, and stripped to a memory-saving bootstrap version. The TC-8 is provided with extensive documentation which is clear and literate, providing examples, a sample program using the OPEN, PRINT#, INPUT#, and CLOSE commands, along with recommendations, suggestions, and warnings (plus sympathy!) about the problems of transferring some commercial machine-language software to the TC-8.

The circuit is quite simple, but well designed and accurate; the capabilities of this elegant circuit comes from the software. The construction manual provides soldering suggestions and explanations, recommendations on the soldering iron to purchase, and drawings of properly soldered connections. For convenience, all work is done on the underside of the board; correct placement and orientation of parts is emphasized. Two-color layouts of the board are provided on every page, along with a checklist of each step. These are some of the finest assembly instructions I have seen for a project.

When complete, the unit loads and saves at 2500 baud on off-the-shelf cassettes. The company recommends certain brands, and also sells the brand *JPC products* uses. All signals to the tape player are non-critical, and the loading routine will accept signals over most of the audible, undistorted output spectrum of most cassette recorders. TC-8 costs $90 in kit form.

The Beta-80 is a tape storage system patterned after professional digital tape devices. Although a standard digital cassette is used, the Beta-80 is configured something like a disk, with directory and fast access. Fast forward and rewind are automatically controlled by the RAM-resident operating system, and the search speed is 100 inches per second.



Photo 9-5. TC-8 tape system.

TC-8 tape system attaches to edge-card connector and cassette recorder to provide high-speed record/save of programs. Photo courtesy JPC Products Company.

```
                 00100 :
                 00110 : ########################################################
                 00120 ; HIGH SPEEO TAPE LOAO ANO SAVE ROUTINE OPERATING AT 1960
                 00130 : BAUO.  THIS CAN BE MAOE TRANSPARENT TO BASIC BY USING
                 00140 : EITHER /SAVE ANO /LOAO OR /PUT ANO /GET.  THE ROUTINE
                 00150 ; PRESENTEO HERE SAVES A BLOCK OF MACHINE COOE, BUT MAY
                 00160 : BE USEO FOR SAVING ANO LOAOING BASIC BY LOCATING START
                 00170 : ANO ENO OF THE BASIC PROGRAM (FOR WRITE), ANO START ANO
                 00180 ; ENO OF BASIC MEMORY (FOR REAO).  SAMPLE ACCESS ROUTINES
                 00190 ; ARE PRESENTEO AT THE ENO OF THIS LISTING.
                 00200 : ########################################################
                 00210 ;
7000             00220         ORG     7000H           ; TOP OF MEMORY - RELOC.
                 00230 :
                 00240 ; ########################################################
                 00250 : WRITE-BYTE SUBROUTINE.  BYTE IS ASSUMEO IN C REGISTER
                 00260 ; ########################################################
                 00270 :
7000 060B        00280 WRITE   LO      B,B             ; NUMBER OF BITS TO WRITE
7002 C5          00290         PUSH    BC              : SAVE BITS OF BYTE
7003 0620        00300         LO      B,20H           ; GET A OELAY VALUE
7005 10FE        00310         OJNZ    $               ; ANO OELAY 117 USECS
7007 C1          00320         POP     BC              : ANO RESTORE BITS
700B C01470      00330 WLOOP   CALL    TIMEX           ; WRITE TIMING BIT
700B CB11        00340         RL      C               ; ROTATE BIT INTO FLAG
7000 17          00350         RLA                     ; ROTATE FLAG INTO A
700E C03670      00360         CALL    BITEX           ; WRITE BIT TO TAPE
7011 10F5        00370         OJNZ    WLOOP           : OO IT TOTAL OF B TIMES
7013 C9          00380         RET                     ; BACK FROM WRITE ROUTINE
                 00390 ;
                 00400 ; ########################################################
                 00410 ; ROUTINE TO WRITE TIMING BIT POSITIVE-NEGATIVE TO TAPE
                 00420 : ########################################################
                 00430 :
7014 C5          00440 TIMEX   PUSH    BC              ; SAVE B ON STACK
7015 3A3040      00450         LO      A,(4030H)       : GET SCREEN INFORMATION
701B E6FC        00460         ANO     OFCH            ; MASK OUT LOW TWO BITS
701A F601        00470         OR      1               : SET LOWEST BIT
701C 03FF        00480         OUT     (OFFH),A        : WRITE BIT TO TAPE
701E 0607        00490         LO      B,07H           ; TIMING VALUE @ 1.77 MHZ
7020 10FE        00500         OJNZ    $               ; IS EQUAL TO 67 USECS
7022 E6FC        00510         ANO     OFCH            : MASK OUT LOW TWO BITS
7024 F602        00520         OR      2               ; SET NEXT LOWEST BIT
7026 03FF        00530         OUT     (OFFH),A        : WRITE NEG. BIT TO TAPE
702B 0607        00540         LO      B.07H           ; TIMING VALUE @ 1.77 MHZ
702A 10FE        00550         OJNZ    $               ; IS EQUAL TO 64 USECS
702C E6FC        00560         ANO     OFCH            : MASK OUT LOW TWO BITS
702E 03FF        00570         OUT     (OFFH),A        ; WRITE NEUTRAL BIT
```

Listing 9-2. High-speed tape loading routine.

Loading is at 4000 baud (tape running at 5 i.p.s.), twice the speed of the TC-8, but about half that of the Exatron Stringy-Floppy and Fastload, but access time (using the directory) is less than a minute for more than a half megabyte of stored programs.

Commands are LOAD in the form of load, load and run, and load array information; SAVE for programs and arrays; MERGE for append (not a true merge) or append and run; and KILL to delete a program or an array. Other commands operate within the various RAM-resident systems.

The Beta-80 uses a reliable Phi-deck drive, and has impressive features. However, as of this writing, users report little support from Meca for converting and saving machine language programs on the Beta-80. The Beta-80 costs under $300.

High-Speed Cassette Loading

Speeds higher than 500 baud are achievable entirely through software, and most systems work exceedingly well. Among the most popular are: SPEED, the first such program, loading and saving at 1500 (?) baud; HISPED (*Palomar Software*, 170 S. Palomar Dr.. Redwood City, CA 94062; $24.95), a 2000-baud system; ZIPLOAD, in the public domain and published in the 80 Encyclopedia (*Wayne Green*, Inc.); and B-17 (*ABS Suppliers*, P.O. Box 8297, Ann Arbor, MI 48107; $25).

Each of these save/load programs patches into the BASIC operating system, and all use the DOS-reserved LOAD and SAVE commands. The last is of particular interest because it is a complete system rather than merely a save/load program.

SAVE, using a six-character name, sends BASIC programs to tape; LOAD? verifies them. LOAD puts the computer into the SYSTEM mode automatically and loads a BASIC program. PUT and GET are used for formatted file arrays. It is also provided with a machine language module. Checksum errors, full memory buffer, continuity errors, and format errors are reported by this module. The entire source code is available for sale if the B-17 program is also purchased.

Aside from B-17's high reliability, it also provides an on-screen prompt indicating saving and loading.

What makes a high-speed loader not only

```
7030 0607      00580         LO      B,07M           ; TIMING VALUE @ 1.77 MHZ
7032 10FE      00590         OJNZ    $               ; IS EQUAL TO 113 USEC5
7034 C1        00600         POP     BC              ; RE5TORE NUMBER OF BITS
7035 C9        00610         RET                     ; BACK TO BIT WRITE ROUT.
               00620 ;
               00630 ; ###################################################
               00640 ; ROUTINE TO WRITE INOIVIOUAL BIT TO TAPE (OR NOT IF 0)
               00650 ; ###################################################
               00660 ;
7036 C5        00670 BITEX   PUSM    BC              ; 5AVE NUMBER OF BIT5
7037 E601      00680         ANO     1               ; MASK OUT ALL BUT BIT 0
7039 47        00690         LO      B,A             ; 5AVE A IN B REGISTER
703A 3A3040    00700         LO      A,(4030H)       ; GET 5CREEN STATUS
7030 E6FC      00710         ANO     0FCH            ; MASK OUT LOW TWO BITS
703F 80        00720         AOO     A.B             ; 5ET BIT OR NOT
7040 03FF      00730         OUT     (0FFH),A        ; 5ENO OUT CAS5ETTE PORT
7042 C5        00740         PU5M    BC              ; 5AVE B REGI5TER AGAIN
7043 0605      00750         LO      B,05M           ; TIMING VALUE FOR BIT
7045 10FE      00760         OJNZ    $               ; OELAY I5 65 U5EC5
7047 C1        00770         POP     BC              ; GET VALUE BACK INTO B
7048 CB00      00780         RLC     B               : ROTATE INTO BIT 1
704A E6FC      00790         ANO     0FCM            ; MASK OUT LOW BITS AGAIN
704C 80        00800         AOO     A,B             ; SET BIT 1 OR NOT
7040 03FF      00810         OUT     (0FFH),A        ; SENO OUT CA55ETTE PORT
704F C5        00820         PU5M    BC              ; 5AVE B REGISTER AGAIN
7050 0606      00830         LO      B,06H           ; OELAY IS 63 U5EC5
7052 10FE      00840         OJNZ    $               ; OELAY FOR BOTTOM OF BIT
7054 E6FC      00850         ANO     0FCH            ; CREATE A NEUTRAL BIT
7056 03FF      00860         OUT     (0FFM),A        : ANO WRITE IT TO TAPE
705B 060B      00870         LO      B,08H           ; GET OELAY VALUE IN B
705A 10FE      00880         OJNZ    $               ; OELAY I5 110 U5ECS
705C C1        00880         POP     BC              ; CLEAR STACK OF BIT
7050 C1        00900         POP     BC              ; GET ORIGINAL BITS BACK
705E C9        00910         RET                     ; BACK TO 5AVING ROUTINE
               00920 ;
               00930 ; ###################################################
               00940 ; ROUTINE TO WRITE LEAOER OF 256 BYTES OF FF PLU5 5YNC A5
               00950 : ###################################################
               00960 ;
705F AF        00970 5YNCMR  XOR     A               ; OEFINE ORIVE NUMBER 0
7060 C01202    00980         CALL    0212M           ; ORIVE MOTOR RUNNING
7063 010000    00890         LO      BC,0            ; NEEO A LOOP ABOUT 1 SEC
7066 C06000    01000         CALL    0060H           ; CALL OELAY IN ROM
7069 C5        01010 5YLOOP  PU5H    BC              ; 5AVE THI5 VALUE (BC=0)
706A 0E00      01020         LO      C,0             ; WRITE BYTE OF 1111 1111
706C C00070    01030         CALL    WRITE           ; WRITE THAT BYTE
706F 060B      01040         LO      B,B             ; 5MORT LOOP BETW. BYTE5
7071 10FE      01050         OJNZ    $               : OELAY JU5T 58 U5ECS
7073 C1        01060         POP     BC              ; RE5TORE VALUE FOR U5E
7074 10F3      01070         OJNZ    5YLOOP          : WRITE TOTAL OF FF BYTE5
7076 0EA5      01080         LO      C,0A5H          ; 5YNCMRONIZATION BYTE
707B C00070    01090         CALL    WRITE           ; WRITE THAT BYTE
707B C9        01100         RET                     ; BACK TO MAIN ROUTINE
               01110 ;
               01120 ; ###################################################
               01130 ; REAO BYTE SUBROUTINE: COMPLETEO BYTE INTO C REGI5TER
               01140 ; ###################################################
               01150 ;
707C 0608      01160 REAO    LO      B,B             ; NUMBER OF BITS TO REAO
707E C0BA70    01170 RLOOP   CALL    REOEX           ; REAO TIMING BIT
7081 C09C70    01180         CALL    REOBIT          ; REAO OATA BIT IF ANY
7084 17        01190         RLA                     ; ROTATE BIT INTO CARRY
7085 CB11      01200         RL      C               ; ROTATE CARRY INTO C
7087 10F5      01210         OJNZ    RLOOP           ; OO IT TOTAL OF B TIME5
7089 C9        01220         RET                     ; BACK FROM REAO ROUTINE
               01230 ;
               01240 ; ###################################################
               01250 ; ROUTINE TO REAO TIMING BIT FROM TAPE ANO OELAY AFTER
               01260 ; ###################################################
               01270 ;
708A C0C770    01280 REOEX   CALL    INSIG           ; KEEP LOOKING FOR ONE
7080 0BFF      01290 REOX2   IN      A,(0FFH)        ; KEEP LOOKING FOR ONE
70BF 17        01300         RLA                     : RO.TATE INTO CARRY
7090 30F8      01310         JR      NC,REOX2        ; KEEP LOOKING FOR ONE
7092 C5        01320         PUSH    BC              ; SAVE NUMBER OF BIT5
7093 060F      01330         LO      B,0FH           ; VALUE TO OELAY
7095 10FE      01340         OJNZ    $               ; ANO OELAY FOR 144 U5EC5
7097 C1        01350         POP     BC              ; RESTORE NUMBER OF BITS
709B C0C770    01360         CALL    IN5IG           ; RE5ET INSIG FLIP-FLOP
709B C9        01370         RET                     ; BACK TO MAIN ROUTINE
               01380 ;
               01390 ; ###################################################
               01400 ; ROUTINE TO REAO INOIVIOUAL OATA BIT (IF ANY) FROM TAPE
               01410 ; ###################################################
               01420 ;
709C C5        01430 REOBIT  PU5H    BC              ; 5AVE VALUE IN B ANO C
7090 061B      01440         LO      B,1BM           ; VALUE FOR OELAY
709F 10FE      01450         OJNZ    $               ; EQUAL TO 197 USEC5
70A1 0BFF      01460         IN      A,(0FFH)        ; GET VALUE FROM CA55ETTE
70A3 C1        01470         POP     BC              : RE5TORE VALUE5 TO B & C
70A4 C9        01480         RET                     ; RETURN WITH VALUE IN A
               01490 :
               01500 ; ###################################################
               01510 : THI5 ROUTINE REA05 TMROUGH TME LEAOER FOR 5YNC BYTE
               01520 ; ###################################################
               01530 ;
70A5 AF        01540 REOSYN  XOR     A               ; OEFINE ORIVE NUMBER 0
70A6 C01202    01550         CALL    0212M           : ORIVE I5 RUNNING
70A9 C0BA70    01560         CALL    REOEX           ; REAO TIMING BIT
70AC C09C70    01570         CALL    REOBIT          ; GET BIT FROM TAPE
70AF 17        01580         RLA                     ; ROTATE INTO CARRY FLAG
70B0 30F3      01590         JR      NC,REOSYN       ; KEEP LOOKING FOR A 1
```

possible, but reliable, especially since the TRS-80's 500-baud rate seems to be full of flaws? As noted in the Supplement to Chapter 6 (?), the 500-baud rate is actually fairly reliable, except that a few misconceptions on the part of the ROM designers led to incorrect load timing. The writers of the high speed loaders noted above took considerably more care in designing their input/output schemes, and thus achieved that reliability.

Listing 9-2 presents a pair of high-speed input/output modules that load and save blocks of memory at 2000 (?) baud. These modules may supplant the CALLs to 0235 in all the input/output routines presented elsewhere in this book, allowing faster saving and loading of memory blocks, data, screens, etc. These routines use the normal cassette output. For a high-speed loader using an 8-track system and digital, very reliable recording, see Chapter 9.

A Paper Tape Reader

One of the more common sights in the early days of larger computers was a bank of spinning tape reels for magnetic and punched tapes. Both still exist, but are not common storage modes for microcomputers like the TRS-80.

However, you may have the chance to pick up some terrific programs written for an 8080-based computer, especially those in the National Semiconductor library. These include double-precision mathematical subroutines, text handlers, light-pen readers, etc., and are sometimes available at low prices. But they are stored on rolls of paper tape. Software for devices such as the Computalker Speech Lab is also provided on paper tape.

Furthermore, though paper tape may no longer be the popular program storage medium it once was, for archival storage or communicating among different styles and types of computers, it still has its place. For occasional use, then, paper tape can be used, but an expensive reader won't be a very good investment. For less than $50, you can interface the TPR-1 paper tape reader and the TRS-80.

The TPR-1 reader is sold by *Raeco*, Box 165, Washington, Maine 04574. The unit consists of a machined, brushed aluminum track for the paper tape, and a circuit board attached to the track. On the board are two integrated circuits, and nine light sensors are on the board under holes in the track; also provided are an LED test light, resistors, and a 14-pin DIP socket. It is sold with a good technical manual for $32.50; an optional

```
7082 C811      01600          RL      C                ; ROTATE INTO C REGISTER
70B4 0607      01610          LO      8,7              ; NUHBER OF BIT5 LEFT
70B6 COBA70    01620 5YNCLP   CALL    REOEX            ; REAO TIMING BIT
70B9 C09C70    01630          CALL    REOBIT           ; GET BIT FROM TAPE
708C 17        01640          RLA                      ; ROTATE INTO CARRY FLAG
70B0 CB11      01650          RL      C                ; ROTATE INTO C REGISTER
70BF 10F5      01660          OJNZ    SYNCLP           ; OO IT 7 TIHES LEFT
70C1 3EA5      01670          LO      A,OA5H           ; LOAO 5YNC BYTE VALUE
70C3 89        01680          CP      C                ; COMPARE AGAIN5T C
70C4 C8        01690          RET     Z                ; RETURN IF A MATCH
70C5 180E      01700          JR      RE05YN           ; BACK TO KEEP LOOKING
               01710 ;
               01720 ; ##################################################
               01730 ; ROUTINE TO RESET INSIG FLIP-FLOP TO 8E A8LE TO REAO
               01740 ; ##################################################
               01750 ;
70C7 F5        01760 IN5IG    PUSH    AF               ; 5AVE VALUE IN AF
70C8 3A3040    01770          LO      A.(4030H)        ; GET SCREEN 5TATU5 8YTE
70C8 03FF      01780          OUT     (OFFH).A         : RE5ET FLIP-FLOP
70C0 F1        01790          POP     AF               ; RE5TORE AF 5TATU5
70CE C9        01800          RET                      ; 8ACK TO REAOING ROUTINE
               01810 :
               01820 : ##################################################
               01830 ; THI5 ROUTINE WILL LOAO A 8ASIC PROGRAM WITH NO FILENAHE
               01840 ; ##################################################
               01850 :
70CF F3        01860 TEMPER   OI                       ; GET RIO OF 8OTHER5
7000 2A8140    01870          LO      HL,(4081H)       ; GET TOP OF 8ASIC MEMORY
7003 E058A440  01880          LO      OE,(40A4H)       ; GET 8A5IC PROGRAH PTR.
7007 05        01890          PU5H    OE               : SAVE IT A HOHENT
7008 E052      01900          5BC     HL,OE            ; GET HEHORY AVAILABLE
700A E5        01910          PUSM    HL               ; GET REAOY FOR TRAN5FER
700B C1        01920          POP     8C               : COUNT OF HEHORY IS IN B
700C E1        01930          POP     HL               ; BEGINNING OF BA5IC = HL
7000 C5        01940          PUSH    BC               ; 5AVE AVAILABLE MEHORY
700E COA570    01950          CALL    RE05YN           ; CALL REAO 5YNC ROUTINE
70E1 C1        01960          POP     8C               ; RESTORE AVAILA8LE HEM.
70E2 C5        01970 TREAO    PUSH    BC               ; 5AVE BYTE COUNT
70E3 C07C70    01980          CALL    REAO             ; REAO ONE 8YTE
70E6 71        01990          LO      (HLJ,C           ; GET VALUE TO VIOEO MEH
70E7 C1        02000          POP     8C               ; GET 8YTE COUNT 8ACK
70E8 08        02010          OEC     8C               ; REOUCE COUNT BY ONE
70E9 78        02020          LO      A,8              ; GET HIGH 8YTE OF MEMORY
70EA 81        02030          OR      C                ; ANO CHECK AGAINST LOW
70EB CA9719    02040          JP      Z,1997H          ; OM ERROR IF TOO MUCH
70EE 7E        02050          LO      A,(ML)           ; GET VALUE IN HL
70EF A7        02060          ANO     A                ; TEST IF A ZERO
70F0 C20271    02070          JP      NZ,JUMP3         ; PAST FLASH IF OKAY
70F3 3A3F3C    02080          LO      A,(3C3FH)        : GET PLACE ON SCREEN
70F6 EE0A      02090          XOR     OAH              ; ANO TOGGLE 5TAR & SPACE
70F8 323F3C    02100          LO      (3C3FH),A        ; ANO PUT 8ACK ON SCREEN
70F8 28        02110          OEC     HL               ; GO 8ACK SPACE FOR TEST
70FC 7E        02120          LO      A,(HL)           ; GET VALUE THERE
70F0 A7        02130          ANO     A                ; TEST IF A ZERO AL5O
70FE CA0571    02140          JP      Z,JUMP4          : GO TO ENO ROUTINE IF O
7101 23        02150          INC     HL               ; BACK TO PROPER 8YTE
7102 23        02160 JUHP3    INC     HL               ; REAOY NEXT MEH LOC'N
7103 1800      02170          JR      TREAO            ; ANO THEN GO 8ACK
7105 23        02180 JUHP4    INC     HL               ; GET NEXT MEMORY LOC'N
7106 AF        02190          XOR     A                ; LET A BE EQUAL TO ZERO
7107 77        02200          LO      (HL],A           ; ANO PUT IT IN PLACE
710B E05BA440  02210          LO      OE,(40A4H)       ; GET START OF PRGRM PTR
710C 3EFF      02220          LO      A,OFFH           ; GET RESETTING COOE
710E 12        02230          LO      (OE),A           ; PUT AT PROGRAH 5TART
710F COFC1A    02240          CALL    1AFCH            ; RE5ET ALL LINE NUM8ER5
7112 23        02250          INC     HL               ; HL HOVEO PAST PROGRAM
7113 22F940    02260          LO      (40F9H),HL       ; 5IHPLE VARIA8LE POINTER
7116 COC901    02270          CALL    01C9H            : CLEAR THE SCREEN NOW
7119 C06118    02280          CALL    1861H            ; CLEAR ALL THE POINTER5
711C COFE01    02290          CALL    01FEH            ; TURN CASSETTE OFF
711F C3CC06    02300          JP      06CCH            ; GO TO 8ASIC "REAOY"
               02310 ;
               02320 ; ##################################################
               02330 ; THI5 ROUTINE I5 A GERMINAL ROUTINE TO C5AVE A PROGRAM
               02340 ; WITHOUT A PROGRAH NAHE.  FORMAT:  /PUT.  THE 500-8AUO
               02350 ; 8LOCK 5AVE CAN 8E U5EO A5 AN EXAHPLE OF HOW TO EMPLOY
               02360 ; A PROGRAM NAME IN 5AVING A PROGRAM.
               02370 ; ##################################################
               02380 ;
7122 F3        02390 TEMPEX   OI                       ; GET RIO OF 8OTHER
7123 3E2A      02400          LO      A,2AH            ; GET REAOY AN ASTERISK
7125 323E3C    02410          LO      (3C3EH),A        ; PLACE 5TAR ON 5CREEN
712B 323F3C    02420          LO      (3C3FM),A        ; PLACE STAR NEXT TO IT
712B 2AA440    02430          LO      ML,(40A4M)       ; START OF 8ASIC PROGRAM
712E EOSBF940  02440          LO      OE,(40F9M)       ; BOTTOM OF VAR. POINTER
7132 COSF70    02450          CALL    SYNCMR           ; WRITE LEAOER ANO SYNC
7135 7C        02460 LOOOOP   LO      A,M              ; GET CURRENT MIGM MSB
7136 BA        02470          CP      O                ; SAME AS TARGET MSB?
7137 C23F71    02480          JP      NZ,JUMP01        ; CONTINUE IF NOT SAME
713A 70        02490          LO      A,L              ; SAME HI MSB - REAOY LOW
713B BB        02S00          CP      E                ; SAME AS TARGET LSB?
713C CA5671    02S10          JP      Z,GOOUT          ; OONE WITH SAVE IF SO
713F 7E        02520 JUMP01   LO      A,(HL)           ; ELSE GET VALUE IN MEH
7140 A7        02S30          ANO     A                ; TEST IF A ZERO
7141 C24E71    02S40          JP      NZ,JUMP02        ; JUST GO ON IF NOT
7144 FS        02550          PUSM    AF               ; SAVE VALUE IN A
714S 3A3F3C    02S60          LO      A,(3C3FM)        ; GET TOGGLE VALUE TO A
714B EE0A      02570          XOR     OAM              ; TOGGLE STAR & SPACE
714A 323F3C    025B0          LO      (3C3FH),A        ; ANO PUT IT ON SCREEN
7140 F1        02S90          POP     AF               ; GET VALUE BACK TO A
714E 4F        02600 JUMP02   LO      C,A              ; PUT BYTE IN C REGISTER
714F C00070    02610          CALL    WRITE            ; WRITE 8YTE TO TAPE
```

case is $5.00. Photo 1 shows the unit mounted inside the smallest Radio Shack equipment box.

Eight-level (eight bit) paper tape is capable of storing parallel bytes of data by means of holes punched in the tape. A smaller, ninth hole – placed between the third and fourth holes – provides a timing signal for the reading program.

The ninth hole also can be used as a data-ready signal. By the time the light just triggers the circuitry as it passes along the edge of the smaller hole, the larger holes are letting in plenty of light for the data to be stable, ready to read.

The TPR-1 comes ready to hook to a computer bus. Its output is in parallel, and all signals are tri-state. Because it uses only 12 mA, it's possible to run the reader directly from the TRS power supply.

Figure 9-4 presents the diagram of the TPR-1. The low-power CMOS integrated circuits U1 and U2 evaluate the state of the data as seen by the light-sensitive transistors and provide a parallel output. Part of U2 is also used to drive the LED, which blinks on whenever data is stable at the output of the reader.

Figure 9-5 is the TRS-80 interface schematic. Z1 and Z2 decode the port address 3F in order to activate tri-state buffer Z3. This separate port decoding is necessary because the TPR-1 was not designed with the READY line separately activated from the data lines. Were that the case, READY might be tested at all times. That way, data would only be input whenever READy indicated stable data. In its present configuration, however, a separate buffer must be used for the TPR-1 data lines.

Z4 is a flip-flop which produces an interrupt signal and sends it to the TRS-80 INT line; INTAK (interrupt acknowledge) is used to clear the interface flip-flop when data has been read. This configuration is similar to that used for the interrupt based real time clock (see Chapter 8).

The circuit can be wire-wrapped on a small piece of perfboard and mounted inside a case with the TPR-1. A detachable 40-pin cable can also be used to save a few dollars.

Listing 9-2 presents the software to read one page (256 bytes) of data into the TRS-80 and store it in memory. Recall that the interrupt patch point at 4012 is initialized with C9, a RETurn instruction. In its place, then, a patch must be made to one of three interrupt service routines which will read each byte of data as it becomes stable at the output of the TPR-1. Since the reader will not likely be a device used very

```
7152 23          02620           INC      HL            ; GET NEXT MEMORY LOC'N
7153 C33571      02630           JP       LOOOOP        ; LOOP AROUNO FOREVER
7156 COFE01      02640 GOOOT     CALL     01FEH         ; TURN OFF CASSETTE
7159 C9          02650           RET                    ; BACK TO MAIN ROOTINE
                 02660 ;
                 02670 ; #######################################################
                 02680 ; REMEMBER:  ENTRY POINT FOR SAVE ROUTINE IS  TEMPEX
                 02690 ; REMEMBER:  ENTRY POINT FOR LOAO ROUTINE IS  TEMPER
                 02700 ; #######################################################
                 02710 ;
0000             02720           ENO
    BITEX  7036 00670   00360
    GOOUT  7156 02640   02510
    INSIG  70C7 01760   01280 01360
    JUMP01 713F 02520   02480
    JUMP02 714E 02600   02540
    JUMP3  7102 02160   02070
    JOMP4  7105 02180   02140
    LOOOOP 7135 02460   02630
    REAO   707C 01160   01980
    REOBIT 709C 01430   01180 01570 01630
    REOEX  708A 01280   01170 01560 01620
    REOSYN 70A5 01540   01590 01700 01950
    REDX2  7080 01290   01310
    RLOOP  707E 01170   01210
    SYLOOP 7069 01010   01070
    SYNCHR 705F 00970   02450
    SYNCLP 7086 01620   01660
    TEMPER 70CF 01860
    TEMPEX 7122 02390
    TIMEX  7014 00440   00330
    TREAO  70E2 01970   02170
    WLOOP  7008 00330   00370
    WRITE  7000 00280   01030 01090 02610
```

often, this kind of interrupt-hogging is not a problem. If you have a Teletype with a built-in paper punch, though, you might want to configure this interrupt software so it can be patched in only when it's needed.


NOTES -
1. OUTPUT OATA IS TRUE:
I.E A "QNE" (HOLE) ON THE TAPE GIVES A HIGH (5V) VOLTAGE LEVEL OUTPUT
2. MAXIMUM LOADING ON ANY OUTPUT IS TWO STANOARD TTL LOADS.
3. QI THRU Q9 = MRD150 OPTICALLY MATCHED, OO NOT SUBSTITUTE.

UI,U2 = 4502

FIG 9-5

9-26

Figure 9-4. TPR-1 schematic diagram.



Photo 9-6. Paper tape reader.
TPR-1 tape reader has machined aluminum track and data indicator LED.



Figure 9-5. TPR-1 interfacing schematic.



Only four integrated circuits form the complete tape reader interface. Power supplies both reader and interface.

The program is entered at line 1160. The screen is cleared, and the user is prompted to enter a base address in hex. This is the address starting at which the tape data is to be loaded into memory. The keyboard is scanned for characters 0 to 9 and A to F; these are displayed, and when ENTER is pressed, the characters are converted to a starting address.

The tape must be threaded before actual data reading is begun, because during threading it's possible to present false information to the TRS-80. The tape reading is begun at line 1740.

Listing 9-3. Paper tape reader program.

```
                 00100 ; ##################################################
                 00110 ; TAPE READER AND 256-BYTE LOADER ROUTINE
                 00120 ; DENNIS BATHORY KITSZ, ROXBURY, VERMONT 05669
                 00130 ; ##################################################
                 00140 ;
4013             00150 VECTOR  EQU     4013H           ;INTERRUPT VECTOR PATCH
06CC             00160 BASIC   EQU     06CCH           ;RETURN TO BASIC READY
3C00             00170 VIDEO   EQU     3C00H           ;BEGINNING OF SCREEN
                 00180 ;
                 00190 ; ##################################################
                 00200 ; INTERRUPT VECTOR AT 4012H
                 00210 ; ##################################################
                 00220 ;
4012             00230         ORG     4012H           ;CURRENT VALUE IS C9
4012 C3          00240         DEFB    0C3H            ;REPLACE WITH JUMP
7000             00250         ORG     07000H          ;ROUTINES BEGIN HERE
                 00260 ;
                 00270 ; ##################################################
                 00280 ; CLEAR SCREEN SUBROUTINE
                 00290 ; ##################################################
                 00300 ;
7000 21003C      00310 CLEAR   LD      HL,VIDEO        ;GET START OF VIDEO
7003 11013C      00320         LD      DE,VIDEO+1      ;GET DESTINATION POINT
7006 01FF03      00330         LD      BC,03FFH        ;GET MEMORY BLOCK SIZE
7009 3620        00340         LD      (HL),20H        ;WRITE SPACE INTO VIDEO
700B EDB0        00350         LDIR                    ;BLOCK MOVE CLEAR SCREEN
700D C9          00360         RET                     ;BACK FROM SUBROUTINE
                 00370 ;
                 00380 ; ##################################################
                 00390 ; SCAN FOR ENTER SUBROUTINE
                 00400 ; ##################################################
                 00410 ;
700E 3A4038      00420 ENTER   LD      A,(3840H)       ;"ENTER" KEYBOARD ROW
7011 FE02        00430         CP      2               ;"ENTER" KEYBOARD COLUMN
7013 20F9        00440         JR      NZ,ENTER        ;LOOP UNTIL KEY PRESSED
7015 C9          00450         RET                     ;BACK FROM SUBROUTINE
                 00460 ;
                 00470 ; ##################################################
                 00480 ; DISPLAY MESSAGE SUBROUTINE
                 00490 ; ##################################################
                 00500 ;
7016 7E          00510 DISPLY  LD      A,(HL)          ;GET BEGINNING OF TEXT
7017 A7          00520         AND     A               ;CHECK IF A NULL
7018 C8          00530         RET     Z               ;EXIT SUBROUTINE IF NULL
7019 12          00540         LD      (DE),A          ;DISPLAY CHARACTER IN A
701A 23          00550         INC     HL              ;GET NEXT MESSAGE LOC'N
701B 13          00560         INC     DE              ;GET NEXT SCREEN LOC'N
701C 18F8        00570         JR      DISPLY          ;LOOP FOR CHARACTER TEST
                 00580 ;
                 00590 ; ##################################################
                 00600 ; CONVERT TO ASCII SUBROUTINE
                 00610 ; ##################################################
                 00620 ;
701E F5          00630 CONVRT  PUSH    AF              ;SAVE ACCUM. AND FLAGS
701F E6F0        00640         AND     0F0H            ;MASK OUT LOW 4 BITS
7021 1F          00650         RRA                     ;MOVE NIBBLE TO RIGHT...
7022 1F          00660         RRA                     ;  ...SOME MORE
7023 1F          00670         RRA                     ;  ...SOME MORE
7024 1F          00680         RRA                     ;  ...UNTIL DONE
7025 FE0A        00690         CP      0AH             ;IS IT TEN OR GREATER?
7027 3004        00700         JR      NC,HIBYTE       ;MOVE ALONG IF > TEN
7029 C630        00710         ADD     A,30H           ;ASCII = NUMBER PLUS 30H
702B 1802        00720         JR      NEXT            ;GO ON TO LOW NIBBLE
702D C637        00730 HIBYTE  ADD     A,37H           ;ASCII = NUMBER PLUS 37H
702F 77          00740 NEXT    LD      (HL),A          ;DISPLAY FIRST ASCII CHAR
7030 23          00750         INC     HL              ;GET NEXT SCREEN LOC'N
7031 F1          00760         POP     AF              ;RESTORE ORIGINAL HEX
7032 E60F        00770         AND     0FH             ;MASK OUT HIGH 4 BITS
7034 FE0A        00780         CP      0AH             ;IS IT TEN OR GREATER?
7036 3004        00790         JR      NC,HIBTE2       ;MOVE ALONG IF > TEN
7038 C630        00800         ADD     A,30H           ;ASCII = NUMBER PLUS 30H
703A 1802        00810         JR      NEXT2           ;GO TO DISPLAY & OUT
703C C637        00820 HIBTE2  ADD     A,37H           ;ASCII = NUMBER PLUS 37H
703E 77          00830 NEXT2   LD      (HL),A          ;DISPLAY NEXT ASCII VALUE
703F C9          00840         RET                     ;BACK FROM SUBROUTINE
                 00850 ;
                 00860 ; ##################################################
                 00870 ; CLEAR TAPE READER INTERRUPT ACKNOWLEDGE
                 00880 ; ##################################################
                 00890 ;
7040 F3          00900 SERVE0  DI                      ;INTERRUPT OFF IN SERVICE
7041 AF          00910         XOR     A               ;CLEAR ACCUM. & FLAGS
7042 C9          00920         RET                     ;BACK FROM SUBROUTINE
                 00930 ;
                 00940 ; ##################################################
                 00950 ; PAGE ADDRESS INTERRUPT SERVICE
                 00960 ; ##################################################
                 00970 ;
7043 F3          00980 SERVE1  DI                      ;INTERRUPT OFF IN SERVICE
7044 DB3F        00990         IN      A,(3FH)         ;GET VALUE FROM READER
7046 CD1E70      01000         CALL    CONVRT          ;CONVERT VALUE TO ASCII
7049 AF          01010         XOR     A               ;CLEAR ACCUM. & FLAGS
704A C9          01020         RET                     ;BACK FROM SUBROUTINE
                 01030 ;
                 01040 ; ##################################################
                 01050 ; READ DATA / PLACE ON SCREEN INTERRUPT
                 01060 ; ##################################################
                 01070 ;
704B F3          01080 SERVE2  DI                      ;INTERRUPT OFF IN SERVICE
```

Listing Continued . .

With the software shown, the tape to be read must be in the following format:

1-byte code of information (tape number, address page, etc.), which is displayed but not to be stored in memory.

256 bytes of data.

1-byte simple checksum.

If the tape is not in this format, the program can be easily altered to accommodate any other 256-byte data block format.

Interrupts are then enabled (lines 1810-1820), and a series of short interrupt service routines are activated. The first routine merely waits for the interrupt line to clear, as it may have been set by stray light in the room when the tape is threaded (lines 1820-1870). 256 bytes are then loaded and displayed (lines 1910-2030). The checksum is calculated and displayed (lines 2050-2130), and the checksum is read from tape and displayed (lines 2150-2280). If there is a match, the memory pointer is advanced in order to read the next block of tape; otherwise, it is reset to the beginning of the block, allowing the tape to be read again. (lines 2210-2420). Finally, the option of loading additional blocks or returning to BASIC is presented (lines 2440-2540).

Using the TPR-1, the interface, and this simple software, the wealth of 8080 programs, as well as programs saved in an archival paper tape format, may be read into your TRS-80 and used.

An 8-Track Mass Storage System

Oh, no! Here comes another one! I'd like to join the mass storage fray with another device capable of loading and saving programs at high speed. It's not as slow as a cassette, not as fast as a Stringy-Floppy, but it has one interesting capability: sequential-random access. That's a mythical term for sequential access of more than one track at a time.

Here's how it works: 8-track cartridges play one-quarter their total length on each pass. Then the head switches from the first stereo pair to the second, the second to the third, the third to the fourth, and from the fourth back up to the first. A so-called '40-minute' cartridge is actually 10 minutes long, four passes. The shortest commercially available cartridges are 20 minutes long, five minutes per pass.

Continued Listing

```
704C DB3F      01090          IN      A,(3FH)          ;GET VALUE FROM READER
704E 77        01100          LD      (HL),A           ;PUT IT INTO MEMORY
704F 81        01110          ADD     A,C              ;GET VALUE FROM CHECKSUM
7050 4F        01120          LD      C,A              ;RESTORE UPDATED CHECKSUM
7051 23        01130          INC     HL               ;GET NEXT MEMORY LOC'N
7052 AF        01140          XOR     A                ;CLEAR ACCUM. & FLAGS
7053 C9        01150          RET                      ;BACK FROM SUBROUTINE
               01160 ;
               01170 ; ##############################################################
               01180 ; CHECKSUM INTERRUPT ROUTINE
               01190 ; ##############################################################
               01200 ;
7054 F3        01210 SERVE3   DI                       ;INTERRUPT OFF IN SERVICE
7055 DB3F      01220          IN      A,(3FH)          ;GET VALUE FROM READER
7057 47        01230          LD      B,A              ;SAVE IT IN B REGISTER
7058 AF        01240          XOR     A                ;CLEAR ACCUM. & FLAGS
7059 C9        01250          RET                      ;BACK FROM SUBROUTINE
               01260 ;
               01270 ; ##############################################################
               01280 ; MESSAGES FOLLOW
               01290 ; ##############################################################
               01300 ;
705A 54        01310 MSGN01   DEFM    'THREAD TAPE AND PRESS CLEAR.'
7076 00        01320          DEFB    00
7077 4C        01330 MSGN02   DEFM    'LOADING PAGE ADDRESS:  '
708E 00        01340          DEFB    00
708F 42        01350 MSGN03   DEFM    'BYTES LOADING AS FOLLOWS:'
70A8 00        01360          DEFB    00
70A9 43        01370 MSGN04   DEFM    'CALCULATED CHECKSUM IS:  '
70C2 00        01380          DEFB    00
70C3 43        01390 MSGN05   DEFM    'CHECKSUM AS READ IS:  '
70D9 00        01400          DEFB    00
70DA 43        01410 MSGN06   DEFM    'CHECKSUM ERROR IN THIS BLOCK.'
70F7 00        01420          DEFB    00
70F8 42        01430 MSGN07   DEFM    'BLOCK LOADED CORRECTLY.'
7E0F 00        01440          DEFB    00
7E10 41        01450 MSGN08   DEFM    'ANOTHER BLOCK?  REPLY 1 FOR YES, 2 FOR NO'
7E39 00        01460          DEFB    00
7E3A 50        01470 MSGN09   DEFM    'PRESS CLEAR TO RETURN TO BASIC.'
7E59 00        01480          DEFB    00
               01490 ;
               01500 ; ##############################################################
               01510 ; REMEMBER THIS IS ENTRY POINT AND NOT!
               01520 ; BEGINNING OF PROGRAM.......
               01530 ; CLEAR SCREEN, DISPLAY "THREAD" MESSAGE
               01540 ; ##############################################################.
               01550 ;
7E5A CD0070    01560 START    CALL    CLEAR            ;OUT TO CLEAR SUBROUTINE
7E5D 215A70    01570          LD      HL,MSGN01        ;GET MESSAGE #1 LOCATION
7E60 11003C    01580          LD      DE,VIDEO         ;GET DISPLAY LOCATION
7E63 CD1670    01590          CALL    DISPLY           ;OUT TO DISPLAY SUBROUT.
7E66 CD0E70    01600          CALL    ENTER            ;WAIT FOR ENTER SUBROUT.
               01610 ;
               01620 ; ##############################################################
               01630 ; DISPLAY "ADDRESS" MESSAGE & FIND IT
               01640 ; ##############################################################
               01650 ;
7E69 217770    01660          LD      HL,MSGN02        ;GET MESSAGE #2 LOCATION
7E6C 11403C    01670          LD      DE,VIDEO+40H     ;GET DISPLAY LOCATION
7E6F CD1670    01680          CALL    DISPLY           ;OUT TO DISPLAY SUBROUT.
7E72 214070    01690          LD      HL,SERVE0        ;GET INT #1 SERVICE ROUT.
7E75 221340    01700          LD      (VECTOR),HL      ;INSTALL AT INT. VECTOR
7E78 37        01710          SCF                      ;CARRY FLAG IS IMPORTANT
7E79 ED56      01720          IM      1                ;SET INTERRUPT MODE
7E7B FB        01730          EI                       ;INTERRUPTS ON & WAITING
7E7C 38FE      01740          JR      C,$              ;SUBROUTINE CLEARS CARRY!
7E7E 214370    01750          LD      HL,SERVE1        ;GET INT #2 SERVICE ROUT.
7E81 221340    01760          LD      (VECTOR),HL      ;INSTALL AT INT. VECTOR
7E84 21573C    01770          LD      HL,VIDEO+57H     ;GET DISPLAY LOCATION
7E87 37        01780          SCF                      ;CARRY DETERMINES LOOP
7E88 FB        01790          EI                       ;INTERRUPTS ON & WAITING
7E89 38FE      01800          JR      C,$              ;SUBROUTINE CLEARS CARRY!
               01810 ;
               01820 ; ##############################################################
               01830 ; DISPLAY "BYTES" MESSAGE & LOAD 256
               01840 ; ##############################################################
               01850 ;
7E8B 218F70    01860          LD      HL,MSGN03        ;GET MESSAGE #3 LOCATION
7E8E 11803C    01870          LD      DE,VIDEO+80H     ;GET DISPLAY LOCATION
7E91 CD1670    01880          CALL    DISPLY           ;OUT TO DISPLAY SUBROUT.
7E94 214870    01890          LD      HL,SERVE2        ;GET INT #3 SERVICE ROUT.
7E97 221340    01900          LD      (VECTOR),HL      ;INSTALL AT INT. VECTOR
7E9A 21003D    01910          LD      HL,VIDEO+100H    ;GET FIRST DISPLAY LOC'N
7E9D AF        01920          XOR     A                ;CLEAR ACCUM. & FLAGS
7E9E 4F        01930          LD      C,A              ;CLEAR CHECKSUM REGISTER
7E9F 0600      01940          LD      B,00H            ;LOAD B REGISTER WITH 256
7EA1 37        01950 LOOP2    SCF                      ;INSTALL "JR C" LOOP
7EA2 FB        01960          EI                       ;INTERRUPS ON & WAITING
7EA3 38FE      01970          JR      C,$              ;SUBROUTINE CLEARS CARRY!
7EA5 10FA      01980          DJNZ    LOOP2            ;WRITE ONE PAGE TO MEMORY
               01990 ;
               02000 ; ##############################################################
               02010 ; DISPLAY "CHECKSUM CALC" MESSAGE
               02020 ; ##############################################################
               02030 ;
7EA7 215470    02040          LD      HL,SERVE3        ;GET INT #4 SERVICE ROUT.
7EAA 221340    02050          LD      (VECTOR),HL      ;INSTALL AT INT. VECTOR
7EAD 21A970    02060          LD      HL,MSGN04        ;GET MESSAGE #4 LOCATION
7EB0 11403E    02070          LD      DE,VIDEO+240H    ;GET DISPLAY LOCATION
7EB3 CD1670    02080          CALL    DISPLY           ;OUT TO DISPLAY SUBROUT.
7EB6 79        02090          LD      A,C              ;GET CHECKSUM CALCULATION
7EB7 D5        02100          PUSH    DE               ;SAVE DISPLAY INFORMATION
```

Listing Continued . . .

For this system, the shortest 8-track cartridges are used in an 8-track deck with an *electrical* fast-forward mode. There are several loading options:

1. Load the next program on the tape from the current track. The machine fast-forwards to the next leader and loads the program.

2. Load the next program on the tape, with the track specified. The machine moves to the specified track, fast-forwards to the next leader, and loads the program.

3. Load the program specified from the track specified. The machine moves to the appropriate track and reads leaders (in fast-forward mode) until the program is found, and then loads it.

4. Load the program specified; the machine moves ahead and reads the directory immediately following the splice. The program is located and read.

In this way, where the locations of programs are known, they may be loaded immediately. Otherwise, the device is *somewhat* directory organized. I add this reservation because the tape is sequential and programs can't be killed easily unless the tape is re-organized. More on that later.

The advantage of this system is obvious: it provides somewhat faster access and loading than cassettes, and allows fairly fast search and storage. In the fast-forward mode, 20-minute 8-track tapes can be run through completely in less than two minutes. Worst-case program access is then two minutes – when you have just passed the program you want to load. Furthermore, eight individual programs can be stored parallel to each other on the cartridge's tracks.

As noted, to build this device, an electrical fast-forward is necessary. Check the manuals for a two-speed motor; the Craig model H240 playback-only deck is the kind I used. Some modifications are necessary to the tape recorder itself, and alignment is a bit more critical.

Continued Listing

```
7E88 E1        02110          POP     HL              ;TRANSFER IT TO HL PAIR
7E89 C01E70    02120          CALL    CONVRT          ;CNVRT. CHECKSUH TO ASCII
               02130 ;
               02140 ; #######################################################
               021S0 ; OISPLAY "CHECKSUH REAO" HESSAGE & OO IT
               02160 ; #######################################################
               02170 ;
7E8C 21C370    02180          LO      HL,HSGN05       ;GET MESSAGE #S LOCATION
7EBF 11803E    02190          LO      OE,VIOEO+280H   ;GET OISPLAY LOCATION
7EC2 C01670    02200          CALL    OISPLY          :OUT TO OISPLAY SUBROUT.
7ECS F8        02210          EI                      ;INTERRUPTS ON & WAITING
7EC6 37        02220          SCF                     ;CARRY FLAG LOOP SET
7EC7 3BFE      02230          JR      C,$             ;SUBROUTINE CLEARS CARRY!
               02240 ;
               022S0 ; #######################################################
               02260 : OISPLAY CHECKSUH ANO CHECK IT
               02270 ; #######################################################
               02280 ;
7EC9 7B        02290          LO      A,B             ;GET REAO CHECKSUM 8ACK
7ECA OS        C2300          PUSH    OE              ;STASH OE REGISTER PAIR
7ECB E1        02310          POP     HL              ;TRANSFER TO HL PAIR
7ECC C01E70    02320          CALL    CONVRT          ;CNVRT. CHECKSUH TO ASCII
7ECF 78        02330          LO      A,8             ;GET VALUE AGAIN FROH 8
7E00 89        02340          CP      C               ;CHECK WITH CALC CHECKSUH
7E01 2808      023S0          JR      Z,CKSHOK        ;CHECKSUH OKAY IF A HATCH
               02360 ;
               02370 ; #######################################################
               02380 ; OISPLAY CHECKSUH 8AO HESSAGE
               02390 ; #######################################################
               02400 ;
7E03 210A70    02410          LO      HL,HSGN06       ;GET HESSAGE #6 LOCATION
7E06 11C03E    02420          LO      OE,VIOEO+2COH   ;GET OISPLAY LOCATION
7E09 C01670    02430          CALL    OISPLY          ;OUT TO OISPLAY SU8ROUT.
7E0C 1809      02440          JR      LEAVE           ;LOAO COMPLETE - GO OUT
               024S0 ;
               02460 ; #######################################################
               02470 ; OISPLAY CHECKSUH OKAY HESSAGE
               02480 ; #######################################################
               02490 ;
7E0E 21F870    02S00 CKSHOK   LO      HL,HSGN07       ;GET MESSAGE #7 LOCATION
7EE1 11C03E    02S10          LO      OE,VIOEO+2COH   ;GET OISPLAY LOCATION
7EE4 C01670    02S20          CALL    OISPLY          :OUT TO OISPLAY SU8ROUT.
7EE7 21107E    02S30 LEAVE    LO      HL,HSGN08       ;GET HESSAGE #8 LOCATION
7EEA 11003F    02S40          LO      OE,VIOEO+300H   ;GET OISPLAY LOCATION
7EE0 C01670    02S50          CALL    OISPLY          ;OUT TO OISPLAY SU8ROUT.
               02S60 ;
               02S70 ; #######################################################
               02S80 ; SCAN KEY8OARO FOR 1 OR 0 & OO IT
               02S90 ; #######################################################
               02600 ;
7EF0 3A103B    02610 FINOYN   LO      A,(3810H)       ;GET 0-7 KEY8OARO ROW
7EF3 FE02      02620          CP      2               ;IS IT NUH8ER ONE?
7EFS CASA7E    02630          JP      Z,START         :8ACK TO START IF SO
7EF8 FE04      02640          CP      4               ;IS IT NUH8ER TWO?
7EFA 2802      026S0          JR      Z,OONE          ;FINISHEO ROUTINE IF SO
7EFC 1BF2      02660          JR      FINOYN          ;KEEP LOOKING IF NEITHER
7EFE 213A7E    02670 OONE     LO      HL,MSGN09       ;GET HESSAGE #9 LOCATION
7F01 11403F    02680          LO      OE,VIOEO+340H   ;GET OISPLAY LOCATION
7F04 C01670    02690          CALL    OISPLY          ;OUT TO OISPLAY SU8ROUT.
7F07 C00E70    02700 LOOKNG   CALL    ENTER   ;LOOK FOR ENTER SUBROUT.
7F0A C3CC06    02710          JP      BASIC           ;BACK TO BASIC READY
               02720 ;
               02730 ; ##########################&############################
7ESA           02740          ENO     START           ;SYSTEH ENTRY POINT
00000 TOTAL ERRORS
```

Eviscerating an 8-Track Cartridge

Chances are that obtaining high quality 8-track cartridges in short lengths won't be easy. It's not hard to make your own in roughly eight minute lengths – two minutes per track, with less than 60 seconds total access time. This will be enough for programs nearly 30,000 bytes in length.

Purchase a few cheap 8-tracks to experiment with. All you will need is a piece of wood, a pair of scissors, and a package of silver foil sensing tape. This is available at Radio Shack (catalog number 44-1155, under $2).

Most 8-tracks are fastened together with plastic tabs recessed in holes on top or bottom of the case. There are usually five: one on each back corner, one under the label in the center, one through the capstan, and one to secure the remaining corner. First, insert the cartridge into a player and run it ahead to its splice.

Make sure you are holding the cartridge with the label down. Slip a thin piece of hobby 'half-round' – a round stick split lengthwise down the center – into each hole and push the tab back, splitting the plastic case gently with your hand. The dull end of a small crocheting hook also works well. When all the tabs are released, split the cartridge apart to about one-quarter inch. Now *turn it over*. Gradually lift the cartridge apart, being careful to note the tape path and *exactly* how much slack is present in the loop.

Snip the splice out first clipping out a length of tape that runs to within an inch of the center hub. Take the loose end of the tape that winds around the outside of the tape 'pancake', and begin to pull it out. Let the hub spin freely as you do this, so that the tension on the wound tape does not change. Measure the tape removed (to produce the 37.5 feet for an 8-minute cartridge) using this table:

Total Cartridge Time	Total Feet	Remove to Create 8-minute Cartridge
20 minutes	94	56
22 minutes	103	65
30 minutes	141	103
40 minutes	188	150
44 minutes	206	169
45 minutes	211	173
60 minutes	281	244

Note: Do not use cartridges over 60 minutes long.

Sound time consuming? It can be if you measure a foot at a time. Instead, anchor the cartridge on a table, and pull the end of the tape across the room (or down the hall). If you've purchased a 40-minute cartridge, that's only ten trips.

Eviscerating an 8-Track Cartridge (5 photos).



Blunt tool is inserted in slots at bottom of the cartridge as the sides are separated and held steady.



Cartridge is flipped right side up and top of case is removed.



Tape is removed from its path and cut at splice.

When you've removed all the tape you need to, leave the same amount of slack as before and splice the two ends together. The oxide (playing) side of the tape is spliced with metal foil sensing tape. Make sure you splice the same sides to each other! Now reroute the tape along the original path, holding it gently in place; use thin cloth gloves if your hands tend to perspire.



Excess tape is pulled gently from outside of the hub, letting hub and platter rotate freely. Note that end near center of hub has been cut fairly short to eliminate the possibility of tangling with the tape being removed.



When enough tape has been removed, ends are spliced together with silver sensing foil. The tape is then re-routed and the case snapped back together.

Without bending the tape or getting it caught, slip the cartridge top back in place. Note the front of the cartridge as you do this, making sure the tape does not slip on the outside of the 'window frames'. You now have an 8-minute cartridge, ready to use.

If you end up with some slack tape hanging out of the cartridge, put on some thin cloth gloves. Now pull the tape out of the case gently from the end opposite the rubber puck. The tape will pull into the other end faster than it is being pulled out. When most of the slack is taken up, give a gentle tug with a bit of 'snap'; the momentum will spool the tape into the cartridge housing.

If you are using the Craig H-240, the directions below will apply directly; since 8-track playback decks are similar, you can put some of them to use in remodeling your 8-track. It is also possible to purchase drives without electronics from surplus houses. These are sold for under $10, and come complete with head assembly, motor, and track-change solenoid. Be sure that you get one with a two-speed motor if you want to implement the fast forward features of the system; an excellent single-speed drive is sold for only $8 by BNF Enterprises.

First of all, you should know that the deck won't be usable as an audio deck when you're done; so don't split up your hi-fi system in hopes that this 8-track storage system will serve double duty.

1. Remove the case. Two screws hold the back panel, and screws through the four feet keep the frame attached to the housing. Set the back aside, and slide the electronics out through the front of the case.

2. Pull off the buttons, and set them aside. Remove the four screws which hold the frame to the face plate, and set the face plate aside.

3. Heat the soldering iron. You will be removing these wires:

   - The two wires connected to the on-off switch; contact is made when a cartridge is inserted in the deck.

   - The two wires from the foil sensor pickup. This is located about an inch from the on-off switch.

   - All wires running to the three switches underneath the deck.

4. Remove the two front screws holding the three switches onto the front plate. Set this switch block aside; also remove all loose wires (those desoldered at both ends), and desolder the far ends of remaining wires which had run to the switches.

5. Unscrew the electronics control board (two screws), which is found to the front of the transformer. Desolder all wires leading to this board, and discard the board, scavenge it for parts, or keep it. It is a legitimate 8-track preamplifier, and can still be used if you need such an animal.

6. The following parts are still intact:

   - The motor and the three wires leading from it. These wires are still attached to a terminal strip.

   - The head assembly. This will be modified later. At present, it contains a shielded, three-wire cable leading from the playback head itself, and a five-wire assembly from the track-select switch.

   - The capstan, drive belt, and track-change mechanics. These remain intact.

   - The transformer. Three wires run from it; the center tap (black wire), won't be used, so cover it with tape or a wire nut.

   - The terminal strip and two audio output jacks. These will be used.

By removing these parts, you have returned the drive to its 'naked' state. If you are using a surplus 8-track drive, this is the condition in which it will be shipped.

To use this in a digital system, several important conditions have to be met:

1. The recording and playback must be done in a digital format.

2. The track, splice, and tape-in-place status must be readable by the computer.

3. Speed must be controlled by the computer.

Figure 9-6. presents the complete circuitry to convert the Craig H-240 to a digital record/playback system. Incoming data is latched by Z12 on the occurrence of the command OUT (0AAH),A and is buffered by Z2a/b. It is fed to a symmetrical pair of output-coupled buffers (Z1 and Z6).

Since the output of these CMOS buffers is capable of rising very high (within a few millivolts of the 12-volt supply voltage), this provides a fast rising pulse to the recording head. The data is recorded in a bipolar manner: that is, when buffers Z1a/b rise, Z1c/d fall, and vice versa.

This information is recorded directly on the tape. During playback, the raw waveform is fed to Z4a, an LF353 FET operational amplifier (a plug-in replacement for the more commonly available LM747, which can be substituted with some signal degradation). This amplifier is set up in an inverted configuration with high gain; it produces a strong waveform which is then fed into Z4b, configured as a high-gain 'clipping' or 'squaring' amplifier (contributed by diodes D1 and D2).

This output is stabilized and buffered by comparator Z5a, and fed to Z5b (Z5 is a simple LM 339 comparator), arranged as a TTL-level driver. Z3a, a three-state inverter, is connected directly to a TRS-80 data line.

Figure 9-7 provides drive status information. Z10e is hooked to the former cartridge on-off switch, informing the computer of the presence of a cartridge in the drive. The track select switches feed their 12-volt signals to Z10a-b, which report the track pair in use. The foil sensor triggers a flip-flop made up of Z8a/b, which latches the fact that the foil has passed, until the computer resets it via the RESET SPLICE line.

The unit is turned on from the front, and power is always applied to the electronics. When the program reads or writes to tape, the motor is turned on via data bit 5; for fast read search and write, the motor is activated by data bit 6. The splice status is reset via data bit 3, and tracks are changed via data bit 4. Writing to the deck is enabled by data bits 1 and 2 (for the upper and lower of the track pairs, respectively), and the actual data writing is done through data bit 0.

Addressing of port AA is provided by Z14a-d and Z13, and this signal is combined with the computer's OUT and IN signals by Z8c/d. All the input data is latched by Z12.



Figure 9-6. Schematic for 8-track storage system.



Figure 9-7. Schematic of tape player modification.


DO0
DO7
RDSS
Z3
Z5
Z4
Z7
Z1
Z2
Z6
H
C1
C2
C3
C4
C5
C6
C7
C8
100P
220P
220K
0.22
10/16
2.2K
10K
22K
470
220
+5
+12
DI0
DI1
DI2

Listing 9-4. 8-track load and save cartridge system.

```
10 CLS : REM * THIS PROGRAM PRINTS CURRENT 8-TRACK DRIVE STATUS
20 OUT85,16 : REM * START 8-TRACK DRIVE BY SETTING OUTPUT BIT 4
30 PRINT@0,"DATA 1:                 DATA 2:"; : REM * L & R TRACKS
40 PRINT@128,"TRACK NO.:"; : REM * CURRENT HEAD POSITION PROMPT
50 A=INP(85) : REM * GET DATA FROM 8-TRACK DRIVE AT PORT 55 HEX
60 PRINT@66,(A AND 128)/128; : REM * TEST FOR HIGH DATA BIT 7
70 PRINT@86,(A AND 1); : REM * TEST FOR HIGH DATA BIT 0 & PRINT
80 B=(A AND 120) : REM * 120 = 78HEX = 01111000 TRACK CONDITION
90 IFB=112THENPRINT@140,"1"; : REM * 01110000 = LO BIT 3 = TK1
100 IFB=104THENPRINT@140,"2"; : REM * 01101000 = LOW BIT 4 =TK2
110 IFB=88THENPRINT@140,"3"; : REM * 01011000 = LOW BIT 5 = TK3
120 IFB=56THENPRINT@140,"4"; : REM * 00111000 = LOW BIT 6 = TK4
130 IF(A AND 4)=4 THEN PRINT @ 256,"SPLICE DETECTED"; : GOTO190
140 IF(A AND 2)=2 THEN PRINT @ 320,"CARTRIDGE IS IN    " ELSE
    PRINT @ 320,"INSERT CARTRIDGE   ";
150 Q = RND(120) : REM * RANDOM TRACK SWITCH FOR TESTING ONLY
160 IF B=Q THEN OUT 85,80 ELSE 30 : REM * SWITCH TRACKS HERE
170 FOR N = 1 TO 100 : NEXT : OUT 85, 16 : REM * RESUME NORMAL
180 GOTO30 : REM * RANDOM TRACK SWITCH COMPLETE; BACK TO START
190 OUT85,0 : A$=INKEY$ : IFA$=""THEN190 : REM * OFF, THEN TEST
200 OUT85,16 : GOTO30 : REM * TURN BACK ON WHEN ANY KEY PRESSED
10 OUT254,2 : REM * HIGH-SPEED SELECT FOR TESTING PURPOSES ONLY
20 CLS : REM * THIS ROUTINE CHECKS TOTAL CURRENT 8-TRACK STATUS
30 Q=148 : OUT85,16 : REM * SET Q VALUE AND TURN ON TAPE DRIVE
40 A=INP(85) : REM * GET CURRENT STATUS OF TAPE DRIVE FROM PORT
50 B=(A AND 128)/128 : REM * GET VALUE AT DATA TRACK 1 (BIT 7)
60 C=(A AND 64)/64 : REM * GET VALUE AT TRACK POSN 4 (BIT 6)
70 D=(A AND 32)/32 : REM * GET VALUE AT TRACK POSN 3 (BIT 5)
80 E=(A AND 16)/16 : REM * GET VALUE AT TRACK POSN 2 (BIT 4)
90 F=(A AND 8)/8 : REM * GET VALUE AT TRACK POSN 1 (BIT 3)
100 G=(A AND 4)/4 : REM * GET VALUE OF SPLICE CONDITION (BIT 2)
110 IF G=1 THEN OUT 85,0 : GOSUB 220 : REM * TURN OFF IF SPLICE
120 H=(A AND 2)/2 : REM * GET VALUE IF CARTRIDGE IS IN (BIT 1)
130 I=A AND 1 : REM * GET VALUE AT DATA TRACK POSN TWO (BIT 0)
140 PRINT@Q,"07 06 05 06 03 02 01 00"; : REM * PRINT DATA HEAD
150 PRINT@Q+64,B;C;D;E;F;G;H;I : REM * PRINT VALUES CALCULATED
160 PRINT@(Q+192),"D  T  T  T  T  S  C  D "; : REM * PRINT SOME
170 PRINT@(Q+256),"A  R  R  R  R  P  A  A"; : REM *    PRETTY
180 PRINT@(Q+320),"T  K  K  K  K  L  R  T"; : REM *    WORDS
190 PRINT@(Q+384),"A  #  #  #  #  C  T  A"; : REM *    FOLLOW
200 PRINT@(Q+448),"1  4  3  2  1  E  N  0"; : REM *   STATUS.
210 GOTO40 : REM * AND REPEAT THE PROCESS AS THE TAPE CONTINUES
220 OUT 255,255 : OUT 255, 0 : REM * A LITTLE SCREEN SHAKING
230 A$=INKEY$ : IF A$="" THEN 220 : REM * TEST, LOOP IF NO CHAR
240 OUT85,24 : RETURN : REM * TAPE BACK ON, START PROCESS OVER
                  00100 ;####################################################
                  00110 ; SHORT 8-TRACK OPERATING SYSTEM FOR CONVERTED 8-TRACK
                  00120 ; TAPE DECK.  FORMAT:
                  00130 ; ON, FAST FORWARD, FIND SPLICE, WRITE ENABLE, WRITE
                  00140 ; 256 BYTES OF DIRECTORY ENTRY, LOOP UNTIL 10 ENTRIES ARE
                  00150 ; WRITTEN OR NUMBER TRANSFERRED FROM BASIC IS ACHIEVED.
                  00160 ; FILL OUT TRACK WITH FF'S, VERIFY WRITE (IF VERIFY FLAG
                  00170 ; IS ON), FIND SPLICE, CHANGE TRACKS, REPEAT PRyyESS FOR
                  00180 ; ALL FOUR TRACKS.
                  00190 ; DIRECTORY READ AT HIGH SPEED, ENTRIES ENTERED AT LOW
                  00200 ; SPEED IN 256-BYTE PACKETS.  EACH PACKET HAS A NUMBER
                  00210 ; WHICH IS STORED IN THE DIRECTORY.  NO DEFAULT ON TRACK
                  00220 ; OR DIRECTORY ENTRY IS ALLOWED.  DIRECTORY ENTRY #0 IS
                  00230 ; RESERVED FOR FREE PACKETS ON EACH TRACK AND SECTOR.
                  00240 ; *** NOTE:  THIS LISTING IS NOT A COMPLETE OPERATING
                  00250 ; SYSTEM.  IT CONTAINS A SAMPLE DIRECTORY FORMATTING AREA
                  00260 ; AND SAMPLE HIGH-SPEED TAPE READ/WRITE ROUTINES.  A FULL
                  00270 ; 8-TRACK OPERATING SYSTEM IS AVAILABLE; WRITE TO:
                  00280 ; MSB ELECTRONICS, MR#1 DRAWER 766, BARRE, VERMONT 05641
                  00290 ; OR DETAILS.  THE INFORMATION PRESENTED IN THIS LISTING
                  00300 ; IS FOR DEMONSTRATION, ALTHOUGH IT MAY BE ORGANIZED,
                  00310 ; TOGETHER WITH OTHER STANDARD SAVE/LOAD PARAMETERS, INTO
                  00320 ; A FULL OPERATING SYSTEM.  ***
                  00330 ; ####################################################
                  00340 ;
7000              00350         ORG     7000H
                  00360 ;
7000              00370 RDBYTE  EQU     $ .         ; ***** REASSIGN TO READ BYTE
7000              00380 WRBYTE  EQU     $           ; ***** REASSIGN TO WRITE BYTE
7000              00390 LEADER  EQU     $           ; ***** REASSIGN TO LEADER WRITE
7000              00400 LEADRD  EQU     $           ; ***** REASSIGN TO LEADER READ
0060              00410 DELAY   EQU     0060H              ; DELAY VALUE IN ROM
7000 0A           00420 HOWMNY  DEFB    100                ; 10 UNLESS BASIC XFER
7001 00           00430 VERFLG  DEFB    00H                ; TRANSFERRED FROM BASIC
0001              00440 VERFON  EQU     01H                ; STATUS REQUIRED BY TOS
0055              00450 PORT    EQU     55H                ; DEFINED AT 85 DECIMAL
0001              00460 WRITEN  EQU     01H                ; OI0 = HIGH FOR WR ENABL
0002              00470 WRITEA  EQU     02H                ; OI1 = HI/LO FOR WRITE A
0004              00480 WRITEB  EQU     04H                ; OI2 = HI/LO FOR WRITE B
0008              00490 RESSPL  EQU     08H                ; OI3 = HI TO RESET SPLCE
0010              00500 START   EQU     10H                ; OI4 = HIGH FOR MOTOR ON
0020              00510 FSTFWD  EQU     20H                ; OI5 = HIGH FOR FAST FWD
0040              00520 CHANGE  EQU     40H                ; OI6 = HIGH TO CHNGE TRK
0001              00530 READA   EQU     01H                ; OQ0 GOES HI/LO DATA A
0002              00540 CARTIN  EQU     02H                ; OQ1 GOES HIGH AT CARTIN
0004              00550 SPLICE  EQU     04H                ; OQ2 GOES HIGH AT SPLICE
0008              00560 TRACK0  EQU     08H                ; OQ3 GOES HIGH AT TRK 0
0010              00570 TRACK1  EQU     10H                ; OQ4 GOES HIGH A TRK 1
0020              00580 TRACK2  EQU     20H                ; OQ5 GOES HIGH AT TRK 2
0040              00590 TRACK3  EQU     40H                ; OQ6 GOES HIGH AT TRK 3
0080              00600 READB   EQU     80H                ; OQ7 GOES HI/LO DATA B
7002 00           00610 STATUS  DEFB    00H                ; COMPOSITE OF ABOVE
                  00620 ;
                  00630 ; BASIC PATCH HERE — USE CUSTOM INTERPRETER
                  00640 ;
                  00650 ; ####################################################
                  00660 ; START 8-TRACK DECK MOTOR RUNNING (GIVE IT ENOUGH TIME)
                  00670 ; ####################################################
                  00680 ;
7003 0E55         00690 AAAAAA  LD      C,PORT             ; START VALUE
7005 3E10         00700         LD      A,START            ; BITS SET TO START
```

Listing Continued . . .

Figure 9- 8 presents the optional decoding of a ROM to contain the 8-track operating system. Notice that the decoding of the addresses is incomplete, so that data from **37C0** to **37FF** must not be entered into the ROM to avoid bus conflict. The ROM should remain in its erased (all one's) condition in that memory area.

Listing 9-4 is an operating system for the 8-track storage system. It is made up of four major sections:

1. **Initialization**. Patching the operating system into the BASIC interpreter.
2. **Formatting**. The directory is set up past the splice on track zero in fast-forward mode. Each track is then written with program #1 headers. Because the tape is sequential, this is not a true disk-style directory. Instead, the directory stores the order and track number for each program, so that the correct track may be searched at high speed for its leader.
3. **Load Module**. This accepts the command, checks for correct syntax and program type, activates the tape deck and searches for the program.
4. **Save Module**. This module also accepts the command, checks syntax and program type, and writes the program to tape. The directory is updated.

The most interesting aspect of the software is the method used for recording the data. After a start level, a low is written to tape. Each subsequent bit changes the level either once (a zero) or twice (a one). Clock bits are not used in this scheme.

The operating system presented here is very basic, allowing only the elementary program save and load functions. However, data of all types may be stored in the system with additions to the software via additional commands.

Several problems may initially be encountered in using this system:

1. System does not respond. Make sure power is on; check for power to track lights. One should be lit. Find a cartridge which does not have its foil splice visible, insert the cartridge, switch to track 1 and PRINT INP (170). The value returned (in binary) should be x001000x. The x's are either one or zero, depending on the status of the data read outputs. Remove the cartridge. The value will change to x101000x. Switch to track 2, and replace the cartridge. Now it should read x000100x.

Continued Listing

```
7007 F620           OR      FSTFWO          ; GET INTO HIGH GEAR
7009 320270         LO      (STATUS),A      ; PUT IT INTO PLACE
700C 06FF           LO      8,OFFH          ; GET LONG LOOPS
700E E079   GOING   OUT     (C),A           ; START 8 TRACK
7010 10FC           OJNZ    GOING           ; MANY TIMES FOR SURE
            ;
            ; ################################################
            ;MOVE TO TRACK ZERO, CHECKING STATUS OF TRACK EACH TIME
            ; ################################################
            ;
7012 1600           LO      0,0             ; TRACK VALUE TO CHECK
7014 E078   LOOP1   IN      A,(C)           ; CHECK TRACK VALUE
7016 8A             CP      0               ; AGAINST VALUE WANTEO
7017 2800           JR      Z,JUMP1         ; GO IF TRACK = 0
7019 3E40           LO      A,CHANGE        ; TRACK CHANGE VALUE
7018 2A0270         LO      HL,(STATUS)     ; GET CURRENT STATUS
701E 84             OR      H               ; CHECK PREVIOUS INFO
701F 320270         LO      (STATUS),A      ; ANO PUT INTO PLACE
7022 E079           OUT     (C),A           ; CHANGE TRACK VALUE
7024 18EE           JR      LOOP1           ; GO 8ACK UNTIL TRK = 0
            ;
            ; ################################################
            ; FINO ENO-OF-TAPE SPLICE, ANO OELAY TO GET PAST SPLICE
            ; ################################################
            ;
7026 E078   JUMP1   IN      A,(C)           ; GET VALUE FROM PORT
7028 E604           ANO     SPLICE          ; CLEAR ALL OTHER VALUES
702A FE04           CP      SPLICE          ; CHECK IF SPLICE OET'O
702C 20F8           JR      NZ,JUMP1        ; 8ACK UNTIL FOUNO
702E E078   JUMP1A  IN      A,(C)           ; GET VALUE FROM PORT
7030 E604           ANO     SPLICE          ; CLEAR ALL OTHER VALUES
7032 FE04           CP      SPLICE          ; CHECK IF STILL SPLICE
7034 28F8           JR      Z,JUMP1A        ; 8ACK UNTIL SPLICE OVER
7036 010010         LO      8C,1000H        ; GET OELAY VALUE
7039 C06000         CALL    OELAY           ; OELAY TILL GOOO TAPE
            ;
            ; ################################################
            ; WRITE LEAOER (NOTE:  LEAOER WRITE ROUTINE NOT INCLUOEO)
            ; ################################################
            ;
703C C00070         CALL    LEAOER          ; WRITE LEAOER
            ;
            ; ################################################
            ; FORMAT OIRECTORY (NOTE:  THIS METHOO IS FOR EXAMPLE)
            ; ################################################
            ;
703F 210070         LO      HL,HOWMNY       ; HOW MANY OIR ENTRIES?
7042 AF             XOR     A               ; START WITH ENTRY #0
7043 06FF   LOOP3   LO      8,OFFH          ; 256 8YTES TO WRITE
7045 C00070 LOOP2   CALL    WR8YTE          ; WRITE THEM IN PLACE
7048 F5             PUSH    AF              ; SAVE ACCUM TEMPORARILY
7049 E078           IN      A,(C)           ; GET VALUE FROM OEVICE
7048 E604           ANO     SPLICE          ; CLEAR ALL OTHER VALUES
7040 FE04           CP      SPLICE          ; SEE IF SPLICE HIT
704F 2802           JR      Z,JMPX          ; GO IF SPLICE IS HIT
7051 10F2           OJNZ    LOOP2           ; ELSE ON TO NEXT 8YTE
7053 F1     JMPX    POP     AF              ; RESTORE ENTRY VALUE
7054 3C             INC     A               ; UP TO NEXT ENTRY
7055 8E             CP      (HL)            ; LAST ENTRY COMPLETEO?
7056 30E8           JR      NC,LOOP3        ; OUT IF NOT OONE
            ;
            ; ################################################
            ; FILL OUT TRACK WITH A SINGLE VALUE (AGAIN, OPTIONAL)
            ; ################################################
            ;
7058 3EFF   LOOP4   LO      A,OFFH          ; WHEN OONE GET ALL FF'S
705A C00070         CALL    WRBYTE          ; WRITE FF 8YTE TO TAPE
7050 E078           IN      A,(C)           ; CHECK CONTENTS OF PORT
705F E604           ANO     SPLICE          ; MASK OUT OTHER 8ITS
7061 FE04           CP      SPLICE          ; CHECK IF TO SPLICE
7063 20F3           JR      NZ,LOOP4        ; IF NOT KEEP WRITING
            ;
            ; ################################################
            ; GET NEXT TRACK VALUE ANO GET TRACK FORMATTING READY
            ; ################################################
            ;
7065 14             INC     O               ; GET NEXT TRACK VALUE
7066 7A             LO      A,O             ; CHECK CURRENT VALUE
7067 FE04           CP      4               ; IS IT FOURTH TRACK?
7069 2819           JR      Z,JUMP2         ; IF NOT THEN 8ACK
            ;
            ; ################################################
            ; FORMAT NEXT TRACK, ANO CONTINUE UNTIL PROCESS COMPLETE
            ; ################################################
            ;
7068 3E40           LO      A,CHANGE        ; GET CHANGE TRACK VALUE
7060 2A0270         LO      HL,(STATUS)     ; GET CURRENT STATUS
7070 84             OR      H               ; STATUS PLUS CHANGE
7071 E079           OUT     (C),A           ; ANO CHANGE THE TRACK
7073 3E40           LO      A,CHANGE        ; GET CHANGE TRACK AGAIN
7075 2F             CPL                     ; SWITCH THE 8ITS
7076 2A0270         LO      HL,(STATUS)     ; GET THE STATUS
7079 A4             ANO     H               ; STATUS PLUS CHANGE
707A 010002         LO      8C,200H         ; GET OELAY VALUE
7070 C06000         CALL    OELAY           ; ANO INVOKE THE OELAY
7080 E079           OUT     (C),A           ; ANO TURN IT OFF
7082 18A2           JR      JUMP1           ; ANO GO 8ACK FOR MORE
            ;
            ; ################################################
            ; CHECK IF VERIFY FLAG IS ON (NOTE: AOO AS 8ASIC COMMANO)
            ; ################################################
            ;
7084 3A0170 JUMP2   LO      A,(VERFLG)      ; STATUS OF VERIFY FLAG
7087 FE01           CP      VERFON          ; SEE IF FLAG IS ON
7089 2036           JR      NZ,JUMP3        ; IF NOT THEN SKIP PAST
            ;
            ; ################################################
            ; MOVE TO THE FIRST TRACK, CHECK EACH AS IT PROGRESSES
            ; ################################################
            ;
7088 1600           LO      0,0             ; ST COUNTER TO ZERO
7080 E078   JUMP4   IN      A,(C)           ; GET STATUS FROM OECK
708F 8A             CP      0               ; CHECK AGAINST TRK 0
7090 2819           JR      Z,JUMP5         ; IF.AT ZERO, THEN GO
7082 3E40           LD      A,CHANGE        ; ELSE 8EGIN TO CHANGE
7084 2A0270         LD      HL,(STATUS)     ; GET VALUE FROM STATUS
```

Listing Continued . . .

2. Tracks do not switch. Check wiring to the solenoid, and that the 75452 is wired correctly. Listen to hear if the solenoid attempts to react (a light click or start). Remove the 75452 from its socket and short the free lead of the solenoid to ground. It should switch. Replace the 75452 if necessary.

3. Programs do not load. If programs do not load at all, check the cartridge on an audio deck to see if something has been written. If not, go on to #4 below. If so, listen for occasional changes in pitch as the machine switches from fast forward to normal. Lengthen the speed change wait period in the program if you can hear the pitch slide as it restarts at a new level. If a loading message is displayed, but an error is detected, try to read from another track. Tracks 1a and 4b are at the edge of the tape, and lower-quality tapes may drop out occasionally in this area. The head may be badly misaligned and not make good contact with the tape. This can be heard as shifting or slewing in the sound. Adjust the Phillips alignment screw on the head to match a prerecorded commercial tape of good quality.

4. Programs do not save. Begin the program-saving process, and place the signal lead of a small amp against one lead of the recording head. If the signal is present, the program should be saving. If not, check the wiring of the buffer IC's, which may not be letting the signal through. Also check that the software is entered correctly, and that a signal is actually being sent to the device (correct connection of the write line, and proper wiring of the address decoding and data latch). If the motor turns on and switches tracks properly, the signal is probably being held up by incorrectly wired buffers to the recording head.

5. Motor speed does not change. Make sure that the third lead from the motor is being switched to ground, not positive voltage. This lead reacts best when switched below ground, and ground potential is its minimum position. If you have substituted another solid-state switch for the one shown, make sure it goes to full ground potential when switched in place.



Craig playback deck disassembled. Front panel, main frame and feet are maintained, but switch panel, playback electronics, wires, and buttons are discarded. Front buttons may be kept for appearance.

Continued Listing

```
7097 B4        01B70          OR      H                 ; AND CHECK STATUS VAL
709B E079      01B80          OUT     (C),A             ; AND SEND OUT CHANGE
709A 3E40      01B90          LD      A,CHANGE          ; GET VALUE AGAIN
709C 2F        01900          CPL                       ; REVERSE THE BITS
709D 2A0270    01910          LD      HL,(STATUS)       ; GET VALUE FROM STATUS
70A0 A4        01920          AND     H                 ; GET VALUE FROM STATUS
70A1 010002    01930          LD      BC,200H           ; GET DELAY VALUE
70A4 CD6000    01940          CALL    DELAY             ; CALL DELAY IN ROM
70A7 E079      01950          OUT     (C),A             ; AND SEND OUT CHANGE
70A9 18E2      01960          JR      JUMP4             ; AND GO DO THE REST
               01970 ;
               01980 ; #######################################################
               01990 ; VERIFY THE TAPE FORMATTING AND QUALITY IF FLAG IS ON
               02000 ; #######################################################
               02010 ;
70AB 1E00      02020 JUMP5    LD      E,0               ; PACKET NUMBER TO START
70AD 06FF      02030 LOOP7    LD      B,0FFH            ; BYTE TO VERIFY WITH
70AF CD0070    02040          CALL    LEADRD            ; GET SYNC AND READ LEADR
70B2 CD0070    02050 LOOP6    CALL    RDBYTE            ; BEGIN READING THE BYTES
70B5 BB        02060          CP      E                 ; AND CHECK FORMAT INFO
70B6 202B      02070          JR      NZ,VERERR         ; IF NOT CORRECT, ERROR
70B8 10FB      02080          DJNZ    LOOP6             ; AND GO BACK UNTIL DONE
70BA 1C        02090          INC     E                 ; GO TO NEXT PACKET
70BB 3A0070    02100          LD      A,(HOWMNY)        ; CHECK IF FORMAT DONE
70BE BB        02110          CP      E                 ; BY GETTING PACKET #
70BF 20EC      02120          JR      NZ,LOOP7          ; BACK IF NOT DONE
               02130 ;
               02140 ; #######################################################
               02150 ; STOP THE TAPE MACHINE AND CLEAR OUT ALL STATUS INFO
               02160 ; #######################################################
               02170 ;
70C1 AF        02180 JUMP3    XOR     A                 ; CLEAR ACCUM TO ZERO
70C2 320270    02190          LD      (STATUS),A        ; PUT IN STATUS LOCATION
70C5 E079      02200          OUT     (C),A             ; AND SEND IT OUT PORT
               02210 ;
               02220 ; #######################################################
               02230 ; GET AND DISPLAY FORMAT COMPLETE MESSAGE (OR ERROR MSG)
               02240 ; #######################################################
               02250 ;
70C7 210070    02260          LD      HL,MESG01         ; GET THE OKAY MESSAGE
70CA CDA728    02270          CALL    28A7H             ; LEVEL II DISPLAY ROUT.
70CD C37B10    02280          JP      107BH             ; BACK TO INTERPRETER
70D0 46        02290 MESG01   DEFM    'FORMATTING COMPLETE'
70E3 21EC70    02300 VERERR   LD      HL,MESG02         ; VERIFY ERROR MESSAGE
70E6 CDA728    02310          CALL    28A7H             ; DISPLAY SUBROUTINE
70E9 C3CC06    02320          JP      06CCH             ; BASIC COMMAND LEVEL
70EC 46        02330 MESG02   DEFM    'FORMAT ERROR'
               02340 ;
               02350 ; #######################################################
               02360 ; THESE ROUTINES MAY BE CALLED WITH THE /LOAD COMMANDS OR
               02370 ; THE /SAVE COMMANDS, AS WELL AS THE FORMATTING ABOVE.
               02380 ; NOTE:  THESE ROUTINES USE AN EXCLUSIVE-OR METHOD OF
```

Listing Continued . . .

Construction and Checkout

Since I recommend wire-wrapping the projects in this book, there are some different considerations when wrapping all the resistors and capacitors necessary for this project. Wire-wrapping is done best when there are sharp, square pins on which to wrap; since resistors and capacitors have round leads, it is best to insert these parts into sockets. Not only will the wrapping be more firmly attached, but the parts will not fall out when you are turning the board over during construction.

Before beginning construction, note that the transformer installed in the Craig recorder is marginal; ideally, it should be replaced with a 12 volt, 1.5 amp transformer of the type sold by Radio Shack. This will fit, though not comfortably, in the present transformer's location. The center tap is not used.

Because there are mechanical and inductive parts in this device, a great deal of electromagnetic noise can be produced. Be sure, then, to do the following:

1. Use bypass capacitors (.01 mF or so) between power and ground on every integrated circuit.
2. Use bypass capacitors (.01 mF) on the 75452 peripheral driver chips as noted, as well as diodes (hobbyist 1N914's are fine) across the three relay coils. Leave the diode already present on the track change solenoid. *Don't* skip these parts; they make the difference between a working system and a continuous return to MEMORY SIZE.
3. Use a central grounding point for all wires on the circuit board, and another central point for all wires on the drive. Don't weave wires from one IC to another.
4. The resistors at the inputs of the CMOS chips (the 80C96 and 80C98s) are vital for a reliable signal, and also prevent damage to the chips themselves.
5. The wires leading to the recording head should be twisted or shielded to prevent picking up extraneous signals. Remember also that the connections of the top and bottom pairs of pins on the head should be the same.

Continued Listing

```
                 02390 ; RECORDING, WHICH WILL FUNCTION WITH A OIRECT OIGITAL
                 02400 ; RECORDING SITUATION SUCH AS THE B-TRACK OEVICE.  FOR
                 02410 ; FURTHER INFORMATION ON ITS OPERATION, ASK FOR THE
                 02420 ; OHIO SCIENTIFIC TAPE WAFER INTERFACE, SOLO 8Y MS8
                 02430 ; ELECTRONICS (AOORESS A8OVE), ANO EXAMINE THE CODE.
                 02440 ; ####################################################
                 02450 ;
40F9             02460 BOTTOM  EQU     40F9H            ; BOTTOM OF 8ASIC PROGRAM
06CC             02470 8ASIC   EQU     06CCH            ; RETURN TO READY MODE
                 02480 ;
70F8 F3          02490 ENTER   OI                       ; KILL THEM SUCKERS
70F9 2AF940      02500         LO      HL,(8OTTOM)      ; GET FIRST PROGRAM LOC'N
70FC 3A3040      02510         LO      A,(4030H)        ; VALUE IN THE MASK
70FF E6FC        02520         ANO     OFCH             ; SET 8IT TO ZERO
7101 323040      02530         LO      (4030H),A        ; PUT 8ACK INTO LATCH
7104 5F          02540         LO      E,A              ; WILL 8E USED A LOT
                 02550 ; ------------------------------------------------
7105 7E          02560 NEXT    LO      A,(HL)           ; SPECIAL TEST (EXAMPLE)
7106 57          02570         LO      O,A              ; THIS IS THE 8IG 8UMPER
7107 0608        02580         LO      8,8              ; NUMBER OF 8ITS TO WRITE
7109 3E01        02590         LO      A,1              ; THIS IS THE START BIT
7108 83          02600         OR      E                ; GET PROPER LATCH MASK
710C 03FF        02610         OUT     (OFFH),A         ; WRITE OUT START LEVEL
710E C04371      02620         CALL    OELAY1           ; WRITE A START OELAY
7111 AF          02630         XOR     A                ; SET UP A WITH O I/O 8IT
7112 B3          02640         OR      E                ; GET PROPER LATCH MASK
7113 03FF        02650         OUT     (OFFH),A         ; WRITE OUT STARTING EOGE
                 02660 ;
                 02670 ; ####################################################
                 02680 ; AOOING 66 T-STATES HERE TO TOTAL 95 US
                 02690 ; ####################################################
                 02700 ;
7115 00E5        02710         PUSH    IX               ; 15 T-STATES
7117 00E1        02720         POP     IX               ; 14 T-STATES
7119 00E5        02730         PUSH    IX               ; 15 T-STATES
7118 00E1        02740         POP     IX               ; 14 T-STATES
7110 00          02750         NOP                      ; 4  T-STATES
711E 00          02760         NOP                      ; 4  T-STATES
                 02770 ; ------------------------------------------------
                 02780 ;
                 02790 ; ####################################################
                 02800 ; THIS IS SET UP FOR 3300 BAUO
                 02810 ; TOTAL LOOP TIME PER 8IT SHOULO 8E 300 US
                 02820 ; TOTAL T-STATES FOR EACH 8IT LOOP = 169 = 95 US
                 02830 ; TOTAL T-STATES FOR 8IT OELAY LOOPS AT 0060 NOTEO 8ELOW
                 02840 ; ####################################################
                 02850 ;
711F C04E71      02860 LOOP    CALL    OELAY2           ; WRITE A NORMAL OELAY
                 02870 ; ................................................
7122 AA          02BB0         XOR     O                ; TEST THE FIRST 8IT
7123 E601        02890         ANO     1                ; MASK OUT OTHER D 8ITS
7125 F5          02900         PUSH    AF               ; SAVE THE VALUE
7126 83          02910         OR      E                ; VALUE OF LATCH MASK
7127 03FF        02920         OUT     (OFFH),A         ; WRITE IT
                 02930 ; ................................................
7129 F1          02940         POP     AF               ; ORIGINAL VALUE 8ACK
712A 2F          02950         CPL                      ; REVERSE THE 8IT
7128 E601        02960         ANO     1                ; MASK OUT ALL BUT ONE
7120 C04E71      02970         CALL    OELAY2           ; WRITE A NORMAL OELAY
7130 F5          02980         PUSH    AF               ; SAVE THE PROPER 8IT
7131 B3          02990         OR      E                ; AGAIN GET THE MASK
7132 220000      03000         LO      (0000),HL        ; NEEO OELAY TIME
7135 00          03010         NOP                      ; 8IT MORE OELAY TIME
7136 03FF        03080         OUT     (OFFH),A         ; WRITE IT
                 03090 ; ................................................
7138 F1          03100         POP     AF               ; GET ORIGINAL BITS 8ACK
7139 CB0A        03110         RRC     O                ; ORIENT  TO NEXT BIT
7138 10E2        03120         OJNZ    LOOP             ; WRITE OUT 8 8ITS
                 03130 ; ................................................
                 03140 ;       XOR     A                ; CLEAR ACC. TO ZERO
                 03150 ;       OR      E                ; GET MASK FROM 403D
                 03160 ;       OUT     (OFFH),A         ; SENO OUT ZERO BIT
7130 C04E71      03170         CALL    OELAY2           ; SPACE OUT LAST BIT TOO
                 03180 ;
7140 23          03190         INC     HL               ; GET NEXT MEMORY LOC'N
                 03200 ;
                 03210 ; ####################################################
                 03220 ; PUT TESTING FOR MEMTOP HERE
                 03230 ; ####################################################
                 03240 ;
                 03250 ;       LO      A,H              ; CURRENT MEMORY STATUS
                 03260 ;       CP      40H              ; ENO? (EXAMPLE ONLY!!)
7141 20C2        03270         JR      NZ,NEXT          ; GO BACK IF NOT OONE
                 03280 ;       JP      06CC             ; READY (USE RETURN!)
                 03290 ;
7143 F5          03300 DELAY1  PUSH    AF               ; SAVE AF REGISTERS
7144 C5          03310         PUSH    8C               ; SAVE BC REGISTERS
7145 012800      03320         LO      8C,28H           ; GET OELAY VALUE
                 03330 ;
                 03340 ; ####################################################
                 03350 ; LINE ABOVE COMPLETES A TOTAL 1000 US OELAY LOOP
                 03360 ; ####################################################
                 03370 ;
7148 C06000      03380         CALL    0060H            ; MAKE A OELAY
714B C1          03390         POP     8C               ; RESTORE BC REGISTERS
714C F1          03400         POP     AF               ; RESTORE AF REGISTERS
7140 C9          03410         RET                      ; 8ACK TO MAIN ROUTINE
                 03420 ;
714E F5          03430 DELAY2  PUSH    AF               ; SAVE AF REGISTERS
714F C5          03440         PUSH    BC               ; SAVE 8C REGISTERS
7150 010300      03450         LO      BC,03H           ; GET SHORTER OELAY VALUE
                 03460 ;
                 03470 ; ####################################################
                 03480 ; LINE A8OVE COMPLETES AT TOTAL 205 US OELAY LOOP
                 03490 ; ####################################################
                 03500 ;
7153 C06000      03510         CALL    0060H            ; MAKE A OELAY
7156 C1          03520         POP     8C               ; RESTORE BC REGISTERS
7157 F1          03530         POP     AF               ; RESTORE AF REGISTERS
7158 C9          03540         RET                      ; 8ACK TO MAIN ROUTINE
                 03550 ;
                 03560 ; ####################################################
70F8             03570         ENO     ENTER
00000 TOTAL ERRORS
21490  TEXT AREA BYTES LEFT
```

Position sockets as close together as possible so the final board will fit into the tape drive's case. Fill the board with sockets and parts, and test its size before beginning the wire-wrapping.

Wire-wrap all connections completely before installing the 80C96 and 80C98 ICs. Because they are static-sensitive CMOS, they can be damaged by improper handling or application of power to partly-connected ICs.

When construction is complete, install the ICs, connect the unit to the TRS-80, and apply power.



Detail view of Craig mechanics. Track change mechanism is operated by a spinning cog on the drive capstan (lower right). Four track change lights are illuminated by switch contacts to the rear of the playback head.

```
AAAAAA 7003 00690
8ASIC  06CC 02470
8OTTOM 40F9 02460   02500
CARTIN 0002 00540
CHANGE 0040 00520   00850 01560 01600 01B50 01890
OELAY  0060 00410   01050 01650 01940
OELAY1 7143 03300   02620
OELAY2 714E 03430   02860 02970 03170
ENTER  70F8 02490   03570
FSTFWO 0020 00510   00710
GOING  700E 00740   00750
HOWMNY 7000 00420   01170 02100
JMPX   7053 01270   01250
JUMP1  7026 00960   00840 00990 01670
JUMP1A 702E 01000   01030
JUMP2  70B4 01730   01500
JUMP3  70C1 02180   01750
JUMP4  70B0 01820   01960
JUMP5  70AB 02020   01B40
LEAOER 7000 00390   01110
LEAORO 7000 00400   02040
LOOP   711F 02860   03120
LOOP1  7014 00820   00900
LOOP2  7045 01200   01260
LOOP3  7043 01190   01300
LOOP4  705B 01360   01410
LOOP6  70B2 02050   02080
LOOP7  70A0 02030   02120
MESG01 7000 02290   02260
MESG02 70EC 02330   02300
NEXT   7105 02560   03270
PORT   0055 00450   00690
ROBYTE 7000 00370   02050
REAOA  0001 00530
REAO8  0080 00600
RESSPL 0008 00490
SPLICE 0004 00550   00970 00980 01010 01020 01230 01240 01390
                    01400
START  0010 00500   00700
STATUS 7002 00610   00720 00860 00880 01570 01620 01860 01910
                    02190
TRACK0 0008 00560
TRACK1 0010 00570
TRACK2 0020 00580
TRACK3 0040 00590
VERERR 70E3 02300   02070
VERFLG 7001 00430   01730
VERFON 0001 00440   01740
WRBYTE 7000 00380   01200 01370
WRITEA 0002 00470
WRITEB 0004 00480
WRITEN 0001 00460
```

10

And Now It's Broken

It is not inevitable that your TRS-80 will fail during your lifetime, but there's always that chance. And if it happens, there's no reason to truck the computer down to the nearby Cost-a-Buck repair center. Do it yourself. This chapter will present the most likely failures or dilemmas you may encounter with your TRS-80, including:

Setting up a reliable, crash-free environment in a typically casual home.

Curing memory crashes in the CPU or the expansion interface, and replacing failed memory.

Solving the garbage-on-screen power-up failure.

Discovering the many sources of mysterious program crashes and keyboard lockup, and how to cure them.

Aligning your video display to cure images off-screen, tearing or jitter.

How program bugs can look like hardware failures, and vice versa.

'Routine' maintenance – the hidden cure for many failures.

Handling the computer and its peripherals.

Overview of difficulties in disk drivers, cables, cassette devices, printers, RS-232 boards, and other add-ons.

A New Keyboard Cable

Virtually every modification to the TRS-80 contains a warning like this: 'Carefully open the case, and carefully take out the unit then carefully spread it out. Work carefully so as not to bust the keyboard cable'. So what's with the cable that makes it so fragile? The connections to the computer boards seem secure, but if you look carefully at the cable itself, you will see that it is made up of flat copper bands inside an insulating strip. The bands themselves are strong, and the connections to the computer are strong.

The problem occurs at the point where the copper bands are clamped to the connectors that attach to the circuit board. Hairline cracks develop in the copper bands, separating them almost invisibly from the connecting pins. The only evidence of these cracks comes when odd combinations of letters appear sporadically while you are typing.

If you plan to open the machine more than a half dozen times, you should replace the conection, with a 20-wire multiconductor cable or very flexible single conductor phono cartridge wire.

First, cut the present cable off with shears, cutting at the point where the copper bands meet the connectors. Now, with generous amounts of solder-wick, remove the 40



Replacing the keyboard cable: *Solder-wick and flux cleaner are used to remove all traces of the old connection cable.*



Replacing the keyboard cable: A new flexible cable is attached to both boards. A removable cable and connector can be used, but the permanent flexible cable serves well enough once most modifications have been made.

connectors on the keyboard and CPU board. Make sure all the copper is out of the holes, and clean what is surely to be a mess with flux remover, then buff the solder so new wires will slip easily through the holes.

The new cable can be six inches long or more without affecting the operation of the unit. My own added keyboard, which is wired into place in the same manner as the original, has a 20 foot cable and suffers no ill effects or program crashes. Cut and strip no more than one quarter inch of insulation off each end, and tin all 40 ends.

Tinning is the process of running some hot solder onto the wire to prepare it for easy soldering to the board. The wire will remain the same diameter, the solder should not lump up, but will become smooth, hard and shiny with a solder coating. This will allow the wire to pass easily through the holes without random strands sticking out sideways and shorting against the neighboring connection. If the insulation creeps back from the heat, finish tinning all the ends and then clip them back to one quarter inch.

Pass the multiconductor through all the holes in advance, and secure it temporarily with masking tape or other tape not affected by warmth. Getting all the wires through can be tricky, but accept the absurdity of the process in advance; outsiders tend to burst into laughter at the sight of a grown adult trying to thread 20 needles simultaneously, so if you can't take a joke, do this with the door locked.

When all the wires are attached to either the keyboard or the CPU board (I recommend the keyboard first because it is lighter), check for shorts, then thread the cable through the other board. Solder, then look carefully for shorts before applying the power; both five volts and ground run through the cable, so be sure everything is well.

Apply power. All characters should work properly, and no odd combinations of letters should be produced. If the power LED does not come on, either a connection was left off or you have a short. Power off immediately, and check again. If letters are missing, a connection was probably not made. If odd combinations of letters appear, you probably have a broken wire. If incorrect letters appear, you have switched wires. Once it's all working, you can ignore those 'carefully . . .' warnings and concentrate on the modifications to be made.

Home and Small Business Environments

Computers are designed in laboratories, tested in laboratories, examined by engineers and run by programmers. There could hardly be a more unlikely manner of producing an appliance-type product like the TRS-80. When you unpack the home computer and plug it in, you begin a torture test unimagined by the professionals in their sleek, air conditioned factories.

Below is a computer environment quick quiz; if you answer 'yes' to any question, your TRS could be in trouble. The more 'yesses', the more potentials for disaster:

- Your computer and peripherals are plugged into extension cords or cube-taps.
- A refrigerator, toaster, water pump, washer, dryer, or other large appliance is on the same fuse or breaker circuit as your computer.
- You have an electric mixer, blender, or food processor which is used when the computer is used.
- You have an electric drill, jigsaw, or table saw which is used when the computer is used.
- Your computer table desk lamp is a push-on and hold fluorescent type.
- You use your computer on or near a television set while the tv is turned on.
- Your computer is used in the kitchen or shop, you or a family member smokes, or you heat with wood or coal.
- You have fur-bearing animals in the house near your computer, especially cats.
- Your power is supplied by a rural cooperative, or is generated by a local power company especially with low-head hydropower systems.
- You live in an industrial area where heavy electrical equipment (winches, cranes) is used.
- Your electrical thermostat is located near the computer.
- Your home is especially dry, and you do not use a humidifier.
- You live in a coastal area, or by a salt-water lake.
- Your computer area is located near a railroad or by a highway traveled by heavy trucks.
- You move your computer while it is on.

Chances are you've got at least one check mark on the list above. Here are some solutions to these environmental problems:

1. Plug your computer directly into a wall outlet, or use a commercial 'power strip'.
2. Make sure that the computer is on a single-appliance circuit, even though it uses very little power.
3. Brush-motor electrical appliances like mixers and drills create an enormous amount of electrical noise. Reach a compromise with the culinary artist or the shop craftsperson to use those tools at some other time, or at least far away from the computer.
4. Use incandescent lamps, which send out virtually no electrical hash, and get rid of the fluorescent ones. Don't use a television for a computer table, because it creates heavy electromagnetic fields. And move the computer or the thermostat; there's a tremendous electrical noise jolt transmitted when that thermostat turns on.
5. Keep smoke and grease of all kinds out of your computer's atmosphere, as well as animal (and people) hair. Tape and disk drives hate the stuff, and cables, connector, and keys build up greasy mudpiles because of them.
6. If your power is unsteady because of an inept or unconcerned power company, or because local industry unexpectedly drains a large amount of power, you will have to install some sort of power regulator. Types such as Solatron, Mayday, and Topaz provide different qualities of regulation, at corresponding costs (see Appendix).
7. Use a humidifier, or place pans of water on radiators or stoves if you house is especially dry in winter, because static electricity is quite powerful. If you live in a salt-air atmosphere, air-condition your computer area during warm, humid days. Salt air corrodes cables and connections.
8. If railroads or trucks are nearby, cushion the computer. Vibration can cause noise in cables and especially the expansion box, and make disk reading and writing very failure-prone. Likewise, moving the computer (or even just pulling or straining the expansion or peripheral cables) can create bursts of electrical noise through the computer. Don't do it. Interestingly, even

pushing away a hard chair that vibrates on a linoleum or hardwood floor can cause disk read/write errors. And don't forget the dummy plug for CTR-41 tape recorders when saving programs!

The home and small business environment is not often conducive to these suggestions, and some of them may not be necessary, depending on other factors. If you maintain your cables, edge card connectors, keyboards, etc., and keep your computer cushioned and seated on a conductive tabletop, you've gone a long way to increasing reliability.

Furthermore, merely thinking of your micrcomputer in the same terms that used to be reserved for larger computers in the past (COMPUTER ROOM! NO SMOKING! . . . CAUTION! SENSITIVE ELECTRONIC EQUIPMENT! . . . NO FOOD OR DRINK IN THIS ROOM!), then you have the right idea. Electronically, your TRS-80 can take a great deal of abuse and still function. But this abuse cannot take place *while the computer is running.* And that is the clue: treat your operating computer as if you were paying $50 an hour in time-sharing charges.

When the Memory Crashes

In early TRS-80's, memory crashes were the most prominent sort of failure. The type of memories used were the culprit, partly because of expansion box design problems, but especially because an unusual condition called the 'soft error' had not then been diagnosed.

The 'soft error' was the tendency of a perfectly good program to crash with some error message when no such error was present. A simple CONTinue command would restore the system. These errors were caused by the internal structure of the memory chips themselves, which, because they are 'dynamic', use a peculiar and surprising principle for their operation.

Memories maintain information. That is their job. 'Static' memories retain information so long as the power is applied to the computer. 'Dynamic' memories, the type used in the TRS-80, retain their information for only a few thousandths of a second, requiring a electronic prodding, called *refresh,* to remember their data. They depend on their internal capacitance, acting much like a leaky tire.

In the early days, this odd way of maintaining memory resulted in occasional erratic behavior, sometimes because the chip itself was flukey, and sometimes because normal low-level radioactive alpha-decay, *present right on the base of the chip,* could knock a memory bit from one state to another. This radioactivity is so delicate that a single sheet of paper can stop it. So this memory failure would occur only when the radioactive alpha particle actually struck a junction, and only when that junction was struck at precisely the right billionth of a second. Newer memories use a 'cool' base which does not emit alpha radioactivity, and so this rather bizarre problem has finally disappeared.

But memory crashes still occur, and they come in a few major forms:

Temporary crashes due to electrical noise in the vicinity of the computer.

Temporary crashes in the expansion interface due to a badly attached or otherwise noisy set of refresh lines.

Temporary crashes due to improperly seated or corroding memory chips.

Permanent crashes due to bad memory chips.

Repairable crashes due to a damage to one of the three lines responsible for memory refresh.

Electrical storms. I'll digress just a moment on this one. During a summer meeting of the Vermont Computer Guild, an electrical storm approached rapidly. We began to engage in a sly but nervous game of electronic chicken, leaving our micros not only attached to the power, but running! Naturally, that was too much of an invitation to Mom Nature, who zapped our very power line with a basketful of megavolts. My TRS-80 kept working; another hung, but reset. An Apple winked and sighed, and its memory cleared. A KIM turned tail completely, taking with it video routines and all. And the expensive DEC PDP/11 was broiled, losing more than a handful of expensive chips. Moral: You know it.

Also, there are crashes which appear to be memory crashes when they are in fact otherwise. Among these:

A wayward program containing errors in PEEK or POKE statements, or machine language subroutines.

A damaged CPU chip or blown buffer chip.

A cracked circuit board trace, solder ball, or solder splash.

Cleaning the Edge Connectors

The expansion connector on the back of the CPU, and the various ports around the expansion interface, were all manufactured using a solder coating instead of gold plating. Because solder is lead, and lead tends to corrode badly, these connections will inevitably get electrically noisy.

Cleaning them is quite easy, and should be done, depending on your environment, from as often as weekly to a minimum of monthly.

Turn the equipment off and remove all cables. Check the edges of the cables for internal bend pins, hairs, or other damage or obstructions. Next, remove the top and bottom of the keyboard and expansion interface cases; if you don't wish to go inside your computer, this process can still be done, although it is awkward.

Using a new dollar bill, a piece of the finest grade of emery paper, or a fine talc buffing wheel, bring the contacts to a bright shine. Brush off any remaining particles, and spray with contact cleaner (sometimes called tv tuner cleaner). Repeat this for all the edge connectors, and reinstall the cables.

If this process is repeated regularly, interconnect noise problems will be completely eliminated. However, if cables slide along the contacts when the computer is in use, noise may still be produced. To cure this, place no strain on the cables, and replace the keyboard expansion cable with a longer, more flexible unit. If your TRS-80 uses the buffered cable, instead of replacing it, merely add to it with one of the cable extenders sold by *Exatron* and others (see Appendix).

There are two software tools which can be used to eke out memory problems: the memory test printed in Chapter 3 , and MEMORY SIZE? itself. Running the memory test will describe which memory locations and chips may be bad. When the MEMORY SIZE? question is answered with only a carriage return, a Level II subroutine begins testing each memory location until it finds a bad one; that final non-memory or bad memory location is found by typing:

```
PRINT PEEK (16561) + 256 * PEEK (16562) + 2
```



Photo 10-1. Power supply transistors.

In a 16K machine, the value returned should be 32768. If it is less, then the value returned is a bad memory location. Since the MEMORY SIZE? test is simplistic, it will not identify all possible memory errors, and if you suspect one, run the memory test.

If the bad memory location seems to move about, then perhaps it is not a true memory problem at all, but rather due to bad connections or electrical noise. Be sure noisy electrical equipment is not located near the computer. Clean cable and edge card connectors (see Box), and see if the problem recurs. If it does, open the case of your keyboard unit (and expansion box), and remove and reseat each memory chip. Look for corrosion, especially on newer chips without gold-plated leads.

If the problem is still not cured, the difficulty may be in the power supply. The location to suspect first is the large transistor (Q 4 – see Photo 10-1), which is screwed down to the circuit board. Corrosion can build up between this transistor and the solder-plated circuit board. Loosen and remove the screws that attach the transistor, but do not attempt to remove the transistor itself. Slide fine emery paper – definitely *not* steel wool or sandpaper – face down between the transistor and the board, and clean out any corrosion.

If a lockwasher was not used between the transistor and the board, insert one, and reinstall and tighten the screws. This should stabilize the power supply inside the case.

Using an Oscilloscope

The oscilloscope is a very sophisticated tool, but in this book it is used for an elementary purpose: merely to see if a signal is 'there' or not, and if it looks pretty good. Almost all TRS-80 circuitry failures can be traced this way, and it requires no previous experience using an oscilloscope, and no special training in reading waveform timings.

The height of an oscilloscope screen trace changes in proportion to the signal present at its input. To see this, plug in the scope, turn it on, and adjust the intensity until a flat line is visible in the center of the display. Attach its cables to the vertical input. Leaving the ground (black) wiring hanging, hold the signal (red) wire in one hand. The flat line displayed on the screen should go wild.

Adjust the vertical calibration (or voltage range) until you can see the trace. Adjust the sweep, sweep vernier and synchronization controls until the trace stabilizes, and looks like this:



Photo 10-3. Photo of sine wave.

Adjust the vertical and horizontal centering until the trace is in the center of the screen. What you see is your own body acting as a kind of transformer, soaking up all the electrical signals from the wiring and equipment all around you.



Photo 10-4. Photo of TRS-80 ground point for scope.

Now hold the black ground wire in your other hand. The wild trace should now flatten out considerably, as you become both signal and ground, essentially 'shorting out' the bulk of the signal received by the oscilloscope.

Next, power down your TRS-80 and open it. Using clips or by soldering a wire temporarily into place, attach the black ground wire to the point shown in the photo below:

Hold onto the red cable, and power-up the computer. Now find pin (?) of the Z-80 microprocessor (Z40 on the circuit board), and hold the red probe to it. Adjust the screen so you can see all of the trace, and it consists of a regular series of pulses.



Photo 10-5. 1.77 MHz clock pulses.

What you are looking at is the actual 1,774,000 pulse per second master clock of the TRS-80. All the signals you see throughout the computer should be of this quality – sharp-edged and clean. They will not have the same regularity, because different lines are turned on and off only as needed. But the signals should always be of the same crispness.

For practice, place the red probe at various points on the computer, being very careful not to short two points together with the tip of the probe. You will see the many kinds of signals present throughout the computer. If your computer has a problem, you will be looking for signal lines which have failed: they will be rounded, or angled instead of vertical, or will be much lower in level than the ones you see now. This is a clue to the area of the failure.

The next step is to switch the external black power supply box with a new one, because your present supply may have a damaged, highly resistive, or intermittent fuse wire. Later supplies can be opened to check this; there are screws under the feet. If the new supply works, have the old one repaired, or open it yourself and replace the fine fuse wire with a new one.

Memory problems caused by damaged refresh lines are subtle, but can be discovered. Load a BASIC program, LIST it, and re-LIST it. If gradually the program shows changes, suspect that the refresh lines may be weak. To diagnose this job fully, you will need an oscilloscope.

Photo 10-2 shows how cleanly a good signal is represented on the scope screen. Anything less than a sharp-edged, rectangular pulse should be suspect. Furthermore, a signal that is distinctly lower than others can be suspected.



Photo 10-2. Digital scope photo.

Aligning the Video

Video jitter in most cases is due to incorrect settings of either the vertical or horizontal controls on the back of the monitor itself. To align these, enter the following short program:

```
10 CLS
20 FOR X = 15360 TO 16383
30 POKE X,191
40 NEXT
50 GOTO 50
```

Listing 10-1. Video centering routine.

This will paint the screen white. Any bulging on either side of the screen can be cured by adjusting the horizontal control on the back of the monitor. Turn it until the bulging is reduced as much as possible. Instability or rolling is most easily cured by adjusting the vertical control on the back of the monitor. 'Zero' it in by making the screen first roll forward, then back, then forward, and back again until you have what feels like the central position of the control.

Open the TRS-80, and set the program above in motion again. The horizontal and vertical positioning controls are located at the far right of the circuit board as shown in Photo 10-1. Adjust these until the image is properly centered, and drop a very small amount of glue or nail polish on the control's plastic handle to hold it in that position against the control's body.

Any remaining instability in the screen display can usually be attributed to low voltage present on your house current line, or problems with the TRS-80 power supply (see above).

Routine Maintenance

Microcomputers like the TRS-80 are generally thought of as maintenance free, except for peripherals with moving parts. But in truth, the keyboard unit and expansion box always need some maintenance, all of which is covered throughout this book. In summary:

1. Clean edge card connectors and check cables regularly.
2. Remove keytops (only on units with the older keyboards susceptible to keybounce) and blow out dust and clean contacts regularly.
3. Blow out dust from the unit itself, and give it a shake, to remove any solder balls and splashes that may come loose as the unit gets older.
4. Keep the unit covered when not in use.

Care of Peripherals

Cassette players. Using ordinary rubbing alcohol and cotton swabs, clean the head, capstan and pinch roller to remove all traces of brown tape oxide. Demagnetize the head using a commercial demagnetization cassette, or a head degausser (available at Radio Shack); follow the directions carefully so you don't make the problem worse.

Always handle the player's buttons gently, as snapping them vigorously will not only shorten their life, but create enough vibration to throw the head out of alignment. If the head does get misaligned, or you suspect it is, turn to the details of cassette player maintenance in Chapter 6.

In summary: clean all parts that come in contact with tape, and treat the unit's controls gently.

Printers. Dot-matrix types like the Radio Shack line printers are workhorses, but there are a few cautions. First and foremost, never move or remove paper when the printer is in motion. The printed characters are formed by fine wires striking against the paper, and these wires can be bent if the paper is pulled against them.

Keep ribbons in good condition, because a ribbon with a slight tear can also catch on a head

and damage the dot-matrix wires. Open the printer and blow out dust and dirt regularly; if you are skilled in handling small machinery, lubricate the printer according to the Radio Shack maintenance manual. If you are a klutz, don't try; alignment of printers has to be accurate to 1/100th of an inch.

In summary: keep printers free of dust and ribbons fresh.

Disk Drives. These horrors are terribly sensitive. Like tape machines, the heads need cleaning, but use only head cleaning diskettes especially made for the purpose. If you have regular data read/write problems, there are several solutions: purchase a better disk operating system (DOS), and/or purchase and install an external data separator.

Keep out of the drive's insides as much as possible. Alignment is sometimes vital, but again, unless you are very good with precision machines, don't try it yourself. And even if you are a born watchmaker, be overly careful with double-sided or double-density drives.

In summary: beyond a regular cleaning, leave them alone. Oh yes, keep the drive cables well away from the monitor or any AC power cables.

Exatron Stringy-Floppy. Despite the manufacturer's warnings, this unit does not come well aligned from the factory, and many units were shipped without head alignment cement (normally Lok-Tite, a grey compound) to hold heads firmly in place. Remove the cover of the unit and check for this gop. If it is not there, turn to Chapter 9 and follow the alignment directions.

If the gop is not there, you'll need an oscilloscope. Turn the scope on, and adjust the vertical calibration for full scale (maximum). Hook the scope's ground (black) lead to a convenient ground point on the ESF or the TRS-80, and place the hot (red) probe on Z6 — pin 7. Start the ESF reading a prerecorded tape from the manufacturer. If the wave won't stay in synchronization on the screen, or if it is outside the vertical bounds of the screen, adjust the scope until it is visible and stable. With a small screwdriver, adjust the playback head's alignment until the amplitude (height) of the waveform is at its maximum. Try several prerecorded tapes to make sure of this position, and put some lok-tite on it. If you have your own tapes recorded on the ESF, you may have to move back and forth to and from the correct position, reading in the original position, and re-recording in the corrected one.

Clean the heads and capstan with a very sparing and gentle application of rubbing alcohol on the end of a lint-free swab. Don't use Q-tips or their equivalent, but rather wrap surgical gauze around a lollipop stick. Blow dust out of the unit regularly. Remember never to operate the ESF in any position but on its feet.

In summary: blow out dust, clean heads, and check for the presence of 'Lok-Tite' on the head screws.

RS-232 Board. In another piece of dream engineering, the connection of this board to the expansion box was done via a flukey, solder-coated connector board pressed against a plastic bridge with plain metal contacts. Clean those contacts regularly with a fine cloth, and brush the solder-coated board connectors vigorously with a buffing cloth or extra-fine emery paper. Spray both sparingly with tuner cleaner, and quickly reattach them, constantly rocking the board to assure a firm connection until you have tightened the screws down.

In summary: clean both sets of contacts occasionally, especially if you notice more than the usual transmission/reception errors.

Diagnostic Programs and Loops

Loading large-scale programs for diagnosis is not only time-consuming, but as often as not impossible when your computer is not working well. If BASIC can be brought up at all, then simple machine language diagnostics can be POKEd into place from command level. This section will present several of those loops, their use in trapping some of the possible difficulties, and how they can be used to examine the operation of the system. All these routines can be POKEd anywhere in your machine's memory; these examples all start at 5000 (20480 decimal).

1. Checking the Write Circuits.

This routine merely writes to a location and jumpsback to itself:

```
Coding:
AF              XOR     A
32 00 3C        LO      (3C00),A
3C              INC     A
18 FA           JR      $-4
```

Listing 10-2. Write circuit diagnostic/machine.

```
From 8ASIC:
X=20480:POKEX,175:POKEX+1,50:POKEX+2,0:POKEX+3,60:
POKEX+4,60:POKEX+5,24:POKEX+6,250      <ENTER>
SYSTEM                                 <ENTER>
/20480                                 <ENTER>
```

Listing 10-3. Write circuit diagnostic/BASIC.

This routine will write the value in A, which is incremented from 00 to FF (0 to 255) each time the loop is passed through. The write line will pulse each time the LDd (3C00),A instruction is commanded. The first position on the video screen will flicker, as this is the memory location being written to. Press the Reset button to return from this routine.

2. Checking the Read Circuits.

Since each instruction must be fetched, this is only a simple loop:

```
Coding:
18 FE             JR      $
```

Listing 10-4. Read circuit diagnostic/machine.

```
From 8ASIC:
POKE20480,24:POKE20481,254                  <ENTER>
SYSTEM                                      <ENTER>
/20480                                      <ENTER>
```

Listing 10-5. Read circuit diagnostic/BASIC.

The Read line will pulse four times for every loop through this routine: twice for each instruction fetch, and twice for each refresh action. Press the Reset button to return from this routine.

Listing 10-6. Output circuit diagnostic/machine.

3. Checking the Output Circuits.

This diagnostic is very much like that for examining the Write line, except that it triggers the Out line.

```
Coding:
AF                XOR     A
03 FF             OUT     (FF),A
3C                INC     A
18 F8             JR      $-3
```

```
From 8ASIC:
X=20480:POKEX,176:POKEX+1,211:POKEX+2,255:POKEX+3,60:
POKEX+4,24:POKEX+5,251                     <ENTER>
SYSTEM                                     <ENTER>
/20480                                     <ENTER>
```

Listing 10-7. Output circuit diagnostic/BASIC.

Each time the loop is passed through, the OUT line will be pulsed once, and the data present on the data lines will be incremented. This routine is also very useful because the cassette relay, the cassette data output, and the video screen will all demonstrate activity as the routine is looped through. Press the Reset button to return from this routine.

4. Checking the Input Circuits.

This routine is similar to the write routine, but does not include any accumulator changes.

```
Coding:
08 00             IN      A,(00)
18 FC             JR      $-2
```

Listing 10-8. Input circuit diagnostic/machine.

```
From 8ASIC:
X=20480:POKEX,219:POKEX+1,0:POKEX+2,24:
POKEX+3,252                                <ENTER>
SYSTEM                                     <ENTER>
/20480                                     <ENTER>
```

Listing 10-9. Input circuit diagnostic/BASIC.

Press the Reset button to return from this routine.

5. Checking the HALT Line.

Since the HALT line is gated together with the Reset button, executing HALT should return to ready (or reboot in a disk system).

```
Coding:
76                HALT
```

Listing 10-10. HALT line diagnostic/machine.

```
From 8ASIC:
POKE20480,118                              <ENTER>
SYSTEM                                     <ENTER>
/20480                                     <ENTER>
```

Listing 10-11. HALT line diagnostic/BASIC.

Since the machine should return to READY, the Reset button need not be used.

6. Checking the Video.

This routine presents a screen full of characters, all identical, and increments through all 256 of the possible characters. With no lower case modification the screen will display three sets of upper case characters, followed by two sets of graphics characters. With a lower case modification, two upper case sets and one lower case, or one of each case plus a set of control characters will be displayed.

```
Coding:
AF                XOR     A
21 00 3C          LO      HL,3C00
11 01 3C          LO      0E,3C01
01 FF 03          LO      8C,03FF
77                LO      (HL),A
E0 80             LOIR
3C                INC     A
F5                PUSH    AF
01 00 C0          LO      8C,C000
C0 60 00          CALL    0060
F1                POP     AF
18 E9             JR      $-210
```

Listing 10-12. Video routine diagnostic/machine.

```
From 8ASIC:
X=20480:POKEX,175:POKEX+1,33:POKEX+2,0:POKEX+3,60:
POKEX+4,17:POKEX+5,1:POKEX+6,60:POKEX+7,1:
POKEX+8,255:POKEX+9,3:POKEX+10,119:POKEX+11,237:
POKEX+12,176:POKEX+13,60                      <ENTER>
POKEX+14,245:POKEX+15,1:POKEX+16,0:POKEX+17,192
POKEX+18,205:POKEX+19,96:POKEX+20,0:POKEX+21,241
POKEX+22,24:POKEX+23,233                      <ENTER>
SYSTEM                                        <ENTER>
/20480                                        <ENTER>
```

Listing 10-13. Video routine diagnostic/BASIC.

Also, the VID* line (noted on the schematic in the Technical Reference Handbook) should pulse in very noticeable groups as each screen is printed. Use the Reset button to exit this routine.

7. Checking the Cassette Output.

This routine calls the byte-output routine, and should write an **FF** (equal to eight timing pulses and eight data pulses) to port **FF** (the cassette output).

```
Coding:
3E FF             LO      A,OFF
CO 35 02          CALL    0264
18 F9             JR      $-5
```

Listing 10-14. Cassette output diagnostic/machine.

```
From 8ASIC:
X=20480:POKEX,62:POKEX+1,255:POKEX+2,205:POKEX+3,100:
POKEX+4,2:POKEX+5,24:POKEX+6,249          <ENTER>
SYSTEM                                    <ENTER>
/20480                                    <ENTER>
```

Listing 10-15. Cassette output diagnostic/BASIC.

You should be able to measure (or hear) a constant group of pulses output to the cassette player. Note that the cassette player must be in record position, and must be running (the small plug must be removed) because this routine does not turn the cassette machine on. Use the Reset button to exit this routine.

8. Checking the Printer.

By writing data to address 37E8, the printer should react by printing that character. The following two routines output the letter 'A' to the printer; the first loops through a delay, outputting about five characters per second. The second waits for a printer handshaking signal.

Print-and-Delay Routine

```
Coding:
3E 41             LO      A,41
32 E8 37          LO      (37E8),A
01 00 30          LO      8C,3000
CO 60 00          CALL    0060
18 F3             JR      $-110
```

Listing 10-16. Printer diagnostic I/machine.

```
From 8ASIC:
X=20480:POKEX,62:POKEX+1,65:POKEX+2,50:POKEX+3,232:
POKEX+4,55:POKEX+5,1:POKEX+6,0:POKEX+7,48:
POKEX+8,205:POKEX+9,96:POKEX+10,0:POKEX+11,24:
POKEX+12,243                                <ENTER>
SYSTEM                                      <ENTER>
/20480                                      <ENTER>
```

Listing 10-17. Printer diagnostic I/BASIC.

Print-and-Wait Routine

```
Coding:
3E 41             LD      A,41
21 E8 37          LO´     HL,37E8
77                LO      (HL),A
C8 76             8IT     6,(HL)
20 FE             JR      NZ,$
18 F4             JR      $-100
```

Listing 10-18. Printer diagnostic II/machine.

```
From 8ASIC:
X=20480:POKEX,62:POKEX+1,65:POKEX+2,33:POKEX+3,232:
POKEX+4,55:POKEX+5,119:POKEX+6,203:POKEX+7,118:
POKEX+8,32:POKEX+9,254:POKEX+10,24:POKEX+11,244
                                  <ENTER>
SYSTEM                            <ENTER>
/20480                            <ENTER>
```

Listing 10-19. Printer diagnostic II/BASIC.

9. Checking the Interrupt Line

For this, of course, interrupt hardware must be attached to the system. In the case of the expansion box, the interrupt flip-flop must be cleared (see Supplement to Chapter 4). This routine performs that function. It is identical to the first service routine presented in the Supplement to Chapter 4, and so only the BASIC coding is presented.

From BASIC, attempt to use this program instead of direct POKEs, because there are so many values:

```
10 FOR X = 20480 TO 20926 : REAO A : POKE X,A : NEXT
20 STOP
30 OATA 243,62,195,50,18,64,33,20,50,34,19,64
40 OATA 33,25,26,229,237,86,251,205
50 OATA 243,245,229,213,197,58,236,55
60 OATA 58,224,55,33,17,1,17,37,62,1,26,0
70 OATA 237,176,193,209,225,251,201

SYSTEM                                  <ENTER>
/20480                                  <ENTER>
```

Listing 10-20. Interrupt line diagnostic/BASIC.

This routine, as described, returns to BASIC command level and displays a RADIO SHACK LEVEL II BASIC message continuously on the screen.

10. Checking Speed Modifications

Among the possible high speed failures are miswirings, ROMs which are two slow, and RAMs which are too slow. Combinations of these can make diagnosing a locked-up computer very frustrating.

The two routines below test, respectively, RAM calling ROM, and RAM alone. The RAM routine may be moved to higher memory for testing that area; a version at **5000** and **B000** are provided.

Coding:

RAM-Resident Version – Origin is at 5000

```
    32 60 30        LO      (3060),A
    3C              INC     A
    F5              PUSH    AF
    AF              XOR     A
    03 FE           OUT     (FE),A
    F1              POP     AF
    32 61 30        LO      (3061),A
    F5              PUSH    AF
    3E FF           LO      A,FF
    03 FE           OUT     (FE),A
    01 00 10        LO      BC,1000
*   0B              OEC     BC
*   7B              LO      A,B
*   B1              OR      C
*   20 FB           DJNZ    FB
    F1              POP     AF
%   C3 00 50        JP      5000

    ROM-Resident Version

    Remove Lines marked (*) end replace with:
    C0 60 00        CALL    0060

    High RAM-Resident Version

    Origin is et B000; replece Line merked (%) with:
    C3 00 B0        JP      B000
```

Listing 10-21. High-speed modification diagnostic machine.

RAM/ROM Version

Remove lines marked (*) and replace with:

High RAM-Resident Version

Origin is at **B000**; replace line marked with percent sign with:

Since speed changes can affect the operation of BASIC, a version with POKE may be useless; if not, however, here is the RAM-resident version:

```
X=20480:POKEX,50:POKEX+1,96:POKEX+2,61:POKEX+3,60:
POKEX+4,245:POKEX+5,175:POKEX+6,211:POKEX+7,254:
POKEX+8,241:POKEX+9,50:POKEX+10,97:POKEX+11,61:
POKEX+12,60:POKEX+13,245:POKEX+14,62:POKEX+15,255:
POKEX+16,211:POKEX+17,254:POKEX+18,1:POKEX+19,0:
POKEX+20,16                                  <ENTER>
POKEX+21,11:POKEX+22,120:POKEX+23,177:POKEX+24,32:
POKEX+25,251:POKEX+26,241:POKEX+27,195:POKEX+28,0:
POKEX+29,80                                  <ENTER>
```

Listing 10-22. High-speed modification diagnostic BASIC.

For the ROM-RAM version, replace the last group of POKEs with:

```
POKEX+21,205:POKEX+22,96:POKEX+23,0:POKEX+24,241:
POKEX+25,195:POKEX+26,0:POKEX+27,80      <ENTER>
```

For the high RAM version, let X = -20480, and replace the last value POKEd (in either configuration) with 176.

These routines will present, just below the center of the screen, a pair of characters. The first of these is printed in the machine's normal configuration (if OUT 254,0 sets your machine to normal). The second character is printed with the effect of OUT 254,255, which should turn all modifications on. Any failure in these routines should point to the specific area of breakdown.

NOTES

11

111 CURES FOR THE COMMON CRASH

Because TRS-80 computers are sold at the 'appliance' level, salespeople and users often forget that they are indeed computers, prone to all the problems that larger computers face. As a user of a personal computer, you become your own service representative, your own diagnostician, and your own repair agency. This is even more true if you have a custom TRS-80.

This chapter is dedicated to you, the user, as service rep, diagnostic engineer, and repair person.

I. SOFTWARE

Symptoms of software problems: all error messages, system lockup and crash, just about everything that doesn't snap, crackle or pop.

1. Correct the program – the greatest cause of crashes.

By far the largest cause of computer 'crashes' is the software. Mishandling of POKE, PEEK and VARPTR are most common as well as improper input/output routines, and insufficient error-checking. If crashes seem to occur only in specific programs, check these for errors before turning to hardware cures, although a 'stuck bit' may always turn up a consistent error.

2. Set memory size correctly for machine language or hybrid programs.

Memory size is a boundary above which BASIC is prohibited. BASIC is not merely the source program, but consists of variable and string storage and the BASIC stack. Some of this uses high memory, and when memory size is not set as specified, these variables and stack information can run into the high-memory machine language program.

3. Wait out or re-write long string searches and sorts.

The memory allocation method for strings has made 'garbage collection' techniques necessary. When sorting is complex and the number of strings is large, this process can take from a few minutes to an hour, during which the computer seems locked up. One cure is clearing as much string space as possible; when all variables have been defined, break and PRINT MEM. To the program, add a line such as CLEAR MEM-N, where N is about 100 bytes more than the difference between the

program with all variables defined and your total memory; subtract about 20 bytes from the CLEAR statement for each nested FOR-NEXT loop and GOSUB. Refer to 'BASIC Faster and Better' and other books for techniques of rewriting string handling using variable pointers, and otherwise using memory economically.

4. Read the manuals.

Most bugs are called 'features' by program authors. Discover these features in the program documentation.

I. POWER

Problems Caused by Poor Power: system reboot, unexpected syntax errors, speckles on screen, shrinking screen, unexpected disk or Stringy-Floppy startup, total lockup of system.

5. Add a line filter or power supply monitor.

'Clean' power enhances system reliability. The simplest help is a line filter such as that sold by Radio Shack. More severe power problems can be ameliorated by using power supply monitors such as Topax or Mayday. Isolating other appliances (power tools, washers, refrigerators, toasters, water pumps, fluorescent lamps, etc.) from your computer's outlet will enhance reliable operation. You can even build some very simple filters yourself:





6. Use 3-wire grounded circuitry for all equipment.

3-wire circuitry is electrically quieter and safer. Some equipment, particularly printers, have damaged computers when used in an ungrounded or improperly-grounded environment. If you have an older, 2-wire system, test for floating voltages using a neon test light, available from hardware stores. Reverse the plugs in the socket until all voltages disappear.

7. Stop strong power drains (granite sheds, arc welders).

Strong power drains are visible as brief but distinct shrinking and dimming of the video. Cassette and disk I/O problems are most likely, but power drains can sometimes result in program failure. A high quality power supply monitor can help. Also, if you don't live in an industrial area, your power company or zoning commission might be able to assist.

8. Fuse in the power supply might be going or gone.

All separate TRS-80 power supplies contain fuses in order to receive an Underwriters Laboratories approval. Earlier supplies are sealed, but the seal can be broken by forcing a screwdriver around the joint at the bottom of the supply and gradually popping off the top section. Later supplies have screws under the rubber feet. Fuses are cheap. Don't test the fuse, replace it. It will need to be resoldered since these fuses are not in sockets.

9. Replace or resolder faulty power cables at the connector.

The power connector is not molded in place, and after a year of abuse, the soldered connections can break inside. Lift the tabs on the plastic sheath and pull it back. The connector can be resoldered.

If the power remains intermittent, the problem may be at the point where a band of metal is crimped around the cable. Loosen it, cut the cable shorter, and resolder. The 5-pin DIN plug is sold by Radio Shack if you want to replace it completely.

10. Install a lightning arrestor in spite of the phone company.

If you have a direct-connect modem, lighting strikes may be damaging your system, or at least affecting its performance. For best protection, always unplug the system from the phone and power lines when a storm is in the area. You can also obtain a TII lightning arrestor from Datadyne, 450 Seventh Avenue, NY 10001.

II. EDGE CONNECTORS

Symptoms of edge connector problems: system reboot, unexpected syntax and line number errors, loss of the end of a program or text file, system lockup, return to READY before program end.

11. Clean edge connectors by erasing them.

Since the solder-coated edge connectors are prone to corrosion, they must be cleaned regularly. The simplest methods are vigorous rubbing with a piece of coarse paper like a dollar bill, or erasing with pink pearl (good) or white plastic (best) erasers.

12. Spray edge connectors with contact cleaner and swab with cotton.

Once you have cleaned the edge connectors thoroughly, a weekly application of a small amount of spray contact cleaner (such as Radio Shack 64-2320), followed by rubbing with a cotton swab, will keep the contacts in good shape.

13. Emery-paper edge connectors for really bad corrosion.

For really bad corrosion or scoring from continuous insertion and removal of connectors, the finest grade of emery paper or cloth can be used. Use wet-or-dry paper soaked in contact cleaner or diluted isopropyl alcohol, and rub smoothly along the connectors. Follow up with more contact cleaner and cotton swabbing. Rub just enough to bring up a shine, and do not use coarse emery paper. Never sand down to the copper traces.

14. Silver solder the edge connectors with Silver-It.

Corrosion can be reduced to a minimum while maintaining the original physical size and shape of the edge connectors by obtaining a Silver-It kit from Fuller Products, Grand Prairie, Texas. This is a process that must be completed with great care, but will result in connectors that (except in chemically violent atmospheres in major cities) need virtually no cleaning. For Radio Shack repairs, this process looks like no modifications have been made.

15. Gold plate the edge connectors.

Most difficult of the solutions is gold plating, which is also a poisonous process. However, when it is complete, the result will be connectors of the original physical size with a corrosion-free gold coating. Refer to 80 Microcomputing, December 1981, for full details.

16. Replace the connectors with gold plugs from EAP.

Easier than silvering or gold plating and less annoying than regular cleaning are replacement gold edge connectors (Gold Plug 80) sold by EAP Products, Box 14, Keller, Texas. Because the connectors are made by Kel/Am, they do not mate properly with AP Products connectors. Peri-

pherals using AP connectors can be easily changed to use the T&B/Ansley connector sold by Radio Shack. Also, the Gold Plug 80 connectors will protrude from the keyboard unit and expansion box somewhat less than an inch.

17. Solder all the connectors into one box and one board.

Model III cases can be purchased as replacement parts through Radio Shack's National Parts distribution system. If you wish to have a one-piece system, this can also cure the edge connector problem. Heavy pieces of copper wire can be soldered to the keyboard and expansion edge connectors, effectively creating a single large board. Don't solder a cable in place and then put one board on top of the other, because electronic noise will be a problem.



18. Both unbuffered and buffered cables are inserted only one way.

The buffered cable is marked clearly as to which end connects to the keyboard and which end to the expansion interface. However, the unbuffered cable is also directional because it contains a shield which should be connected to ground. If the cable is reversed, the large shield will be connected to a system reset signal — a sure troublemaker. Examine the cable for a fine copper wire sliding out from between the grey plastic 'sandwich'. It should be on the left side of the cable when the cable is attached, with the smooth face of the cable toward the top.

19. Cables not inserted all the way or crooked on connector.

Interconnect cables, particularly AP Products connectors, need to be fully inserted to make electrical contact. Although the expansion cable is not usually inserted partly or crooked, it is easier to do with the printer and disk cables, which are somewhat out of sight. Also, Kel/Am connectors have a limited life — about 50 insertions and removals before the contacts bend inside the connector. Examine the end — all contacts should be even.

20. File carefully to cure a tight fit on the edge connector.

Most Model I TRS-80's contain printed circuit board slightly thicker than that normally used with edge connectors. Although the cable will go on, it has to be forced. To avoid this, smooth the very edge of the circuit board with a fine file, to round the edge. File back not more than 1/8 inch:



III. MEMORY

Symptoms of memory problems: erratic operation, unexpected syntax, unidentified-line, next-without-for and subscript-out-of-range errors, incorrectly reported memory on power-up, program lock-up.

21. Replace slow memory with faster chips, but check speeds.

All dynamic memory has a window during which data is valid for the CPU. Refer to Chapter 4 for a table of memory speeds for keyboard unit and expansion interface. Also, note that memories can deteriorate with age, and poorer access time is one of the first signs of age.

22. Replace bad memory with good memory, using a memory test.

A memory test will reveal memory chips which are genuinely bad, identifying both their address and the bit (chip) involved. Remember that addresses **4000-7FFF** are in the keyboard, and the expansion interface contains two banks, **8000-BFFF** and **C000-FFFF.**

23. Replace older memory with newer (post-1979) memory.

Early dynamic memories were plagued with the occasional 'soft error' — a program crash not caused by any permanent hardware affliction. The error was finally identified as a slow emission of alpha particles from the substrate (base) of the memory circuitry inside the chip. These particles would strike a memory cell, changing it. The occurrence was unpredictable. The best cure for this dilemma is the replacement of all such memories. Date codes are stamped on the chip in year/week format, such as 7851 (end of December 1978); use memories with an 8001 or later date code.

24. Increase access with a modification to Z69.

If the problem seems to be slow or aging memory, the Z69 modification can help. Cut trace from Z69 pin 5. Attach Z69 pin 12 either to Z69 pin 10 or to Z69 pin 13.

25. Install a buffered cable according to modified Radio Shack instructions.

When memory failure seems to occur as more items are added to the system via the expansion interface, then (in earlier units) a buffered cable is called for. It provides additional fan-out (drive) capabilities to the keyboard unit. This item is available from Radio Shack at no charge to owners of early expansion interfaces. You can identify the earlier interfaces because the 32K memory runs from back to front; in newer boxes it runs along the back. Refer to Chapter 4 for installation instructions.

26. Install the twisted-pair DIN plug modification.

In addition to the buffered cable, some earlier interfaces may require the 'twisted pair' modification. This is a 6-wire DIN cable combination to carry memory select signals RAS, CAS and MUX. Refer to Chapter 4 for installation instructions.

27. Modify twisted pair resistors upward to 470/680 ohm pairs.

If the installation of the twisted pair mod deteriorates rather than ameliorates operation, change the resistor values specified by Radio Shack to 470 ohms to ground, and 680 ohms to 5 volts. Both are originally 220 ohms.

28. Straighten bent pins under socketed ICs.

Memory chips and the CPU were the only chips socketed in earlier machines. However, various runs of the computer had the character generator, line buffers, and so forth, in sockets. Evidence of bent pins is a machine which acts up when given a light physical shock — such as hard typing. Lift each IC and check for bent pins; be sure not to bend any pins when putting it back! If your machine has had a recent trip to salt-water environments, the problem will be more severe; see #104.

IV. FIRMWARE

Symptoms of firmware problems: incorrectly read data, equality failures in IF-THEN statements.

29. POKE 16553, 255 to correct READ/DATA error.

In Version 1 of the Level II ROM, under certain conditions the same data would be read over and over, with the data pointer not being stepped through memory. The most common fix is POKE 16553,255 added as the first line of any program. Also, any INPUT statement before the reading of data begins will take care of properly stepping the pointer.

30. There are floating point accuracy errors, such as X-Y<> X-Y%.

Because of the way real numbers are handled digitally, there is a very small numeric residue left after some types of calculations. Where IF-THEN statements don't seem to work when you know they should, break into the program and print the offending variables. Chances are you will see that a value, instead of being 20 as you expected, is actually 20.00001 as a result of residual binary information. Use integers where you can for such tests; see the Level II manual for details.

V. RS-232

Symptoms of RS-232 problems: incorrectly received or transmitted characters, system crashing or lockup when not using RS-232, electronic failure.

31. Place bar across RS-232 to keep it in place.

Heat buildup and general stress in the expansion box will cause a warping of the RS-232 board, lifting some contacts above the connection pins, or making the unit vibration sensitive. By using longer mounting screws and a heavy insulated metal bar, the warp can be prevented. You may have one made at a local metal shop, then cover it with 'heat-shrink' tubing sold by Radio Shack. Recently, some sources have been making such bars available; look for ads.

32. Clean RS-232 contacts vigorously with cotton cloth.

These contacts too are solder-plated, and prone to corrosion. But they are also very thin, and only a clean cotton cloth - together with vigorous rubbing (and perhaps a little contact cleaner) should be used. Make the contacts shiny.

33. Reseat the RS232 board, checking for bent pins.

The RS-232 board contacts are 1/20 inch from center to center, exactly half the size of the edge connectors. Bent pins on the expansion interface RS-232 connector can cause shorts which will affect not only the operation of the RS-232 system, but the computer as a whole. Reseat the board, checking under strong light that all the connecting pins are straight and contact properly.

34. COM/TERM on RS-232 must be in correct position.

Recheck the RS-232 manual, and make sure that the Communications/Terminal switch is in the correct position for the software you are using.

VI. DISK

Symptoms of disk problems: lost data, hang-up during disk access, rattling and banging of disk mechanism.

35. Use better disks, the best you can get if data is critical.

If you've spent an hour entering data, you've paid for the best diskette you can buy. Purchasing cheap disks is false economy.

36. Install a data separator, doubler, or other separation.

Data is stored on disk as a continuous stream of clock pulses separating data pulses. As a matter of economy, Radio

Shack chose to use 'internal' separation — that is, using the disc controller integrated circuit to distinguish between clock and data pulses. The disc controller's manufacturer does not recommend this method; therefore, a piggyback data separator (sold by several sources) reinstates the proper electronic design. Similarly, a double-density controller contains the essential data separation. If you obtain a 1771B-01 data sheet from Western Digital Corporation, you can build your own data separator.

37. Align the disk drive read/write head professionally.

When a single-drive system is in use, misalignment of a drive head might not be noticed. However, in a multi-drive system, one drive may produce an unusual number of re-seeks or error messages. If you suspect misalignment of the head, don't attempt to service it yourself. You can obtain an alignment diskette (a good one is manufactured by Dysan) to confirm your suspicions, but professional service is called for in this case.

38. Clean the disk drive read/write head with cleaning disks.

When a large number of disks are in use, especially inexpensive ones, tiny bits of oxide are shed onto the drive read/write head. Since this is not immediately visible, it's good practice to obtain a disk cleaning kit (Scotch and others) and use it weekly.

39. Erase-clean connections to the disk drive.

The edge connector to the disk drive is afflicted with the same corrosion problem as other edge connectors. The solutions are the same: cleaning, plating, and replacement with gold plugs. See under edge connectors (#11 above) for more information.

40. Replace 74LS38/LS16 c lector ICs and socket them.

The cable to disk drives is long and must be driven by higher-current integrated circuits, type 74LS38 (74LS16 in the newer expansion box). These can often break down under continuous use and in situations where the drives are often plugged in incorrectly. The most evident symptom is failure during formatting or backup, because the stepping signal (low to move outward, high to move inward) deteriorates and missteps the read/write head. Remove these chips, and solder in sockets. Then keep a small stock handy so they can be replaced when these symptoms show up.

41. Lubricate disk drive and rails sparingly with silicones.

Many disk drives squeal and clatter. There is no need to risk mechanical failure. Remove the cover and lubricate the motor bearings and the guide rails; use only a very light grade silicone lubricant, and wipe any extra lubricant off once it has spread across the area that needs it. Refer to Exclusive Oracle, 80 Microcomputing, January 1982, for details.

42. Keep the disk door closed till it stops to protect loaded heads.

Your disk drive may contain 'loaded' heads, which means that the door mechanics do not lift the head away from the disk when the door is opened. If you remove or insert a disk before the select light goes out, you may damage the head assembly. You can tell if your drive has loaded heads from the documentation, or by listening for a 'clack' when the drive is - selected, and a second 'clack' when the select light goes out. In any case, it is good practice to leave the disk in place in any drive while the motor is spinning.

43. Put disks in correct keyed cable position.

Disk drive selection (drive 0 to 3) can be made in two ways: the drive itself may be programmed with internal jumpers, or the cable may have teeth pulled to eliminate the unwanted select signals. If your drive programming and missing teeth do not match, then the drive will appear dead when selection is attempted. Make sure your drives are marked 0, 1, 2 and 3, and that you match them correctly to the cable.

44. Disk cable must be right side up.

If your disk drive keeps running and doesn't otherwise work, the drive is probably plugged into the cable upside down. Try reversing the connection. Since many drives have cables protruding out the back, and the physical position of these cables is not standard, the plug-in may look correct with respect to the other drives, but be backwards.

45. Disk cable must be fully installed inside case.

The cable protruding from the back of some brands of disk drives is usually not hard-wired, but simply an extension cable from an internal edge card. Under the weight of the long multi-drive cable, or simply from regular moving and unplugging, this internal connector can come loose, resulting in erratic operation. Remove the case top and re-insert the extension cable. A piece of strong plastic packing tape can keep this cable from shifting.

46. Insert the disk correctly into the drive.

This is not as obvious as it seems. If you mix different brand drives on your system, you may discover some in which the disk must be inserted with the write-protect notch pointing down rather than up. Usually the write-protect notch points toward the side of the drive where the select light is mounted, but even that is not standard. Be especially careful about this when using an unfamiliar system, as a hangup during disk access can be fatal to data in memory.

47. Remove or pad sources of vibration nearby disks.

If you have lived or worked in an area for some time, you have probably blocked out sources of vibration, such as heavy equipment, trains, etc. However, this kind of vibration can ruin a disk write or read. The simplest solution is padding: a layer of heavy cloth, a layer of cork, a layer of wood or metal. If you have occasional inexplicable read/write errors, tune your senses to the environment.

48. Update the DOS, especially if it's an early version of TRSDOS.

Most of the bugs and inconveniences of early versions of TRSDOS have been corrected either by Radio Shack, or by other software houses who have created new disk operating systems. To avoid frustrating errors, update your DOS.

49. Keep disks clean, unbent, and store them straight up in cases.

Though this may seem obvious, there are hidden causes of dirt: smoking, heavy dust or other airborne particles, air freshener sprays, animals, etc. Bending can be caused by storing disks sideways, keeping them in a car window, or inserting them hastily into the drive. Don't drink soda nearby — unless you put your disks right back in their sleeves (which you should do); the bursting bubbles of carbonation can carry sugar residue to the disk surface, damaging the recorded data and abrading the disk head.

VII. TAPE

Symptoms of tape problems: loading impossible, hangup during load, tape won't go on or off, tape won't record.

50. Align the tape recorder head by drilling a hole.

Misalignment is singly the largest tape problem. Put the recorder in playback mode with no cassette in place, and shine a bright light so you can see the Phillips alignment screw to the left of the tape head. Drill a hole directly above it. Align the head by popping in a good commercial music tape, and turning the screw until the sound is at is brightest. Use this for standard recording and playback, but readjust for any commercial tapes that don't sound 'bright'.

51. Clean the tape recorder head with isopropyl alcohol only.

An oxide buildup is common on all tape recorders. Using head cleaner or isopropyl alcohol (not acetone!), swab the tape head and other metal parts which exhibit brown oxide caking. This will prevent scratching or scraping of the tape surface, as well as ensure good contact with the tape head.

52. Demagnetize the tape recorder head with proper devices.

The high frequencies are the most crucial element in good tape loading, and a magnetized tape head erases some of - these high frequencies every time the tape is played. Pick up a cassette tape head demagnetizer, either a plug-in type or the kind packaged in a cassette case, and demagnetize the cassette player at least monthly.

53. Use better tape but not the very best audio stuff.

Good tape will always give good loads. Avoid inexpensive tapes like Certron, Concertape, and questionable department store house brands. Radio Shack red-label Realistic tape is just fine, as is most any good audio tape. Very high quality tapes (chromium dioxide, metal, etc.) are not necessary, except for archival backups. Digital tapes from Microsette are only about $.65 and are sold in handy lengths (C-10 and C-20).

54. Modify the CTR-80 with a diode to prevent head glitches.

If the stop button was pressed during loading, a head field collapse in early CTR-80 tape recorders would put glitches on program tapes. Radio Shack provides a free modification for this problem. If you wish to do it yourself, a small silicon diode (such as type 1N4148) can be connected across the tape head contacts.

55. Replace cassette relay to prevent sticking.

The current drain of the CTR-41 tape recorder, and many non-Radio Shack recorders, is too high for the relay contacts in the keyboard unit. This causes it to stick closed, keeping the tape recorder running when it should not. There are two options: change tape recorders, or change relays. The relay change is permanent, and a new unit can be obtained from Lab Service, Inc., in Hustisford, WI.

56. Use CTR-80 to prevent cassette relay burnout.

If you don't want the trouble of replacing a relay, use a CTR-80 tape recorder. It also prevents wear and tear on the cables, because rewind and fast-forward can be used without pulling the motor-control plug.

57. Clean the capstan and pinch roller with isopropyl alcohol.

As the tape recorder sees a lot of use, two things will happen to the rubber pinch roller: oxide buildup and glazing. Oxide buildup is similar to that on the tape head,

but on the roller it can cause tape to slip out of place, creasing it. Glazing is a shininess of the rubber surface, also causg tape slip and speed variations. Both can be cured with the liberal application of isopropyl alcohol, acetone, or tape roller cleaner. Hard-glazed rollers need to be brought down with fine emery paper.

58. Add a switch box to the cable assembly for hand operation and sound.

A very useful addition to your tape system is a small switch box containing a speaker; headphone speakers are best. With a simple two-switch box you can listen to programs being saved, keep the motor running, and stop it when you wish:





59. Get the XRX-II cassette modification.

Radio Shack created a special cassette system modification, which is available at no charge. It improves 500-baud loading, but consists of a 500-baud window — which means using cassettes running at any other baud rate (hardware or software based) is impossible. However, the modification can be switched out if you wish to have the advantages of good 500-baud loading and not lose the option of other speeds:

60. Ground loop hum in cassette system is cured by breaking the loop.

Some loading problems can be attributed to hum during program saves. This is due to a 'ground loop' created by the input and output cables. Pull back the plastic sheath on the computer end of the cassette cable, and cut either one — but not both — of the two shields going to ground (pin 2, the center pin). This will kill ground loop hum.

61. Replace or resolder a faulty cassette cable at the connector.

If you often pull the cassette cables out of the recorder, you may break the internal wiring. This will be evident as a crackling sound during program saves, or partial good loads from tapes which once loaded perfectly. You can replace the connectors with mini and submini plugs, or you can obtain a complete new cable.

62. Replace the dual cassette relay or driver IC.

If the dual-cassette system from the expansion interface ceases to function, either the relay or its associated driver integrated circuit (Z41) may be bad. You can test the operation with:

```
1 A=14308:POKEA,0:FORX=1TO9:NEXT
 :POKEA,1:FORX=1TO9:NEXT:GOTO1
```

The relay in the expansion box should clack rapidly.

63. Cassette cables must go to correct expansion box positions.

If one cassette seems to load and the other doesn't, then check that the cassette cables are properly installed. The order (looking from the back) is not particularly logical: Common Cable, Cassette #1, Cassette #0.

VIII. HARDWARE

Symptoms of hardware problems: loss of power, changing of memory contents, keyboard lockup, no apparent expansion interface memory, miscellaneous woes.

64. Tighten the power transistor screw and resolder screw head.

The keyboard unit's power transistor (Q2) was screwed into place, with the screw acting as an electrical connection. This screw can corrode, resulting in erratic operation and frequent complete system crashes. Remove, clean and tighten this screw.

65. Terminate data lines either up or down, but only once.

The eight data lines are flying free in the TRS-80 system. For reliable operation, they should be terminated with resistors — but only once. Since some peripherals contain terminating resistors, the best idea is to obtain an edge connector, and solder resistors to it. Eight resistors (680 ohms, 1/4 watt) go from data lines to ground, eight resistors (470 ohms, 1/4 watt) go from data lines to 5 volts.

66. Add two capacitors to RAM bank the expansion interface.

The absence of two capacitors from the expansion interface has never been explained. There was a place for them, and their inclusion improves operation. Install two electrolytic capacitors (10 mF, 16V) in the positions marked C54 and C55 in the two rows of memory in the expansion interface.

67. Replace the CPU with a Z80A for high speed, or a Z80B for best operation.

If you are running your computer at high speed (100% increase or greater), you are exceeding the formal specifications for the Z80 processor. Although many Z80s can run at that higher speed, certain complex operations (stack operations, for example) can fail. Replacing the chip with a Z80A (4MHz version) or Z80B (6MHz version) will enhance reliability.

68. Replace memory for high speed, but observe DDU wiring changes.

Replacing expansion interface memory for high speed operation may not always help run the machine reliably. Newer expansion boxes contain a digital delay unit for memory selection, which has a fixed access time. Refer to Chapter 4 for wiring changes to the DDU for high speed.

69. Check power supply voltages with a calibrated meter.

Since the miniature voltage adjustment controls were not lacquered, vibration can cause them to move, resulting in the voltages being out of calibration. Units showing as little as 3.2 volts on the 5-volt line have been seen. Obtain a calibrated meter (not a $10 off-the-shelf number) and adjust the voltages — 12 volts first, then 5 volts. These are R10 (12 volts) and R5 (5 volts) in the keyboard unit.

70. Increase C48 in the expansion interface to keep the disk going.

A discouraging aspect of some disk operating systems is that they cannot recover from a disk drive which has 'timed out' — the motor has stopped. Some DOSes contain a Shift/Break option, but this does not always function, depending on when the disk timed out. A better solution is to increase the value of C48 (C62 in the newer expansion box) from 33 mF to 47 mF or 68 mF. Use a bead tantalum capacitor, not an aluminum electrolytic, if possible.

71. Add or remove disk termination resistors.

In order for disk selection to take place properly, termination resistors are required. Normally, these should only be installed in the furthest drive on the cable. However, as people trade or sell units, or purchase them from a variety of manufac-

turers, the number of termination resistors may vary. These can be found by removing the disk drive cover; they are a red, white or blue integrated-circuit sized package, usually near the edge connector. Make sure only one set of resistors is in place, no matter how many drives are in the system.

72. Make the reset modification to the expansion interface.

It seems the option to turn off a disk system should have been provided with the expansion interface. Ironically, other manufacturers have followed the original unresettable design. You can get out of many program hangups by pressing reset in a Level II keyboard only — so why not with an expansion box attached? Refer to Chapter 4 for details.

73. Change LNW termination resistors to 470/680 pairs.

LNW expansion systems have placed very low termination resistor values in their boards. If too many peripherals (or any peripherals with their own termination) are added to the system, computer lockup will probably occur. For reliability, these values should be changed to 680 ohms to ground, and 470 ohms to 5 volts.

74. Check the DDU in the newer expansion interface.

Sudden failure of memory in new expansion interfaces can almost always be traced to failure in the digital delay unit (DDU), marked Z37. This unit should be slightly warm — neither hot nor cold — to the touch. Since replacement DDUs are about $20, get some help if you're not sure whether the DDU is bad.

75. Make sure the ROM cable is okay, neither pulled from its sockets, nor with bent pins.

If the computer crashes with an occasional screenful of garbage, or patterns of@9@9, @A@A, etc., or it fills the screen from the bottom left with A A A , then suspect a flukey Level II ROM cable, or a cracked DIP shunt (see #7 below). Make sure the cable is fully installed. No pins should be bent or broken on the cable; replace it with another 24-pin jumper cable if any pins are bent or broken. (If they're bent, chances are they'll be broken when you try to bend them back).

76. Cold solder joints, splashes, balls, etc., can be anywhere.

This is the worst problem. TRS-80 computer boards are soldered mechanically, and residual solder bits are cleaned away. However, a few balls, splashes or hairs of solder may remain, breaking loose after the vibration of a year of use to cause trouble. Remove all cables and shake out the computer; small solder bits may drop out of the case. Also, broken traces can occur, particularly where any scratches in the green solder mask have occurred. This might be a 'professional help' category.

77. Check DIP shunts for correct or accidental breaks.

Another cause of @9@9, @A@A, @S@S, or the moving A A A A are DIP shunts. Only certain pins (see Chapter 4) should be broken in the DIP shunts (Z3 and Z72 in the keyboard unit). DIP shunts may have hairline cracks; remove them and check with an ohmmeter to be sure. You can replace DIP shunts with DIP switches or ordinary staples.

78. Reset problems are a bad CPU and related capacitor, no disk system in use, or are program-caused.

Users who recently install an expansion interface often forget that the reset button no longer works as it used to, and this is particularly a problem if no disk drives are attached (see #72 above). However, there are three other reasons for reset failure, even if disks are in place: the reset

pin of the Z80 CPU is bad (meaning replace it), or the associated charging capacitor and bleeder resistor (R47 and C42) are bad (replace them), or the program attempts to use the machine language HALT intruction (see Chapter 3).

IX. KEYBOARD

Symptoms of keyboard problems: keybounce, keys not working, multiple different characters, continuous scrolling ?SN or ?S errors on screen, constant repeating memory size question followed by odd characters.

79. Clean keyboard contacts — old one only — not ALPS.

The most straightforward cure for keybounce is cleaning the keyboard. On the bounce-prone keyboards (see photos in Chapter 4), the keycaps lift off. The keys can be cleaned with dry air, spray cleaner (works well but requires cleaning more often), or filled with silicone grease (some people say this improves the feel of the keyboard). The latter technique reduces bounce from vibration as well.

80. Use KBFIX and other software instead of a new keyboard.

A debounce program — automatic on most disk systems — can be loaded at the beginning of each session. Radio Shack's KBFIX is clumsy to get loaded, but works. The debounce routine presented in Chapter 3 works well. Note that new ROMs ('R/S L2 BASIC') contain a debounce routine, and a second routine added to this can result in very slow key response.

81. Get ALPS keyboard, which is the debounced keyboard.

If you can afford the $75 replacement cost, a Radio Shack Hall-effect ('ALPS') keyboard will permanently take care of bounce problems. If you switch often between BASIC and machine language programs, play games, or have a variety of disk operating systems or text editing programs, the ALPS keyboard may be the best solution.

82. Replace 74LS05s in the keyboard if multiple or unusual characters appear.

If multiple or unusual combinations of characters appear unexpectedly on the screen, or if characters begin to repeat by themselves, then the 74LS05s on the keyboard baseplate are probably bad. Replace them both, in sockets.

83. Replace or repair the keyboard cable if odd stuff shows up.

Another cause of odd character combinations — usually this like 'FIAQ9' or some such when a single or pair of letters is pressed — is a cracked or intermittent keyboard cable. Replace it; see Chapter 10.

X. VIDEO

Symptoms of video problems: no video, dim video, screen tearing or twitching, blurred screen, screen glitches.

84. Add a buffer stage or resistor to cure video tear.

Lowering the value of R14 in the video monitor will reduce the 'tearing' present when large blocks of graphics are displayed, especially using reverse video. See Chapter 4 for details. The other option is to obtain a video buffer circuit from Archbold Electronics.

85. Add a deglitch modification for a prettier screen.

The video 'hash' created when graphics are being drawn is caused by a conflict between the relatively independent video display circuitry and the need of the CPU to access video memory. Add the deglitch modification for a clearer screen, presented in 80 Microcomputing, Feb. 1982.

86. Get a new character generator, with descenders.

Upper case characters on the TRS-80 have always been consistent, but lower case characters can be displayed either with flying letters (g, p, q and y) or with descenders. The presence of a 'flying a' is normal on early computers. The new character generator with descenders can be obtained as a 'word processing character generator' from Radio Shack.

87. Horizontal and vertical image adjustment can be done.

If the image is not centered on the screen (use

```
10 FORX=15360TO16383:POKEX,191:NEXT
20 GOTO20
```

as a test program), adjust variable resistors R20 and R21 in the keyboard unit.

88. Adjust horizontal and vertical sync on the monitor.

If the image flickers badly, tears sideways, or rolls, the video monitor may be out of adjustment. Turn the white horizontal and vertical adjustment controls on the back of the monitor, just as with an ordinary television that exhibits the same symptoms.

89. Add a capacitor to cure video twitch.

A continuous, annoying screen twitch is the result of oscillations present at the video output. The insertion of a small capacitor (47 to 220 pF) between Z50 pin 3 and ground will eliminate the twitch.

90. Dimmers off! Get rid of the little runners on screen.

Similar to a twitch is the 'runner', a shaking horizontal line that works its way up or down through the screen, rocking one line of letters back and forth. This is a kind of reverse RFI — not caused by the computer for a change — which can be cured by turning off light dimmers, faulty fluorescent or neon lights, or similar interference producers. If you live in an apartment building, neighboring dimmers should not (but may) affect your computer.

91. Adjust the monitor for blurred characters.

There is no high-voltage adjustment for blurred characters; however, there are a few kludges. First, a higher line voltage (a full 120 volts) will increase the sharpness. Adjusting the internal vertical height control may reduce the image to the more in-focus (center) area of the screen.
Also, replacing the power transistor on the bottom of the chassis and the high-voltage rectifier (they both may exhibit undesirable characteristics) can improve the image. Unfortunately, the monitor is a very basic video display, and has few adjustments.

92. Correct the lowercase software for LDOS.

The 'universal' (alas, a dangerous word) lowercase modification presented in this book is not universal at bootup for one disk operating system — LDOS. However, the LDOS driver can be invoked separately and will work; refer to the documentation.

93. Check the 5 volts or the opto-isolator in the monitor.

A hardly existent or dim picture can be caused by insufficient 5 volts into the video cable from the computer (check for a bad connection), or a weak or dying optical isolator on the plug-in card inside the video monitor. First, try another monitor. If the system works with that monitor, resolder the cable connection if necessary; if that does not work, replace the optical isolator.

XI. RFI

Symptoms of RFI (Radio Frequency Interference): herringbone across television screens, complete loss of TV stations, whistling on radio (AM or FM), disconnection of wireless telephones, blockout of shortwave transmissions.

94. Shield the entire system for RFI.

The TRS-80 system is a broad-band interference generator; that is, what it sends out affects all bands of radio and television reception. The interference can be lowered by shielding: spray the inside of the case with aluminum paint and hook that to signal ground; use shielded multi-conductor cable for all peripherals (it's expensive); and create a 'Faraday cage' — if your decor will allow it — by shielding the room in which the computer is used with fine mesh.

XII. HEAT

Symptoms of heat problems: loss or lockup of program consistently after the machine has been on several hours.

95. Ventilate case or add fan, latter if it's an all-in-one system.

Normal ventilation using the slots cut into the TRS-80 and expansion box is adequate. However, if speed modifications, internal memory additions, etc., have been made, the power supply is asked to do extra work. A hard desk with good circulation around the computer is essential, and a small 'Sprite' type fan can be used occasionally to cool the system. A quiet fan may be added for continuous use, and is a necessity for an all-in-one-case system.

96. Remove power supplies from the expansion interface.

The two power supplies in the expansion interface generate a great deal of heat. With the video monitor stacked above, this can create an undesirably hot environment for memory. Remove the two supplies from the expansion box; the system won't look as compact, but it will have a longer life.

XIII. PRINTER

Symptoms of printer problems: will not backspace or underline, will not move up a line at a time during program listings.

97. Printer may need a line feed with every carriage return.

Many printers require not only a carriage return, but a line feed as well; examples are Teletypes and some Centronics printers. If you have this problem, first check with the manufacturer for a modification kit or instructions. If none is available, use a disk operating system with a CR/LF option, a printer driver patch, or a text-editing system with the CR/LF option. A hardware addition can be made to most printer interfaces to generate a linefeed when a carriage return is received.

XIV. USER PROCEDURE

98. Hide furry animals, keep away from wood stoves, etc.

Insignificant as it may seem, smoke is a severe abrasive to disks. Smoking, wood stoves, unskilled kitchen use (ahem), animal hair, and so forth, can result in airborne particles that affect disks, whose rotation acts as a static vortex to pull in those particles. Similar cautions apply to the piles of hair and grit that can gather in the keyboard. If you wonder just how much dirt is in the air, open the video monitor (with the power off, of course), and have a look. All around the high voltage will be piles of grit pulled in because of the electrical attraction.

99. Don't pull the cables while you're using the system.

This might seem obvious, but realize that pressing the reset button jostles the cable, just as does moving the keyboard to make it comfortable. Dropping a pencil, a cassette, or a diskette case on the cable may generate noise; see Chapter 7 for vibration protection.

100. Wait before power-up after power-down to protect memory.

When the manual cautions to wait ten seconds before repowering the system, it is not merely because the system doesn't always fully reset during that time, but also because the application of power to the memory must be done in this order: -5 volts, 5 volts, 12 volts. The -5 volt line can be lost with too hasty repowering of the system, and memory will be physically damaged.

101. Neither steel wool, nor metal filings, nor metal bits should be nearby.

Using the computer in a home 'shop' is dangerous. Wood bits may cause key-bounce and disk damage, but metal filings may cause the entire system to fail. A buildup of metal dust will decrease local resistance levels to short-circuits, or create unexpected current drains and intermittent operation.

102. No water or drinks nearby or open windows.

Drinking cups can damage disks, water glasses can fall over, carbonated soda can bubble tiny sugar globs onto tapes and disks, and open windows can invite water-carrying breezes and even rainstorms.

103. No magnets nearby, especially unobtrustive refrigerator types.

Refrigerator or bulletin board magnets are handy things, but because they are so ubiquitous, their danger to magnetic media is easy to forget. If there are any in the house, keep track of them . . . magnets shaped like daisies or fruits, bars, magnetic kiddie letters, even magnetic screwdrivers and scissors.

104. Watch out for salt air areas.

There's nothing like salt air for corroding metal, and metal is the heart of the computer's interconnections. Integrated circuit pins can corrode, cables can corrode, even screw connections can corrode. In boards previously reliable, salt air can corrode unseen bent pins, making the system flakey.

105. Keep telephone bells away, which are bulk erasers.

More than 50 volts shoot into a telephone bell's electromagnet. It's a strong magnetic field, and can act as a bulk eraser for disks sitting under them. Keep phones 'way back on the desk.

106. Keep out of Xray at airports; hand check disks and tape.

Xrays are damaging to magnetic materials. When going through an airport check, keep all your disks and tapes under your arm. Don't check them with your luggage, and don't let them go through the carry-on luggage conveyor belt Xray device. Insist on a hand check for those items.

107. Attach cables correctly.

Make sure all cables are correctly in place. Mark disk cables (the worst culprit) with 0, 1, 2 and 3, as well as 'top' and 'bottom'. Mark the expansion cable the same way (the metal wire or blue stripe is to the left, smooth side up). Mark all peripherals, particularly those which require power from the expansion box. Also, be sure the cassette cables are incorrectly (see #63 above).

108. Attach cables with power off, no matter who says what.

Occasionally, a manual may say something about turning the computer on, then attaching the cables. This is dead wrong. Correctly designed peripherals are always connected with the power off. If it is a construction project, avoid it; there's something wrong with the author's judgment. If it is a commercial product, return it; it shows poor design sense.

109. Disconnect power especially during summer.

High transient voltages can be present over the power and telephone lines during electrical storms. If your area is prone to electrical storms, keep your system unplugged — not just turned off. Also, disconnect direct-connect modems which can carry high voltages straight through to the rest of the system.

110. Obtain a static-free mat for computer and peripherals.

In dry climates, static buildup is common. A static zap can: change memory contents; damage memory; glitch a disk or cassette write; glitch a load; crash a program; reboot the system; or simulate just about any crash your system might be sensitive to. Obtain a static-free mat, or line your table with aluminum foil, and discharge to it — don't touch your computer first.

111. Keep temperature 55 to 80 degrees, relative humidity 50 to 80 percent.

This is simply good practice; although my computer is used in 40 degrees or below, disk reliability is lessened. Dry weather (low humidity) encourages static (see #110), and wet weather encourages corrosion (see #104).

112. Test homebrew devices before installation.

There is very little more to say; always 'proofread' your circuit with a second person, no matter how exhausting it may seem. It will prolong the life of your computer, and the homebrew device might even work the first time.

What are the chances that your problem will be one of these? Probably, the difficulty will be a combination. This list is derived from work on hundreds of TRS-80 system combinations and relatives. Virtually every suggestion has been made and every cure implemented. Sometimes the problems were multiple: one unit suffered from salt air, bent pins, corroded connectors, unbuffered cables, slow memory, and a bum program. Another was the victim of modifications made with a Boy Scout woodburning kit instead of a soldering iron.

Even if your problem is not included here,these suggestions should give you a clue about where and how to begin looking. Use the Radio Shack technical manual diagnostic chart — but don't believe the 'ROM is bad' section, because I've never seen a bad ROM. Instead, suspect a bus driver difficulty (Z22, 38, 39, 55, 75 and 76 in the keyboard). Otherwise, the manual will give you a good start on the tough stuff.

Last Thoughts

The solons at Radio Shack have done something very impressive: they have created a popular personal computer. From it have come the Models II and III, the Pocket Computers I and II, the Color Computers, the Model 16 is on the way, and a host of engineers across the world have been encouraged to come up with TRS-80 compatible hardware and software, and even full computer improvements like the LNW-80.

But they have done something unwittingly even more special: they have, through strict and strange corporate policies, challenge users to create the Custom TRS-80. Because computers become appliances more and more each day, there will only be one Custom TRS-80 . . . the humble Model I.

NOTES

INDEX

* indicates discussion of topic
\# indicates a program listing
$ indicates a schematic diagram

NOTES

Appendix I

Parts Suppliers

The Four Stars

Digi-Key Corporation, Hiway 32 South, P.O. Box 677, Thief River Falls, MN 56701. 800 346-5144. *COD, check, money order, credit cards. Volume discounts over $100; shipping, insurance prepaid.*

This company is in my opinion the hobbyist's best. Shipping is fast (five days from ordering to my door in Vermont), and most items are in stock. Their catalog is monthly, and items not stocked are not listed. All merchandise is prime; no bubble packs.

QT Computer Systems, 15335 S. Hawthorne Blvd., Lawndale, CA 90260. 800 421-5150. *COD under $100, check, money order; credit cards preferred. Quantity discounts, no insurance.*

A good hobbyist catalog similar to Digi-Key, with competitive prices. This is a new company, but they are already beginning to make a mark for promptness, exceeding courtesy, and prime parts. Their catalog is very complete and quite up-to-date.

Advanced Computer Products, 1310 E. Edinger, Santa Ana, CA 92705. 800 854-8230. *COD, check, money order, credit cards. Volume discounts, no insurance.*

One of the best catalogs in the business, prompt, but be wary of substitutions in orders. Specify voltages of devices and check upon receipt. Expect harrassment from Customer Service. Otherwise, they have what you can't get anywhere else.

Jameco Electronics, 1355 Shoreway Road, Belmont, CA 94002. 415 592-8097. *COD, check, money order, no credit cards. No discounts, no insurance.*

One almost wonders why to put Jameco in with the four best, but their selection is contemporary and their response prompt. They have items others don't have in stock for the popular computer hobbyist. Bubble pack stuff on retail store racks at Lafayette Radio and others. Highest prices in the business.

And Others

Jade Computer Products, 4901 West Rosecrans Ave., Hawthorne, CA 90250. 800 421-5500. *No CODs; checks, money order; credit cards preferred. Quantity discounts; insurance under 50 lbs.*

This company works hard at immediate hobbyist needs and some unusual items. Get their catalog, but consult monthly ads in electronics magazines for hot items.

Priority One Electronics, 16723C Roscoe Blvd., Sepulveda, CA 91343. 800 423-5633. *No CODs; check, money order, credit cards. Quantity discounts, insurance.*

Priority deals for the most part in larger items for computer hobbyists, with only a token selection of small parts. This company concentrates on boards and naked disk drives, and heavier hardware.

Hobbyworld Electronics, 19511 Business Center Dr., Northridge, CA 91324. 800 423-5387, (800 382-3651 in CA). *COD ($1.25 extra), check, credit cards. No discounts, no insurance.*

Hobbyworld is the computer hobbyist's pop culture. It stocks all the hot items with a high turnover. Look to them for low prices on items you need right away.

Electrolabs, P.O. Box 6721, Stanford, CA 94305.

The best part is always their funny and schizophrenic catalog with an honest selection and a wealth of good information. For example . . .

"Save yourselves $6.75 and use a 25 cent transistor the next time your looking for a temperature probe." Also, TTL Family rules of Incest are great.) The shipping was always prompt and the merchandise prime.

Not Recommended

Active Electronic Sales, P.O. Box 1035, Framingham, MA 01701. 617 879-0077. *Minimum $10, handling $2, check (wait to clear), money order. No discounts, no insurance.*

This group claims to be "The World's Largest International Semiconductor Distributor", which implies lots of stock, in stock. No way. All my orders have been returned 25 percent filled, with 50 percent errors.

Appendix II.
Bibliography.

Manuals, Guides, and Data Books

Radio Shack, Tandy Corporation. Forth Worth, Texas.

- *TRSDOS & Disk BASIC Reference Manual*, 1979.
- *TRS-80 Micro Computer Technical Reference Handbook*, 1978.
- Printer Interface Cable, Service Manual.
- Expansion Interface, Service Manual.
- TRS-80 16K RAM Expansion, Service Manual. With Addendum.

National Semiconductor, 2900 Semiconductor Drive, Santa Clara, California 95051.

- *TTL Databook*, 1975.
- *Memory Databook*, 1977.
- *CMOS Databook*, 1977.
- *Series 8000 Microprocessor Family Handbook*, 1978.
- — *Special Functions Databook*, 1979.
- — *Linear Data Book*, 1976.
- — *Linear Applications*, Volume 1, 1973.
- — *Linear Applications*, Volume 2, 1977.
- — *Voltage Regulator Handbook*, 1975.
- — *Pressure & Temperature Transducers*, 1974.

Motorola, Inc. *The Complete Motorola Microcomputer Data Library*. Technical Information Center, Box 20912, Phoenix, Arizona 85036. 1978.

Pro-Log Corporation. *Microprocessor User's Guide*. 2411 Garden Road, Monterey, California 93940. 1980.

Zilog, Inc. *Z80-CPU / Z80A-CPU Technical Manual*. 10340 Bubb Road, Cupertino, California 95014. 1977.

Reference Books

Jonathan A. Titus, Christopher A. Titus, and David G. Larsen, *TRS-80 Interfacing. Books 1 and 2*. Each 250 pp. Howard W. Sams and Co., Inc., 4300 West 62nd St., Indianapolis, Indiana 46268. 1979, 1980.

Sybex, 2020 Milvia Street, Berkeley, California 94704.

- Rodnay Zaks, *Microprocessors, from Chips to Systems*. 416 pp. 2nd ed., 1977.
- Rodnay Zaks, *Programming the Z80*. 624 pp. 1979.
- Austin Lesea and Rodnay Zaks, *Microprocessor Interfacing Techniques*. 416 pp. 2nd ed., 1978.

William Barden, Jr., *The Z-80 Microcomputer Handbook*. 304 pp. Howard W. Sams and Co., Inc., 4300 West 62nd St., Indianapolis, Indiana 46268. 1978.

William Barden, Jr., *TRS-80 Assembly Language Programming*. 224 pp. Radio Shack, Fort Worth, Texas. 1979.

Adam Osborne, Jerry Kane, Russell Rector, and Susanna Jacobson, *Z80 Programming for Logic Design*. Osborne and Associates, P. O. Box 2036, Berkeley, California 94702. 1978.

Jim Perry and Chris Brown, eds., *80 Programs for the TRS-80*. 234 pp. 1001001 Inc., Peterborough, New Hampshire 03458. 1979.

John Blattner and Bryan Mumford, *Inside Level II, A Programmer's Guide to the TRS-80 ROMs*. 65 pp. Mumford Micro Systems, Box 435, Summerland, California 93067. 1980.

H. C. Pennington, *TRS-80 Disk and Other Mysteries*. IJG Computer Services, 1260 W. Foothill Blvd., Upland, California 91768. 1979, 1980, 1981.

James Farvour, *Microsoft BASIC Decoded and Other Mysteries*. IJG Computer Services, 1260 W. Foothill Blvd., Upland, California 91768. 1981.

David A. Lien, *User's manual for Level 1*. 232 pp. Radio Shack, Fort Worth. 1978.

W. J. Weller, *Practical Microcomputer Programming: The Z80*. 480 pp. Northern Technology Books, Box 62, Evanston, Illinois 60204. 1978.

Thomas C. McIntire, *Software Interpreters for Microcomputers*. 233 pp. John Wiley and Sons, New York. 1978.

Robert Richardson, *Disassembled Handbook for TRS-80.* (In continuing volumes; 1, 2 and 3 published to date). Richcraft Engineering Ltd., Drawer 1065, Chautauqua, New York 14722. 1980.

Forest M. Mims, III, *Engineer's Notebook: A Handbook of Integrated Circuit Applications.* 128 pp. Radio Shack, Fort Worth, 1979.

Paul Warme, *BASEX: A Simple Language and Compiler for 8080 Systems.* With TRS-80 addendum. 97 pp. BYTE Books, 70 Main Street, Peterborough, New Hampshire 03458. 1979.

Forth, Inc., *Microforth Primer.* FORTH, Inc., 815 Manhattan Avenue, Manhattan Beach, California 90266. 1978.

Hal Chamberlin. *Musical Applications of Microprocessors.* 660 pp. Hayden Book Company, Inc., Rochelle Park, New Jersey. 1980.

Wayne Bateman, *Introduction to Computer Music.* 314 pp. John Wiley and Sons, New York. 1980.

G. Michael Schneider, Steven W. Weingart, and David M. Perlman, *An Introduction to Programming and Problem Solving with Pascal.* 394 pp. John Wiley and Sons, New York. 1978.

Periodicals and Irregulars

80 Microcomputing. 80 Pine St., Peterborough, New Hampshire 03458. $18 per year.

Kilobaud Microcomputing. 73 Pine St., Peterborough, New Hampshire 03458. $25 per year.

BYTE. 70 Main St., Peterborough, New Hampshire 03458. $19 per year.

onComputing. 70 Main St., Peterborough, New Hampshire 03458. $12 per year.

80-U.S. Journal. 3838 South Warner Street, Tacoma, Washington 98409. $24 per year.

Softside. 6 South Street, Milford, New Hampshire 03055. $24 per year.

Popular Electronics. One Park Avenue, New York, New York 10016. $14 per year.

The Alternate Source. 1806 Ada Street, Lansing, Michigan 48910. $12 per year.

Radio Electronics. 200 Park Avenue South, New York, New York 10003. $9.98 per year.

CLOAD. P.O. Box 1267, Goleta, California 93017. $42 per year, on cassette.

Fairfield County Users Group, *Voice of the 80.* C/O Alan Abrahamson, 10 Richlee Road, Norwalk, Connecticut 06851.

Marin County TRS-80 Users Group Newsletter. P.O. Box 895, Novato, California 94948.

Computer Base Lubbock. C/O Roger Smith, 2601 Nonesuch Dr., Lot 1802, Abilene, Texas 79606.

TCS, Club Project of the Tidewater TRS-80 Users Group. P.O. Box 10281, Norfolk, Virginia 23513.

Northern Bytes. Micrcomputer Users International. C/O Jack Decker, 1804 West 18th Street, Lot 155 Sault Suite. Marie, Michigan 49783.

Orange Country TRS-80 Users Group Newsletter. C/O Ed Faulk, 2531 E. Commonwealth, Fullerton, CA 92631.

The Bit Bucket. Texhoma Microcomputer Enthusiasts, P.O. Box 1384, Wichita Falls, Texas 76301.

Amateur Computer Group of New Jersey News. UCTI, 1776 Raritan Road, Scotch Plains, New Jersey 07076.

Delaware Valley Computer Club Newsletter. P.O. Box 651, Levittown, Pennsylvania 19058.

Cleveland Digital Group, *TRS-80 User's Group Newsletter.* C/O Cleveland Heights Public Library, 2345 Lee Road, Cleveland Heights, Ohio 44112. Or C/O 1838 Willowhurst Ave., Cleveland, Ohio 44112.

Chicatrug News. Chicago TRS-80 Users Group. Emmanual B. Garcia Jr., and Associates, 203 N. Wabash, Room 2102, Chicago, Illinois 60601.

Thought and Relaxation

Frederick P. Brooks, Jr., *The Mythical Man-Month: Essays on Software Engineering.* Addison-Wesley Publishing Company, Reading, Massachusetts. 1978.

Douglas Hofstadter. *Godel, Escher, Bach: The Eternal Golden Braid.* Vintage Books. 1980.

NOTES

APPENDIX 3

Byte Values and Their Equivalents

Code		POKE displays:			PRINT:	Edtasm	Standrd
Hex Val	Dec Val	Without L/Case	With Old LC	With New LC	w/ LC Driver	Z80 Opcode	ASCII Meaning
00	0	@	gaming	@	none	NOP	NUL
01	1	A	gaming	A	none	LD BC,NN	SOH
02	2	B	gaming	B	none	LD (BC),A	STX
03	3	C	gaming	C	none	INC BC	ETX
04	4	D	gaming	D	none	INC B	EOT
05	5	E	gaming	E	none	DEC B	ENQ
06	6	F	gaming	F	none	LD B,N	ACK
07	7	G	gaming	G	none	RLCA	BEL
08	8	H	gaming	H	bkspce	EX AF,AF'	BS
09	9	I	gaming	I	bksp lin	ADD HL,BC	HT
0A	10	J	gaming	J	linefeed	LD A,(BC)	LF
0B	11	K	gaming	K	none	DEC BC	VT
0C	12	L	gaming	L	formfeed	INC C	FF
0D	13	M	gaming	M	car retn	DEC C	CR
0E	14	N	gaming	N	crsr on	LD C,N	SO
0F	15	O	gaming	O	crsr off	RRCA	SI
10	16	P	gaming	P	none	DJNZ d	DLE
11	17	Q	gaming	Q	none	LD DE,NN	DC1
12	18	R	gaming	R	none	LD (DE),A	DC2
13	19	S	gaming	S	none	INC DE	DC3
14	20	T	gaming	T	none	INC D	DC4
15	21	U	gaming	U	none	DEC D	NAK
16	22	V	gaming	V	none	LD D,N	SYN
17	23	W	gaming	W	widemode	RLA	ETB
18	24	X	gaming	X	bkspcrsr	JR d	CAN
19	25	Y	gaming	Y	adv crsr	ADD HL,DE	EM
1A	26	Z	gaming	Z	dn linfd	LD A,(DE)	SUB
1B	27	l brace	gaming	up arr	up linfd	DEC DE	ESC
1C	28	dn arr	gaming	dn arr	home crsr	INC E	FS
1D	29	r brace	gaming	leftarr	strt crsr	DEC E	GS
1E	30	rt arr	gaming	rt arr	erase lin	LD E,N	RS
1F	31		gaming		clr frame	RRA	US
20	32	space	space	space	space	JR NZ,d	space
21	33	!	!	!	!	LD HL,NN	!
22	34	"	"	"	"	LD (NN),HL	"
23	35	#	#	#	#	INC HL	#
24	36	$	$	$	$	INC H	$
25	37	%	%	%	%	DEC H	%
26	38	&	&	&	&	LD H,N	&
27	39	'	'	'	'	DAA	'
28	40	(	(	(	(	JR Z,d	(
29	41	)	)	)	)	ADD HL,HL	)
2A	42	*	*	*	*	LD HL,(NN)	*
2B	43	+	+	+	+	DEC HL	+
2C	44	,	,	,	,	INC L	,
2D	45	–	–	–	–	DEC L	–
2E	46	.	.	.	.	LD L,N	.
2F	47	/	/	/	/	CPL	/
30	48	0	0	0	0	JR NC,d	0

Code		POKE displays:			PRINT:	Edtasm	Standrd
Hex Val	Dec Val	Without L/Case	With Old LC	With New LC	w/ LC Driver	Z80 Opcode	ASCII Meaning
31	49	1	1	1	1	LD SP,NN	1
32	50	2	2	2	2	LD (NN),A	2
33	51	3	3	3	3	INC SP	3
34	52	4	4	4	4	INC (HL)	4
35	53	5	5	5	5	DEC (HL)	5
36	54	6	6	6	6	LD (HL),N	6
37	55	7	7	7	7	SCF	7
38	56	8	8	8	8	JR C,d	8
39	57	9	9	9	9	ADD HL,SP	9
3A	58	:	:	:	:	LD A,(NN)	:
3B	59	;	;	;	;	DEC SP	;
3C	60	<	<	<	<	INC A	<
3D	61	=	=	=	=	DEC A	=
3E	62	>	>	>	>	LD A,N	>
3F	63	?	?	?	?	CCF	?
40	64	@	open quote	@	@	LD B,B	@
41	65	A	A	A	A	LD B,C	A
42	66	B	B	B	B	LD B,D	B
43	67	C	C	C	C	LD B,E	C
44	68	D	D	D	D	LD B,H	D
45	69	E	E	E	E	LD B,L	E
46	70	F	F	F	F	LD B,(HL)	F
47	71	G	G	G	G	LD B,A	G
48	72	H	H	H	H	LD C,B	H
49	73	I	I	I	I	LD C,C	I
4A	74	J	J	J	J	LD C,D	J
4B	75	K	K	K	K	LD C,E	K
4C	76	L	L	L	L	LD C,H	L
4D	77	M	M	M	M	LD C,L	M
4E	78	N	N	N	N	LD C,(HL)	N
4F	79	O	0	O	O	LD C,A	O
50	80	P	P	P	P	LD D,B	P
51	81	Q	Q	Q	Q	LD D,C	Q
52	82	R	R	R	R	LD D,D	R
53	83	S	S	S	S	LD D,E	S
54	84	T	T	T	T	LD D,H	T
55	85	U	U	U	U	LD D,L	U
56	86	V	V	V	V	LD D,(HL)	V
57	87	W	W	W	W	LD D,A	W
58	88	X	X	X	X	LD E,B	X
59	89	Y	Y	Y	Y	LD E,C	Y
5A	90	Z	Z	Z	Z	LD E,D	Z
5B	91	l.brkt.	l.brkt.	up arr.	up arr.	LD E,E	l.brkt.
5C	92					LD E,H	slant
5D	93					LD E,L	r.brkt.
5E	94					LD E,(HL)	carat
5F	95					LD E,A	l.arr.
60	96	@	open quote	pound	@	LD H,B	undef.
61	97	A	a	a	a	LD H,C	a
62	98	B	b	b	b	LD H,D	b
63	99	C	c	c	c	LD H,E	c
64	100	D	d	d	d	LD H,H	d
65	101	E	e	e	e	LD H,L	e

Code		POKE displays:			PRINT:	Edtasm	Standrd
Hex Val	Dec Val	Without L/Case	With Old LC	With New LC	w/ LC Driver	Z80 Opcode	ASCII Meaning
66	102	F	f	f	f	LD H,(HL)	f
67	103	G	g	g	g	LD H,A	g
68	104	H	h	h	h	LD L,B	h
69	105	I	i	i	i	LD L,C	i
6A	106	J	j	j	j	LD L,D	j
6B	107	K	k	k	k	LD L,E	k
6C	108	L	l	l	l	LD L,H	l
6D	109	M	m	m	m	LD L,L	m
6E	110	N	n	n	n	LD L,(HL)	n
6F	111	O	o	o	o	LD L,A	o
70	112	P	p	p	p	LD (HL),B	p
71	113	Q	q	q	q	LD (HL),C	q
72	114	R	r	r	r	LD (HL),D	r
73	115	S	s	s	s	LD (HL),E	s
74	116	T	t	t	t	LD (HL),H	t
75	117	U	u	u	u	LD (HL),L	u
76	118	V	v	v	v	HALT	v
77	119	W	w	w	w	LD (HL),A	w
78	120	X	x	x	x	LD A,B	x
79	121	Y	y	y	y	LD A,C	y
7A	122	Z	z	z	z	LD A,D	z
7B	123					LD A,E	l.brace
7C	124					LD A,H	separator
7D	125					LD A,L	r.brace
7E	126					LD A,(HL)	wave
7F	127					LD A,A	delete

Upper Character Set

HEX Val	DEC Val	POKE Display:	BASIC Keyword:	PRINT Display:	Z80 Opcode:
80	128	/G/	END	/G/	ADD A,B
81	129	/G/	FOR	/G/	ADD A,C
82	130	/G/	RESET	/G/	ADD A,D
83	131	/G/	SET	/G/	ADD A,E
84	132	/G/	CLS	/G/	ADD A,H
85	133	/G/	CMD	/G/	ADD A,L
86	134	/G/	RANDOM	/G/	ADD A,(HL)
87	135	/G/	NEXT	/G/	ADD A,A
88	136	/G/	DATA	/G/	ADC A,B
89	137	/G/	INPUT	/G/	ADC A,C
8A	138	/G/	DIM	/G/	ADC A,D
8B	139	/G/	READ	/G/	ADC A,E
8C	140	/G/	LSET	/G/	ADC A,H
8D	141	/G/	GOTO	/G/	ADC A,L
8E	142	/G/	RUN	/G/	ADC A,(HL)
8F	143	/G/	IF	/G/	ADC A,A
90	144	/G/	RESTORE	/G/	SUB B
91	145	/G/	GOSUB	/G/	SUB C
92	146	/G/	RETURN	/G/	SUB D
93	147	/G/	REM	/G/	SUB E

Upper Character Set

HEX Val	DEC Val	POKE Display:	BASIC Keyword:	PRINT Display:	Z80 Opcode:
94	148	/G/	STOP	/G/	SUB H
95	149	/G/	ELSE	/G/	SUB L
96	150	/G/	TRON	/G/	SUB (HL)
97	151	/G/	TROFF	/G/	SUB A
98	152	/G/	DEFSTR	/G/	SBC A,B
99	153	/G/	DEFINT	/G/	SBC A,C
9A	154	/G/	DEFSNG	/G/	SBC A,D
9B	155	/G/	DEFDBL	/G/	SBC A,E
9C	156	/G/	LINE	/G/	SBC A,H
9D	157	/G/	EDIT	/G/	SBC A,L
9E	158	/G/	ERROR	/G/	SBC A,(HL)
9F	159	/G/	RESUME	/G/	SBC A,A
A0	160	/G/	OUT	/G/	AND B
A1	161	/G/	ON	/G/	AND C
A2	162	/G/	OPEN	/G/	AND D
A3	163	/G/	FIELD	/G/	AND E
A4	164	/G/	GET	/G/	AND H
A5	165	/G/	PUT	/G/	AND L
A6	166	/G/	CLOSE	/G/	AND (HL)
A7	167	/G/	LOAD	/G/	AND A
A8	168	/G/	MERGE	/G/	XOR B
A9	169	/G/	NAME	/G/	XOR C
AA	170	/G/	KILL	/G/	XOR D
AB	171	/G/	LSET	/G/	XOR E
AC	172	/G/	RSET	/G/	XOR H
AD	173	/G/	SAVE	/G/	XOR L
AE	174	/G/	SYSTEM	/G/	XOR (HL)
AF	175	/G/	LPRINT	/G/	XOR A
B0	176	/G/	DEF	/G/	OR B
B1	177	/G/	POKE	/G/	OR C
B2	178	/G/	PRINT	/G/	OR D
B3	179	/G/	CONT	/G/	OR E
B4	180	/G/	LIST	/G/	OR H
B5	181	/G/	LLIST	/G/	OR L
B6	182	/G/	DELETE	/G/	OR (HL)
B7	183	/G/	AUTO	/G/	OR A
B8	184	/G/	CLEAR	/G/	CP B
B9	185	/G/	CLOAD	/G/	CP C
BA	186	/G/	CSAVE	/G/	CP D
BB	187	/G/	NEW	/G/	CP E
BC	188	/G/	TAB(	/G/	CP H
BD	189	/G/	TO	/G/	CP L
BE	190	/G/	FN	/G/	CP (HL)
BF	191	/G/	USING	/G/	CP A
C0	192	/G/	VARPTR	/G/	RET NZ
C1	193	/G/	USR	TAB+01	POP BC
C2	194	/G/	ERL	TAB+02	JP NZ,NN
C3	195	/G/	ERR	TAB+03	JP NN
C4	196	/G/	STRING$	TAB+04	CALL NZ,NN
C5	197	/G/	INSTR	TAB+05	PUSH BC
C6	198	/G/	POINT	TAB+06	ADD A,N
C7	199	/G/	TIME$	TAB+07	RST 00H

Upper Character Set

HEX Val	OEC Val	POKE Oisplay:	BASIC Keyword:	PRINT Display:	ZBO Dpcode:
CB	2D0	/G/	MEM	TAB+DB	RET Z
C9	201	/G/	INKEY$	TAB+D9	RET
CA	202	/G/	THEN	TAB+1D	JP Z, NN
CB	203	/G/	NOT	TAB+11	<Note 1>
CC	204	/G/	STEP	TAB+12	CALL Z,NN
CO	205	/G/	+	TAB+13	CALL NN
CE	206	/G/	–	TAB+14	AOC A,N
CF	207	/G/	*	TAB+15	RST OBH
00	20B	/G/	/	TAB+16	RET NC
01	209	/G/	**	TAB+17	POP OE
02	210	/G/	ANO	TAB+18	JP NC,NN
03	211	/G/	OR	TAB+19	OUT (N],A
04	212	/G/	>	TAB+20	CALL NC,NN
05	213	/G/	=	TAB+21	PUSH DE
06	214	/G/	<	TAB+22	SUB N
D7	215	/G/	SGN	TAB+23	RST 10H
0B	216	/G/	INT	TAB+24	RET C
D9	217	/G/	ABS	TAB+25	EXX
0A	21B	/G/	FRE	TAB+26	JP C,NN
0B	219	/G/	INP	TAB+27	IN A,(N]
0C	220	/G/	POS	TAB+2B	CALL C,NN
00	221	/G/	SQR	TAB+29	<Note 2>
DE	222	/G/	RNO	TAB+3D	SBC A,N
0F	223	/G/	LOG	TAB+31	RST 1BH
E0	224	/G/	EXP	TAB+32	RET PD
E1	225	/G/	COS	TAB+33	PDP HL
E2	226	/G/	SIN	TAB+34	JP PD,NN
E3	227	/G/	TAN	TAB+35	EX (SP],HL
E4	22B	/G/	ATN	TAB+36	CALL P0,NN
E5	229	/G/	PEEK	TAB+37	PUSH HL
E6	230	/G/	CVI	TAB+3B	AND N
E7	231	/G/	CVS	TAB+39	RST 2DH
E8	232	/G/	CVD	TAB+40	RET PE
E9	233	/G/	EOF	TAB+41	JP (HL]
EA	234	/G/	LOC	TAB+42	JP PE,NN
EB	235	/G/	LOF	TAB+43	EX DE,HL
EC	236	/G/	MKI$	TAB+44	CALL PE,NN
E0	237	/G/	MKS$	TAB+45	<Note 3>
EE	23B	/G/	MKO$	TAB+46	XDR N
EF	239	/G/	CINT	TAB+47	RST 2BH
F0	240	/G/	CSNG	TAB+48	RET P
F1	241	/G/	COBL	TAB+49	PDP AF
F2	242	/G/	FIX	TAB+50	JP P,NN
F3	243	/G/	LEN	TAB+51	DI
F4	244	/G/	STR$	TAB+52	CALL P,NN
F5	245	/G/	VAL	TAB+53	PUSH AF
F6	246	/G/	ASC	TAB+54	DR N
F7	247	/G/	CHR$	TAB+55	RST 3DH
FB	248	/G/	LEFT$	TAB+56	RET M
F9	249	/G/	RIGHT$	TAB+57	LD SP,HL
FA	250	/G/	MIO$	TAB+5B	JP M,NN
FB	251	/G/	———	TAB+59	EI

Upper Character Set

HEX Val	DEC Val	PDKE Display:	BASIC Keyword:	PRINT Display:	ZBD Dpcode:
FC	252	/G/	------	TAB+6D	CALL M,NN
FD	253	/G/	------	TAB+61	<Note 4>
FE	254	/G/	------	TAB+62	CP N
FF	255	/G/	------	TAB+63	RST 38H

Note 1: CB includes RLC, RRC, RL, RR, SLA, SRL, BIT, RES, SET.

Note 2: DD includes IX register manipulations.

Note 3: ED includes miscellaneous IN, OUT, LD, and ADC functions as well as block move and compare commands, and interrupt mode setting and handling.

Note 4: FD includes IY register manipulations.

Graphics Note: In the table above /G/ means a graphics character will be displayed. The table below shows the graphics characters and their ASCII code in decimal.



```
               00100 ;
               00110 ; -----------------------------------------------------
               00120 ;    * * * * *   K E E P I T   3 . 2   * * * * *
               00130 ; -----------------------------------------------------
               00140 ;    >>>>      SYSTEM /1234S TO ENTER       <<<<
               001S0 ; -----------------------------------------------------
               00160 ;    >>>>      USE   *REAO   FOR MENU       <<<<
               00170 ; -----------------------------------------------------
               00180 ;
               00190 ; COPYRIGHT (C) 1980, 1981 BY OENNIS 8ATHORY KITSZ
               00200 ; ALL RIGHTS RESERVED.  NO PART OF THIS PROGRAM MAY
               00210 ; 8E REPRODUCEO 8Y ANY MEANS, ELECTRONIC, ELECTRO-
               00220 ; MECHANICAL, OR IN PRINT, WHETHER 8Y METHOOS IN
               00230 ; USE OR CONCEIVEO IN THE FUTURE, WITHOUT SPECIFIC
               00240 ; WRITTEN PERMISSION OF THE AUTHOR.
               00250 ;
4099           00260 INKEYS  EQU     4099H    ;INKEY$ 8YTE STORAGE AREA
03FB           00270 KYSCAN  EQU     03FBH    ;KEYBOARO SCAN ROUTINE
4030           00280 PORTFF  EQU     4030H    ;CASSETTE OUTPUT PORT
401A           00290 KPLACE  EQU     401AH    ;1-BYTE KEYSTROKE STORE
4019           00300 SHIFTR  EQU     4019H    ;STORAGE FOR LC ORIVER
4004           00310 RESTRT  EQU     4004H    ;8ASIC INTERP PATCH POINT
40A0           00320 STGENO  EQU     40A0H    ;ENO OF STRINGS POINTER
40E8           00330 STACKR  EQU     40E8H    ;8ASIC STACK POINTER
40F0           00340 VARENO  EQU     40F0H    ;ENO OF VARIA8LE POINTER
06CC           00350 REAOY   EQU     06CCH    ;RETURN TO REAOY INTACT
4081           00360 MEMTOP  EQU     4081H    ;TOP OF 8ASIC MEMORY
4000           00370 SETPTS  EQU     4000H    ;SETPOINT RESTART AOORESS
0264           00380 WRT8YT  EQU     0264H    ;ROM 8YTE WRITE ROUTINE
1078           00390 BYTE    EQU     1078H    ;ROM READ KEYS & TOKENIZE
3C00           00400 VIOEO   EQU     3C00H    ;FIRST SCREEN LOCATION
               00410 ;
3039           00420         ORG     3039H
               00430 ; PREPARE RAM AREAS FOR USE
3039 2AB140    00440 START   LD      HL,(40B1H)
303C E0SBA040  00450         LD      OE,(40A0H)
3040 0607      00460         LD      B,7
3D42 2B        0D47D         DEC     HL
3D43 18        00480         DEC     DE
3044 10FC      00490         DJNZ    $-2
3046 22B140    00500         LO      (40B1H),HL
3049 ED53AD40  00510         LD      (40A0H),DE
304D 23        00520         INC     HL
304E E5        0D530         PUSH    HL
304F FDE1      00S40         PDP     IY
               0D550 ; READY INTERPRETER VECTDR PATCH
               00560 ; GET CURRENT CDNTENTS OF 4004H
30S1 3EC3      0D57D         LD      A,0C3H
3D53 FD7700    0DS8D         LD      (IY+0),A
3056 EDS80440  00590         LD      DE,(RESTRT)
305A FD73D1    0060D         LD      (IY+1),E
30S0 F07202    D0610         LD      (IY+2),0
3060 FD77D3    00620         LD      (IY+3),A
3D63 117631    0063D         LD      OE,SKPSTP
3D66 F07304    00640         LD      (IY+4),E
3069 FD72DS    006SD         LD      (IY+5),D
306C 23        0066D GRINS   INC     HL
306D 23        00670         INC     HL
306E 23        00680         INC     HL
306F 220440    00690         LD      (RESTRT),HL
3072 AF        00700         XOR     A
3073 321940    00710         LO      (SHIFTR),A
               00720 ; CALL CLEAR AND RETURN TD BASIC
3D76 COC901    D073D RSLVII  CALL    01C9H
3079 C0611B    D0740         CALL    1661H
307C 211101    007S0         LD      HL,0111H
307F COA72B    0076D         CALL    28A7H
3082 C3CC06    00770         JP      REAOY
               0D780 ; START KEYBOARD SCAN
3085 213640    00790 KBPFIX  LO      HL,4036H
3D8B 01013B    00800         LD      BC,3801H
3D8B 1600      D081D         LD      D,D
               00820 ; CHECK EACH RDW OF KEYS
308D 0A        00830 KEYPRS  LD      A,(BC)
308E 5F        00840         LD      E,A
308F A3        00850         AND     E
3090 2D1B      00860         JR      NZ,STROKE
3092 77        00870         LD      (HL),A
               0088D ; INC ANO RDTATE TD CHECK NEXT ROW
3093 14        00890 RECHEK  INC     0
3094 2C        0090D         INC     L
309S C801      0091D         RLC     C
3097 79        0092D         LD      A,C
               00930 ; CHECK IF LAST ROW (NOT INCL. SHIFT)
309B 0680      00940         SUB     80H
3D9A 20F1      0D950         JR      NZ,KEYPRS
               00960 ; CHECK IF KEYBOARO CLEAR
309C 0607      00970         LD      8,7
309E 20        00980 CLRMEM  DEC     L
309F B6        00990         ADO     A,(HL)
30AD 10FC      01D00         DJNZ    CLRMEM
30A2 A7        01010         AND     A
30A3 3E00      01020         LD      A,0
30AS C0        01030         RET     NZ
               01040 ; RESET AUTOREPEAT OELAY TO 0
30A6 321A40    010S0         LD      (KPLACE),A
30A9 C9        01060         RET
               01070 ; IF KEYSTROKE FOUNO CHECK AUTOREPEAT LOOP
30AA A6        01080 STROKE  ANO     (HL)
30AB 281E      01090         JR      Z,FOUNO
30A0 3A9940    01100         LD      A,(INKEYS)
3080 A7        01110         ANO     A
30B1 20E0      01120         JR      NZ,RECHEK
30B3 3A1A40    01130         LD      A,(KPLACE)
3086 3C        01140         INC     A
3087 321A40    011S0         LO      (KPLACE),A
30BA FEFF      01160         CP      0FFH
308C 280B      01170         JR      Z,0ECA
30BE CS        01180         PUSH    8C
308F 06FF      01190         LD      8,0FFH
30C1 10FE      01200 TMWSTE  OJNZ    TMWSTE
30C3 C1        01210         POP     8C
30C4 18C0      01220         JR      RECHEK
30C6 30        01230 OECA    OEC     A
30C7 321A40    01240         LO      (KPLACE),A
               01250 ; GET ANO SAVE FOUNO KEYBOARO 8YTE
30CA 78        01260         LO      A,E
30C8 73        01270 FOUNO   LO      (HL),E
30CC 7A        01280         LD      A,0
30C0 07        01290         RLCA
30CE 07        01300         RLCA
30CF 07        01310         RLCA
3000 57        01320         LO      0,A
3001 0E01      01330         LD      C,1
3003 79        01340 BACKUP  LO      A,C
3004 A3        01350         ANU     E
3005 2005      01360         JR      NZ,AROUNO
3007 14        01370         INC     0
300B C801      01380         RLC     C
300A 18F7      D1390         JR      BACKUP
300C 3AB038    01400 AROUNO  LO      A,(3880H)
300F 47        01410         LD      B,A
3DE0 7A        01420         LO      A,D
30E1 C640      01430         ADD     A,40H
30E3 FE60      D1440         CP      60H
30ES 3016      014S0         JR      NC,ZD429H
30E7 57        D1460         LO      0,A
30E8 3A4038    D1470         LD      A,(3840H)
30EB E610      01480         ANO     10H
30E0 2009      01490         JR      NZ,CNTRDL
30EF 7A        01500         LD      A,0
30F0 C808      D1510         RRC     8
30F2 383D      D1S2D         JR      C,GOAWAY
30F4 C62D      0153D         ADD     A,20H
30F6 1839      01540         JR      GOAWAY
30F8 7A        D15S0 CNTRDL  LO      A,D
30F9 0640      01560         SUB     40H
30F8 1834      01570         JR      GOAWAY
30FD 067D      0158D Z0429H  SUB     70H
30FF 3D10      D1S90         JR      NC,Z0430H
3101 C640      01600         AOO     A,40H
31D3 FE3C      01610         CP      3CH
3105 3B02      01620         JR      C,Z0435H
3107 EE1D      0163D         XDR     10H
3109 C808      01640 Z0435H  RRC     8
3108 3024      0165D         JR      NC,GOAWAY
3100 EE10      0166D         XOR     1DH
310F 1820      D1670         JR      GOAWAY
3111 07        01680 Z0430H  RLCA
3112 C808      01690         RRC     8
3114 3001      017UD         JR      NC,Z0443H
3116 3C        01710         INC     A
3117 212131    01720 Z0443H  LD      HL,TABLET
311A 4F        01730         LD      C,A
311B 0600      01740         LD      B,D
311D 09        01750         AOD     HL,BC
311E 7E        01760         LO      A,(HL)
311F 1B10      0177U         JR      GOAWAY
3121 000D      0178D TABLET  OEFW    0D00H
3123 1F1F      01790         DEFW    1F1FH
3125 D101      01800         DEFW    0101H
3127 5B1B      0181D         DEFW    185BH
3129 0A00      01820         DEFW    000AH
312B 0818      0183D         DEFW    1808H
312D 0919      D1840         OEFW    1909H
312F 2020      018S0         OEFW    2020H
3131 57        D1860 GOAWAY  LO      D,A
3132 3A1038    01870 8EEEEP  LD      A,(381DH)
313S FE01      01880         CP      1
3137 2016      01890         JR      NZ,BLEEEP
3139 3A8038    01900         LD      A,(3880H)
313C FE01      01910         CP      1
313E 20UF      D1920         JR      NZ,8LEEEP
3140 3A1940    01930         LO      A,(SHIFTR)
3143 EE01      01940         XOR     1
```

```
3145 321940   01950          LD      (SHIFTR),A
3148 010005   01960          LD      BC,500H
314B CD6D00   01970          CALL    006DH
314E C9       01980          RET
              01990 ; DEBOUNCE
314F 01B001   02000 BLEEEP   LD      BC,1B0H
3152 CD6D00   02010          CALL    006DH
3155 7A       02020          LD      A,D
              02030 ; BEEP ROUTINE ON FOUND KEYSTROKE
3156 C5       02040          PUSH    BC
3157 F5       02050          PUSH    AF
3158 0640     02060          LD      B,40H
315A 3A3040   02070          LD      A,(PORTFF)
315D E6FD     02080          AND     0FDH
315F 67       02090          LD      H,A
3160 F602     02100          OR      2
3162 6F       02110          LD      L,A
3163 7D       02120 BEEPER   LD      A,L
3164 D3FF     02130          OUT     (0FFH),A
3166 7C       02140          LD      A,H
3167 D3FF     02150          OUT     (0FFH),A
3169 C5       02160          PUSH    BC
316A 0640     02170          LD      B,40H
316C 10FE     02180 FREQCY   DJNZ    FREQCY
316E C1       02190          POP     BC
316F 10F2     02200          DJNZ    BEEPER
3171 F1       02210          POP     AF
3172 C1       02220          POP     BC
3173 C35204   02230          JP      0452H
              02240 ; CHECK FOR STATUS OF BASIC STACK
3176          02250 SKPSTP   EQU     $
3176 E3       02260 BEGIN    EX      (SP),HL
3177 7D       02270          LD      A,L
3178 FE58     02280          CP      58H
317A 2003     02290          JR      NZ,NOTROY
317C 7C       02300          LD      A,H
317D FE10     02310          CP      10H
317F E3       02320 NOTROY   EX      (SP),HL
3180 C27810   02330          JP      NZ,BYTE
              02340 ; CHECK TO SEE IF SPECIAL STAR (*) COMMAND
3183 CD7810   02350          CALL    BYTE
3186 FECF     02360          CP      0CFH
3188 2803     02370          JR      Z,DKSTAR
318A 2B       02380          DEC     HL
318B FDE9     02390          JP      (IY)
318D CD7810   02400 DKSTAR   CALL    BYTE
3190 CABE31   02410          JP      Z,SYNERR
              02420 ; CHECK STATUS OF SAVE COMMAND
3193 FEA0     02430 SAVE     CP      0A0H
3195 287F     02440          JR      Z,SAVER
3197 FE8B     02450          CP      088H
3199 2866     02460          JR      Z,RENEW
319B FEA2     02470          CP      0A2H
319D CAE432   02480          JP      Z,OPENER
31A0 FECC     02490          CP      0CCH
31A2 CAB034   02500          JP      Z,STPSET
31A5 FECB     02510          CP      0CBH
31A7 CACE34   02520          JP      Z,MEMSET
31AA FEF2     02530          CP      0F2H
31AC 284A     02540          JR      Z,INBEEP
31AE FEB2     02550          CP      0B2H
31B0 2829     02560          JR      Z,LOWCAS
31B2 FEAD     02570          CP      0ADH
31B4 283A     02580          JR      Z,BIPOFF
31B6 FEAA     02590          CP      0AAH
31B8 282E     02600          JR      Z,UPPPER
31BA FE88     02610          CP      08BH
31BC 2803     02620          JR      Z,MENU
31BE C39719   02630 SYNERR   JP      1997H
              02640 ; THIS IS THE MENU
31C1 213B35   02650 MENU     LD      HL,INTRO1
31C4 CDA72B   02660          CALL    2BA7H
31C7 21A335   02670          LD      HL,INTRO2
31CA CDA72B   02680          CALL    2BA7H
31CD 214236   02690          LD      HL,INTRO3
31D0 CDA72B   02700          CALL    2BA7H
31D3 21DB36   02710          LD      HL,INTRO4
31D6 CDA72B   02720          CALL    2BA7H
31D9 1823     02730          JR      READYX
              02740 ; THIS PUTS LOWER CASE IN PLACE
31DB 3E01     02750 LOWCAS   LD      A,1
31DD 321940   02760          LD      (SHIFTR),A
31E0 211035   02770          LD      HL,LOWER
31E3 221E40   02780          LD      (401EH),HL
31E6 1816     02790          JR      READYX
              02800 ; THIS REMOVES LOWER CASE DISPLAY
31E8 215804   02810 UPPPER   LD      HL,0458H
31EB 221E40   02820          LD      (401EH),HL
31EE 180E     02830          JR      READYX
              02840 ; THIS REMOVES KBPFIX ROUTINE
31F0 21E303   02850 BIPOFF   LD      HL,03E3H
31F3 221640   02860          LD      (4016H),HL
31F6 1806     02870          JR      READYX
```

```
              02880 ; THIS PUTS KBPFIX IN PLACE
31F8 21B530   02890 INBEEP   LD      HL,KBPFIX
31FB 221640   02900          LD      (4016H),HL
31FE C3CC06   02910 READYX   JP      READY
              02920 ; THIS IS BEGINNING OF RENEW SEQUENCE
3201 ED5BA440 02930 RENEW    LD      DE,(40A4H)
3205 3EFF     02940          LD      A,0FFH
3207 12       02950          LD      (DE),A
3208 CDFC1A   02960          CALL    1AFCH
320B 23       02970          INC     HL
320C 22F940   02980          LD      (40F9H),HL
320F ED7BE840 02990          LD      SP,(40E8H)
3213 C37630   03000 FGHIJ    JP      RSLVII
              03010 ; THIS CHECKS NEXT BYTE FOR RUN COMMAND
3216 CD7810   03020 SAVER    CALL    BYTE
3219 FED0     03030          CP      0D0H
321B 20A1     03040          JR      NZ,SYNERR
321D CD7810   03050          CALL    BYTE
3220 FE8E     03060          CP      8EH
3222 C2F433   03070          JP      NZ,MACH
              03080 ; CHECK FOR QUOTATION MARK DELIMITER
3225 CD7810   03090          CALL    BYTE
3228 FE22     03100          CP      022H
322A 2092     03110          JR      NZ,SYNERR
              03120 ; CHECK TO SEE THAT NAME IS IN PLACE
322C CD7810   03130          CALL    BYTE
322F CAAD24   03140          JP      Z,24ADH
              03150 ; SAVE BASIC POINTERS IN STACK
3232 E5       03160          PUSH    HL
3233 F5       03170          PUSH    AF
3234 D5       03180          PUSH    DE
3235 C5       03190          PUSH    BC
              03200 ; DEFINE TAPE DRIVE 0, TURN ON RECORDER
              03210 ; THEN WRITE LEADER AND SYNC BYTE
              03220 ; AND WRITE MACHINE PROGRAM CODE 55H
3236 AF       03230          XOR     A
3237 CD1202   03240          CALL    0212H
323A CD8702   03250          CALL    0287H
323D 3E55     03260          LD      A,55H
323F CD6402   03270          CALL    WRTBYT
              03280 ; WRITE PROGRAM NAME TO TAPE
3242 0606     03290          LD      B,06
3244 2B       03300          DEC     HL
3245 CD7810   03310 NAMES    CALL    BYTE
3248 FE22     03320          CP      22H
324A 2807     03330          JR      Z,NEXTBT
324C CD6402   03340          CALL    WRTBYT
324F 10F4     03350          DJNZ    NAMES
3251 1807     03360          JR      DUMP
              03370 ; FILL OUT WITH 20H (ASCII BLANKS) IF NECESSARY
3253 3E20     03380 NEXTBT   LD      A,20H
3255 CD6402   03390          CALL    WRTBYT
3258 10F9     03400          DJNZ    NEXTBT
              03410 ; DUMP FIRST TWO PAGES (4000 TO 41FF) TO TAPE
325A 210040   03420 DUMP     LD      HL,SETPTS
325D CDC032   03430          CALL    OUTSEQ
3260 CDC032   03440          CALL    OUTSEQ
              03450 ; DUMP REST OF POINTERS (4200 TO 42E9) TO TAPE
3263 06E9     03460          LD      B,0E9H
3265 CDC032   03470          CALL    OUTSEQ
              03480 ; FIND END OF PROGRAM VARIABLES AND ARRAYS
3268 ED5BFD40 03490          LD      DE,(VAREND)
              03500 ; DUMP FIRST SEGMENT OF PROGRAM TO TAPE
326C 7B       03510          LD      A,E
326D 95       03520          SUB     L
326E 47       03530          LD      B,A
326F CDC032   03540          CALL    OUTSEQ
              03550 ; DUMP PROGRAM TO TAPE PAGE BY PAGE
3272 7C       03560 NXTPGE   LD      A,H
3273 3D       03570          DEC     A
3274 BA       03580          CP      D
3275 2805     03590          JR      Z,FINSH1
3277 CDC032   03600          CALL    OUTSEQ
327A 18F6     03610          JR      NXTPGE
              03620 ; FIND BEGINNING OF STRING STORAGE AREA
327C 2AEB40   03630 FINSH1   LD      HL,(STACKR)
              03640 ; FIND TOP OF AVAILABLE MEMORY
327F ED5BB140 03650          LD      DE,(MEMTOP)
              03660 ; DUMP FIRST SEGMENT OF STRING-TO-MEMORY END
3283 13       03670          INC     DE
3284 7B       03680          LD      A,E
3285 95       03690          SUB     L
3286 47       03700          LD      B,A
3287 CDC032   03710          CALL    OUTSEQ
              03720 ; DUMP REMAINDER OF MEMORY PAGE BY PAGE
328A 7C       03730 NXTBCH   LD      A,H
328B 3D       03740          DEC     A
328C BA       03750          CP      D
328D 2805     03760          JR      Z,KEEPIT
328F CDC032   03770          CALL    OUTSEQ
3292 18F6     03780          JR      NXTBCH
              03790 ; DUMP KEEPIT CONTROL BYTES
3294 2A8140   03800 KEEPIT   LD      HL,(4081H)
3297 0610     03810          LD      B,10H
```

```
3299 CDC032   03820          CALL   OUTSEQ
              03830 ; DUMP COMPLETE VIDEO MEMORY
32BC 21003C   03840          LD     HL,VIDEO
329F 0604     03850          LD     B,4
32A1 C5       03860 COEF     PUSH   BC
32A2 COBE32   03870          CALL   PREOUT
32A5 C1       03880          POP    BC
32A6 10F9     03890          DJNZ   COEF
              03900 ; WRITE ENO OF PROGRAM COOE (78)
32AB 3E78     03910          LD     A,78H
32AA C06402   03920          CALL   WRTBYT
              03930 ; WRITE START AOORESS AFTER LOAO (06CCH)
32A0 3ECC     03940          LD     A,0CCH
32AF C06402   03950          CALL   WRTBYT
32B2 3E06     03960          LD     A,06
32B4 C06402   03970          CALL   WRTBYT
              03980 ; RESTORE BASIC INFORMATION TO REGISTERS
32B7 C1       03990          POP    BC
32B8 01       04000          POP    OE
32B9 F1       04010          POP    AF
32BA E1       04020          POP    HL
              04030 ; RETURN TO BASIC PROGRAM IN PROGRESS
32BB C3CC06   04040          JP     READY
              04050 ; OUTPUT SEQUENCE SUBROUTINE
              04060 ; WRITE BLOCK HEADER COOE (3C)
32BE 0600     04070 PREOUT   LO     B,0
32C0 3E3C     04080 OUTSEQ   LD     A,3CH
32C2 C06402   04090          CALL   WRTBYT
              04100 ; GET NUMBER OF BYTES TO WRITE
32C5 78       04110          LD     A,B
32C6 C06402   04120          CALL   WRTBYT
              04130 ; GET START AOORESS LSB, SAVE IN C (CHECKSUM)
32C9 70       04140          LD     A,L
32CA 4F       04150          LO     C,A
32CB C06402   04160          CALL   WRTBYT
              04170 ; GET START AOORESS MSB, SAVE IN C (CHECKSUM)
32CE 79       04180          LD     A,C
32CF 84       04190          A00    A,H
32D0 4F       04200          LD     C,A
3201 7C       04210          LD     A,H
32D2 C06402   04220          CALL   WRTBYT
              04230 ; GET BLOCK OF DATA, WRITE, ANO SAVE IN C
3205 79       04240 WRTPGE   LO     A,C
3206 B6       04250          ADO    A,(HL)
32D7 4F       04260          LO     C,A
32D8 7E       04270          LD     A,(HL)
32D9 C06402   04280          CALL   WRTBYT
320C 23       04290          INC    HL
3200 10F6     04300          OJNZ   WRTPGE
              04310 ; GET CHECKSUM FROM C ANO WRITE TO TAPE
320F 79       04320          LO     A,C
32E0 C06402   04330          CALL   WRTBYT
32E3 C9       04340          RET
              04350 ; GET REST OF DATA ANO CONVERT
32E4 C07810   04360 OPENER   CALL   BYTE
32E7 FE22     04370          CP     22H
32E9 C2BE31   04380          JP     NZ,SYNERR
32EC E5       04390          PUSH   HL
32E0 C00133   04400          CALL   XX99
32F0 COC901   04410          CALL   01C9H
32F3 184D     0442D          JR     NEXT99
              04430 ; GET 16 SCREEN POSITIONS REAOY (10H)
32F5 7A       04440 CONTNT   LO     A,0
32F6 21403C   04450          LO     HL,3C40H
32F9 E6F0     04460          ANO    0F0H
32FB COB833   04470          CALL   RRRRS
32FE 7A       04480          LO     A,0
32FF E60F     04490          ANO    0FH
3301 COB033   04500          CALL   HEXASC
3304 77       04510          LD     (HL),A
3305 23       04520          INC    HL
3306 7B       04530          LO     A,E
3307 E6F0     04540          ANO    0F0H
3309 COBB33   04550          CALL   RRRRS
330C 7B       04560          LD     A,E
3300 E60F     04570          ANO    0FH
330F COB033   04580          CALL   HEXASC
3312 77       04590          LD     (HL),A
3313 21B03C   04600          LD     HL,3CB0H
3316 0610     04610          LO     B,10H
              04620 ; OISPLAY CONTENTS OF AOORESS CHOSEN
331B 1A       04630 CONTO2   LO     A,(OE)
3319 E6F0     04640          ANO    0F0H
331B COBB33   04650          CALL   RRRRS
331E 1A       04660          LO     A,(OE)
331F E60F     04670          ANO    0FH
3321 COB033   04680          CALL   HEXASC
3324 77       04690          LD     (HL),A
3325 23       04700          INC    HL
3326 23       04710          INC    HL
3327 13       04720          INC    OE
              04730 ; REOO IT 16 TIMES FOR FULL LINE
3328 10EE     04740          OJNZ   CONTO2
```

```
              04750 ; OISPLAY ASCII VALUES TOO
332A 0610     04760          LD     B,10H
332C C5       04770          PUSH   BC
3320 1B       04780          OEC    OE
332E 10F0     04790          DJNZ   $-1
3330 C1       04800          POP    BC
3331 C5       04810          PUSH   BC
3332 21C03C   04820          LO     HL,3CC0H
3335 1A       04830 BBBA     LO     A,(OE)
3336 77       04840          LO     (HL),A
3337 23       04850          INC    HL
3338 23       04860          INC    HL
3339 23       04870          INC    HL
333A 13       04880          INC    OE
333B 10F8     04890          DJNZ   BBBA
3330 C1       04900          POP    BC
333E 1B       04910          OEC    OE
333F 10F0     04920          OJNZ   $-1
3341 C9       04930          RET
              04940 ; SCAN FOR EOIT / GET THIRO SCREEN LINE
3342 COF532   04950 NEXT99   CALL   CONTNT
              04960 ; SCAN KEYBOARO FOR BREAK, ARROWS
3345 3A4038   04970 EOITOR   LD     A,(3B40H)
3348 17       04980          RLA
3349 17       04990          RLA
334A 3003     05000          JR     NC,AAAA
334C 13       05010          INC    OE
3340 1850     05020          JR     STNORO
334F 17       05030 AAAA     RLA
3350 3003     05040          JR     NC,AAAB
3352 1B       05050          OEC    OE
3353 184A     05060          JR     STNORO
3355 0610     05070 AAAB     LO     B,10H
3357 17       05080          RLA
3358 3005     05090          JR     NC,AAAC
335A 1B       05100          OEC    OE
335B 10F0     05110          OJNZ   $-1
3350 1840     05120          JR     STNORO
335F 17       05130 AAAC     RLA
3360 3005     05140          JR     NC,BREEK
3362 13       05150          INC    OE
3363 10F0     05160          OJNZ   $-1
3365 1838     05170          JR     STNORO
3367 17       05180 BREEK    RLA
3368 3004     05190          JR     NC,AAAD
336A E1       05200          POP    HL
336B C3CC06   05210          JP     REAOY
              05220 ; OISPLAY EOITING / GET FIFTH SCREEN LINE
336E 210130   05230 AAA0     LO     HL,3001H
3371 365F     05240          LO     (HL),5FH
3373 2B       05250          OEC    HL
3374 365F     05260          LO     (HL),5FH
3376 0602     05270          LD     B,2
3378 05       05280 AAAE     PUSH   OE
3379 E5       05290          PUSH   HL
337A C04900   05300          CALL   0049H
3370 E1       0531U          POP    HL
337E 01       05320          POP    OE
337F FE47     05330          CP     47H
3381 30C2     05340          JR     NC,EOITOR
3383 FE30     05350          CP     30H
3385 38BE     05360          JR     C,EDITOR
3387 FE3A     05370          CP     3AH
3389 3804     05380          JR     C,AAAF
338B FE40     05390          CP     40H
3380 3886     05400          JR     C,EOITOR
338F 77       05410 AAAF     LO     (HL),A
3390 23       05420          INC    HL
3391 10E5     05430          OJNZ   AAAE
              05440 ; CONVERT CHOSEN OATA TO HEX
3393 2B       05450          OEC    HL
3394 COA733   05460          CALL   ASCHEX
3397 4F       05470          LD     C,A
3398 2B       05480          OEC    HL
3399 COC233   05490          CALL   LLLLS
339C 81       U5500          A00    A,C
              05510 ; PUT NEW BYTE IN PLACE
3390 12       05520          LD     (OE),A
339E 13       05530          INC    OE
              05540 ; OISPLAY REVISEO LINE OF OATA
339F COF532   05550 STNORO   CALL   CONTNT
33A2 COCA33   05560          CALL   OELAY
33A5 1B9E     05570          JR     EOITOR
              05580 ; ASCII TO HEXAOECIMAL CONVERSION
33A7 7E       05590 ASCHEX   LO     A,(HL)
33AB 0630     05600          SUB    30H
33AA FE0A     05610          CP     0AH
33AC 08       05620          RET    C
33A0 0607     05630          SUB    7
33AF C9       05640          RET
              05650 ; HEXAOECIMAL TO ASCII CONVERSION
3380 C630     05660 HEXASC   A00    A,30H
3382 FE3A     05670          CP     3AH
```

```
33B4 D8       05680          RET     C
33B5 C607     05690          ADD     A,7
33B7 C9       05700          RET
              05710 ; RIGHT ROTATES FOR CONVERSIONS
33B8 0F       05720 RRRRS    RRCA
33B9 0F       05730          RRCA
33BA 0F       05740          RRCA
33BB 0F       05750          RRCA
33BC CDB033   05760          CALL    HEXASC
33BF 77       05770          LD      (HL),A
33C0 23       05780          INC     HL
33C1 C9       05790          RET
              05800 ; LEFT ROTATES FOR CONVERSION
33C2 CDA733   05810 LLLLS    CALL    ASCHEX
33C5 07       05820          RLCA
33C6 07       05830          RLCA
33C7 07       05840          RLCA
33C8 07       05850          RLCA
33C9 C9       05860          RET
              05870 ; DELAY FOR SCREEN DISPLAYS
33CA 010020   05880 DELAY    LD      BC,2000H
33CD CD6000   05890          CALL    0060H
33D0 C9       05900          RET
              05910 ; GET/CONVERT ASCII FROM BUFFER
              05920 ; TO HEXADECIMAL ADDRESS
33D1 0604     05930 XX99     LD      B,4
33D3 CD7810   05940 SSSS     CALL    BYTE
33D6 F5       05950          PUSH    AF
33D7 10FA     05960          DJNZ    SSSS
33D9 F1       05970          POP     AF
33DA 77       05980          LD      (HL),A
33DB CDA733   05990          CALL    ASCHEX
33DE 5F       06000          LD      E,A
33DF F1       06010          POP     AF
33E0 77       06020          LD      (HL),A
33E1 CDC233   06030          CALL    LLLLS
33E4 83       06040          ADD     A,E
33E5 5F       06050          LD      E,A
33E6 F1       06060          POP     AF
33E7 77       06070          LD      (HL),A
33E8 CDA733   06080          CALL    ASCHEX
33EB 57       06090          LD      D,A
33EC F1       06100          POP     AF
33ED 77       06110          LD      (HL),A
33EE CDC233   06120          CALL    LLLLS
33F1 82       06130          ADD     A,D
33F2 57       06140          LD      D,A
33F3 C9       06150          RET
              06160 ; RESULT OF ABOVE IN DE REGISTER
              06170 ; CHECK FOR "OPEN" COMMAND
33F4 FEA2     06180 MACH     CP      0A2H
33F6 2005     06190          JR      NZ,SYN2
              06200 ; CHECK FOR QUOTATION MARK DELIMITER
33F8 CD7810   06210          CALL    BYTE
33FB D622     06220          SUB     22H
33FD C2BE31   06230 SYN2     JP      NZ,SYNERR
              06240 ; TURN ON TAPE DRIVE, WRITE LEADER
              06250 ; AND SYNC BYTE, MACHINE CODE HEADER
3400 CD1202   06260          CALL    0212H
3403 CD8702   06270          CALL    0287H
3406 3E55     06280          LD      A,55H
3408 CD6402   06290          CALL    WRTBYT
              06300 ; WRITE NAME TO TAPE UNTIL
              06310 ; COMMA DELIMITER IS FOUND
340B 0606     06320          LD      B,06
340D CD7810   06330 NAME99   CALL    BYTE
3410 FE2C     06340          CP      2CH
3412 2807     06350          JR      Z,NXTB99
3414 CD6402   06360          CALL    WRTBYT
3417 10F4     06370          DJNZ    NAME99
3419 1807     06380          JR      DUMP99
              06390 ; FILL OUT WITH BLANKS IN NAME
              06400 ; LESS THAN 6 CHARACTERS
341B 3E20     06410 NXTB99   LD      A,20H
341D CD6402   06420          CALL    WRTBYT
3420 10F9     06430          DJNZ    NXTB99
              06440 ; CHECK FOR COMMA DELIMITER
3422 CD7810   06450 DUMP99   CALL    BYTE
3425 FE2C     06460          CP      2CH
3427 20D4     06470          JR      NZ,SYN2
              06480 ; GET START ADDRESS AND SAVE
3429 CDD133   06490          CALL    XX99
342C D5       06500          PUSH    DE
              06510 ; CHECK FOR NEXT COMMA DELIMITER
342D CD7810   06520          CALL    BYTE
3430 FE2C     06530          CP      2CH
3432 2805     06540          JR      Z,TTTT
3434 D1       06550          POP     DE
3435 AF       06560          XOR     A
3436 C3A024   06570          JP      24A0H
              06580 ; GET END ADDRESS AND SAVE
3439 CDD133   06590 TTTT     CALL    XX99
343C D5       06600          PUSH    DE
```

```
              06610 ; EXECUTION ADDRESS AFTER FINAL COMMA
343D CD7810   06620          CALL    BYTE
3440 FE2C     06630          CP      2CH
3442 2808     06640          JR      Z,EXECU
              06650 ; AUTOEXECUTE 06CC IF NOT SPECIFIED
3444 21CC06   06660          LD      HL,06CCH
3447 227E40   06670          LD      (407EH),HL
344A 1807     06680          JR      WRIT99
              06690 ; GET EXECUTION ADDRESS
344C CDD133   06700 EXECU    CALL    XX99
344F ED537E40 06710          LD      (407EH),DE
              06720 ; 16-BIT SUBTRACTION GETS NUMBER OF
              06730 ; BYTES; GET START ADDR. & COMPL'T.
3453 E1       06740 WRIT99   POP     HL
3454 D1       06750          POP     DE
3455 D5       06760          PUSH    DE
3456 7A       06770          LD      A,D
3457 2F       06780          CPL
3458 57       06790          LD      D,A
3459 7B       06800          LD      A,E
345A 2F       06810          CPL
345B 5F       06820          LD      E,A
              06830 ; END ADDRESS + COMPL'T = BYTES
              06840 ; ADD 1 FOR SUB, 1 FOR INCLUSIVE
345C 19       06850          ADD     HL,DE
345D 23       06860          INC     HL
345E 23       06870          INC     HL
              06880 ; TRANSFER BYTES TO WRITE TO DE
345F E5       06890          PUSH    HL
3460 D1       06900          POP     DE
              06910 ; RESTORE START ADDRESS TO HL
3461 E1       06920          POP     HL
3462 43       06930          LD      B,E
              06940 ; ZERO E REGISTER, INC D, TO GET
              06950 ; TOTAL NUMBER OF PAGES; SAVE IT
3463 04       06960          INC     B
3464 14       06970          INC     D
3465 D5       06980 LP99     PUSH    DE
3466 CDC032   06990          CALL    OUTSEQ
              07000 ; CHECK IF ALL PAGES WRITTEN
3469 D1       07010          POP     DE
346A 15       07020          DEC     D
346B 20F8     07030          JR      NZ,LP99
              07040 ; WRITE END OF PROGRAM CODE
346D 3E78     07050          LD      A,78H
346F CD6402   07060          CALL    WRTBYT
              07070 ; WRITE START ADDRESS; 06CC = DEFAULT
3472 3A7E40   07080          LD      A,(407EH)
3475 CD6402   07090          CALL    WRTBYT
3478 3A7F40   07100          LD      A,(407FH)
347B CD6402   07110          CALL    WRTBYT
              07120 ; RETURN TO COMMAND LEVEL
347E 1837     07130          JR      PREP2
              07140 ; START SETUP OF STEPPER ROUTINE
              07150 ; FIRST FIND IF ARGUMENT EXISTS
3480 F5       07160 STPSET   PUSH    AF
3481 E5       07170          PUSH    HL
3482 CD7810   07180          CALL    BYTE
3485 B7       07190          OR      A
              07200 ; ARGUMENT EXISTS - JUMP TO ROUTINE
3486 200C     07210          JR      NZ,IIII
              07220 ; OTHERWISE JUMP PAST SINGLE STEPPER
3488 FD360476 07230          LD      (IY+4),SKPSTP&00FFH
348C FD360531 07240          LD      (IY+5),SKPSTP&0FF00H<-8
3490 E1       07250          POP     HL
3491 F1       07260          POP     AF
3492 1823     07270          JR      PREP2
              07280 ; GET VALUE FROM A REGISTER INTO D
3494 D630     07290 IIII     SUB     30H
3496 17       07300          RLA
3497 17       07310          RLA
3498 17       07320          RLA
3499 17       07330          RLA
349A 57       07340          LD      D,A
              07350 ; GET NEXT BUFFER VALUE ELSE SN ERROR
349B CD7810   07360          CALL    BYTE
349E B7       07370          OR      A
349F 2005     07380          JR      NZ,ABCD
34A1 E1       07390          POP     HL
34A2 F1       07400          POP     AF
34A3 C3BE31   07410 SYN3     JP      SYNERR
              07420 ; GET NEXT VALUE FROM BUFFER INTO E
34A6 D630     07430 ABCD     SUB     30H
34A8 82       07440          ADD     A,D
34A9 57       07450          LD      D,A
              07460 ; PATCH STEPPER INTO PLACE
34AA FD36048A 07470          LD      (IY+4),JMPPOS&00FFH
34AE FD360534 07480          LD      (IY+5),JMPPOS&0FF00H<-8
              07490 ; GET DELAY VALUE INTO REGISTER
              07500 ; AND GO OUT TO READY PROMPT
34B2 FD7206   07510          LD      (IY+6),D
34B5 E1       07520          POP     HL
34B6 F1       07530          POP     AF
```

```
34B7 C3CC06    07540 PREP2   JP      READY
               07550 ; THIS I5 THE STEPPER ROUTINE
34BA           07560 JMPPOS  EQU     $
34BA F5        07570 5TEPPR  PU5H    AF
34BB C5        075B0         PU5H    BC
               07590 ; WAIT FOR 5HIFT TO BE PRESSEO
34BC 3A803B    07600 LUPER   LD      A,(3BB0H)
34BF A7        07610         ANO     A
34C0 28FA      07620         JR      Z,LUPER
               07630 ; LOAO OELAY VALUE INTO BC
34C2 4F        07640         LO      C,A
34C3 F04606    07650         LO      B,(IY+6)
               07660 ; CALL OELAY IN ROM
34C6 C06000    07670         CALL    0060H
34C9 C1        076B0         POP     BC
34CA F1        07690         POP     AF
               07700 ; BACK TO REST DF TEST 5EQUENCE
34CB C37631    07710         JP      BEGIN
               0772U ; BEGIN MEMORY RESET 5EQUENCE
               07730 ; CHECK FOR QUOTE MARK OELIMITER
34CE C07B10    07740 MEM5ET  CALL    BYTE
3401 FE22      07750         CP      22H
3403 20CE      07760         JR      NZ,5YN3
               07770 ; CONVERT *MEM OPERANO TO HEX
3405 C00133    07780         CALL    XX99
               07790 ; CHECK FOR >4400H MEMORY AOORES5
               07800 ; GO TO OM ERROR IF NOT ENOUGH
340B 210044    07B10         LO      HL,4400H
340B AF        07820         XOR     A
34DC E052      07830         58C     HL,OE
340E 027A19    07B40         JP      NC,197AH
               07850 ; TE5T FOR MEMORY RE5ET <FBBBH
               07B60 ; OM ERROR IF TDO MUCH
34E1 05        07870         PU5H    OE
34E2 E1        07880         POP     HL
34E3 0607      07890         LO      8,7
34E5 23        07900         INC     HL
34E6 1UF0      07910         OJNZ    $-1
34EB 7E        07920         LO      A,(HL)
34E9 47        07930         LO      B,A
34EA 2F        07940         CPL
34EB 77        07950         LO      (HL),A
34EC BE        07960         CP      (HL)
34E0 C27A19    07970         JP      NZ,197AH
34F0 70        079B0         LO      (HL),B
               07990 ; PUT NEW MEMORY 5IZE INTO PLACE
34F1 E053B140  09000         LO      (40B1H),DE
               08010 ; TRANSFER KEEPIT OATA ROW
               0B020 ; ANO PUT NEW AOORES5 IN IY
34F5 F0E5      0B030         PUSH    IY
34F7 E1        0B040         POP     HL
34FB 13        08050         INC     OE
34F9 05        08060         PUSH    OE
34FA F0E1      08070         POP     IY
34FC 010700    0B0B0         LO      BC,7
34FF E0B0      0B090         LOIR
3501 F0E5      0B100         PUSH    IY
3503 E1        0B110         POP     HL
               0B120 ; MAKE FRE(A$) MEM 5IZE - 50 OECIMAL
3504 0632      0B130         LD      B,32H
3506 1B        0B140 STRING  OEC     OE
3507 10F0      08150         OJNZ    STRING
               08160 ; PUT NEW STRING POINTER IN PLACE
3509 E053A040  08170         LO      (40A0H),OE
3500 C36C30    08160         JP      GRIN5
               08190 ; THIS I5 LOWER CA5E OETERMINATION
3510 F5        0B200 LOWER   PU5H    AF
3511 3A1940    0B210         LO      A,(SHIFTR)
3514 FE01      0B220         CP      1
3516 2604      0B230         JR      Z,LOWER1
3518 F1        U8240         POP     AF
3519 C35B04    0B250         JP      045BH
351C F1        0B260 LOWER1  POP     AF
3510 006E03    0B270         LD      L,(IX+3)
3520 006604    08280         LD      H,(IX+4)
3523 0A9A04    08290         JP      C,049AH
3526 007E05    0B300         LO      A,(IX+5)
3529 B7        0B310         OR      A
352A 2B01      0B320         JR      Z,GETCHR
352C 77        0B330         LD      (HL),A
3520 79        08340 GETCHR  LO      A,C
352E FE20      0B350         CP      20H
3530 0A0605    0B360         JP      C,0506H
3533 FE80      0B370         CP      B0H
3535 02A604    0B3B0         JP      NC,04A6H
3538 C37004    0B390         JP      0470H
353B 2A        0B400 INTR01  OEFM    '*FIX = 5ET OEBOUNCE/BEEP/AUTOREPEAT'
355E 0A        0B410         OEFB    0AH
355F 2A        08420         OEFM    '*KILL = RESET TO NORMAL KEY8OARO'
357F 0A        0B430         OEFB    0AH
35B0 2A        0B440         OEFM    '*MEM = RE5ET MEMORY SIZE (NOTE 1)
35A1 00        0B450         OEFB    00H
35A2 00        0B460         OEFB    00H
35A3 2A        0B470 INTR02  OEFM    '*PRINT = LOWERCASE KEYBOARO/OI5PLAY ON'
35CB 0A        0B480         OEFB    0AH
35CA 2A        0B490         OEFM    '*OUT = LOWERCA5E KEYBOARO/OISPLAY OFF'
35EF 0A        0B500         OEFB    0AH
35F0 2A        08510         OEFM    '*NEW = RESTORE PROGRAM VICTIM OF NEW'
3614 0A        08520         OEFB    0AH
3615 2A        08530         OEFM    '*OPEN = HEX/ASCII/GRAPHIC5 MONITOR (NOTE 1)'
3640 00        08540         OEFB    00H
3641 00        0B550         OEFB    00H
3642 2A        08560 INTR03  OEFM    '*SAVE/RUN = SAVE RUNNING PROGRAM (NOTE 2)'
366B 0A        0B670         DEFB    0AH
366C 2A        0B5B0         OEFM    '*SAVE/OPEN = MEMORY BLOCK SAVE (NOTE 3)'
3693 0A        0B590         OEFB    0AH
3694 2A        0B60D         DEFM    '*STEPXX = SINGLE 5TEPPER ON, XX = OELAY'
36BB 0A        0B610         OEF8    0AH
36BC 2A        0B620         OEFM    '*STEP = SINGLE STEPPER OFF'
3606 00        0BB30         OEFB    00H
3607 00        0BB40         OEFB    00
360B 4E        0B650 INTR04  DEFM    'NOTE 1.  REQUIRE5 4-CHARACTER HEX VALUE IN QUOTES.'
370A 0A        0B660         OEFB    0AH
370B 4E        0B670         OEFM    'NOTE 2.  REQUIRE5 6-CHARACTER NAME IN QUOTES.'
3738 0A        0BB80         OEFB    0AH
373B 4E        0B690         OEFM    'NOTE 3.  SAME A5 ABOVE PLUS HEX 5TART,
3773 00        08700         OEFB    00H       ENO, OPTIONAL ENTRY'
3774 00        0B710         OEFB    00H
303B           0B720         ENO     START
00000 TOTAL ERRORS
1B637  TEXT AREA BYTES LEFT
```

```
AAAA   334F 05030   05000
AAAB   3355 05070   05040
AAAC   335F 05130   05090
AAAD   336E 05230   05190
AAAE   3378 05280   05430
AAAF   33BF 05410   053B0
ABC0   34A6 07430   073B0
AROUNO 300C 01400   01360
ASCHEX 33A7 05590   05460 05810 05990 060B0
BACKUP 3003 01340   01390
BBBA   3335 04830   04890
BEEEEP 3132 01B70
BEEPER 3163 02120   02200
BEGIN  3176 02260   07710
BIPOFF 31F0 02850   02580
BLEEEP 314F 02000   01B90 01920
BREEK  3367 05180   05140
BYTE   1078 00390   02330 02350 02400 03020 03050 03090 03130
                    03310 04360 05940 06210 06330 06450 06520
                    06620 071B0 07360 07740
COEF   32A1 03B60   03890
CLRMEM 309E 00980   01000
CNTROL 30F8 01550   01490
CONTO2 3318 04630   04740
CONTNT 32F5 04440   04950 05550
OECA   30C6 01230   01170
OELAY  33CA 05880   05560
DUMP   325A 03420   03360
DUMP99 3422 06450   063B0
EOITOR 3345 04970   05340 05360 05400 05570
EXECU  344C 06700   06640
FGHIJ  3213 03000
FIN5H1 327C 03630   03590
FOUNO  30CB 01270   01090
FREQCY 316C 021B0   021B0
GETCHR 3520 0B340   0B320
GOAWAY 3131 01B60   01520 01540 01570 01650 01670 01770
GRIN5  306C 00660   081B0
HEXASC 33B0 05660   04500 045B0 046B0 05760
IIII   3494 07290   07210
INBEEP 31FB 02890   02540
INKEYS 4099 00260   01100
INTR01 353B 0B400   02650
INTR02 35A3 08470   02670
INTR03 3642 08560   02690
INTR04 360B 0B650   02710
JMPPOS 34BA 07560   07470 07480
KBPFIX 3085 00790   02890
KEEPIT 32B4 03800   03760
KEYPRS 30B0 00B30   00950
KPLACE 401A 00290   01050 01130 01150 01240
KYSCAN 03FB 00270
LLLLS  33C2 05B10   05490 06030 06120
LOWCAS 310B 02750   02560
LOWER  3510 0B200   02770
LOWER1 351C 082E0   08230
LP99   3465 06980   07030
LUPER  348C 07600   07620
MACH   33F4 061B0   03070
MEMSET 34CE 07740   02520
MEMTOP 40B1 00360   03650
MENU   31C1 02650   02620
NAME99 3400 06330   06370
```

```
NAMES  3245 03310   03350
NEXT99 3342 04950   04420
NEXTBT 3253 03380   03330 03400
NOTRDY 317F 02320   02290
NXTB99 3418 06410   06350 06430
NXTBCH 328A 03730   03780
NXTPGE 3272 03560   03610
OKSTAR 3180 02400   02370
OPENER 32E4 04360   02480
OUTSEQ 32C0 04080   03430 03440 03470 03540 03600 03710 03770
                    03820 06990
PORTFF 4030 00280   02070
PREOUT 328E 04070   03870
PREP2  3487 07540   07130 07270
READY  06CC 00350   00770 02910 04040 05210 07540
READYX 31FE 02910   02730 02790 02830 02870
RECHEK 3093 00890   01120 01220
RENEW  3201 02930   02460
RESTRT 4004 00310   00590 00690
RRRRS  3388 05720   04470 04550 04650
RSLVII 3076 00730   03000
SAVE   3193 02430
SAVER  3216 03020   02440
SETPTS 4000 00370   03420
SHIFTR 4019 00300   00710 01930 01950 02760 08210
SKPSTP 3176 02250   00630 07230 07240
SSSS   3303 05940   05960
STACKR 40E8 00330   03630
START  3039 00440   08720
STEPPR 34BA 07570
STGEND 40A0 00320
STNDRD 339F 05550   05020 05060 05120 05170
STPSET 3480 07160   02500
STRING 3506 08140   08150
STROKE 30AA 01080   00860
SYN2   33F0 06230   06190 06470
SYN3   34A3 07410   07760
SYNERR 318E 02630   02410 03040 03110 04380 06230 07410
TABLET 3121 01780   01720
TMWSTE 30C1 01200   01200
TTTT   3439 06590   06540
UPPPER 31E8 02810   02600
VAREND 40F0 00340   03490
VIDEO  3C00 00400   03840
WRIT99 3453 06740   06680
WRTBYT 0264 00380   03270 03340 03390 03920 03950 03970 04090
                    04120 04160 04220 04280 04330 06290 06360
                    06420 07060 07090 07110
WRTPGE 3205 04240   04300
XX99   3301 05930   04400 06490 06590 06700 07780
Z0429H 30F0 01580   01450
Z0435H 3109 01640   01620
Z0430H 3111 01680   01590
Z0443H 3117 01720   01700
```

KEEPIT 3.2 is a 2K utility program created to extend the capabilities of Level II BASIC. It was originally sold by The Alternate Source in a RAM-based format (version 2.1), and has appeared variously from Personal Micro Computers, The Peripheral People, and Computer Accessory Technology. It is still available from C.A.T., and (together with the Memory Sidecar) from MSB Electronics, Drawer 766, Barre, Vermont 05641. However, since it contains many of the software drivers and other routines presented in The Custom TRS-80, and represents a complete implementation of the custom interpreter (Chapter 3), it is offered here as a completely revised version in source code format. Its current origin is 3000H, for use with the Memory Sidecar project presented in Chapter 8.

74LS00



$Y = \overline{AB}$

74LS02



$Y = \overline{A+B}$

74LS04



$Y = \overline{A}$

74LS08



$Y = AB$

74LS10

$Y = \overline{ABC}$



74LS11

$Y = ABC$



74LS14

$Y = \overline{A}$



74LS20

$Y = \overline{ABCD}$



74LS27



$Y = \overline{A+B+C}$

74LS30



$Y = \overline{ABCDEFGH}$

74LS32



$Y = A + B$

74LS74



INPUTS				OUTPUTS	
PR	CLR	CLK	D	Q	$\overline{Q}$
L	H	X	X	H	L
H	L	X	X	L	H
L	L	X	X	H*	H*
H	H	↑	H	H	L
H	H	↑	L	L	H
H	H	L	X	Q0	$\overline{Q}$0

74LS75

INPUTS		OUTPUTS	
D	G	Q	$\overline{Q}$
L	H	L	H
H	H	H	L
X	L	Q_0	$\overline{Q}_0$

H = High Level, L = Low Level, X = Don't Care
Q_0 = The Level of Q Before the High-to-Low Transition of G



74LS86

INPUTS		OUTPUT
A	B	Y
L	L	L
L	H	H
H	L	H
H	H	L

$Y = A \oplus B = \overline{A}B + A\overline{B}$



74LS90

LS90
BCD COUNT SEQUENCE
(See Note A)

COUNT	OUTPUT			
	Q_D	Q_C	Q_B	Q_A
0	L	L	L	L
1	L	L	L	H
2	L	L	H	L
3	L	L	H	H
4	L	H	L	L
5	L	H	L	H
6	L	H	H	L
7	L	H	H	H
8	H	L	L	L
9	H	L	L	H

LS90
RESET/COUNT TRUTH TABLE

RESET INPUTS				OUTPUT			
R0(1)	R0(2)	R9(1)	R9(2)	Q_D	Q_C	Q_B	Q_A
H	H	L	X	L	L	L	L
H	H	X	L	L	L	L	L
X	X	H	H	H	L	L	H
X	L	X	L	COUNT			
L	X	L	X	COUNT			
L	X	X	L	COUNT			
X	L	L	X	COUNT			

LS90 BI-QUINARY (5-2)
(See Note B)

COUNT	OUTPUT			
	Q_A	Q_D	Q_C	Q_B
0	L	L	L	L
1	L	L	L	H
2	L	L	H	L
3	L	L	H	H
4	L	H	L	L
5	H	L	L	L
6	H	L	L	H
7	H	L	H	L
8	H	L	H	H
9	H	H	L	L

Notes:
(A) Output Q_A is connected to input B for BCD count.
(B) Output Q_D is connected to input A for bi-quinary count.
(C) Output Q_A is connected to input B.
(D) H = High Level, L = Low Level, X = Don't Care.



74LS92

LS92
COUNT SEQUENCE
(See Note C)

COUNT	OUTPUT			
	Q_D	Q_C	Q_B	Q_A
0	L	L	L	L
1	L	L	L	H
2	L	L	H	L
3	L	L	H	H
4	L	H	L	L
5	L	H	L	H
6	H	L	L	L
7	H	L	L	H
8	H	L	H	L
9	H	L	H	H
10	H	H	L	L
11	H	H	L	H

LS92
RESET/COUNT TRUTH TABLE

RESET INPUTS		OUTPUT			
R0(1)	R0(2)	Q_D	Q_C	Q_B	Q_A
H	H	L	L	L	L
L	X	COUNT			
X	L	COUNT			



74LS93



COUNT SEQUENCE
(See Note C)

COUNT	OUTPUT			
	Q_D	Q_C	Q_B	D_A
0	L	L	L	L
1	L	L	L	H
2	L	L	H	L
3	L	L	H	H
4	L	H	L	L
5	L	H	L	H
6	L	H	H	L
7	L	H	H	H
8	H	L	L	L
9	H	L	L	H
10	H	L	H	L
11	H	L	H	H
12	H	H	L	L
13	H	H	L	H
14	H	H	H	L
15	H	H	H	H

LS93
Notes:
(A) Output D_A is connected to input B for BCD count.
(B) Output Q_D is connected to input A for bi-quinary count.
(C) Output Q_A is connected to input B
(D) H = High Level, L = Low Level, X = Don't Care.

74LS125

74LS154



INPUTS						OUTPUTS															
G1	G2	D	C	B	A	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
L	L	L	L	L	L	L	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H
L	L	L	L	L	H	H	L	H	H	H	H	H	H	H	H	H	H	H	H	H	H
L	L	L	L	H	L	H	H	L	H	H	H	H	H	H	H	H	H	H	H	H	H
L	L	L	L	H	H	H	H	H	L	H	H	H	H	H	H	H	H	H	H	H	H
L	L	L	H	L	L	H	H	H	H	L	H	H	H	H	H	H	H	H	H	H	H
L	L	L	H	L	H	H	H	H	H	H	L	H	H	H	H	H	H	H	H	H	H
L	L	L	H	H	L	H	H	H	H	H	H	L	H	H	H	H	H	H	H	H	H
L	L	L	H	H	H	H	H	H	H	H	H	H	L	H	H	H	H	H	H	H	H
L	L	H	L	L	L	H	H	H	H	H	H	H	H	L	H	H	H	H	H	H	H
L	L	H	L	L	H	H	H	H	H	H	H	H	H	H	L	H	H	H	H	H	H
L	L	H	L	H	L	H	H	H	H	H	H	H	H	H	H	L	H	H	H	H	H
L	L	H	L	H	H	H	H	H	H	H	H	H	H	H	H	H	L	H	H	H	H
L	L	H	H	L	L	H	H	H	H	H	H	H	H	H	H	H	H	L	H	H	H
L	L	H	H	L	H	H	H	H	H	H	H	H	H	H	H	H	H	H	L	H	H
L	L	H	H	H	L	H	H	H	H	H	H	H	H	H	H	H	H	H	H	L	H
L	L	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H	L
L	H	X	X	X	X	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H
H	L	X	X	X	X	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H
H	H	X	X	X	X	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H	H

H = High Level, L = Low Level, X = Don't Care

74LS125

INPUTS		OUTPUT
A	C	Y
H	L	H
L	L	L
X	H	Hi-Z

Y = A



74LS154

74LS157

INPUTS				OUTPUT Y	
STROBE	SELECT	A	B	157, L157A LS157, S157	LS158 S158
H	X	X	X	L	H
L	L	L	X	L	H
L	L	H	X	H	L
L	H	X	L	L	H
L	H	X	H	H	L

H = High Level, L = Low Level, X = Don't Care



74LS166

INPUTS						INTERNAL OUTPUTS		OUTPUT Q_H
CLEAR	SHIFT/ LOAD	CLOCK INHIBIT	CLOCK	SERIAL	PARALLEL A . . . H	Q_A	Q_B	
L	X	X	X	X	X	L	L	L
H	X	L	L	X	X	Q_{A0}	Q_{B0}	Q_{H0}
H	L	L	↑	X	a . . . h	a	b	h
H	H	L	↑	H	X	H	Q_{An}	Q_{Gn}
H	H	L	↑	L	X	L	Q_{An}	Q_{Gn}
H	X	H	↑	X	X	Q_{A0}	Q_{B0}	Q_{H0}

H = High Level (steady state), L = Low Level (steady state)

X = Don't Care (any input, including transitions)

↑ = Transition from low to high level

a . . . h = The level of steady-state input at inputs A through H, respectively.

Q_{A0}, Q_{B0}, Q_{H0} = The level of Q_A, Q_B or Q_H, respectively, before the indicated steady-state input conditions were established.

Q_{An}, Q_{Gn} = The level of Q_A or Q_G, respectively, before the most recent ↑ transition of the clock



74LS174



INPUTS			OUTPUTS	
CLEAR	CLOCK	D	Q	$\overline{Q}^{\dagger}$
L	X	X	L	H
H	↑	H	H	L
H	↑	L	L	H
H	L	X	Q_0	$\overline{Q}_0$

H = High Level (steady state)
L = Low Level (steady state)
X = Don't Care
↑ = Transition from low to high level
Q_0 = The level of Q before the indicated steady-state input conditions were established.
† = 175, LS175, and S175 only

74LS260



$Y = \overline{A+B+C+D+E}$



INPUTS			OUTPUT
$\overline{G}1$	$\overline{G}2$	A	Y
H	X	X	Z
X	H	X	Z
L	L	H	H
L	L	L	L

74LS366

INPUTS			OUTPUT
$\overline{G}1$	$\overline{G}2$	A	Y
H	X	X	Z
X	H	X	Z
L	L	H	L
L	L	L	H



74LS367

INPUTS		OUTPUT
$\overline{G}$	A	Y
H	X	Z
L	H	H
L	L	L



74LS368

INPUTS		OUTPUT
$\overline{G}$	A	Y
H	X	Z
L	H	L
L	L	H



74LS373



OUTPUT CONTROL	CLOCK	O	OUTPUT
L	H	H	H
L	H	L	L
L	L	X	O0
H	X	X	Z

74LS374



OUTPUT CONTROL	CLOCK	O	OUTPUT
L	↑	H	H
L	↑	L	L
L	L	X	O0
H	X	X	Z

80C96



INPUTS			OUTPUT
$\overline{G1}$	$\overline{G2}$	A	Y
H	X	X	Hi-Z
X	H	X	Hi-Z
L	L	H	L
L	L	L	H

80C98

INPUTS		OUTPUT
$\overline{G}$	A	Y
H	X	Hi-Z
L	H	L
L	L	H



81LS95

INPUTS			OUTPUT
$\overline{G}1$	$\overline{G}2$	A	Y
H	X	X	Z
X	H	X	Z
L	L	H	H
L	L	L	L



81LS96

INPUTS			OUTPUT
$\overline{G}1$	$\overline{G}2$	A	Y
H	X	X	Z
X	H	X	Z
L	L	H	L
L	L	L	H







FD1771 SYSTEM BLOCK DIAGRAM



READ TIMING ($\overline{XTDS}$ = 1)



MISCELLANEOUS TIMING

PIN OUTS

Pin No.	Pin Name	Symbol	Function
1	Power Supplies	V_{BB}/NC	-5V
19	$\overline{\text{MASTER RESET}}$	$\overline{\text{MR}}$	A logic low on this input resets the device and loads "03" into the command register. The Not Ready (Status bit 7) is reset during $\overline{\text{MR}}$ ACTIVE. When $\overline{\text{MR}}$ is brought to a logic high, a Restore Command is executed, regardless of the state of the Ready signal from the drive.
20		V_{SS}	Ground
21		V_{CC}	+5V
40		V_{DD}	+12V
Computer Interface			
2	$\overline{\text{WRITE ENABLE}}$	$\overline{\text{WE}}$	A logic low on this input gates data on the DAL into the selected register when $\overline{\text{CS}}$ is low.
3	$\overline{\text{CHIP SELECT}}$	$\overline{\text{CS}}$	A logic low on this input selects the chip and enables computer communication with the device.
4	$\overline{\text{READ ENABLE}}$	$\overline{\text{RE}}$	A logic low on this input controls the placement of data from a selected register on the DAL when $\overline{\text{CS}}$ is low.
5, 6	REGISTER SELECT LINES	A_0, A_1	These inputs select the register to receive/transfer data on the DAL lines under $\overline{\text{RE}}$ and $\overline{\text{WE}}$ control: A_1 A_0 $\overline{\text{RE}}$ $\overline{\text{WE}}$ 0 0 Status Register Command Register 0 1 Track Register Track Register 1 0 Sector Register Sector Register 1 1 Data Register Data Register
7-14	$\overline{\text{DATA ACCESS LINES}}$	$\overline{\text{DAL0-DAL7}}$	Eight bit inverted bidirectional bus used for transfer of data, control, and status. This bus is a receiver enabled by $\overline{\text{WE}}$ or a transmitter enabled by $\overline{\text{RE}}$.
24	CLOCK	CLK	This input requires a free-running 2 MHz ± 1% square wave clock for internal timing reference.
38	DATA REQUEST	DRQ	This open drain output indicates that the DR contains assembled data in Read operations, or the DR is empty in Write operations. This signal is reset when serviced by the computer through reading or loading the DR in Read or Write operation, respectively. Use 10K pull-up resistor to +5.
39	INTERRUPT REQUEST	INTRQ	This open drain output is set at the completion or termination of any operation and is reset when a new command is loaded into the command register. Use 10K pull-up resistor to +5.
Floppy Disk Interface:			
15	$\overline{\text{Phase 1/Step}}$	$\overline{\text{PH1}}$/STEP	If the $\overline{\text{3PM}}$ input is a logic low the three-phase motor control is selected and $\overline{\text{PH1}}$, $\overline{\text{PH2}}$, and PH3 outputs

Pin No.	Pin Name	Symbol	Function
16	Phase 2/Direction	$\overline{\text{PH2}}$/DIRC	form a one active low signal out of three. $\overline{\text{PH1}}$ is active low after $\overline{\text{MR}}$. If the $\overline{\text{3PM}}$ input is a logic high the step and direction motor control is selected. The step output contains a 4 usec high signal for each step and the direction output is active high when stepping in; active low when stepping out.
17	Phase 3	PH3	
18	$\overline{\text{3-Phase Motor Select}}$	$\overline{\text{3PM}}$	
22	$\overline{\text{TEST}}$	$\overline{\text{TEST}}$	This input is used for testing purposes only and should be tied to +5V or left open by the user.
23	HEAD LOAD TIMING	HLT	The HLT input is sampled after 10 ms. When a logic high is sampled on the HLT input the head is assumed to be engaged.
25	$\overline{\text{EXTERNAL DATA}}$ SEPARATION	$\overline{\text{XTDS}}$	A logic low on this input selects external data separation. A logic high or open selects the internal data separator.
26	FLOPPY DISK CLOCK (External Separation)	FDCLOCK	This input receives the externally separated clock when $\overline{\text{XTDS}}$ = 0. If $\overline{\text{XTDS}}$ = 1, this input should be tied to a logic high.
27	FLOPPY DISK DATA	FDDATA	This input receives the raw read disk data if $\overline{\text{XTDS}}$=1, or the externally separated data if $\overline{\text{XTDS}}$=0.
28	HEAD LOAD	HLD	The HLD output controls the loading of the Read-Write head against the media.
29	Track Greater than 43	TG43	This output informs the drive that the Read-Write head is positioned between tracks44-76. This output is valid only during Read and Write commands.
30	WRITE GATE	WG	This output is made valid when writing is to be performed on the diskette.
31	WRITE DATA	WD	This output contains both clock and data bits of 500 ns duration.
32	Ready	READY	This input indicates disk readiness and is sampled for a logic high before Read or Write commands are performed. If Ready is low, the Read or Write operation is not performed and an interrupt is generated. A Seek operation is performed regardless of the state of Ready. The Ready input appears in inverted format as Status Register bit 7.
33	$\overline{\text{WRITE FAULT}}$	$\overline{\text{WF}}$	This input detects wiring faults indications from the drive. When WG=1 and $\overline{\text{WF}}$ goes low, the current Write command is terminated and the Write Fault status bit is set. The $\overline{\text{WF}}$ input should be made inactive (high) when WG becomes inactive.
34	$\overline{\text{TRACK 00}}$	$\overline{\text{TR00}}$	This input informs the FD1771 that the Read-Write head is positioned over Track 00 when a logic low.
35	$\overline{\text{INDEX PULSE}}$	$\overline{\text{IP}}$	Input, when low for a minimum of 10 usec, informs the FD1771 when an index mark is encountered on the diskette.
36	$\overline{\text{WRITE PROTECT}}$	$\overline{\text{WPRT}}$	This input is sampled whenever a Write command is received. A logic low terminates the command and sets the Write Protect status bit.
37	$\overline{\text{DISK INITIALIZATION}}$	$\overline{\text{DINT}}$	The iput is sampled whenever a Write Track command is received. If $\overline{\text{DINT}}$=0, the operation is terminated and the Write Protect status bit is set.

COMMAND DESCRIPTION

The FD1771 will accept and execute eleven commands. Command words should only be loaded in the Command Register when the Busy status bit is off (status bit 0). The one exception is the Force Interrupt command. Whenever a command is being executed, the Busy status bit is set. When a command is completed, an interrupt is generated and the Busy status bit is reset. The Status Register indicates whether the completed command encountered an error or was fault-free. For ease of discussion, commands are divided into four types. Commands and types are summarized in Table 2.

TYPE 1 COMMANDS

The Type 1 Commands include the RESTORE, SEEK, STEP, STEP-IN, and STEP-OUT commands. Each of the Type 1 Commands contain a rate field (r_0r_1), which determines the stepping motor rate as defined in Table 1, page 4.

The Type 1 Commands contain a head load flag (h) which determines if the head is to be loaded at the beginning of the command. If h=1, the head is loaded at the beginning of the command (HLD output is made active). If h=0, HLD is deactivated. Once the head is loaded, the head will remain engaged until the FD1771 receives a command that specifically disengages the head. If the FD1771 does not receive any commands after two revolutions of the disk, the head will be automatically disengaged (HLD made inactive). The Head Load Timing Input is sampled after a 10 ms delay, when reading or writing on the disk is to occur.

Table 2. COMMAND SUMMARY

		BITS							
TYPE	COMMAND	7	6	5	4	3	2	1	0
I	Restore	0	0	0	0	h	V	r_1	r_0
I	Seek	0	0	0	1	h	V	r_1	r_0
I	Step	0	0	1	u	h	V	r_1	r_0
I	Step In	0	1	0	u	h	V	r_1	r_0
I	Step Out	0	1	1	u	h	V	r_1	r_0
II	Read Command	1	0	0	0	1	1	0	0
II	Write Command	1	0	1	0	1	1	0	a_0
III	Read Address	1	1	0	0	0	E	0	0
III	Read Track	1	1	1	0	0	1	0	$\overline{s}$
III	Write Track	1	1	1	1	0	1	0	0
IV	Force Interrrupt	1	1	0	1	I_3	I_2	I_1	I_4

Note: Bits shown in TRUE form.

Table 3. FLAG SUMMARY

TYPE I

h = Head Load flag (Bit 3)

h = 1, Load head at beginning
h = 0, Do not load head at beginning

V = Verify flag (Bit 2)

V = 1, Verify on last track
V = 0, No verify

r_1r_0 = Stepping motor rate (Bits 1-0)

Refer to Table 1 for rate summary

u = Update flag (Bit 4)

u = 1, Update Track register
u = 0, No update

Table 4. FLAG SUMMARY

TYPE II

m = Multiple Record flag (Bit 4)

m=0, Single Record
m=1, Multiple Records

b = Block length flag (Bit 3)

b=1, IBM format (128 to 1024 bytes)
b=0, Non-IBM format (16 to 4096 bytes)

a_1a_0= Data Address Mark (Bits 1-0)

a_1a_0= 00, FB (Data Mark)
a_1a_0= 01, FA (User defined)
a_1a_0= 10, F9 (User defined)
a_1a_0= 11, F8 (Deleted Data Mark)

Table 5. FLAG SUMMARY

TYPE III

s = Synchronize flag (Bit 0)

$\overline{s}$=0, Synchronize to AM
$\overline{s}$=1, Do Not Synchronize to AM

TYPE IV

Ii = Interrupt Condition flags (Bits 3-0)

I_0=1, Not Ready to Ready Transition
I_1=1, Ready to Not Ready Transition
I_2=1, Index Pulse
I_3=1, Immediate interrupt

E = Enable HLD and 10 msec Delay

E=1, Enable HLD, HLT and 10 msec Delay
E=0, Head is assumed Engaged and there is no 10 msec Delay

The Type 1 Commands also contain a verification (V) flag which determines if a verification operation is to take place on the destination track. If V=1, a verification is performed; if V=0, no verification is performed.

During verification, the head is loaded and after an internal 10 ms delay, the HLT input is sampled. When

ELECTRICAL CHARACTERISTICS

Maxium Ratings

V_{DD} with respect to V_{BB} (Ground)	+20 to -0.3V
Max Voltage to any input with respect to V_{BB}	+20 to -0.3V
Operating Temperature	0°C to 70°C
Storage Temperature	-55°C to +125°C

OPERATING CHARACTERISTICS (DC)

T_A = 0°C to 70°C, V_{DD} = +12.0V ± .6V,
V_{BB} = -5.0 ± .5V, V_{SS} = 0V, V_{CC} = +5V ± .25V
I_{DD} = 10 ma Nominal, I_{CC} = 30 ma Nominal,
I_{BB} = 0.4 μa Nominal

Symbol	Characteristic	Min.	Typ.	Max.	Units	Conditions
I_{LI}	Input Leakage			10	µA	$V_{IN} = V_{DD}$
I_{LO}	Output Leakage			10	µA	$V_{OUT} = V_{DD}$
V_{IH}	Input High Voltage	2.6			V	
V_{IL}	Input Low Voltage (All Inputs)			0.8	V	
V_{OH}	Output High Voltage	2.8			V	$I_O = -100$ uA
V_{OL}	Output Low Voltage			0.45**	V	$I_O = 1.0$ mA

**Write Gate $V_{OL} \leq 0.5V$.

TIMING CHARACTERISTICS

TA = 0°C to 70°C, V_{DD} = +12V ± .6V,
V_{BB} = -5V ± .25V, V_{SS} = 0V, V_{CC} = +5V ± .25V

NOTE: Timings are given for 2 MHz Clock. For those timings noted, values will double when chip is operated at 1 MHz. Use 1 MHz when using mini-floppy.

Read Operations

Symbol	Characteristic	Min.	Typ.	Max.	Units	Conditions
TSET	Setup ADDR and CS to $\overline{\text{RE}}$	100			nsec	
THLD	Hold ADDR and CS from $\overline{\text{RE}}$	10			nsec	
TRE	$\overline{\text{RE}}$ Pulse Width	500			nsec	C_L = 25 pf
TDRR	DRQ Reset from $\overline{\text{RE}}$			500	nsec	
TIRR	INTRQ Reset from $\overline{\text{RE}}$			3000	nsec	
TDACC	Data Access from $\overline{\text{RE}}$			450	nsec	C_L = 25 pf
TDOH	Data Hold from $\overline{\text{RE}}$	50		150	nsec	C_L = 25 pf

Write Operations

Symbol	Characteristic	Min.	Typ.	Max.	Units	Conditions
TSET	Setup ADDR and CS to $\overline{\text{WE}}$	100			nsec	See Note
THLD	Hold ADDR and CS from $\overline{\text{WE}}$	10			nsec	
TWE	$\overline{\text{WE}}$ Pulse Width	350			nsec	
TDRR	DRQ Reset from $\overline{\text{WE}}$			500	nsec	
TIRR	INTRQ Reset from $\overline{\text{WE}}$			3000	nsec	
TDS	Data Setup to $\overline{\text{WE}}$	250			nsec	
TDH	Data Hold from $\overline{\text{WE}}$	150			nsec	

External Data Separation ($\overline{\text{XTDS}}$ = 0)

Symbol	Characteristic	Min.	Typ.	Max.	Units	Conditions
TPWX	Pulse Width Read Data & Read Clock	150		350	nsec	
TCX	Clock Cycle External	2500			nsec	
TDEX	Data to Clock	500			nsec	
TDDX	Data to Data Cycle	2500			nsec	



NOTE
1 CS MAY BE PERMANENTLY TIED LOW IF DESIRED
2 FOR READ TRACK COMMAND, THIS TIME MAY BE 12* TO 32* μSEC WHEN S = 0
3 $t_{service}$ WORST CASE 26 μSEC
*TIME DOUBLES WHEN CLK = 1 MHZ

READ ENABLE TIMING



NOTE
1 CS MAY BE PERMANENTLY TIED LOW IF DESIRED
2 WHEN WRITING DATA INTO THIS SECTOR TRACK OR DATA REGISTER USER CANNOT READ THIS REGISTER UNTIL AT LEAST 8 μSEC AFTER THE RISING EDGE OF WE WHEN WRITING INTO THE COMMAND REGISTER STATUS IS NOT VALID UNTIL SOME 20 μSEC LATER THESE TIMES ARE DOUBLED WHEN CLK = 1 MHZ
3 $t_{service}$ WORST CASE 24 μSEC
* = TIME DOUBLES WHEN CLK = 1 MHZ

WRITE ENABLE TIMING



NOTE
1 ABOVE TIMES ARE DOUBLED WHEN CLK = 1 MHZ
2 CONTACT WDC FOR EXTERNAL CLOCK/DATA SEPARATOR CIRCUITS
3 FDCLK AND FDDATA MAY BE REVERSED FD1771 DECIDES WHAT IS CLOCK AND WHAT IS DATA

READ TIMING ($\overline{XTDS}$ = 0)

Internal Data Separation ($\overline{XTDS}$ = 1)

Symbol	Characteristic	Min.	Typ.	Max.	Units	Conditions
TPWI	Pulse Width Data and Clock	150		1000	nsec	
TCI	Clock Cycle Internal	3500		5000	nsec	

Write Data Timing

Symbol	Characteristic	Min.	Typ.	Max.	Units	Conditions
TWGD	Write Gate to Data		1200		nsec	300 nsec ± CLK tolerance
TPWW	Pulse Width Write Data	500		600	nsec	
TCDW	Clock to Data		2000		nsec	± CLK tolerance
TCW	Clock Cycle Write		4000		nsec	± CLK tolerance
TWGH	Write Gate Hold to Data	0		100	nsec	

Miscellaeous Timing

Symbol	Characteristic	Min.	Typ.	Max.	Units	Conditions
TCD_1	Clock Duty	175			nsec	2 MHz ± 1% See Note
TCD_2	Clock Duty	210			nsec	
TSTP	Step Pulse Output	3800		4200	nsec	These times doubled when CLK = 1 MHz
TDIR	Direct Setup to Step	24			usec	
TMR	Master Reset Pulse Width	10			usec	
TIP	Index Pulse Width	10			usec	
TWF	Write Fault Pulse Width	10			usec	



WRITE DATA TIMING

Mode Definition Summary Table

Port Bits	Mode 0		Mode 1		Mode 2
	IN	OUT	IN	OUT	Group A Only
PA_0	IN	OUT	IN	OUT	Bidirectional
PA_1	IN	OUT	IN	OUT	↕
PA_2	IN	OUT	IN	OUT	
PA_3	IN	OUT	IN	OUT	
PA_4	IN	OUT	IN	OUT	
PA_5	IN	OUT	IN	OUT	
PA_6	IN	OUT	IN	OUT	
PA_7	IN	OUT	IN	OUT	Bidirectional
PB_0	IN	OUT	IN	OUT	(Mode 0 or Mode 1 only)
PB_1	IN	OUT	IN	OUT	
PB_2	IN	OUT	IN	OUT	
PB_3	IN	OUT	IN	OUT	
PB_4	IN	OUT	IN	OUT	
PB_5	IN	OUT	IN	OUT	
PB_6	IN	OUT	IN	OUT	
PB_7	IN	OUT	IN	OUT	
PC_0	IN	OUT	INTR_B	INTR_B	I/O
PC_1	IN	OUT	IBF_B	$\overline{\text{OBF}}_B$	I/O
PC_2	IN	OUT	$\overline{\text{STB}}_B$	$\overline{\text{ACK}}_B$	I/O
PC_3	IN	OUT	INTR_A	INTR_A	INTR_A
PC_4	IN	OUT	$\overline{\text{STB}}_A$	I/O	$\overline{\text{STB}}_A$
PC_5	IN	OUT	IBF_A	I/O	IBF_A
PC_6	IN	OUT	I/O	$\overline{\text{ACK}}_A$	$\overline{\text{ACK}}_A$
PC_7	IN	OUT	I/O	$\overline{\text{OBF}}_A$	$\overline{\text{OBF}}_A$

Physical Dimensions



Ceramic Dual-In-Line Package [Cerdip (J)]
Order Number INS8255J



Plastic Dual-In-Line Package (N)
Order Number INS8255N

National Semiconductor Corporation
2900 Semiconductor Drive
Santa Clara CA 95051
Tel (408)737-5000
TWX (910)339-9240

National Semiconductor GmbH
Eisenheimerstrasse 61/11
8000 Munchen 21
West Germany
Tel (089)576091
Telex 05-22772

NS International Inc., Japan
Miyake Building
1-9 Yotsuya Shinjuku-ku 160
Tokyo Japan
Tel (03)355-3711
TWX 232-2015 NSCJ—J

National Semiconductor (Hong Kong) Ltd
8th Floor
Cheung Kong Electronic Bldg
4 Hing Yip Street
Kwun Tong
Kowloon Hong Kong
Tel 3-899235
Telex 43866 NSEHK HX
Cable NATSEMI

NS Electronics Do Brasil
Avda Brigadeiro Faria Lima 844
11 Andar Conjunto 1104
Jardim Paulistano
Sao Paulo Brasil
Telex 1121008 Cabine Sao Paulo

NS Electronics Pty. Ltd.
Cnr Stud Rd & Mtn Highway
Bayswater Victoria 3153
Australia
Tel 03-729-6333
Telex 32096

National does not assume any responsibility for use of any circuitry described no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry

Timing Waveforms



Mode 0 (Basic Input)



Mode 0 (Basic Output)



Mode 1 (Strobed Input)

Timing Waveforms (cont'd.)



Mode 1 (Strobed Output)



Mode 2 (Bidirectional)

INPUT/OUTPUT SIGNALS

Data (D7–D0) Bus, Pins 27–34: This bus comprises eight TRI-STATE®input/output lines. The bus provides bi-directional communication between the INS8255 and the INS8080A. Data is routed to or from the internal data bus buffer upon execution of an OUT or IN Instruction, respectively, by the INS8080A In addition, control words and status information are transferred through the data bus buffer.

Port A (PA7–PA0), Pins 37–40, 1–4: This 8-bit input/output port forms one 8-bit data output latch/buffer and/or one 8-bit data input latch.

NOTE

The system software uses a Mode Definition Control Word (see figure) as the second byte of OUT Instruction(s) to program the functional configuration of Ports A through C Whenever the mode is changed, all output registers (and status flip-flops) are reset.

Port B (PB7–PB0), Pins 18–25: This 8-bit input/output port forms one 8-bit data output latch/buffer or one 8-bit data input buffer.

Port C (PC7–PC0), Pins 10–17: This 8 bit input/output port forms one 8-bit data output latch/buffer or one 8-bit data input buffer The port can be split into two 4-bit ports under the mode control Each of these 4-bit ports contains a 4-bit latch that may be used for the control and status signals, in conjunction with Ports A and B. The system software includes a Bit Set/Reset Control Word (see figure) for setting or resetting any of the eight bits of Port C When Port C is being used as a status/control for Port A or B, the Port C bits can be set or reset by using the Bit Set/Reset Control Word as the second byte of OUT Instruction(s).

Pin Configuration





Mode Definition Control Word Format



Bit Set/Reset Control Word Format (Port C Only)

® Registered National Semiconductor Corp

Operating Modes

Mode 0 (Basic Input/Output)

In this mode, simple input and output operations for each of the three ports are provided No "handshaking" is required; data is simply written to or read from a specified port

Mode 0 Port Definition Chart

No.	Control Word Bits								Group A		Group B	
	D_7	D_6	D_5	D_4	D_3	D_2	D_1	D_0	Port A	Port C (Upper)	Port B	Port C (Lower)
0	1	0	0	0	0	0	0	0	OUTPUT	OUTPUT	OUTPUT	OUTPUT
1	1	0	0	0	0	0	0	1	OUTPUT	OUTPUT	OUTPUT	INPUT
2	1	0	0	0	0	0	1	0	OUTPUT	OUTPUT	INPUT	OUTPUT
3	1	0	0	0	0	0	1	1	OUTPUT	OUTPUT	INPUT	INPUT
4	1	0	0	0	1	0	0	0	OUTPUT	INPUT	OUTPUT	OUTPUT
5	1	0	0	0	1	0	0	1	OUTPUT	INPUT	OUTPUT	INPUT
6	1	0	0	0	1	0	1	0	OUTPUT	INPUT	INPUT	OUTPUT
7	1	0	0	0	1	0	1	1	OUTPUT	INPUT	INPUT	INPUT
8	1	0	0	1	0	0	0	0	INPUT	OUTPUT	OUTPUT	OUTPUT
9	1	0	0	1	0	0	0	1	INPUT	OUTPUT	OUTPUT	INPUT
10	1	0	0	1	0	0	1	0	INPUT	OUTPUT	INPUT	OUTPUT
11	1	0	0	1	0	0	1	1	INPUT	OUTPUT	INPUT	INPUT
12	1	0	0	1	1	0	0	0	INPUT	INPUT	OUTPUT	OUTPUT
13	1	0	0	1	1	0	0	1	INPUT	INPUT	OUTPUT	INPUT
14	1	0	0	1	1	0	1	0	INPUT	INPUT	INPUT	OUTPUT
15	1	0	0	1	1	0	1	1	INPUT	INPUT	INPUT	INPUT



Mode 0 Timing

Operating Modes (cont'd.)

Mode 1 (Strobed Input/Output)

In thismode, a means for transferring input/output data to or from a specified port in conjunction with strobes or "handshaking" signals is provided Port A and Port B use the lines on Port C to generate or accept these "handshaking" signals in Mode 1 The programmer can read the contents of Port C to test or verify the status of each peripheral device Since no special instruction is provided in the INS8080A microcomputer system to read the Port C status information, a normal read operation must be executed to perform this function





Notes:

1 INTE$_A$ is controlled by bit set/reset of PC$_4$

2 INTE$_B$ is controlled by bit set/reset of PC$_2$

Mode 1 Input



Mode 1 Input Timing

Operating Modes (cont'd.)



Notes:

1 INTE$_A$ is controlled by bit set/reset of PC$_6$

2 INTE$_B$ is controlled by bit set/reset of PC$_2$



Mode 1 Output



Mode 1 Output Timing



Mode 1 Combinations

Operating Modes (cont'd.)

Mode 2 (Strobed Bidirectional Bus Input/Output)

This mode enables communication with a peripheral device or structure on a single 8-bit bus for both transmitting and receiving data (bidirectional bus input/output) "Handshaking" signals are provided to maintain proper bus flow discipline in a manner similar to Mode 1 In addition, interrupt generation and enable/disable functions are available in Mode 2

Notes:
1 $INTE_1$ is controlled by bit set/reset of PC_6
2 $INTE_2$ is controlled by bit set/reset of PC_4





Mode 2



Mode 2 Timing

Operating Modes (cont'd.)



MODE 2 AND MODE 0 (INPUT)

MODE 2 AND MODE 0 (OUTPUT)



MODE 2 AND MODE 1 (OUTPUT)

MODE 2 AND MODE 1 (INPUT)

Mode 2 Combinations

Z80®-CPU
Z80A-CPU

Zilog®

Product Specification

MARCH 1978

The Zilog Z80 product line is a complete set of microcomputer components, development systems and support software. The Z80 microcomputer component set includes all of the circuits necessary to build high-performance microcomputer systems with virtually no other logic and a minimum number of low cost standard memory elements.

The Z80 and Z80A CPU's are third generation single chip microprocessors with unrivaled computational power. This increased computational power results in higher system through-put and more efficient memory utilization when compared to second generation microprocessors. In addition, the Z80 and Z80A CPU's are very easy to implement into a system because of their single voltage requirement plus all output signals are fully decoded and timed to control standard memory or peripheral circuits. The circuit is implemented using an N-channel, ion implanted, silicon gate MOS process.

Figure 1 is a block diagram of the CPU, Figure 2 details the internal register configuration which contains 208 bits of Read/Write memory that are accessible to the programmer. The registers include two sets of six general purpose registers that may be used individually as 8-bit registers or as 16-bit register pairs. There are also two sets of accumulator and flag registers. The programmer has access to either set of main or alternate registers through a group of exchange instructions. This alternate set allows foreground/background mode of operation or may be reserved for very fast Interrupt response. Each CPU also contains a 16-bit stack pointer which permits simple implementation of multiple level interrupts, unlimited subroutine nesting and simplification of many types of data handling.

The two 16-bit index registers allow tabular data manipulation and easy implementation of relocatable code. The Refresh register provides for automatic, totally transparent refresh of external dynamic memories. The I register is used in a powerful interrupt response mode to form the upper 8 bits of a pointer to a interrupt service address table, while the interrupting device supplies the lower 8 bits of the pointer. An indirect call is then made to this service address.

FEATURES

- Single chip, N-channel Silicon Gate CPU.
- 158 instructions—includes all 78 of the 8080A instructions with total software compatibility. New instructions include 4-, 8- and 16-bit operations with more useful addressing modes such as indexed, bit and relative.
- 17 internal registers.
- Three modes of fast interrupt response plus a non-maskable interrupt.
- Directly interfaces standard speed static or dynamic memories with virtually no external logic.
- 1.0 μs instruction execution speed.
- Single 5 VDC supply and single-phase 5 volt Clock.
- Out-performs any other single chip microcomputer in 4-, 8-, or 16-bit applications.
- All pins TTL Compatible
- Built-in dynamic RAM refresh circuitry.



Z80, Z80A CPU BLOCK DIAGRAM



MAIN REG SET		ALTERNATE REG SET	
ACCUMULATOR A	FLAGS F	ACCUMULATOR A'	FLAGS F'
B	C	B'	C'
D	E	D'	E'
H	L	H'	L'

GENERAL PURPOSE REGISTERS

INTERRUPT VECTOR I	MEMORY REFRESH R
INDEX REGISTER IX	
INDEX REGISTER IY	
STACK POINTER SP	
PROGRAM COUNTER PC	

SPECIAL PURPOSE REGISTERS

Z80, Z80A CPU REGISTERS



Z80, Z80A CPU PIN CONFIGURATION

A_0-A_{15} (Address Bus)	Tri-state output, active high. A_0-A_{15} constitute a 16-bit address bus. The address bus provides the address for memory (up to 64K bytes) data exchanges and for I/O device data exchanges.
D_0-D_7 (Data Bus)	Tri-state input/output, active high. D_0-D_7 constitute an 8-bit bidirectional data bus. The data bus is used for data exchanges with memory and I/O devices.
$\overline{M_1}$ (Machine Cycle one)	Output, active low. $\overline{M_1}$ indicates that the current machine cycle is the OP code fetch cycle of an instruction execution.
$\overline{\text{MREQ}}$ (Memory Request)	Tri-state output, active low. The memory request signal indicates that the address bus holds a valid address for a memory read or memory write operation.
$\overline{\text{IORQ}}$ (Input/Output Request)	Tri-state output, active low. The $\overline{\text{IORQ}}$ signal indicates that the lower half of the address bus holds a valid I/O address for a I/O read or write operation. An $\overline{\text{IORQ}}$ signal is also generated when an interrupt is being acknowledged to indicate that an interrupt response vector can be placed on the data bus.
$\overline{\text{RD}}$ (Memory Read)	Tri-state output, active low. $\overline{\text{RD}}$ indicates that the CPU wants to read data from memory or an I/O device. The addressed I/O device or memory should use this signal to gate data onto the CPU data bus.
$\overline{\text{WR}}$ (Memory Write)	Tri-state output, active low. $\overline{\text{WR}}$ indicates that the CPU data bus holds valid data to be stored in the addressed memory or I/O device.
$\overline{\text{RFSH}}$ (Refresh)	Output, active low. $\overline{\text{RFSH}}$ indicates that the lower 7 bits of the address bus contain a refresh address for dynamic memories and the current $\overline{\text{MREQ}}$ signal should be used to do a refresh read to all dynamic memories.
$\overline{\text{HALT}}$ (Halt state)	Output, active low. $\overline{\text{HALT}}$ indicates that the CPU has executed a HALT software instruction and is awaiting either a non-maskable or a maskable interrupt (with the mask enabled) before operation can resume. While halted, the CPU executes NOP's to maintain memory refresh activity.
$\overline{\text{WAIT}}$ (Wait)	Input, active low. $\overline{\text{WAIT}}$ indicates to the Z-80 CPU that the addressed memory or I/O devices are not ready for a data transfer. The CPU continues to enter wait states for as long as this signal is active.
$\overline{\text{INT}}$ (Interrupt Request)	Input, active low. The Interrupt Request signal is generated by I/O devices. A request will be honored at the end of the current instruction if the internal software controlled interrupt enable flip-flop (IFF) is enabled.
$\overline{\text{NMI}}$ (Non Maskable Interrupt)	Input, active low. The non-maskable nterrupt request line has a higher priority than $\overline{\text{INT}}$ and is always recognized at the end of the current instruction, independent of the status of the interrupt enable flip-flop. $\overline{\text{NMI}}$ automatically forces the Z-80 CPU to restart to location 0066_H.
$\overline{\text{RESET}}$	Input, active low. $\overline{\text{RESET}}$ initializes the CPU as follows: reset interrupt enable flip-flop, clear PC and registers I and R and set interrupt to 8080A mode. During reset time, the address and data bus go to a high impedance state and all control output signals go to the inactive state.
$\overline{\text{BUSRQ}}$ (Bus Request)	Input, active low. The bus request signal has a higher priority than $\overline{\text{NMI}}$ and is always recognized at the end of the current machine cycle and is used to request the CPU address bus, data bus and tri-state output control signals to go to a high impedance state so that other devices can control these busses.
$\overline{\text{BUSAK}}$ (Bus Acknowledge)	Output, active low. Bus acknowledge is used to indicate to the requesting device that the CPU address bus, data bus and tri-state control bus signals have been set to their high impedance state and the external device can now control these signals.

Timing Waveforms

INSTRUCTION OP CODE FETCH

The program counter content (PC) is placed on the address bus immediately at the start of the cycle. One half clock time later $\overline{\text{MREQ}}$ goes active. The falling edge of $\overline{\text{MREQ}}$ can be used directly as a chip enable to dynamic memories. $\overline{\text{RD}}$ when active indicates that the memory data should be enabled onto the CPU data bus. The CPU samples data with the rising edge of the clock state T_3. Clock states T_3 and T_4 of a fetch cycle are used to refresh dynamic memories while the CPU is internally decoding and executing the instruction. The refresh control signal $\overline{\text{RFSH}}$ indicates that a refresh read of all dynamic memories should be accomplished.



MEMORY READ OR WRITE CYCLES

Illustrated here is the timing of memory read or write cycles other than an OP code fetch (M_1 cycle). The $\overline{\text{MREQ}}$ and $\overline{\text{RD}}$ signals are used exactly as in the fetch cycle. In the case of a memory write cycle, the $\overline{\text{MREQ}}$ also becomes active when the address bus is stable so that it can be used directly as a chip enable for dynamic memories. The $\overline{\text{WR}}$ line is active when data on the data bus is stable so that it can be used directly as a R/W pulse to virtually any type of semiconductor memory.



INPUT OR OUTPUT CYCLES

Illustrated here is the timing for an I/O read or I/O write operation. Notice that during I/O operations a single wait state is automatically inserted (Tw*). The reason for this is that during I/O operations this extra state allows sufficient time for an I/O port to decode its address and activate the $\overline{\text{WAIT}}$ line if a wait is required.



INTERRUPT REQUEST/ACKNOWLEDGE CYCLE

The interrupt signal is sampled by the CPU with the rising edge of the last clock at the end of any instruction. When an interrupt is accepted, a special M_1 cycle is generated. During this M_1 cycle, the $\overline{\text{IORQ}}$ signal becomes active (instead of $\overline{\text{MREQ}}$) to indicate that the interrupting device can place an 8-bit vector on the data bus. Two wait states (Tw*) are automatically added to this cycle so that a ripple priority interrupt scheme, such as the one used in the Z80 peripheral controllers, can be easily implemented.



A.C. Characteristics Z80-CPU

T_A = 0°C to 70°C, Vcc = +5V ± 5%, Unless Otherwise Noted.

Signal	Symbol	Parameter	Min	Max	Unit	Test Condition
Φ	t_c	Clock Period	.4	[12]	µsec	
	$t_{w(\Phi H)}$	Clock Pulse Width, Clock High	180	[E]	nsec	
	$t_{w(\Phi L)}$	Clock Pulse Width, Clock Low	180	2000	nsec	
	$t_{r,f}$	Clock Rise and Fall Time		30	nsec	
A_{0-15}	$t_{D(AD)}$	Address Output Delay		145	nsec	C_L = 50pF
	$t_{F(AD)}$	Delay to Float		110	nsec	
	t_{acm}	Address Stable Prior to $\overline{MREQ}$ (Memory Cycle)	[1]		nsec	
	t_{aci}	Address Stable Prior to $\overline{IORQ}$, $\overline{RD}$ or $\overline{WR}$ (I/O Cycle)	[2]		nsec	
	t_{ca}	Address Stable from $\overline{RD}$, $\overline{WR}$, $\overline{IORQ}$ or $\overline{MREQ}$	[3]		nsec	
	t_{caf}	Address Stable From $\overline{RD}$ or $\overline{WR}$ During Float	[4]		nsec	
D_{0-7}	$t_{D(D)}$	Data Output Delay		230	nsec	C_L = 50pF
	$t_{F(D)}$	Delay to Float During Write Cycle		90	nsec	
	$t_{S\Phi(D)}$	Data Setup Time to Rising Edge of Clock During M1 Cycle	50		nsec	
	$t_{S\overline{\Phi}(D)}$	Data Setup Time to Falling Edge of Clock During M2 to M5	60		nsec	
	t_{dcm}	Data Stable Prior to $\overline{WR}$ (Memory Cycle)	[5]		nsec	
	t_{dci}	Data Stable Prior to $\overline{WR}$ (I/O Cycle)	[6]		nsec	
	t_{cdf}	Data Stable From $\overline{WR}$	[7]			
	t_H	Any Hold Time for Setup Time	0		nsec	
$\overline{MREQ}$	$t_{DL\overline{\Phi}(MR)}$	$\overline{MREQ}$ Delay From Falling Edge of Clock, $\overline{MREQ}$ Low		100	nsec	C_L = 50pF
	$t_{DH\Phi(MR)}$	$\overline{MREQ}$ Delay From Rising Edge of Clock, $\overline{MREQ}$ High		100	nsec	
	$t_{DH\overline{\Phi}(MR)}$	$\overline{MREQ}$ Delay From Falling Edge of Clock, $\overline{MREQ}$ High		100	nsec	
	$t_{w(\overline{MRL})}$	Pulse Width, $\overline{MREQ}$ Low	[8]		nsec	
	$t_{w(\overline{MRH})}$	Pulse Width, $\overline{MREQ}$ High	[9]		nsec	
$\overline{IORQ}$	$t_{DL\Phi(IR)}$	$\overline{IORQ}$ Delay From Rising Edge of Clock, $\overline{IORQ}$ Low		90	nsec	C_L = 50pF
	$t_{DL\overline{\Phi}(IR)}$	$\overline{IORQ}$ Delay From Falling Edge of Clock, $\overline{IORQ}$ Low		110	nsec	
	$t_{DH\Phi(IR)}$	$\overline{IORQ}$ Delay From Rising Edge of Clock, $\overline{IORQ}$ High		100	nsec	
	$t_{DH\overline{\Phi}(IR)}$	$\overline{IORQ}$ Delay From Falling Edge of Clock, $\overline{IORQ}$ High		110	nsec	
$\overline{RD}$	$t_{DL\Phi(RD)}$	$\overline{RD}$ Delay From Rising Edge of Clock, $\overline{RD}$ Low		100	nsec	C_L = 50pF
	$t_{DL\overline{\Phi}(RD)}$	$\overline{RD}$ Delay From Falling Edge of Clock, $\overline{RD}$ Low		130	nsec	
	$t_{DH\Phi(RD)}$	$\overline{RD}$ Delay From Rising Edge of Clock, $\overline{RD}$ High		100	nsec	
	$t_{DH\overline{\Phi}(RD)}$	$\overline{RD}$ Delay From Falling Edge of Clock, $\overline{RD}$ High		110	nsec	
$\overline{WR}$	$t_{DL\Phi(WR)}$	$\overline{WR}$ Delay From Rising Edge of Clock, $\overline{WR}$ Low		80	nsec	C_L = 50pF
	$t_{DL\overline{\Phi}(WR)}$	$\overline{WR}$ Delay From Falling Edge of Clock, $\overline{WR}$ Low		90	nsec	
	$t_{DH\overline{\Phi}(WR)}$	$\overline{WR}$ Delay From Falling Edge of Clock, $\overline{WR}$ High		100	nsec	
	$t_{w(\overline{WRL})}$	Pulse Width, $\overline{WR}$ Low	[10]		nsec	
$\overline{M1}$	$t_{DL(M1)}$	$\overline{M1}$ Delay From Rising Edge of Clock, $\overline{M1}$ Low		130	nsec	C_L = 50pF
	$t_{DH(M1)}$	$\overline{M1}$ Delay From Rising Edge of Clock, $\overline{M1}$ High		130	nsec	
$\overline{RFSH}$	$t_{DL(RF)}$	$\overline{RFSH}$ Delay From Rising Edge of Clock, $\overline{RFSH}$ Low		180	nsec	C_L = 50pF
	$t_{DH(RF)}$	$\overline{RFSH}$ Delay From Rising Edge of Clock, $\overline{RFSH}$ High		150	nsec	
$\overline{WAIT}$	$t_{s(WT)}$	$\overline{WAIT}$ Setup Time to Falling Edge of Clock	70		nsec	
$\overline{HALT}$	$t_{D(HT)}$	$\overline{HALT}$ Delay Time From Falling Edge of Clock		300	nsec	C_L = 50pF
$\overline{INT}$	$t_{s(IT)}$	$\overline{INT}$ Setup Time to Rising Edge of Clock	80		nsec	
$\overline{NMI}$	$t_{w(\overline{NML})}$	Pulse Width, $\overline{NMI}$ Low	80		nsec	
$\overline{BUSRQ}$	$t_{s(BQ)}$	$\overline{BUSRQ}$ Setup Time to Rising Edge of Clock	80		nsec	
$\overline{BUSAK}$	$t_{DL(BA)}$	$\overline{BUSAK}$ Delay From Rising Edge of Clock, $\overline{BUSAK}$ Low		120	nsec	C_L = 50pF
	$t_{DH(BA)}$	$\overline{BUSAK}$ Delay From Falling Edge of Clock, $\overline{BUSAK}$ High		110	nsec	
$\overline{RESET}$	$t_{s(RS)}$	$\overline{RESET}$ Setup Time to Rising Edge of Clock	90		nsec	
	$t_{F(C)}$	Delay to Float ($\overline{MREQ}$, $\overline{IORQ}$, $\overline{RD}$ and $\overline{WR}$)		100	nsec	
	t_{mr}	$\overline{M1}$ Stable Prior to $\overline{IORQ}$ (Interrupt Ack.)	[11]		nsec	

[12] $t_c = t_{w(\Phi H)} + t_{w(\Phi L)} + t_r + t_f$

[1] $t_{acm} = t_{w(\Phi H)} + t_f - 75$

[2] $t_{aci} = t_c - 80$

[3] $t_{ca} = t_{w(\Phi L)} + t_r - 40$

[4] $t_{caf} = t_{w(\Phi L)} + t_r - 60$

[5] $t_{dcm} = t_c - 210$

[6] $t_{dci} = t_{w(\Phi L)} + t_r - 210$

[7] $t_{cdf} = t_{w(\Phi L)} + t_r - 80$

[8] $t_{w(MRL)} = t_c - 40$

[9] $t_{w(MRH)} = t_{w(\Phi H)} + t_f - 30$

[10] $t_{w(\overline{WR}L)} = t_c - 40$

[11] $t_{mr} = 2t_c + t_{w(\Phi H)} + t_f - 80$

NOTES.

A. Data should be enabled onto the CPU data bus when $\overline{RD}$ is active. During interrupt acknowledge data should be enabled when $\overline{M1}$ and $\overline{IORQ}$ are both active.

B. All control signals are internally synchronized, so they may be totally asynchronous with respect to the clock.

C. The $\overline{RESET}$ signal must be active for a minimum of 3 clock cycles.

D. Output Delay vs. Loaded Capacitance
TA = 70°C Vcc = +5V ±5%

Add 10nsec delay for each 50pf increase in load up to a maximum of 200pf for the data bus & 100pf for address & control lines

E. Although static by design, testing guarantees $t_{w(\Phi H)}$ of 200 µsec maximum



Load circuit for Output

A.C. Timing Diagram

Timing measurements are made at the following voltages, unless otherwise specified:

	"1"	"0"
CLOCK	V_{cc} -.6V	.45V
OUTPUT	2.0 V	.8 V
INPUT	2.0 V	.8 V
FLOAT	Δ V	± 0.5 V



Absolute Maximum Ratings

Temperature Under Bias	Specified operating range.
Storage Temperature	-65°C to +150°C
Voltage On Any Pin with Respect to Ground	-0.3V to +7V
Power Dissipation	1.5W

*Comment

Stresses above those listed under "Absolute Maximum Rating" may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other condition above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

Note: . For Z80-CPU all AC and DC characteristics remain the same for the military grade parts except I_{cc}.

I_{cc} = 200 mA

Z80-CPU D.C. Characteristics

T_A = 0°C to 70°C, V_{cc} = 5V ± 5% unless otherwise specified

Symbol	Parameter	Min.	Typ.	Max.	Unit	Test Condition
V_{ILC}	Clock Input Low Voltage	-0.3		0.45	V	
V_{IHC}	Clock Input High Voltage	V_{cc} -.6		V_{cc}+.3	V	
V_{IL}	Input Low Voltage	-0.3		0.8	V	
V_{IH}	Input High Voltage	2.0		V_{cc}	V	
V_{OL}	Output Low Voltage			0.4	V	I_{OL}=1.8mA
V_{OH}	Output High Voltage	2.4			V	I_{OH} = -250μA
I_{CC}	Power Supply Current			150	mA	
I_{LI}	Input Leakage Current			10	μA	V_{IN}=0 to V_{cc}
I_{LOH}	Tri-State Output Leakage Current in Float			10	μA	V_{OUT}=2.4 to V_{cc}
I_{LOL}	Tri-State Output Leakage Current in Float			-10	μA	V_{OUT}=0.4V
I_{LD}	Data Bus Leakage Current in Input Mode			±10	μA	$0 \leqslant V_{IN} \leqslant V_{cc}$

Capacitance

T_A = 25°C, f = 1 MHz,
unmeasured pins returned to ground

Symbol	Parameter	Max.	Unit
C_Φ	Clock Capacitance	35	pF
C_{IN}	Input Capacitance	5	pF
C_{OUT}	Output Capacitance	10	pF

Z80-CPU Ordering Information

C – Ceramic
P – Plastic
S – Standard 5V ±5% 0° to 70°C
E – Extended 5V ±5% -40° to 85°C
M – Military 5V ±10% -55° to 125°C

Z80A-CPU D.C. Characteristics

T_A = 0°C to 70°C V_{cc} = 5V ± 5% unless otherwise specified

Symbol	Parameter	Min.	Typ.	Max.	Unit	Test Condition
V_{ILC}	Clock Input Low Voltage	-0.3		0.45	V	
V_{IHC}	Clock Input High Voltage	V_{cc} -.6		V_{cc}+.3	V	
V_{IL}	Input Low Voltage	-0.3		0.8	V	
V_{IH}	Input High Voltage	2.0		V_{cc}	V	
V_{OL}	Output Low Voltage			0.4	V	I_{OL}=1.8mA
V_{OH}	Output High Voltage	2.4			V	I_{OH} = -250μA
I_{CC}	Power Supply Current		90	200	mA	
I_{LI}	Input Leakage Current			10	μA	V_{IN}=0 to V_{cc}
I_{LOH}	Tri-State Output Leakage Current in Float			10	μA	V_{OUT}=2.4 to V_{cc}
I_{LOL}	Tri-State Output Leakage Current in Float			-10	μA	V_{OUT}=0.4V
I_{LD}	Data Bus Leakage Current in Input Mode			±10	μA	$0 \leqslant V_{IN} \leqslant V_{cc}$

Capacitance

T_A = 25°C, f = 1 MHz,
unmeasured pins returned to ground

Symbol	Parameter	Max.	Unit
C_Φ	Clock Capacitance	35	pF
C_{IN}	Input Capacitance	5	pF
C_{OUT}	Output Capacitance	10	pF

Z80A-CPU Ordering Information

C – Ceramic
P – Plastic
S – Standard 5V ±5% 0° to 70°C

T_A = 0°C to 70°C, Vcc = +5V ± 5%, Unless Otherwise Noted.

Signal	Symbol	Parameter	Min	Max	Unit	Test Condition
Φ	t_c	Clock Period	.25	[12]	μsec	
	$t_{w(\Phi H)}$	Clock Pulse Width, Clock High	110	[E]	nsec	
	$t_{w(\Phi L)}$	Clock Pulse Width, Clock Low	110	2000	nsec	
	$t_{r,f}$	Clock Rise and Fall Time		30	nsec	
A_{0-15}	$t_{D(AD)}$	Address Output Delay		110	nsec	C_L = 50pF
	$t_{F(AD)}$	Delay to Float		90	nsec	
	t_{acm}	Address Stable Prior to $\overline{\text{MREQ}}$ (Memory Cycle)	[1]		nsec	
	t_{aci}	Address Stable Prior to $\overline{\text{IORQ}}$, $\overline{\text{RD}}$ or $\overline{\text{WR}}$ (I/O Cycle)	[2]		nsec	
	t_{ca}	Address Stable from $\overline{\text{RD}}$, $\overline{\text{WR}}$, $\overline{\text{IORQ}}$ or $\overline{\text{MREQ}}$	[3]		nsec	
	t_{caf}	Address Stable From $\overline{\text{RD}}$ or $\overline{\text{WR}}$ During Float	[4]		nsec	
D_{0-7}	$t_{D(D)}$	Data Output Delay		150	nsec	C_L = 50pF
	$t_{F(D)}$	Delay to Float During Write Cycle		90	nsec	
	$t_{S\Phi(D)}$	Data Setup Time to Rising Edge of Clock During M1 Cycle	35		nsec	
	$t_{S\overline{\Phi}(D)}$	Data Setup Time to Falling Edge of Clock During M2 to M5	50		nsec	
	t_{dcm}	Data Stable Prior to $\overline{\text{WR}}$ (Memory Cycle)	[5]		nsec	
	t_{dci}	Data Stable Prior to $\overline{\text{WR}}$ (I/O Cycle)	[6]		nsec	
	t_{cdf}	Data Stable From $\overline{\text{WR}}$	[7]			
	t_H	Any Hold Time for Setup Time		0	nsec	
$\overline{\text{MREQ}}$	$t_{DL\overline{\Phi}(MR)}$	$\overline{\text{MREQ}}$ Delay From Falling Edge of Clock, $\overline{\text{MREQ}}$ Low		85	nsec	C_L = 50pF
	$t_{DH\Phi(MR)}$	$\overline{\text{MREQ}}$ Delay From Rising Edge of Clock, $\overline{\text{MREQ}}$ High		85	nsec	
	$t_{DH\overline{\Phi}(MR)}$	$\overline{\text{MREQ}}$ Delay From Falling Edge of Clock, $\overline{\text{MREQ}}$ High		85	nsec	
	$t_{w(\overline{MRL})}$	Pulse Width, $\overline{\text{MREQ}}$ Low	[8]		nsec	
	$t_{w(\overline{MRH})}$	Pulse Width, $\overline{\text{MREQ}}$ High	[9]		nsec	
$\overline{\text{IORQ}}$	$t_{DL\Phi(IR)}$	$\overline{\text{IORQ}}$ Delay From Rising Edge of Clock, $\overline{\text{IORQ}}$ Low		75	nsec	C_L = 50pF
	$t_{DL\overline{\Phi}(IR)}$	$\overline{\text{IORQ}}$ Delay From Falling Edge of Clock, $\overline{\text{IORQ}}$ Low		85	nsec	
	$t_{DH\Phi(IR)}$	$\overline{\text{IORQ}}$ Delay From Rising Edge of Clock, $\overline{\text{IORQ}}$ High		85	nsec	
	$t_{DH\overline{\Phi}(IR)}$	$\overline{\text{IORQ}}$ Delay From Falling Edge of Clock, $\overline{\text{IORQ}}$ High		85	nsec	
$\overline{\text{RD}}$	$t_{DL\Phi(RD)}$	$\overline{\text{RD}}$ Delay From Rising Edge of Clock, $\overline{\text{RD}}$ Low		85	nsec	C_L = 50pF
	$t_{DL\overline{\Phi}(RD)}$	$\overline{\text{RD}}$ Delay From Falling Edge of Clock, $\overline{\text{RD}}$ Low		95	nsec	
	$t_{DH\Phi(RD)}$	$\overline{\text{RD}}$ Delay From Rising Edge of Clock, $\overline{\text{RD}}$ High		85	nsec	
	$t_{DH\overline{\Phi}(RD)}$	$\overline{\text{RD}}$ Delay From Falling Edge of Clock, $\overline{\text{RD}}$ High		85	nsec	
$\overline{\text{WR}}$	$t_{DL\Phi(WR)}$	$\overline{\text{WR}}$ Delay From Rising Edge of Clock, $\overline{\text{WR}}$ Low		65	nsec	C_L = 50pF
	$t_{DL\overline{\Phi}(WR)}$	$\overline{\text{WR}}$ Delay From Falling Edge of Clock, $\overline{\text{WR}}$ Low		80	nsec	
	$t_{DH\overline{\Phi}(WR)}$	$\overline{\text{WR}}$ Delay From Falling Edge of Clock, $\overline{\text{WR}}$ High		80	nsec	
	$t_{w(\overline{WRL})}$	Pulse Width, $\overline{\text{WR}}$ Low	[10]		nsec	
$\overline{\text{M1}}$	$t_{DL(M1)}$	$\overline{\text{M1}}$ Delay From Rising Edge of Clock, $\overline{\text{M1}}$ Low		100	nsec	C_L = 50pF
	$t_{DH(M1)}$	$\overline{\text{M1}}$ Delay From Rising Edge of Clock, $\overline{\text{M1}}$ High		100	nsec	
$\overline{\text{RFSH}}$	$t_{DL(RF)}$	$\overline{\text{RFSH}}$ Delay From Rising Edge of Clock, $\overline{\text{RFSH}}$ Low		130	nsec	C_L = 50pF
	$t_{DH(RF)}$	$\overline{\text{RFSH}}$ Delay From Rising Edge of Clock, $\overline{\text{RFSH}}$ High		120	nsec	
$\overline{\text{WAIT}}$	$t_{s(WT)}$	$\overline{\text{WAIT}}$ Setup Time to Falling Edge of Clock	70		nsec	
$\overline{\text{HALT}}$	$t_{D(HT)}$	$\overline{\text{HALT}}$ Delay Time From Falling Edge of Clock		300	nsec	C_L = 50pF
$\overline{\text{INT}}$	$t_{s(IT)}$	$\overline{\text{INT}}$ Setup Time to Rising Edge of Clock	80		nsec	
$\overline{\text{NMI}}$	$t_{w(\overline{NML})}$	Pulse Width, $\overline{\text{NMI}}$ Low	80		nsec	
$\overline{\text{BUSRQ}}$	$t_{s(BQ)}$	$\overline{\text{BUSRQ}}$ Setup Time to Rising Edge of Clock	50		nsec	
$\overline{\text{BUSAK}}$	$t_{DL(BA)}$	$\overline{\text{BUSAK}}$ Delay From Rising Edge of Clock, $\overline{\text{BUSAK}}$ Low		100	nsec	C_L = 50pF
	$t_{DH(BA)}$	$\overline{\text{BUSAK}}$ Delay From Falling Edge of Clock, $\overline{\text{BUSAK}}$ High		100	nsec	
$\overline{\text{RESET}}$	$t_{s(RS)}$	$\overline{\text{RESET}}$ Setup Time to Rising Edge of Clock	60		nsec	
	$t_{F(C)}$	Delay to Float ($\overline{\text{MREQ}}$, $\overline{\text{IORQ}}$, $\overline{\text{RD}}$ and $\overline{\text{WR}}$)		80	nsec	
	t_{mr}	M1 Stable Prior to IORQ (Interrupt Ack.)	[11]		nsec	

[12] $t_c = t_{w(\Phi H)} + t_{w(\Phi L)} + t_r + t_f$

[1] $t_{acm} = t_{w(\Phi H)} + t_f - 65$

[2] $t_{aci} = t_c - 70$

[3] $t_{ca} = t_{w(\Phi L)} + t_r - 50$

[4] $t_{caf} = t_{w(\Phi L)} + t_r - 45$

[5] $t_{dcm} = t_c - 170$

[6] $t_{dci} = t_{w(\Phi L)} + t_r - 170$

[7] $t_{cdf} = t_{w(\Phi L)} + t_r - 70$

[8] $t_{w(\overline{MRL})} = t_c - 30$

[9] $t_{w(\overline{MRH})} = t_{w(\Phi H)} + t_f - 20$

[10] $t_{w(\overline{WRL})} = t_c - 30$

[11] $t_{mr} = 2t_c + t_{w(\Phi H)} + t_f - 65$

NOTES:

A. Data should be enabled onto the CPU data bus when $\overline{\text{RD}}$ is active. During interrupt acknowledge data should be enabled when $\overline{\text{M1}}$ and $\overline{\text{IORQ}}$ are both active.

B. All control signals are internally synchronized, so they may be totally asynchronous with respect to the clock.

C. The $\overline{\text{RESET}}$ signal must be active for a minimum of 3 clock cycles.

D. Output Delay vs. Loaded Capacitance
TA = 70°C   Vcc = +5V ±5%
Add 10nsec delay for each 50pf increase in load up to maximum of 200pf for data bus and 100pf for address & control lines.

E. Although static by design, testing guarantees $t_{w(\Phi H)}$ of 200 μsec maximum



Load circuit for Output

NOTES

I GLOSSARY

ACCESS The operation of seeking, reading or writing data on a storage unit (in this case, the diskette).

ACCESS TIME The time that elapses between any instruction being given to access some data and that data becoming available for use.

ACTIVE RECORDS TABLE (ART) A table of binary values in which the relative position of a single value determines the status of a record with the same relative position; i.e., the Nth binary number determines the status of the Nth record. EXAMPLE: If the 8th binary number in the table is a zero, then the 8th record is inactive. Conversely, if the 8th binary number in the table is a one, then the 8th record is active.

ADDRESS An identification (number, name, or label) for a location in which data is stored.

ALGORITHM A computational procedure.

ALPHANUMERIC (CHARACTERS) A generic term for numeric digits, alphabetic characters, punctuation characters and special characters.

ALPHANUMERIC STRING A group of characters which may include digits, alphabetic characters, punctuation characters and special characters, and may include spaces. (NOTE: a space is a 'character' to the computer, as it must generate a code for spaces as well as symbols.)

ASCII Abbreviation for American Standard Code for Information Interchange. Pronounced: Ass-KEY. Usually refers to a standard method of encoding letter, numeral, symbol and special function characters, as used by the computer industry.

ASSEMBLY LANGUAGE A machine level language for programming, such as Radio Shack's "EDITOR/ASSEMBLER" which uses Z-80 processor mnemonics and automatically 'assembles' machine readable code from the mnemonics.

BASE A quantity of characters for use in each of the digital positions of a numbering system.

BASE 2 The 'BINARY' numbering system consisting of more than one symbol, representing a sum, in which the individual quantity represented by each figure is based on a multiple of 2.

BASE 10 The 'DECIMAL' numbering system - consisting of more than one symbol, representing a sum, in which the individual quantity represented by each symbol is based on a multiple of 10.

BASE 16 The 'HEXADECIMAL' numbering system - consisting of more than one symbol representing a sum, in which the individual quantity represented by each symbol is based on a multiple of 16.

BINARY See 'BASE 2'

BIT A single 'BINARY' digit whose value is 'zero' or 'one'.

BOOLEAN A form of algebra applied to binary numbers which is similar in form to ordinary algebra. It is especially useful for logical analysis of binary numbers as used in computers.

'BOOT' - BOOTSTRAP A machine language program file that is put onto every diskette by the 'FORMAT' routine. This routing is invoked when reset or power-on occurs. It automatically loads the necessary programs (SYS0/SYS) to cause the computer to respond to the DOS commands; i.e., the machine is 'BOOTSTRAPPED' or 'BOOTED' into operation.

BUFFER A small area of memory used for the temporary storage of data to be processed.

BUFFER TRACK A track on a diskette used for the temporary storage of data or program material during a recovery process.

BUG A software fault that results in the malfunction of a program. May also refer to hardware malfunctions.

BYTE Eight 'BITS'. A 'BYTE' may represent any numerical value between '0' and '255'.

CLOBBERED A slang term referring to the non-operation of software, hardware, computer device, or storage media (such as disk) usually as the result of a program or hardware error.

COMMAND FILE A file consisting of a list of commmands, to be executed in sequence.

CONTIGUOUS Adjacent or adjoining.

CONTROL CODE In programming, instructions which determine conditional jumps are often referred to as control instructions and the time sequence of execution of instructions is called the flow of control.

CRC ERROR Cyclic Redundancy Check. A means of checking for errors by using redundant information used primarily to check disk I/O on the TRS-80.

DATA BASE A collection of interrelated data stored together with controlled redundancy to serve one or more applications. The data are stored so that they are independent of programs which use the data. A common and controlled approach is used in adding new data and in modifying and retrieving existing data within a data base. A system is said to contain a collection of data-based information if they are disjoint in structure.

DATA BASE MANAGEMENT SYSTEM The collection of software required for using a data base.

DATA ELEMENT Synonymous with 'DATA ITEM' or 'FIELD'

DATA TYPE The form in which data is stored; i.e., integer, single precision, double precision, 'alphanumeric' character strings or 'strings'.

DEC Initials for Directory Entry Code.

DECIMAL See 'BASE 10'.

DIRECT ACCESS Retrieval or storage of data by a reference to its location on a disk, rather than relative to the previously retrieved or stored data.

DIRECT STATEMENT (IN FILE) A program statement that exists in the disk file that is not assigned a line number.

DIRECTORY A table giving the relationships between items of data. Sometimes a table or an index giving the addresses of data.

DISPLACEMENT A specified number of sectors, at the top or beginning of the file, in which the 'bookkeeping' and file parameters are stored for later use by the various program modules.

DISTRIBUTED FREE SPACE Space left empty at intervals in a data layout to permit the possible insertion of new data.

DOUBLE PRECISION A positive or negative numeric value, 16 digits in length, not including a decimal point (EXAMPLE: 99999999999999.99).

DUMP To transfer all or part of the contents of one section of computer memory or disk into another section, or to some other computer device.

DYNAMIC STORAGE ALLOCATION The allocation of storage space by a procedure based on the instantaneous or actual demand for storage space by that procedure, rather than allocating storage space to a procedure based on its anticipated or predicted demand.

EATEN (DIRECTORY/DISK) Slang term. See 'CLOBBERED'.

EMBEDDED POINTERS Pointers in the data records rather than in a directory.

ENTITY Something about which data is recorded.

EOF Initials for 'END OF FILE'. It is common practice to say that the EOF is record number nn or that the EOF is byte 15 of sector 12. Hence, it is a convenient term to use in describing the location of the last record or last byte in a file.

EXTENT A contiguous area of data storage.

FILE A collection of related records treated as a unit; The word file is used in the general sense to mean any collection of informational items similar to one another in purpose, form and content.

FILE PARAMETERS The data that describes or defines the structure of the file.

FILESPEC A file specification and may include the 'FILE NAME', 'FILE NAME EXTENSION', 'PASSWORD', and 'DISK DRIVE' specification.

FIELD See 'DATA ITEM'.

FLAKY Slang term - Alludes to less than acceptable performance.

FILE AREA The physical location of the file, on the disk, or in memory.

'FPDE' Initials for File Primary Directory Entry; a file's entry and file area pointers in the disk directory.

'FXDE' Initials for File Extended Directory Entry; a file's entry and file area pointers, in the case of an overflow in the 'FPDE'.

GAT Initials for Granule Allocation Table; A table from which available file areas are assigned to file entries.

GRANULE Unit of 5 sectors. On the TRS-80 disk operating system, a 'granule' is the basic unit of disk storage allocation. The diskette 'DIRECTORY' file keeps track of free and assigned disk space in terms of 'granules'.

HASH CODE A code number generated and used as a direct addressing technique in which the key is converted to a pseudo-random number from which the required address is derived.

HEADER RECORD A record containing common, constant or identifying information for a group of records which follow.

HEXADECIMAL See 'BASE 16'

HIT Initials for Hash Index Table; an addressing technique in which a disk file is referenced by a code number in a table, and the position of that code in the table relates to the file entry in the directory.

INDEX A table used to determine the location of a record.

INDIRECT ADDRESSING Any method of specifying or locating a storage location whereby the key (of itself or through calculation) does not represent an address. For example, locating an address through indices.

INSTRING (INSTRING SEARCH) Refers to the capability of locating a substring of characters that may exist in another character string. An example would be: Substring = "THE" String = "NOW IS THE TIME". An INSTRING routine would locate the substring and return its starting position within that string. In this example, it would return a value of eight.

INTEGER A natural or whole number. In the TRS-80, integer values may not exceed the range of +32767 to -32768.

INVERTED FILE A file structure which permits fast spontaneous searching for previous unspecified information. Independent lists or indices are maintained in records' keys which are accessible according to the values of specific fields.

INVERTED LIST A list organized by a secondary key --- not a primary key.

IPL Initials for Initial Program Loader; a program usually executed upon pressing of the 'RESET' button.

KEY A data item used to identify or locate a record or other data grouping.

LABEL A set of symbols used to identify or describe an item, record, message or file. Occasionally, it may be the same as the address in storage.

LEAST SIGNIFICANT BYTE The significant byte contributing the smallest quantity to the value of a numeral.

LIST An ordered set of data items. A 'chain'.

LOAD MODULE A program developed for loading into storage and being executed when control is passed to the program.

LOCK-OUT (TRACKS) Unusable tracks, on the disk, that are not accessible because of damage or by user option.

LOGICAL An adjective describing the form of data organization, hardware or system that is perceived by an application program, programmer, or user; it may be different than the real (PHYSICAL) form.

LOGICAL DATA-BASE DESCRIPTION A schema. A description of the overall data-base structure, as perceived for the users, which is employed by the data base management software.

LOGICAL FILE A file as perceived by an application program; it may be in a completely different form from that in which it is stored on the storage units.

LOGICAL OPERATOR A mathematical symbol that represents a mathematical process to be performed on an associated operand. Such operators are 'AND', 'OR', 'NOT', 'AND NOT' and 'OR NOT'.

LOGICAL RECORD A record or data item as perceived by an application program; it may be in a completely different form from that in which it is stored on the storage units.

LSB See LEAST SIGNIFICANT BYTE.

MACHINE LANGUAGE Direct machine readable code.

MAINTENANCE OF A FILE (1) The addition, deletion, changing or updating of records in the database. (2) Periodic reorganization of a file to better accommodate items that have been added.

MONITOR A program that may supervise the operation of another program for operation or debugging or other purposes.

MOST SIGNIFICANT BYTE The significant byte contributing the greatest quantity to the value of a numeral.

MSB See MOST SIGIFICANT BYTE.

MULTIPLE-KEY RETRIEVAL Retrieval which requires searches of data based on the values of several key fields (some or all of which are secondary keys).

NULL An absence of information as contrasted with zero or blank for the presence of no information.

NYBBLE The four right most or left most binary digits of a byte.

ON-LINE An on-line system is one in which the input data enter the computer directly from their point of origin, and/or output data are transmitted directly to where they are used. The intermediate stages such as writing tape, loading disks or off-line printing are avoided.

ON-LINE STORAGE Storage devices and especially the storage media which they contain under the direct control of a computing system, not off-line or in a volume library.

OPEN RECORDS TABLE (ORT) A table of binary values in which the relative position of a single value determines the status of a record with the same relative position; i.e., the Nth binary number determines the status of the Nth record. EXAMPLE: If the 8th binary number in the table is a zero, then the 8th record is open. Conversely, if the 8th binary number in the table is a one, then the 8th record is on file.

OPERATING SYSTEM Software which enables a computer to supervise its own operations, automatically calling in programs, routines, language and data as needed for continuous throughput of different types of jobs.

PARITY Parity relates to the maintenance of a sameness of level or count, i.e., keeping the same number of binary ones in a computer word and thus be able to perform a check based on an even or odd number for all words under examination.

PHYSICAL An adjective, contrasted with logical, which refers to the form in which data or systems exist in reality. Data is often converted by software from the form in which it is physically stored to a form in which a user or programmer perceives it.

PHYSICAL DATA BASE A data base in the form in which it is stored on the storage media, including pointers or other means of interconnecting it. Multiple logical data bases may be derived from one or more physical data bases.

PHYSICAL RECORD A collection of bits that are physically recorded on the storage medium and which are read or written by one machine input/output instruction.

POINTER The address or a record (or other data groupings) contained in another record so that a program may access the former record when it has retrieved the latter record. The address can be absolute, relative or symbolic, hence, the pointer is referred to as absolute, relative or symbolic.

PRIMARY ENTRY The main entry made to the directory. Also see 'FPDE'.

RANDOM ACCESS To obtain data directly from any storage location regardless of its position, with respect to the previously referenced information. Also called 'DIRECT ACCESS'.

RANDOM ACCESS STORAGE A storage technique in which the time required to obtain information is independent of the location of the information most recently obtained.

READ To accept or copy information or data from input devices or a memory register; i.e., to read out, to read in.

RECORD A group of related fields of information treated as a unit by an application program.

RELATIONAL OPERATOR A mathematical symbol that represents a mathematical process to perform a comparison describing the relationsnip between two values (< less than....> greater than... = equal.... <> not equal... and combinations thereof (see TRS-80 LEVEL II manual, Section 1, Page 5). On the TRS-80, relational comparisons may be made on string values as well as numerical values.

RELATIVE (as pertains to position) An address or position that is referenced to a point of origin; i.e. X+20 is a specific positon, 20 places from the reference point. If the reference point was at 50, then the absolute position would be at 70 (50+20=70). Also, 50 (since it is the starting reference point) is at relative position 0.

SCHEMA A map of the overall logical structure of a database.

SEARCH To examine a series of items for any that have a desired property or properties.

SECONDARY INDEX An index composed of secondary keys rather than primary keys.

SECTOR The smallest addressable portion of storage on a diskette (a unit of 256 bytes on a TRS-80 diskette).

SEEK To position the access mechanism of a direct-access storage device at a specified location.

SEQUENTIAL ACCESS Access in which records must be read serially or sequentially one after the other; i.e., ASCII files, tape.

SINGLE PRECISION A positive or negative numerical value of 6 digits in length, not including a decimal point (EXAMPLE: 99999.9).

SORT To arrange a file or data in a sequence by a specified key (may be alphabetic or numeric and in descending or ascending order).

SOURCE CODE The text from which code that may be executed is derived.

SYSTEM FILE A program used by the operating system to manage the executing program and/or the computer's resources.

SUB-STRINGS SUB-STRING SEARCH See INSTRING

TABLE A collection of data suitable for quick reference, each item being uniquely identified either by a label or its relative position.

TALLY To add or subtract a digit from a quantity.

TOKEN A one byte code representing a larger word consisting of 2 or more characters.

TRACK The circular recording surface traversed by a read/write head on the disk. On the TRS-80 a track contains 10 sectors (2 granules).

TRANSACTION An input record applied to an established file. The input record describes some "event" that will either cause a new file record to be generated, an existing record to be changed or an existing record to be deleted.

TRANSPARENT Complexities that are hidden from the programmers or users (made transparent to them) by the software.

VECTOR A line representing the properties of magnitude and direction. Since such a 'line' can be described in mathematical terms, a mathematical description (expressed in numbers, of course) of a given 'direction' and 'magnitude' is referred to as a "vector".

VERIFY To check a data transfer or transcription.

WORKING STORAGE A portion of storage, usually computer main memory, reserved for the temporary results of operations.

WRITE To record information on a storage device.

ZAP To change a byte or bytes of data in memory or on diskette by using a software utility program.

ZEROETH Zeroeth is to '0' as first is to '1'; in computer terms the first position of anything is usually described as the 'zeroeth' and the next position is the 'first' and so on.

NOTES

PARTS LIST
SIMPLE HOBBYIST INTERFACE

IC	TYPE	+5 VOLTS	GROUND
Z1	81LS95	20	10
Z2	81LS96	20	10
Z3	81LS95	20	10
Z4	81LS95	20	10
Z5	74LS75	5	12
Z6	74LS75	5	12
Z7	74LS30	14	7
Z8	74LS02	14	7

PARTS LIST
ONE-SECOND INTERRUPT REAL-TIME CLOCK

IC	TYPE	+5 VOLTS	GROUND
Z1	7805	3 (OUTPUT)	2
Z2	74LS14	14	7
Z3	74LS90	5	10
Z4	74LS92	5	10
Z5	74LS74	14	7
Z6	74LS75	5	12

PART	VALUE	NOTES
C1	4700 mf, 16 volts	
C2	220 mf, 16 volts	
C3	100 nf (0.1 mf)	
C4	100 nf (0.1 mf)	

PARTS LIST
MSM5832 REAL-TIME CLOCK/CALENDAR

IC	TYPE	+5 VOLTS	GROUND
Z1	74LS30	14	7
Z2	74LS260	14	7
Z3	INS8255	26	7
Z4	MSM5832	1	13

PART	VALUE	NOTES
C1	20 pf	
C2	20 pf	
C3	100 nf (0.1 mf)	
C4	100 nf (0.1 mf)	
C5	100 nf (0.1 mf)	
C6	100 nf (0.1 mf)	
R1-R12	10k (10,000 ohms)	

Battery backup:

PART	VALUE	NOTES
C6	470 mf, 16 volts	
C7	10 mf, 16 volts	
C8	100 nf (0.1 mf)	
C9	10 mf, 16 volts	
01	Bridge rectifier, 1A 50V	
02	1N914 or equivalent	
Q1	PNP transistor, Vce=0.1 volt	
Q2	NPN transistor	
R13	47k (47,000 ohms)	
R14	10k (10,000 ohms)	
R15	10k (10,000 ohms)	
R16	100R (100 ohms), 0.5 W	
T1	6V3 (6.3 volt), 1A transformer	
Z5	7805 5-volt regulator	

PARTS LIST
QUAD SOUND, BOOPS AND BLEEPS GENERATOR

IC	TYPE	+5 VOLTS	GROUND
Z1	74LS374	20	10
Z2	74LS125	14	7
Z3	74LS30	14	7
Z4	74LS30	14	7
Z5	7LS02	14	7

PART	VALUE	NOTES
R1-R5	1k (10,000 ohms)	

PARTS LIST
MEMORY SIDECAR ROM AND RAM ADDITION

IC	TYPE	+5 VOLTS	GROUND
Z1	74LS30	14	7
Z2	74LS02	14	7
Z3	74LS00	14	7
Z4	74LS00	14	7
Z5	74LS125	14	7
Z6,7,8,9	2114-AN4L	18	9
Z10	2716	24	12

PART	VALUE	NOTES
R1-R16	1k0 (10,000 ohms)	

PARTS LIST
MUSIC SYNTHESIZER INTERFACE BOARD

IC	TYPE	+5 VOLTS	GROUND
Z1	81LS95	20	10
Z2	74LS154	24	12
Z3	74LS00	14	7
Z4	74LS04	14	7
Z5	INS8255	26	7
Z6	MC1408L8 OR OAC0808	13	2
Z7	MC1408L8 OR OAC0808	13	2
Z8	74LS123	14	7
Z9	74LS123	14	7
Z10	LM324	4	11

Note that Z6 and Z7 also require −15 volts on pin number 3 and and +7.5 volt reference at pin 14 (through a variable resistor).

PART	VALUE	NOTES
C1,2	20 pf	
C3,4,5,6	100 nf (0.1 mf)	(may be changed)
R1,3	4k7 (4700 ohms)	
R2,4	1k0 (1000 ohms)	(may be changed)
R5,6,7,8	1M0 (1,000,000 ohms)	

PARTS LIST
BANK-SELECT ROM/RAM ADDITION

IC	TYPE	+5 VOLTS	GROUND
Z1	81LS95	20	10
Z2	81LS95	20	10
Z3	81LS95	20	10
Z4	81LS95	20	10
Z5–11	2716 OR 4118	24	12
Z12	74LS20	14	7
Z13	74LS260	14	7
Z14	74LS02	14	7
Z15	74LS75		
Z16	74154	24	12
Z17	74LS04	14	7
Z18–26	2716 OR 4118	24	12

PARTS LIST
8-TRACK MASS STORAGE SYSTEM

IC	TYPE	+5 VOLTS	+12 VOLTS	GROUND
Z1	70C98/60C98	.		.
Z2	74LS04	14		7
Z3	74LS125	14		7
Z4	LF353		.	.
Z5	LM339		.	.
Z6	70C98/80C98	.		.
Z7	LF353		.	.
Z8	74LS00	14		7
Z9	75452	8		4
Z10	70C96/80C96	.		.
Z11	75452	8		4
Z12	74LS373	20		10
Z13	74LS30	14		7
Z14	74LS04	14		7

PART	VALUE	NOTES
C1	100 pf	
C2	220 pf	
C3	220 nf (0.22 mf)	
C4	10 mf, 16 volts	
C5	100 pf	
C6	220 pf	
C7	220 nf (0.22 mf)	
C8	10 mf, 16 volts	
C9,10,11	100 nf (0.1 mf)	
C12	470 mf, 35 volts	
D1,2,3,4,5	1N914 or equivalent	
K1,2,3	Miniature SPST 5-volt relay	
R1,2,14,17, 18,30,38,39, 40,41	10k (10,000 ohms)	
R3,4,12,19, 20,28	470R (470 ohms)	
R5,6,9,11,16, 22,25,27,32	2k2 (2200 ohms)	
R7,8,23,24	220k (220,000 ohms)	
R10,26	100k (100,000 ohms)	
R13,29	22k (22,000 ohms)	
R15,31	220R (220 ohms)	
R33,34,35,36, 37,42	1k0 (1000 ohms)	
R43	100R (100 ohms)	
R44	75R (75 ohms)	May need adjustment
S1	Cartridge-in-place leaf switch	
S2	Track change light switch	
S3	Split-pole foil sensor switch	

PARTS LIST
MICRO FRONT PANEL MONITOR

IC	TYPE	+5 VOLTS	GROUND
Z1	74LS373	20	10
Z2	74LS373	20	10
Z3	74LS373	20	10
Z4	74LS20	14	7

PART	VALUE	NOTES
DIS1,2,3	10-segment bar LED	
LED1-24	Subminiature LED	
R1-24	270R (270 ohms)	
R25,26,27,28	1k0 (1000 ohms)	
S1	4-position DIP switch	

PARTS LIST
4K DYNAMIC RAM ADDITION

IC	TYPE	+5 VOLTS	GROUND
Z1	81LS95	20	10
Z2	74LS157	16	8
Z3	81LS95	20	10
Z4	74LS157	16	8
Z5	81LS95	20	10
Z6-13	MK4114 4K RAMS	9	16
Z14	74LS20	14	7
Z15	74LS86	14	7
Z16	81LS95	20	10

Note that Z6 through Z13 also require -5 volts on pin number 1 and +12 volts on pin number 8.

PART	VALUE	NOTES
R1,2,3	1k0 (1000 ohms)	
S1	4-position DIP switch	

PARTS LIST
HIGH-SPEED, REVERSE VIDEO, UPPER/LOWER CASE, INDIVIDUAL REVERSE VIDEO MODS

IC	TYPE	+5 VOLTS	GROUND
F45 (ZMEM)	2102-4L	10	9
P25 (Z8ITS)	74LS10	14	7
P6 (ZFAZE)	74LS04	14	7
P27 (ZMODE)	74LS368	20	10
P24 (ZMUXX)	74LS86	14	7
P26 (ZFLOP)	74LS74	14	7
P53 (ZPORT)	74LS02	14	7
P44 (ZFAST)	74LS367	20	10
PC VERSION ONLY:			
Z25	74LS04	14	7

PART	VALUE	NOTES
C1	330 pf	
C2	33 nf (.033 mf)	
R1	10k (10,000 ohms)	
VCR1	100k (100,000 ohms)	Variable

Miscellaneous:
One 16-pin wire-wrap integrated circuit socket for piggybacking the PC board version onto Z45.
No socket is needed for the hard-wired version.

PARTS LIST
HIGH-RESOLUTION GRAPHICS BOARD POWER SUPPLY

PART	VALUE	NOTES
C1	4700 mf, 35 volts	
C2	100 mf, 25 volts	
C3	100 nf (0.1 mf)	
C4	10,000 mf, 35 volts	
C5	100 mf, 16 volts	
C6	100 nf (0.1 mf)	
C7	470 mf, 16 volts	
C8	100 mf, 16 volts	
C9	100 nf (0.1 mf)	
R1	220 ohms, 1/2 watt	

PARTS LIST
HIGH-RESOLUTION GRAPHICS BOARD

IC	TYPE	+5 VOLTS	GROUND
Z1	74LS04	14	7
Z2	74LS92	5	10
Z3	74LS74	14	7
Z4	74LS93	5	10
Z5	74LS93	5	10
Z6	74LS93	5	10
Z7	74LS93	5	10
Z8	74LS11	14	7
Z9	74LS02	14	7
Z10	74LS157	16	8
Z11	74LS157	16	8
Z12	74LS157	16	8
Z13	74LS157	16	8
Z14	74LS74	14	7
Z15	74LS00	14	7
Z16	74LS174	16	8
Z17	74LS166	16	8
Z18	74LS157	16	8
Z19	74LS157	16	8
Z20	74LS157	16	8
Z21	MK4116	9	16
Z22	MK4116	9	16
Z23	MK4116	9	16
Z24	MK4116	9	16
Z25	MK4116	9	16
Z26	MK4116	9	16
Z27	74C04	14	7
Z28	74C04	14	7
Z29	74C00	14	7
Z30	75452	8	4
Z31	74LS00	14	7

Note that Z21 through Z26 also need -5 volts on pin number 1, and +12 volts on pin number 8.

PART	VALUE	NOTES
C1*	47 pf	Miniature variable
C2	10 nf (.01 mf)	
C3	10 mf, 16v	
C4	330 pf	10% or better
C5	47 nf (.047 mf)	10% or better
C6	750 pf	10% or better
C7	22 nf (.022 mf)	10% or better
Q1	2N3904	NPN switching
Q2	2N3904	NPN switching
R1	1k0 (1000 ohms)	
R2	1k0 (1000 ohms)	
R3	1k0 (1000 ohms)	
R4*	910R (910 ohms)	
R5*	910R (910 ohms)	
R6	1k8 (1800 ohms)	
R7	47R (47 ohms)	
R8	270R (270 ohms)	
R9	120R (120 ohms)	
R10	330R (330 ohms)	
R11	75R (75 ohms)	
R12	10k (10,000 ohms)	
R13	10k (10,000 ohms)	
VCR1	100k (100,000 ohms)	Variable
VCR2	100k (100,000 ohms)	Variable
X1*	10.6445 MHz	

*Not needed if computer's internal clock is used.


MSM 5 8 3 5
R. T C
-
+
R1
R12
C1
C2
C3
C4
XTAL
Z4
MSM 5835 RTC
Z2
Z1
Z3
8 9
TOP
1
39
1 3 5 7 9 11 13 15 17 19 21 23 25 27 29 31 33 35 37 39


MSM 5 8 3 5
R. T. C.
-
+
MSM 5835 R.T.C.
8 9
TOP
1
39
1 3 5 7 9 11 13 15 17 19 21 23 25 27 29 31 33 35 37 39


+
-
BOTTOM
9 8
40
2
40 38 36 34 32 30 28 26 24 22 20 18 16 14 12 10 8 6 4 2







c1980 D. Kitsz


EARIE
R1
R4
Z5
Z2
Z4
Z3
Z1
GND
+5V
TOP


1 - SEC INTERRUPT BOARD
Z2
Z3
Z4
Z5
CLR
INT
GND
C3
C4
Z6
C1
C2
C5 (0.1μF)
Z1
BOTTOM


EARIE
GND
+5V
TOP


1 - SEC. INTERRUPT BOARD
CLR
INT
GND
+
+
+
+
BOTTOM
−


4
3
2
1
OUT
BOTTOM
2
40
2
4
6
8
10
12
14
16
18
20
22
24
26
28
30
32
34
36
38
40


HIGH SPEED VIDEO MODS
Z MODE
CB
USE
Z FAZE
41-6
30-1
60-4
60-5
30-13
27-4
63-12
27-5
33-4
59-5
52-6
54-8
32-3
56-8
72-2
56-11 OR 12





MUSIC SYNTHESIZER INTERFACE BOARD


14
1
1
16
1
1
1
16
40
1
1
28
1
14
20
24
1
1
14
1
40
2




THE MEMORY SIDECAR
BY
THE PERIPHERAL PEOPLE
MS 1-1
SW1
R16
SW2
IC10
L2
R17
SW3
D1
D2
C
IC7
IC9
IC6
IC5
C4
C6
IC4
IC2
IC3
R1-R


THE MEMORY SIDECAR
BY
THE PERIPHERAL PEOPLE
MS 1-1


MS 1-2

OTHER MYSTERIES BOOKS FROM I.J.G.


TRS-80 INFORMATION SERIES — VOLUME I

H.C. Pennington

TRS-80® DISK & OTHER MYSTERIES

THE "HOW TO" BOOK OF DATA RECOVERY

TRS-80® DISK AND OTHER MYSTERIES

by H. C. Pennington

TRS-80 Disk and Other Mysteries is the definitive fix-it book for disk users. More than 130 pages of easy to read entertaining and immensely useful information. Find out how to recover disk files, the layout of information on disks, memory maps, problem solutions . . . the list goes on!

Many readers have saved days of work by recreating disk files that were unreadable. *TRS-80 Disk and Other Mysteries*, which has received favorable reviews in several magazines, is yours for only $22.50 (plus $3.00 shipping. CA residents add $1.35 sales tax. Canada add 20% for exchange rate.) TRS-80 is a trademark of Tandy

---


James Farvour

MICROSOFT BASIC DECODED & OTHER MYSTERIES for the TRS-80

The complete guide to the LEVEL II operating system & BASIC

MICROSOFT* BASIC DECODED AND OTHER MYSTERIES

by James Farvour

Microsoft Basic and Other Mysteries is the definitive guide to your Level II ROMs. With more than 7,000 lines of detailed comments and 6 additional chapters packed with information, it is easily the biggest and best book about the Level II ROMs available.

Exploit the full power of Microsoft Basic with the aid of more than 300 pages of tested examples, explanations, and detailed comments. *Microsoft Basic and Other Mysteries* is yours for only $29.95 (plus $3.00 shipping. CA residents add $1.80 sales tax. Canadaa add 20% for exchange rate.)

* T.M. Microsoft


TRS-80 INFORMATION SERIES · VOLUME IV

Lewis Rosenfelder

BASIC FASTER AND BETTER & OTHER MYSTERIES

BASIC

A guided tour of BASIC programming tricks and techniques

BASIC FASTER AND BETTER AND OTHER MYSTERIES

by Lewis Rosenfelder

Basic is not nearly as slow as most programmers think. *Basic Faster and Better* shows you how to supercharge your BASIC with almost 300 pages of fast, functions and subroutines.

You won't find any trivial poorly designed "check-book balancing" programs in this book — it's packed with *useful* programs.

Tutorial for the beginner, instructive for the advanced, and invaluable for the professional, this book doesn's just talk . . . it shows how! All routines are also available on disk, so that you can save hours of keyboarding and debugging.

The #1 disk *BFBDEM* contains all the demonstration programs, and #2 disk *BFBLIB* has all the library functions.

Basic Faster and Better is $29.95, and the two disks are $19.95 each (plus $3.00 shipping for book and disks together or separate. CA residents add $1.80 sales tax for the book, disks add $1.20 each. Canada add 20% for exchange rate.)

ISBN 0 936200 02 2